Lumora Aria X2 - User Manual

Model: LA-AX2. Document version 2.2, January 2026.

1. Getting started

Press the power button for 2 seconds. The speaker enters pairing mode automatically the first time. Select 'Lumora Aria X2' in your device's Bluetooth menu.

2. Party Mode

Party Mode links several Aria X2 speakers so they play the same music. Press the Party button on the first speaker, then on each additional speaker within 30 seconds. Up to 4 Aria X2 speakers can be linked in one Party Mode session. Party Mode works only between Aria X2 speakers.

3. Battery

Up to 20 hours of playback at 50% volume, about 9 hours at maximum volume. Charging from empty to full takes 3.5 hours with a 20 W USB-C charger. The speaker can charge a phone through its USB-C port (power bank function).

4. Water and dust resistance

Aria X2 is rated IP67: dust tight, and protected against immersion in fresh water up to 1 meter for 30 minutes. The rubber cover over the USB-C port must be fully closed for the rating to apply. After exposure to salt water or chlorinated water, rinse the speaker with fresh water and let it dry for 2 hours before charging.

5. Specifications

Item	**Value**
Output power	2 x 15 W
Frequency response	55 Hz - 20 kHz
Bluetooth	5.3, range up to 30 m
Weight	890 g
Multipoint	Supported (from firmware 2.2.0)