

Practical Questions - If-Else, Switch Case

Question 1:

Write a program that takes an integer input and determines whether it's positive, negative, or zero using an "if-else" statement.

Question 2:

Create a program that enter a day of the week (1-7) and then prints the corresponding day's name using a "switch" statement.

Question 3:

Write a program that checks if a given year is a leap year. Use both "if-else" and "switch" statements to handle the logic.

Question 4:

Design a program that calculates the total cost of a shopping cart. The user should input the item price and quantity for three items. Apply a 10% discount if the total cost is above \$100 using an "if-else" statement.

Question 5:

Create a simple calculator program that takes two numbers and an operator (+, -, *, /) as input from the user. Perform the operation using a "switch" statement and display the result.

Question 6:

Write a program that takes three sides of a triangle as input and determines whether it's an equilateral, isosceles, or scalene triangle using an "if-else" statement.

Question 7:

Design a program that simulates a simple vending machine. The user enters the item code (1-5) and the program displays the selected item. Use a "switch" statement for the item selection.

Question 8:

Practical Questions - If-Else, Switch Case

Create a program that converts a numeric grade (0-100) into a letter grade based on the following scale: 90-100: A, 80-89: B, 70-79: C, 60-69: D, below 60: F. Use an "if-else" statement to handle the conversion.