

Hardware Quick Start

Connect, read, generate, audition, and save your first AI-assisted JUNO-DS patch. This guide matches the current app, including local model settings, patch history, deletion, and JUNO-safe names.

SAFE BY DESIGN

Send to JUNO writes only to the instrument's temporary edit buffer. It does not store over a user patch. You still confirm every hardware write.

01 BEFORE YOU LAUNCH

Connect the keyboard

1

Connect USB and power on

Connect the JUNO-DS directly to the PC, then switch it on. Avoid an unpowered USB hub for the first test.

2

Confirm the Roland MIDI driver

Windows should expose JUNO MIDI input and output ports. If not, install Roland's JUNO-DS USB driver and reconnect.

3

Choose a harmless starting sound

Select a simple factory patch on the keyboard and note its name. Keep the keyboard volume moderate.

02 START PATCHMAKER

Launch the local GUI

From PowerShell in `C:\Users\adamr\patchmaker-juno_ds`:

```
.\.venv\Scripts\patchmaker-juno.exe gui
```

The browser opens at <http://127.0.0.1:8765>. Patchmaker always starts with a neutral default patch and a randomized, editable sound prompt.

03 VERIFY BOTH CONNECTIONS

Model first, then MIDI

MODEL CONNECTION

Confirm endpoint, model, and API key. Click **Save settings locally**, then **Test connection**. Proceed only after **Connection successful** appears.

Settings are stored in the local, Git-ignored `.env` file.

JUNO CONNECTION

Click refresh, then select the JUNO for both **MIDI input** and **MIDI output**. Click **Read current patch** and verify its name appears as the current result.

No ports? Reconnect USB, restart the app, and check the Roland driver.

Your First Hardware Session

Start with a no-change round trip, then make one audible change at a time.

04 FIRST SAFE HARDWARE TEST

Prove the round trip before generating

- 1 Read current patch**
Use Read current patch and confirm the displayed name matches the keyboard.
- 2 Send it back unchanged**
Click Send to JUNO, approve the confirmation, and play several notes. It should sound unchanged.
- 3 Generate a subtle variation**
Try: *Make it slightly darker with a softer attack.* Click Generate variation and review the result.
- 4 Send and audition**
Send the generated result to the temporary edit buffer. Play low, middle, and high notes; test velocity, sustain pedal, and pitch/mod controls.
- 5 Iterate**
Describe one change at a time, generate another version, send it, and compare by ear.

05 PATCH LIBRARY

Every successful generation is saved

Saved generations appear newest-first under **Previous generations**. Click a card to restore the complete patch and its original prompt. Duplicate names are labeled **v1**, **v2**, and so on. Click **x** to delete only that saved snapshot after confirmation. All names are automatically converted to printable ASCII and limited to the JUNO-DS maximum of 12 characters.

QUICK TROUBLESHOOTING

SYMPTOM	WHAT TO DO
No MIDI ports	Reconnect USB directly, power-cycle the JUNO-DS, install/check the Roland driver, then restart Patchmaker.
Connection says Needs attention	Read the detailed message below the prompt. Re-test endpoint, exact model, and API key; save settings again if changed.
Generation fails	Copy the complete error. Confirm the model test still succeeds. Current builds safely normalize names longer than 12 characters.
Patch sounds wrong	Return to a saved library version or read the keyboard patch again. Nothing is permanently stored on the JUNO until you use the keyboard's own write procedure.

GOOD FIRST-NIGHT CHECKLIST

Read current patch / Send unchanged / Generate subtle edit / Send and play / Restore history / Delete a test snapshot / Try one randomized prompt