L-Representation: A Finite-Precision Single-Integer Substrate for Geometric Algebra Computing

Tight error bounds, necessary-and-sufficient no-bleed conditions, sparse multivector packing, segmentation theory, and FPGA validation

Hung Dinh Phu Dang
https://github.com/nahhididwin/L-Representation
Ho Chi Minh City, Vietnam

March 15, 2026

Abstract

We present a complete, finite-precision theory for the *L-Representation* (L-Rep)—a single-integer substrate in which all 2^n blade coefficients of a Geometric Algebra (GA) multivector are packed into one machine word, and all GA operations are implemented as arithmetic on that word using mixed-radix field layout with controlled carry semantics.

Context. Existing GA hardware (CliffordALU5, quadruple-based designs, CliffoSor, GA-FU) achieves impressive throughput (4–23× over struct-of-arrays) but provides *no* formal finite-precision guarantee: accumulator widths are chosen empirically, no necessary-and-sufficient no-overflow conditions exist in the literature, and no bit-exact error bounds are proved for GA products. L-Rep addresses exactly this gap. It is not claimed to maximise raw throughput; it is claimed to be the *first formally analysed GA single-integer substrate* from which correctness and bit budget can be derived algorithmically.

Contributions. We prove eight theorems, each with a complete human-verified proof (machine verification in Lean 4 is ongoing; see §**??**):

1. **Finite-precision approximation** (Thm. **??**): constructive, error-bounded mapping between $\mathbb{G}(p, q, r)$ multivectors and packed integers; complete error decomposition.
2. **No-bleed NSC** (Thm. **??**): tight, necessary-and-sufficient integer conditions on storage bits b_i for zero inter-field carry; proved minimal.
3. **Accumulator growth** (Thm. **??**): exact worst-case integer bound S_k at every DAG node; tight witnesses for unconstrained inputs; conservative but correct for normalisation-constrained inputs.
4. **Segmented correctness** (Thm. **??**): additive, budgeted error from requantisation boundaries; amplification factors computed in polynomial time.
5. **Probabilistic overflow** (Thm. **??**): Bernstein-based failure probability under a documented independence assumption; degradation under correlated inputs bounded.
6. **Quantisation optimality** (Thm. **??**): optimal scale σ_i^* and lossless-mapping characterisation.
7. **Format comparison** (Thm. **??**): closed-form equivalence between L-Rep guard-bit requirements and posit/quire accumulator sizes.
8. **Sparse L-Rep** (Thm. **??**): **new.** For grade-κ sparse multivectors, the bit budget reduces from $O(2^n b)$ to $O(\binom{n}{\kappa} b)$, yielding 4×–8× storage savings for practical algebras.

Empirical results. Verilator RTL simulation ($n \leq 6$, exhaustive adversarial test vectors) shows zero bleed events and error within 5% of theoretical bounds. Python arbitrary-precision reference model confirms tightness. Synthesis on Xilinx Artix-7 and Intel Cyclone

V gives 1.7×–2.3× throughput over float32 struct-of-arrays at 37–59% the bit cost. These results are complementary to, not competitive with, prior GA accelerators: L-Rep's distinguishing property is *formal correctness*, not maximum throughput.

All artifacts (RTL, Python, test vectors, Lean proof stubs, LaTeX source) are publicly available at https://github.com/nahhididwin/L-Representation.

Contents

1 Introduction

1.1 Motivation

Geometric Algebra (GA) provides a unified mathematical language for geometry: rotations, translations, reflections, and projections are all expressed as algebraic products of multivectors [?, ?]. Applications in robotics [?], computer vision [?], physics simulation [?], and emerging geometric deep learning [?] demand high-throughput, numerically reliable GA kernels.

A key structural observation motivates this work: *a multivector's $m = 2^n$ blade coefficients are collectively small when quantised to fixed-point integers.* If each coefficient fits in b_i bits, the entire multivector occupies $B = \sum_i b_i$ bits—often 128–512 bits, fitting in two to four 128-bit SIMD registers or a single wide memory word. Packing all coefficients into one integer word and implementing the geometric product as arithmetic on this single integer has potential advantages for cache efficiency, lock-free concurrent access, FPGA wide-datapath exploitation, and formal analysis.

The fundamental obstacle is inter-field carry ("bleed"). If field i's integer value overflows its b_i-bit slot during a computation, its carry bits propagate into field $i+1$, corrupting it silently. Prior sketches of L-Rep [?] assumed an unbounded accumulator oracle to sidestep this, making the approach mathematically undefined on real hardware.

This paper removes the oracle entirely. We prove, constructively and with complete human-verified proofs, that choosing accumulator widths and storage widths according to our formulae is both *necessary* and *sufficient* for correctness. No prior GA hardware work provides equivalent guarantees.

1.2 What L-Rep Is and Is Not

Scope clarification (added in response to peer review). L-Rep is *not* primarily a throughput-maximisation proposal. Its distinguishing property is *formal correctness*: given quantised inputs, the output error is bounded by a provably tight, pre-computable constant. Raw throughput (1.7×–2.3× over SoA float32) is a secondary benefit. Prior GA accelerators (CliffordALU5 [?], quadruple-based [?], CliffoSor [?]) achieve higher throughput (4–23×) but provide no such guarantee; L-Rep and those systems target different requirements and are complementary.

Specifically, L-Rep is valuable when:

- a formal, pre-computable error bound is required (safety-critical robotics, certified avionics, hardware formal verification);
- lock-free atomic multivector access is needed (real-time concurrent GA);
- bit-exact quantisation-aware training of Clifford neural networks [?] is desired;
- extremely constrained FPGA resources demand minimal bit budgets.

1.3 Problem Statement

Let $\mathbb{G}(p, q, r)$ be the geometric algebra over $\mathbb{R}^{p+q+r}$ with $n = p + q + r$ generators, $m = 2^n$ basis blades $\{e_0, e_1, \ldots, e_{m-1}\}$. A multivector $A = \sum_i a_i e_i$ is encoded as the coefficient vector

$(a_0, \ldots, a_{m-1}) \in \mathbb{R}^m$. The geometric product $C = A \cdot B$ satisfies:

$$c_k = \sum_{i=0}^{m-1} s(i,\, k \oplus i)\, a_i\, b_{k \oplus i}, \tag{1}$$

where $s(i,j) \in \{+1, -1, 0\}$ is the sign from the Cayley table of $\mathbb{G}(p,q,r)$, and $\oplus$ denotes bitwise XOR on blade indices.

Goal. Define a packing map $\Phi_{\mathcal{L}} : \mathbb{R}^m \to \mathbb{Z}_{\geq 0}$, a finite-precision arithmetic procedure `LMUL` on packed integers, and prove that $\Phi_{\mathcal{L}}^{-1}(\texttt{LMUL}(\Phi_{\mathcal{L}}(A), \Phi_{\mathcal{L}}(B))) \approx C$ with *explicit, pre-computable, tight* error bounds. Additionally, derive *minimal* bit widths $\{b_i\}$ and accumulator widths $\{w_i\}$ that prevent any carry overflow.

1.4 Summary of Contributions

Eight contributions, each with a complete proof or validated implementation:

C1. Finite-precision approximation theorem with explicit error decomposition (§**??**).

C2. Tight, necessary-and-sufficient no-bleed conditions (§**??**).

C3. Exact worst-case accumulator growth for arbitrary DAGs (§**??**).

C4. Segmented correctness with integer amplification matrices (§**??**).

C5. Probabilistic overflow bound under documented independence assumption, with correlated-input degradation bound (§**??**).

C6. Optimal scale selection for fixed bit budget (§**??**).

C7. Fixed-point vs. posit/quire accumulator size comparison (§**??**).

C8. **Sparse L-Rep**: $O(\binom{n}{\kappa} b)$ bit budget for grade-κ multivectors (§**??**). **New.**

1.5 Paper Organisation

Section **??** gives comprehensive related work. Section **??** covers GA preliminaries. Section **??** defines the L-Rep model. Section **??** proves all eight theorems. Section **??** gives algorithms. Section **??** describes the hardware architecture with synthesisable RTL. Section **??** gives empirical validation. Section **??** discusses limitations, comparisons, and future work. Section **??** concludes.

2 Related Work

2.1 Geometric Algebra Software Libraries

GA software libraries represent multivectors as arrays of floating-point scalars. Gaalop [**?**] and Gaigen2 [**?**] perform compile-time optimisation (grade projection, zero-elimination) and can emit SIMD-optimised C++ or FPGA code. Versor [**?**] uses C++ expression templates. GATL [**?**] is a header-only C++ template library. clifford [**?**] is a Python library for prototyping. *None* of these libraries pack coefficients into a single integer word, and none provide formal finite-precision error guarantees.

2.2 Formal Floating-Point and Fixed-Point Analysis Tools

The formal analysis of finite-precision arithmetic is a mature field outside GA. Tools most relevant to our work:

Gappa [?] is a proof assistant for floating-point and fixed-point programs that generates Coq certificates. It handles straight-line programs with rounding operators and can prove error bounds automatically. **Fluctuat** [?] uses abstract interpretation (affine interval arithmetic) to bound rounding errors in C programs. **MPFI** [?] provides multi-precision interval arithmetic. **Precimonious** [?] is a tool that searches for mixed-precision configurations minimising bit usage for a target error. **FPTaylor** [?] uses a Taylor-form sound enclosure to bound round-off errors.

Positioning relative to L-Rep. These tools are general-purpose but are not adapted to the XOR-indexed convolution structure of GA products, which has m^2 terms with alternating signs determined by a non-standard Cayley table. Applying Gappa to a fully-unrolled GA product for $n = 5$ ($m = 32$, up to $32^2 = 1024$ terms per field) would require an enormously large input program; runtime would be impractical. L-Rep's Theorem **??** provides the same result—tight worst-case bounds—but specifically for the GA convolution structure, in $O(m^2)$ per product node. Connecting L-Rep's bounds to Gappa/Coq certificates for the RTL is future work (§**??**).

2.3 Hardware GA Accelerators

Table **??** summarises the hardware GA landscape.

Table 1: Hardware GA implementations compared to L-Rep. Published throughput numbers from original papers; "—" means not reported. *Formal error guarantee* means a pre-computable, provably tight bound exists for every input within specification.

System	Algebra	Platform	Speedup†	Formal err. guar.	Key property
CliffordALU5 [?]	$\mathbb{G}(3,0,1)$	Virtex-5	4–5×	No	SoC integration; app study
Quadruple-based [?]	$\mathbb{G}(p,q,0)$	Virtex-6	23× (prods)	No	Fixed 4-blade packing
CliffoSor [?]	$\mathbb{G}(4,1,0)$	Stratix-IV	5–20×	No	Blade-sorted datapath
GA-FU [?]	$\mathbb{G}(3,0,0)$	ASIC	8–12×	No	Custom silicon
Breuils et al. [?]	$\mathbb{G}(9,6,0)$	Cyclone V	3–6×	No	Large-algebra focus
L-Rep (this work)	Any $\mathbb{G}(p,q,r)$	Artix-7	1.7–2.3×	**Yes**	Single-integer packing; formal correctness; atomic r/w

† Speedup over struct-of-arrays float32 on same platform, as reported in respective papers.

Why does L-Rep have lower throughput? CliffordALU5 and CliffoSor are highly optimised for throughput, exploit grade sparsity at compile time, and use the full DSP grid of their target FPGAs without formal overhead. L-Rep's conservative accumulator widths (Theorem **??**) ensure no overflow under *any* input within specification—this conservatism costs bits and, consequently, DSP resources. For applications requiring formal guarantees (safety-critical systems, formally verified hardware), this tradeoff is necessary and desirable. For maximum-throughput applications without formal requirements, CliffordALU5 or CliffoSor remain better choices. Section **??** analyses the design-space tradeoff quantitatively.

2.4 Packed and Mixed-Radix Representations

Mixed-radix number systems [?] and Chinese Remainder Theorem (CRT) / Residue Number System (RNS) [?] representations pack multiple values into one word. RNS uses modular residues: value v is stored as $(v \bmod p_1, v \bmod p_2, \ldots)$ for coprime moduli $\{p_k\}$. Operations are component-wise, and overflow-free bounds come from the product $\prod p_k$.

Key distinction from L-Rep. L-Rep uses *additive positional packing*: field i occupies bits $[o_i, o_i + b_i - 1]$ with scale factor σ_i. The geometric product is *not* component-wise; it is a cross-field convolution (**??**). The no-overflow conditions for RNS (residue rings) do not transfer: in RNS, each modulus is independent; in L-Rep, the product of two packed words mixes all fields together. Our no-bleed theorem (Thm. **??**) is the L-Rep analogue of RNS no-overflow, derived from scratch for the GA convolution structure.

2.5 Geometric Deep Learning and Clifford Neural Networks

Recent work on geometric deep learning uses GA structure in neural network architectures [?, ?]. Clifford Group Equivariant Neural Networks [?] and Clifford Layers [?] represent feature vectors as GA multivectors and use GA products (geometric, inner, outer) as learned layers. For efficient inference, these networks require quantised multivectors, but no prior work provides a principled quantisation scheme for GA-structured layers.

L-Rep as a quantisation framework for Clifford nets. Theorem **??** and Theorem **??** directly provide optimal scale selection and error bounds for quantised Clifford layers. Theorem **??** (Sparse L-Rep) reduces memory by 4–8× for grade-structured layers. This connection is explored in Section **??**.

2.6 Comparison Summary

Table **??** positions L-Rep's seven theoretical properties against the landscape.

Table 2: Property comparison: L-Rep vs. representative prior works. ✓ = provided; ˜ = partial; × = not provided.

Property	L-Rep	CliffordALU5	Gaalop	RNS/CRT	Gappa
GA multivector focus	✓	✓	✓	×	×
Single-integer packing	✓	×	×	˜	×
Formal error bound	✓	×	×	×	✓
No-bleed NSC proved	✓	×	×	˜	✓
Tight witness inputs	✓	×	×	×	×
Sparse support	✓	˜	✓	×	×
Lock-free atomic r/w	✓	×	×	×	×
GDL quantisation ready	✓	×	×	×	×

3 Geometric Algebra Preliminaries

Definition 3.1 (Geometric Algebra $\mathbb{G}(p, q, r)$)**.** Let $V = \mathbb{R}^n$ with $n = p + q + r$. Choose an orthonormal basis $\{e_1, \ldots, e_n\}$ with $e_i^2 = +1$ for $i \leq p$, $e_i^2 = -1$ for $p < i \leq p + q$, $e_i^2 = 0$ for $i > p + q$. The geometric algebra $\mathbb{G}(p, q, r)$ is the 2^n-dimensional associative algebra generated by $\{e_1, \ldots, e_n\}$ with these squaring rules and $e_i e_j + e_j e_i = 0$ for $i \neq j$. Basis blades are indexed

by subsets $I \subseteq \{1, \ldots, n\}$; we identify I with its characteristic binary integer $0 \le i \le m-1$ by setting bit $k-1$ if $k \in I$.

Definition 3.2 (Cayley table and sign function)**.** For basis blades e_i, e_j, define $e_i e_j = s(i,j)\, e_{i \oplus j}$ where $i \oplus j$ is bitwise XOR and $s(i,j) \in \{+1, -1, 0\}$. The sign is

$$s(i,j) = (-1)^{c(i,j)} \prod_{k:\, \text{bit } k \in i \cap j} e_k^2, \tag{2}$$

where $c(i,j) = \sum_{a<b,\, a \in i,\, b \in j} 1$ counts the reorderings needed to sort the concatenated index sequence. In degenerate algebras ($r > 0$), $s(i,j) = 0$ if any null generator appears twice.

Lemma 3.1 (Sign computation)**.** *$s(i,j)$ is computed in $O(n^2)$ time by the standard bubble-sort algorithm on bit indices. For $n \le 6$ ($m \le 64$), the full $m \times m$ sign table fits in ≤ 512 bytes.*

Definition 3.3 (Geometric product in coordinates)**.** The geometric product $C = AB$ satisfies (**??**). The outer, inner, and scalar products are grade-projections of the geometric product.

Definition 3.4 (Grade-κ and sparse multivectors)**.** The *grade-κ part* of A, written $\langle A \rangle_\kappa$, is the projection onto the $\binom{n}{\kappa}$-dimensional subspace spanned by blades with exactly κ indices. A multivector is *grade-κ pure* if $A = \langle A \rangle_\kappa$, and k-sparse if at most k blade coefficients are nonzero. Motors in $\mathbb{G}(3,0,1)$ are even-grade: $A \in \langle A \rangle_0 \oplus \langle A \rangle_2 \oplus \langle A \rangle_4$, occupying $\binom{4}{0} + \binom{4}{2} + \binom{4}{4} = 1 + 6 + 1 = 8$ out of $m = 16$ blades.

4 The L-Rep Finite-Precision Model

4.1 Key Definitions

Definition 4.1 (Mixed-radix field layout)**.** A *mixed-radix field layout* is the representation of multiple integer values $(q_0, q_1, \ldots, q_{m-1})$ as a single non-negative integer $W = \sum_{i=0}^{m-1} (q_i \bmod 2^{b_i}) \cdot 2^{o_i}$, where $o_i = \sum_{j<i} b_j$ is the bit offset of field i and b_i is the field width. The term "mixed-radix" distinguishes this from uniform-width packing: different fields may have different widths b_i. This is *not* a Residue Number System: values are positional, not modular residues, and the fields interact through the GA product.

Definition 4.2 (Oracle assumption (eliminated))**.** In [**?**], the term *unbounded accumulator oracle* referred to the assumption that the integer accumulator for each field can hold an arbitrarily large value—effectively, infinite-precision integers per field. Under this assumption, no carry ever bleeds from field i into field $i+1$. The oracle assumption is **eliminated in this paper**: we derive explicit finite widths w_i that are both necessary and sufficient to prevent carry bleed for all inputs within specification.

Definition 4.3 (L-layout)**.** An L-layout is a tuple $\mathcal{L} = \big((b_0, s_0, \sigma_0), \ldots, (b_{m-1}, s_{m-1}, \sigma_{m-1})\big)$ where for each field i:

- $b_i \in \mathbb{Z}_{>0}$ is the storage width in bits;
- $s_i \in \{\text{unsigned}, \text{two}'\text{scomplement}\}$ is the signedness;
- $\sigma_i \in \mathbb{Q}_{>0}$ is the scale factor, so raw integer q_i represents real value $\hat{a}_i = q_i / \sigma_i$.

The bit offset for field i is $o_i = \sum_{j<i} b_j$ and the total word size is $B = \sum_i b_i$ bits.

Definition 4.4 (Quantisation map)**.** Quantize$(x, \sigma, b, \text{sgn})$ returns:

$$q = \begin{cases} \text{round}(x\sigma) \text{ clipped to } [0, 2^b - 1] & \text{if unsigned,} \\ \text{round}(x\sigma) \text{ clipped to } [-2^{b-1}, 2^{b-1} - 1] & \text{if signed.} \end{cases}$$

"round" is round-half-to-even. When no clipping occurs: $|\delta_i| := |x - q/\sigma| \leq 1/(2\sigma)$. When clipping occurs: $|\delta_i| = |x| - (2^{b-1} - 1)/\sigma > 0$; Theorem **??** gives conditions under which clipping is prevented.

Definition 4.5 (Packing map $\Phi_{\mathcal{L}}$)**.** Given coefficients $(a_0, \ldots, a_{m-1})$ and layout $\mathcal{L}$:

$$\Phi_{\mathcal{L}}(A) := \sum_{i=0}^{m-1} \big(\text{Quantize}(a_i, \sigma_i, b_i, s_i) \bmod 2^{b_i}\big) \cdot 2^{o_i} \in \mathbb{Z}_{\geq 0}.$$

The unpacking map $\Phi_{\mathcal{L}}^{-1}$ extracts field i by $q_i = \lfloor \Phi_{\mathcal{L}}(A)/2^{o_i} \rfloor \bmod 2^{b_i}$, applies two's-complement sign extension if $s_i =$ signed, and returns $\hat{a}_i = q_i/\sigma_i$.

Lemma 4.1 (Packing correctness)**.** *For any A within the representable range (no clipping), $\Phi_{\mathcal{L}}^{-1}(\Phi_{\mathcal{L}}(A))$ recovers $\hat{A} = (\hat{a}_0, \ldots, \hat{a}_{m-1})$ with $|a_i - \hat{a}_i| \leq 1/(2\sigma_i)$ for all i.*

Proof. Field i in $\Phi_{\mathcal{L}}(A)$ occupies bits $[o_i, o_i + b_i - 1]$. By Definition **??**, fields are non-overlapping (strict partition of bit positions). The masking in $\Phi_{\mathcal{L}}^{-1}$ isolates exactly the b_i bits placed by $\Phi_{\mathcal{L}}$ for field i. The quantisation error bound follows from Definition **??** in the no-clipping case. □

Definition 4.6 (Local accumulator)**.** For field k, a *local accumulator* is a signed integer register of width $w_k \geq b_k$ bits that computes intermediate results *exactly* (no overflow within w_k bits). Accumulators are logically independent per field; physically, they may share DSP resources via time-multiplexing.

Assumption 4.1 (Finite-range inputs)**.** *Every real-valued input coefficient a_i satisfies $a_i \in [L_i, U_i]$ with L_i, U_i known at compile time. We define $M_i = \max(|L_i|, |U_i|)$ and the input integer bound $Q_i^{(0)} = \lceil \sigma_i M_i \rceil$.*

Remark on constrained inputs (normalization-constrained GA elements). Assumption **??** treats input fields as *independently* bounded. In many GA applications, inputs satisfy additional algebraic constraints: for example, PGA motors must satisfy $MM^\dagger = 1$ (unit-normalization), which creates correlations between blade coefficients. Under normalization, the worst-case bounds $Q_k^{(\text{gamul})}$ from Theorem **??** are conservative (achievable only if all fields can be simultaneously maximized with consistent signs, which normalization may preclude). Theorem **??** therefore gives *valid but potentially over-conservative* bounds for normalised inputs; tighter analysis via constrained interval arithmetic [**?**] is future work. This conservatism increases b_i beyond the strict minimum for normalised inputs, but never produces incorrect results.

Definition 4.7 (L-Rep computation DAG)**.** A computation on L-Rep words is a DAG $G = (V, E)$ where each node $v \in V$ is one of: `input`, `add`, `sub`, `scalarmul`(α), `gamul`. Edges carry L-words. We write $Q_i^{(v)}$ for the worst-case absolute integer magnitude at field i at the output of node v.

5 Main Theorems

5.1 Theorem 1: Finite-Precision Approximation

Terminology note (revised from v1 in response to peer review). The original draft called this result a "finite-precision isomorphism." This terminology is incorrect: a mathematical isomorphism requires a bijective, structure-preserving map with zero error. The correct term is *finite-precision approximation*. We apologise for the confusion in the prior draft.

Theorem 5.1 (Finite-precision approximation and error decomposition)**.** *Let $\mathcal{L}$ be an L-layout with storage bits $\{b_i\}$ and scales $\{\sigma_i\}$. Let A, B be multivectors packed via $\Phi_{\mathcal{L}}$. Let $\texttt{LMUL}(\Phi_{\mathcal{L}}(A), \Phi_{\mathcal{L}}(B))$ implement the L-Rep geometric product using local accumulators of widths $\{w_k\}$ chosen by Algorithm* **??**. *Then the decoded result satisfies:*

$$\left|\Phi_{\mathcal{L}}^{-1}(\texttt{LMUL}(\Phi_{\mathcal{L}}(A), \Phi_{\mathcal{L}}(B)))_k - c_k\right| \leq \varepsilon_k^{(\text{in})} + \varepsilon_k^{(\text{quant})}, \tag{3}$$

where the terms are:

$$\varepsilon_k^{(\text{in})} = \sum_{i=0}^{m-1} \left(|\hat{a}_i| \cdot \frac{1}{2\sigma_{k\oplus i}} + |\hat{b}_{k\oplus i}| \cdot \frac{1}{2\sigma_i} + \frac{1}{4\sigma_i \sigma_{k\oplus i}} \right), \tag{4}$$

$$\varepsilon_k^{(\text{quant})} \leq \frac{1}{2\sigma_k}. \tag{5}$$

The intermediate accumulation term $\varepsilon_k^{(\text{round})}$ is exactly zero *when accumulator widths satisfy Theorem* **??**.

Proof. Step 1: Quantised inputs. Let $\hat{a}_i = q_i^A/\sigma_i$ and $\hat{b}_j = q_j^B/\sigma_j$ with $q_i^A = \text{Quantize}(a_i, \sigma_i, b_i, s_i)$. Write $a_i = \hat{a}_i + \delta_i^A$ and $b_j = \hat{b}_j + \delta_j^B$ with $|\delta_i^A| \leq 1/(2\sigma_i)$, $|\delta_j^B| \leq 1/(2\sigma_j)$ (by Lemma **??**, assuming no clipping).

Step 2: Error expansion. The exact product coefficient is:

$$\begin{aligned} c_k &= \sum_i s(i, k\oplus i)(\hat{a}_i + \delta_i^A)(\hat{b}_{k\oplus i} + \delta_{k\oplus i}^B) \\ &= \underbrace{\sum_i s(i, k\oplus i)\, \hat{a}_i\, \hat{b}_{k\oplus i}}_{\tilde{c}_k} + \underbrace{\sum_i s(i, k\oplus i)(\delta_i^A\, \hat{b}_{k\oplus i} + \hat{a}_i\, \delta_{k\oplus i}^B + \delta_i^A\, \delta_{k\oplus i}^B)}_{E_k^{(\text{in})}}. \end{aligned} \tag{6}$$

Step 3: Input error bound. Since $|s(i,j)| \leq 1$, $|\hat{a}_i| = |q_i^A|/\sigma_i \leq M_i$ (bounded by Assumption **??**), and similarly for $\hat{b}$:

$$|E_k^{(\text{in})}| \leq \sum_i \left(\frac{|\hat{b}_{k\oplus i}|}{2\sigma_i} + \frac{|\hat{a}_i|}{2\sigma_{k\oplus i}} + \frac{1}{4\sigma_i \sigma_{k\oplus i}} \right) = \varepsilon_k^{(\text{in})}.$$

Step 4: Integer accumulation. The L-ALU computes $\tilde{C}_k = \sum_i s(i, k\oplus i)\, q_i^A\, q_{k\oplus i}^B$ using exact integer arithmetic. By Theorem **??**, width w_k satisfies $|\tilde{C}_k| \leq 2^{w_k - 1} - 1$ under Assumption **??**, so no overflow occurs: $\varepsilon_k^{(\text{round})} = 0$.

Step 5: Output quantisation. The accumulator value is quantised to storage: $q_k^C = \text{Quantize}(\tilde{C}_k/\sigma_k,\, \sigma_k,\, b_k,\, s_k)$ (after dividing by σ_k to convert from integer to real scale). This introduces $|\varepsilon_k^{(\text{quant})}| \leq 1/(2\sigma_k)$.

Step 6: Triangle inequality. $|c_k - \Phi_{\mathcal{L}}^{-1}(\cdots)_k| \leq |E_k^{(\text{in})}| + |\varepsilon_k^{(\text{quant})}|$, giving (**??**). □

Corollary 5.1 (Exact integer case)**.** *If all input coefficients are integer multiples of $1/\sigma_i$ and $\sigma_i \in \mathbb{Z}_{>0}$, then $\delta_i^A = \delta_j^B = 0$, so $\varepsilon_k^{(\text{in})} = 0$. L-Rep then computes the exact geometric product up to output quantisation $\varepsilon_k^{(\text{quant})} \leq 1/(2\sigma_k)$.*

Remark 5.1 (Comparison with Gappa-style bounds). Gappa [?] and FPTaylor [?] produce similar error-decomposition bounds for floating-point programs by abstracting each rounding operation. Theorem **??** is the fixed-point analogue for the GA XOR-convolution structure. The decomposition (**??**) is fully constructive and matches what these tools would derive if applied to the fully-unrolled GA product (at vastly lower analysis cost for large m).

Remark 5.2 (Scaling behaviour). From (**??**), input quantisation error scales as $O(mM/\sigma)$ where $M = \max_i M_i$, $\sigma = \min_i \sigma_i$. Increasing σ_i (more bits per unit range) decreases all error terms proportionally, at the cost of larger b_i. Theorem **??** makes this tradeoff optimal.

5.2 Theorem 2: No-Bleed — Tight Necessary and Sufficient Conditions

Definition 5.1 (Inter-field carry bleed)**.** L-Rep word W experiences *inter-field bleed at field i* if the arithmetic computation of W's i-th field produces an integer $|q_i| \geq 2^{b_i-1}$ (signed overflow), causing carry to propagate into the storage bits of field $i+1$.

Theorem 5.2 (No-bleed: necessary and sufficient conditions)**.** *Let $X_i = \max_{v \in V} Q_i^{(v)}$ be the globally worst-case absolute integer magnitude at field i. Then:*

1. ***(Sufficiency)*** *If $b_i \geq \lceil \log_2(X_i + 1) \rceil + 1$ (signed), no inter-field bleed occurs under any execution on inputs satisfying Assumption* **??**.
2. ***(Necessity)*** *If $b_i < \lceil \log_2(X_i+1) \rceil + 1$ (signed), there exists an input within Assumption* **??** *achieving $|q_i| = X_i \geq 2^{b_i-1}$, triggering bleed.*
3. ***(Minimality)*** *The formula $b_i^* = \lceil \log_2(X_i + 1) \rceil + 1$ (signed) is the minimum bit width satisfying no-bleed.*

Proof. Part 1 (Sufficiency). By Theorem **??**, $|q_i| \leq X_i$ for all i throughout any execution. For signed two's complement, the representable range is $[-2^{b_i-1},\ 2^{b_i-1} - 1]$. No-bleed requires $X_i \leq 2^{b_i-1} - 1$, i.e., $2^{b_i-1} \geq X_i + 1$, i.e., $b_i \geq \lceil \log_2(X_i + 1) \rceil + 1$. This is exactly the choice; hence no overflow, no bleed.

Part 2 (Necessity). If $b_i = \lceil \log_2(X_i + 1) \rceil$, then $2^{b_i-1} \leq X_i$, so the two's-complement range $[-2^{b_i-1}, 2^{b_i-1} - 1]$ does not cover X_i. By Theorem **??**, Part 2 (tight bounds), there exists an admissible input achieving $|q_i| = X_i$. At this value the b_i-bit field overflows, causing bleed.

Part 3 (Minimality). Part 1 establishes b_i^* is sufficient; Part 2 establishes $b_i^* - 1$ is not. Hence b_i^* is minimal. □

5.3 Theorem 3: Accumulator Growth Algebra

Theorem 5.3 (Exact worst-case bound propagation)**.** *Define $Q_i^{(v)}$ as the supremum of $|q_i|$ over all inputs within Assumption* **??** *at node v. These satisfy:*

$$Q_i^{(\text{input})} = Q_i^{(0)}, \tag{7}$$

$$Q_i^{(\text{add})} = Q_i^{(v_1)} + Q_i^{(v_2)}, \tag{8}$$

$$Q_i^{(\text{sub})} = Q_i^{(v_1)} + Q_i^{(v_2)}, \tag{9}$$

$$Q_i^{(\text{smul},\alpha)} = \lceil |\alpha| \rceil \cdot Q_i^{(v)}, \tag{10}$$

$$Q_k^{(\text{gamul})} = \sum_{i=0}^{m-1} Q_i^{(v_1)} \cdot Q_{k \oplus i}^{(v_2)}. \tag{11}$$

Part 1 (Correctness): *These are valid upper bounds for all inputs within Assumption* **??**.

Part 2 (Tightness for unconstrained inputs): *For each node v and field k, if inputs are unconstrained (i.e., each field is independently bounded as in Assumption* **??** *with no algebraic relations between fields), there exists an input vector that achieves $|q_k| = Q_k^{(v)}$.*

Part 3 (Conservatism for constrained inputs): *If inputs satisfy additional algebraic constraints (e.g., motor normalization $MM^\dagger = 1$), the bounds remain valid upper bounds but may not be achieved. The gap can be quantified via constrained interval arithmetic.*

Proof. Part 1 (Correctness of recurrences).

(**??**): $|q_i^{(0)}| \le Q_i^{(0)}$ by Assumption **??**.

(**??**): $|q_i^{(v_1)} + q_i^{(v_2)}| \le |q_i^{(v_1)}| + |q_i^{(v_2)}| \le Q_i^{(v_1)} + Q_i^{(v_2)}$ by triangle inequality.

(**??**): $|q_i^{(v_1)} - q_i^{(v_2)}| \le Q_i^{(v_1)} + Q_i^{(v_2)}$ by triangle inequality.

(**??**): $|\alpha q_i^{(v)}| \le |\alpha| Q_i^{(v)} \le \lceil |\alpha| \rceil Q_i^{(v)}$.

(**??**): By (**??**),

$$|q_k^{(\text{gamul})}| = \left| \sum_i s(i, k \oplus i)\, q_i^{(v_1)}\, q_{k\oplus i}^{(v_2)} \right| \le \sum_i |q_i^{(v_1)}|\, |q_{k\oplus i}^{(v_2)}| \le \sum_i Q_i^{(v_1)}\, Q_{k\oplus i}^{(v_2)}.$$

(The bound on the sum uses $|s(i,j)| \le 1$.)

Part 2 (Tightness for unconstrained inputs). We construct witness inputs by induction on the DAG.

Base: For an input node, choose $a_i = M_i$; then $q_i = Q_i^{(0)}$.

Add/sub: By induction, independent sub-DAGs achieve $q_i^{(v_1)} = Q_i^{(v_1)}$ and $q_i^{(v_2)} = Q_i^{(v_2)}$ simultaneously (since inputs to distinct sub-DAGs are independent). The sum achieves $Q_i^{(v_1)} + Q_i^{(v_2)}$.

GA multiply: We need all terms $s(i, k\oplus i)\, q_i^{(v_1)}\, q_{k\oplus i}^{(v_2)}$ to be non-negative. Set $q_i^{(v_1)} = Q_i^{(v_1)}$ (positive maximum). For each i, choose the sign of $q_{k\oplus i}^{(v_2)}$ to match $\text{sign}(s(i, k \oplus i))$: if $s(i, k \oplus i) > 0$, set $q_{k\oplus i}^{(v_2)} = +Q_{k\oplus i}^{(v_2)}$; if $s(i, k \oplus i) < 0$, set $q_{k\oplus i}^{(v_2)} = -Q_{k\oplus i}^{(v_2)}$ (feasible because the field range is symmetric for signed two's complement). Then each term is $+Q_i^{(v_1)} Q_{k\oplus i}^{(v_2)}$, and the sum achieves $\sum_i Q_i^{(v_1)} Q_{k\oplus i}^{(v_2)}$.

Part 3 (Conservatism for constrained inputs). Under normalization $MM^\dagger = 1$, the set of feasible input vectors is a manifold strictly contained in the hypercube $\prod_i [-M_i, M_i]$. The witness construction in Part 2 requires choosing signs of each field independently, which may not be feasible on this manifold. The bounds (**??**) remain valid because Part 1 only uses the unconstrained upper bound. They are conservative because the witness may lie outside the normalization manifold. □

Corollary 5.2 (Accumulator width formula)**.** *To represent $q_k^{(\text{gamul})}$ without overflow, the accumulator must be:*

$$w_k = \left\lceil \log_2 \left(\sum_{i=0}^{m-1} Q_i^{(v_1)}\, Q_{k\oplus i}^{(v_2)} + 1 \right) \right\rceil + 1 \quad \textit{(signed)}. \tag{12}$$

This is $O(m)$ per GA product node and $O(m \cdot |V|)$ total.

5.4 Theorem 4: Segmented Correctness

Definition 5.2 (DAG segmentation)**.** A *segmentation* of DAG G is a partition $V = S^{(1)} \cup \cdots \cup S^{(p)}$ where each $S^{(t)}$ is a connected sub-DAG. At each segment boundary t, a requantisation $\texttt{Reqt} : \mathbb{Z}^m \to \mathbb{Z}^m$ maps accumulator integers to b_i-bit storage integers, introducing $|\varepsilon_i^{(t)}| \leq 1$ integer unit (one-bit truncation).

Definition 5.3 (Amplification matrix)**.** For segment $S^{(t)}$, define the amplification matrix $K^{(t)} \in \mathbb{Z}_{\geq 0}^{m \times m}$ where $K_{r,i}^{(t)}$ is the supremum of $|\partial q_r^{(\text{out})} / \partial q_i^{(\text{in})}|$ over all executions within $S^{(t)}$.

Lemma 5.1 (Amplification matrix computation)**.** *For a linear segment (add, sub, scalarmul), $K^{(t)}$ is the product of the coefficient matrices: add/sub give $K = 2I$ (diagonal); scalarmul α gives $K = |\alpha| I$. For a segment containing one GA product with the other operand having field magnitudes $Q_j^{(\text{other})}$: $K_{r,i}^{(t)} = Q_{r \oplus i}^{(\text{other})}$.*

Theorem 5.4 (Segmented finite-precision correctness)**.** *For a DAG partitioned into p segments with requantisation at each boundary, and with composed amplification matrix $K^{(t:p)} = K^{(p)} K^{(p-1)} \cdots K^{(t+1)}$, the final real-valued error at field r satisfies:*

$$|\Delta a_r^{(\text{final})}| \leq \frac{1}{\sigma_r} \sum_{t=1}^{p-1} \sum_i (K^{(t:p)})_{r,i} + \varepsilon_r^{(\text{in})}. \tag{13}$$

Proof. By backward induction on segment index.

Base ($t = p$): The segment-p computation is exact by Theorem **??** (accumulators sized for no overflow within the segment). Requantisation at boundary $p-1$ introduces integer error $\delta^{(p-1)}$ with $|\delta_i^{(p-1)}| \leq 1$.

Inductive step: The segment-t operator (linear or GA) propagates integer error $\delta^{(t)}$ from its input to its output with amplification $K^{(t+1)} \delta^{(t)}$ (element-wise absolute value), by Lemma **??**.

Composition: Error introduced at boundary t propagates through segments $t+1, \ldots, p$ with amplification $K^{(t+1:p)}$. The final integer error at field r is:

$$|\Delta q_r^{(\text{final})}| \leq \sum_{t=1}^{p-1} \|(K^{(t:p)})_{r,\cdot}\|_1.$$

Dividing by σ_r converts to real error, giving the first term of (**??**). Adding the input quantisation terms from Theorem **??** completes the proof. □

5.5 Theorem 5: Probabilistic Overflow Bound

Theorem 5.5 (Bernstein probabilistic overflow bound)**.** *Let $\{X_j\}_{j=1}^N$ be zero-mean independent random variables with $|X_j| \leq R$ a.s. and $\sum_j \text{Var}(X_j) = V_{\text{tot}}$. Let $S = \sum_j X_j$. Then for all $T > 0$:*

$$\Pr(|S| \geq T) \leq 2 \exp\left(-\frac{T^2/2}{V_{\text{tot}} + RT/3} \right). \tag{14}$$

*Applied to the accumulation in field k: each term $X_j = s(i_j, k \oplus i_j)\, q_{i_j}^A\, q_{k \oplus i_j}^B$ satisfies $|X_j| \leq Q_{\max}^2$. Under the independence assumption (Assumption **??** below), the overflow probability at threshold $T = 2^{w_k - 1}$ decays doubly-exponentially in w_k.*

Assumption 5.1 (Field independence)**.** *The input fields q_i^A and q_j^B are mutually independent across all i, j. This holds for white-noise sensor inputs (where each field component is an independent noise source) but does* not *hold for normalization-constrained inputs (motors, rotors) or for inputs with physically coupled coordinates.*

Proof. Equation (**??**) is Bernstein's inequality [**?**]. Under Assumption **??**, the products $X_j = s(i_j, k \oplus i_j)\, q^A_{i_j}\, q^B_{k\oplus i_j}$ are functions of disjoint independent pairs of fields, hence independent. Zero-mean follows by assuming mean-subtracted inputs (a scale-selection design choice from Theorem **??**). Applying (**??**) with $R = Q^2_{\max}$ and $V_{\text{tot}} = N\,\mathrm{Var}(X_j)$ gives the result. Overflow iff $|S| \geq 2^{w_k-1}$; the probability decays as $\exp(-\Theta(4^{w_k}/(NQ^4_{\max})))$. □

Theorem 5.6 (Correlated-input degradation bound)**.** *Suppose fields are not independent but satisfy* $\mathrm{Cov}(X_j, X_\ell) \leq \rho$ *for all* $j \neq \ell$*. Then:*

$$\Pr(|S| \geq T) \leq 2\exp\left(-\frac{T^2/2}{V_{\text{tot}} + N^2\rho + RT/3}\right). \tag{15}$$

For PGA motors with $|\rho| \leq 1/(2\sigma^2)$ *(arising from unit-normalization at scale* σ*), the extra term* $N^2\rho \leq m^2/(2\sigma^2)$ *is bounded and decreases with* σ*.*

Proof. Replace the variance bound with $\mathrm{Var}(\sum_j X_j) = \sum_j \mathrm{Var}(X_j) + 2\sum_{j<\ell}\mathrm{Cov}(X_j, X_\ell) \leq V_{\text{tot}} + N^2\rho$ and apply Bernstein's inequality with the inflated variance. For PGA motors, the normalization constraint $\sum_i a_i^2 = 1$ implies all coefficients lie on a unit sphere; the covariance between distinct products is bounded by $E[a_i^2 b_j^2] \leq 1/(\sigma_i^2\sigma_j^2)$ (product of variance bounds), giving the stated bound. □

Remark 5.3. For deterministic worst-case inputs (Assumption **??**), Theorem **??** applies and no probabilistic bound is needed. Theorems **??** and **??** serve workloads with noisy or random inputs where the deterministic worst-case bound would require impractically wide accumulators.

5.6 Theorem 6: Quantisation Optimality

Theorem 5.7 (Optimal scale selection)**.** *Given storage width* b_i *and input range* $[-M_i, M_i]$*, the scale* σ_i^* *minimising the worst-case quantisation error subject to no clipping is:*

$$\sigma_i^* = \frac{2^{b_i-1} - 1}{M_i}. \tag{16}$$

This achieves $\varepsilon_i^* = 1/(2\sigma_i^*) = M_i/(2^{b_i} - 2)$*.*

Necessary and sufficient condition for lossless mapping: $\sigma_i a \in \mathbb{Z}$ *for all* $a \in \mathrm{supp}(\mathcal{D}_i)$ *and* $|\sigma_i a| \leq 2^{b_i-1} - 1$*.*

Proof. Error formula. For fixed σ_i and b_i, the quantisation error for any a in the unclipped range is $\leq 1/(2\sigma_i)$. Clipping error is $(|a| - (2^{b_i-1} - 1)/\sigma_i)^+$, zero iff $\sigma_i|a| \leq 2^{b_i-1} - 1$.

Optimisation. To minimise worst-case rounding error $1/(2\sigma_i)$, maximise σ_i subject to the no-clipping constraint $\sigma_i \leq (2^{b_i-1} - 1)/M_i$. Setting σ_i to this maximum gives (**??**).

Lossless condition. Error is exactly zero iff $\sigma_i a \in \mathbb{Z}$ (no rounding) and $|\sigma_i a| \leq 2^{b_i-1} - 1$ (no clipping). Both are necessary and sufficient. □

5.7 Theorem 7: Format Comparison — L-Rep vs. Posit/Quire

Theorem 5.8 (Fixed-point vs. quire accumulator equivalence)**.** *A Gustafson posit quire of width* Q_{bits} *exactly accumulates* N *posit-*P *numbers iff:* $Q_{\text{bits}} \geq P + 2\lceil\log_2 N\rceil + \mathrm{es} + 2$ *[**?**]. For the L-Rep field-*k *accumulator to achieve equivalent exact accumulation of* N *terms of* P*-bit effective precision:*

$$w_k^{(\text{L-Rep})} = P + \lceil\log_2 N\rceil + 1. \tag{17}$$

L-Rep requires $\lceil\log_2 N\rceil + \mathrm{es} + 1$ *fewer bits than a quire.*

Proof. Quire. Carry capacity $\lceil \log_2 N \rceil$ bits above the sum (for N addends), P bits mantissa, es bits exponent range, 2 guard bits (posit standard [**?**]). Total: $P + 2\lceil \log_2 N \rceil + \mathrm{es} + 2$.

L-Rep. In L-Rep all values in field k share scale σ_k: no exponent alignment overhead. The accumulator needs P bits for precision and $\lceil \log_2 N \rceil$ carry bits, plus 1 sign bit. Total: $P + \lceil \log_2 N \rceil + 1$.

Comparison. $Q_{\text{bits}} - w_k^{(\text{L-Rep})} = \lceil \log_2 N \rceil + \mathrm{es} + 1 \geq 1$ for any $\mathrm{es} \geq 0$. □

5.8 Theorem 8: Sparse L-Rep

New contribution (not in v1). Theorem **??** addresses sparse and graded multivectors, which arise in virtually all practical GA applications. It is the primary mechanism by which L-Rep's storage overhead is reduced beyond the 37%–60% of float32 reported in the dense case.

Definition 5.4 (Sparse L-layout)**.** Let $\mathcal{I} \subseteq \{0, \ldots, m-1\}$ be the set of *active blades* (blades known to be non-zero at design time). A *sparse L-layout* $\mathcal{L}_{\mathcal{I}}$ packs only the $|\mathcal{I}|$ active fields. Total word size is $B_{\mathcal{I}} = \sum_{i \in \mathcal{I}} b_i$.

Definition 5.5 (Sparse Cayley table)**.** For active set $\mathcal{I}$, the *sparse sign function* $\tilde{s}(i,j)$ coincides with $s(i,j)$ from (**??**) but is zero for pairs (i,j) where either $i \notin \mathcal{I}$ or $j \notin \mathcal{I}$. The *sparse product result set* is $\mathcal{K}(\mathcal{I}) = \{k \oplus i : i, k \oplus i \in \mathcal{I},\ \tilde{s}(i, k \oplus i) \neq 0\}$.

Theorem 5.9 (Sparse L-Rep bit budget and correctness)**.** *Let A and B be multivectors with active blades $\mathcal{I}_A$ and $\mathcal{I}_B$ respectively. Let $\mathcal{K} = \mathcal{K}(\mathcal{I}_A, \mathcal{I}_B)$ be the set of blades that can have non-zero coefficients in $C = AB$.*

1. ***(Storage reduction)*** *The sparse L-layout for A (or B) uses $B_{\mathcal{I}} = \sum_{i \in \mathcal{I}} b_i$ bits, reducing storage from $B = \sum_{i=0}^{m-1} b_i$ to $B_{\mathcal{I}}/B = |\mathcal{I}|/m$. For grade-$\kappa$ pure multivectors: $|\mathcal{I}| = \binom{n}{\kappa}$, so $B_{\mathcal{I}}/B = \binom{n}{\kappa}/2^n$.*

2. ***(Accumulator reduction)*** *The sparse accumulator for output field $k \in \mathcal{K}$ has width:*

$$w_k^{(\text{sp})} = \left\lceil \log_2 \left(\sum_{\substack{i \in \mathcal{I}_A \\ k \oplus i \in \mathcal{I}_B}} Q_i^{(v_1)} Q_{k \oplus i}^{(v_2)} + 1 \right) \right\rceil + 1. \tag{18}$$

   This equals w_k (the dense case) only when $\mathcal{I}_A = \mathcal{I}_B = \{0, \ldots, m-1\}$.

3. ***(Correctness)*** *Theorems **??** through **??** hold verbatim for the sparse case with $Q_i^{(v)} = 0$ for $i \notin \mathcal{I}$ and the reduced sums (**??**).*

4. ***(Tightness)*** *The bounds (**??**) are tight: there exist admissible inputs (respecting the sparsity pattern) achieving $|q_k| = w_k^{(\text{sp})} - 1$ for $k \in \mathcal{K}$.*

Proof. Part 1. Only $|\mathcal{I}|$ fields are stored; the $m - |\mathcal{I}|$ zero-coefficient fields require no bits. $B_{\mathcal{I}} = \sum_{i \in \mathcal{I}} b_i$ follows directly from Definition **??**. For grade-κ multivectors, $|\mathcal{I}| = \binom{n}{\kappa}$ by Definition **??**, giving the ratio.

Part 2. By Theorem **??**, $Q_i^{(v)} = 0$ for $i \notin \mathcal{I}$ (since those fields are identically zero throughout all executions). Substituting into (**??**):

$$Q_k^{(\text{gamul,sp})} = \sum_{\substack{i \in \mathcal{I}_A \\ k \oplus i \in \mathcal{I}_B}} Q_i^{(v_1)} Q_{k \oplus i}^{(v_2)},$$

and the accumulator formula (**??**) follows from Corollary **??**.

Part 3. Setting $Q_i^{(v)} = 0$ for $i \notin \mathcal{I}$ is a valid specialization of Assumption **??** ($M_i = 0$ for zero fields). All theorems use only the recurrences over the non-zero fields, so they hold with the restricted sums.

Part 4 (Tightness). The witness construction of Theorem **??**, Part 2, applied with only the active fields in $\mathcal{I}$ achieves the maximum for each $k \in \mathcal{K}$. Fields outside $\mathcal{I}$ contribute zero, but the remaining terms are still maximized by the same sign-matching argument. □

Table 3: Sparse L-Rep bit savings for common GA subalgebras ($b_i = 16$ bits per field uniformly; dense B $= m \times 16$ bits).

Algebra	n	m	Subalgebra	$\lvert\mathcal{I}\rvert$	$B_{\mathcal{I}}$ (bits)	Reduction
$\mathbb{G}(3,0,1)$	4	16	Even (motors)	8	128	2×
$\mathbb{G}(3,0,1)$	4	16	Grade-1 (lines)	4	64	4×
$\mathbb{G}(4,1,0)$	5	32	Grade-1 (points)	5	80	6.4×
$\mathbb{G}(4,1,0)$	5	32	Grade-3 (circles)	10	160	3.2×
$\mathbb{G}(4,1,0)$	5	32	Even (versors)	16	256	2×
$\mathbb{G}(3,3,0)$	6	64	Grade-3 (lines)	20	320	3.2×

6 Algorithms

6.1 Algorithm 1: Optimal Bit Allocation (Dense and Sparse)

Algorithm 1 Optimal Bit Allocation for L-Rep (Dense and Sparse)

Require: DAG $G = (V, E)$, input bounds $Q_i^{(0)}$, scale factors σ_i, target error ε, active set $\mathcal{I}$ (or $\emptyset$ for dense)

Ensure: Storage bits $\{b_i\}$, accumulator widths $\{w_v^{(i)}\}$

if $\mathcal{I} = \emptyset$ **then**
  $\mathcal{I} \leftarrow \{0, \ldots, m-1\}$
end if
Phase 1: Forward bound propagation
for each node v in topological order **do**
  if v is input **then**
    $Q_i^{(v)} \leftarrow Q_i^{(0)}$ for $i \in \mathcal{I}$; $Q_i^{(v)} \leftarrow 0$ for $i \notin \mathcal{I}$
  else if v is add/sub **then**
    $Q_i^{(v)} \leftarrow Q_i^{(L)} + Q_i^{(R)}$ for all i
  else if v is scalarmul(α) **then**
    $Q_i^{(v)} \leftarrow \lceil |\alpha| \rceil \cdot Q_i^{(C)}$
  else if v is gamul **then**
    for each k with $k \in \mathcal{K}$ (output active set) **do**
      $Q_k^{(v)} \leftarrow \sum_{i \in \mathcal{I}_L,\, k \oplus i \in \mathcal{I}_R} Q_i^{(L)} \cdot Q_{k \oplus i}^{(R)}$
    end for
    $Q_k^{(v)} \leftarrow 0$ for $k \notin \mathcal{K}$
  end if
  $w_i^{(v)} \leftarrow \lceil \log_2(Q_i^{(v)} + 1) \rceil + 1$ for $i \in \mathcal{I}$
end for
Phase 2: Global maximum
$X_i \leftarrow \max_{v \in V} Q_i^{(v)}$ for $i \in \mathcal{I}$
Phase 3: Storage bits
$b_i \leftarrow \lceil \log_2(X_i + 1) \rceil + 1$ for $i \in \mathcal{I}$; $b_i \leftarrow 0$ for $i \notin \mathcal{I}$
Phase 4: Error check
Compute ε_k using Theorem **??**
if $\varepsilon_k > \varepsilon$ for some k **then**
  Increase σ_k by a factor of 2; $Q_k^{(0)} \leftarrow \lceil \sigma_k M_k \rceil$; go to Phase 1 {This loop terminates: each doubling reduces $\varepsilon_k^{(\text{quant})}$ by half; at most $\lceil \log_2(\varepsilon_k^{(0)}/\varepsilon) \rceil$ iterations.}
end if
return $\{b_i\}_{i \in \mathcal{I}}$, $\{w_v^{(i)}\}$

Complexity. Phase 1 is $O(|\mathcal{I}|^2|V|)$ (dominated by GA product nodes, each $O(|\mathcal{I}|^2)$). Dense: $O(m^2|V|)$. Sparse grade-κ: $O\big(\binom{n}{\kappa}^2|V|\big)$, which is smaller by $(\binom{n}{\kappa}/2^n)^2$ relative to the dense case. For $n = 5$, grade-1 ($|\mathcal{I}| = 5$, dense $m = 32$): $25/1024 \approx 2.4\%$ of the dense work.

6.2 Algorithm 2: Greedy Segmentation with Error Budget

Algorithm 2 Greedy Segmentation with Error Budget

Require: DAG G, global error budget $\varepsilon_{\max}$, growth threshold τ
Ensure: Segment boundaries $\{T_1, \ldots, T_{p-1}\}$

```
Run Algorithm ?? with p = 1 (no boundaries)
if max_i b_i ≤ B_max (bit budget fits) then
    return ∅
end if
Compute amplification matrix K^(t) for each candidate segment
Initialize: t ← 1, seg_start = 0, running Q ← Q^(0)
for each node v in topological order do
    R ← max_{i∈I} Q_i^(v) / (Q_i^(seg_start) + 1)
    if R > τ then
        Place segment boundary before v; t ← t + 1
        Compute amplification contribution via Theorem ??
        if total error > ε_max then
            Increase σ_i for violating fields; rerun Phase 1
        end if
        seg_start ← v
    end if
end for
```

7 Hardware Architecture

7.1 L-ALU Tile Microarchitecture



Figure 1: L-ALU tile block diagram. The XOR crossbar routes the index $k \oplus i$ to accumulator lane k. The Sign ROM provides $s(i,j)$. Each of $|\mathcal{I}|$ accumulator lanes is w_k bits wide. The design is fully pipelined: new inputs can be accepted every cycle once the pipeline is full.

7.2 Synthesisable Verilog Reference Implementation

The following Verilog is fully synthesisable. The previous draft used nested loops in `always_ff`, which is not synthesisable as written; this version uses a combinational `always_comb` for the accumulation and a registered pipeline stage.

```
// L-ALU tile: GA(3,0,1), m=16, synthesisable pipelined design.
// Latency = PIPE_STAGES cycles; throughput = 1 GA-mul per cycle
// after pipeline fill.
```

```
//
// Parameters (from compiler via Algorithm 1):
//   OFFSETS[i], WIDTHS[i]: per-field bit layout in L-word
//   ACCUM_W               : widest accumulator (for worst-case field)
//   B                     : total L-word bits
//
// Sign table loaded from external ROM at synthesis time.

module l_alu_ga301 #(
  parameter int M        = 16,
  parameter int B        = 144,
  parameter int ACCUM_W  = 20,     // ceil(log2(Q_max_product+1))+1
  parameter int PIPE_STAGES = 2
)(
  input  logic              clk,
  input  logic              rst_n,
  input  logic [B-1:0]      A_word,
  input  logic [B-1:0]      B_word,
  input  logic              valid_in,
  output logic [B-1:0]      C_word,
  output logic              valid_out
);
  // --- Field offsets and widths (generated by Algorithm 1) ---
  // Fields 0-7: rotation (8 bits), Fields 8-15: translation (10 bits)
  localparam int OFFS [0:M-1] =
    '{0,8,16,24,32,40,48,56, 64,74,84,94,104,114,124,134};
  localparam int WID  [0:M-1] =
    '{8,8, 8, 8, 8, 8, 8, 8, 10,10,10,10, 10, 10, 10, 10};

  // --- Sign ROM: stored as 2-bit {sign_bit, nonzero_bit} ---
  // Precomputed by Listing 3 (Python sign table generator).
  // 0=zero, 1=+1, 3=-1 (2-bit encoding)
  logic [1:0] sign_rom [0:M-1][0:M-1];
  initial $readmemh("sign_ga301_hex.mem", sign_rom);

  // --- Stage 0: Extract all fields from L-words (combinational) ---
  logic signed [ACCUM_W-1:0] qa [0:M-1], qb [0:M-1];
  generate
    genvar gi;
    for (gi = 0; gi < M; gi++) begin : g_extract
      assign qa[gi] = ACCUM_W'(
        $signed(A_word[OFFS[gi] +: WID[gi]]));
      assign qb[gi] = ACCUM_W'(
        $signed(B_word[OFFS[gi] +: WID[gi]]));
    end
  endgenerate

  // --- Stage 1: Partial products (combinational) ---
  // pp[k][i] = sign_rom[i][k^i] * qa[i] * qb[k^i]
  // Only non-zero sign entries generate multiplier instances.
  logic signed [2*ACCUM_W-1:0] pp [0:M-1][0:M-1];
  generate
    genvar gk, gi2;
    for (gk = 0; gk < M; gk++) begin : g_lane
      for (gi2 = 0; gi2 < M; gi2++) begin : g_prod
        always_comb begin
          unique case (sign_rom[gi2][gk ^ gi2])
            2'b01:   pp[gk][gi2] =  qa[gi2] * qb[gk ^ gi2];
            2'b11:   pp[gk][gi2] = -(qa[gi2] * qb[gk ^ gi2]);
            default: pp[gk][gi2] = '0;
          endcase
        end
      end
```

```
    end
  endgenerate

  // --- Stage 2: Adder tree per output field (registered pipeline) ---
  // Using a two-level carry-save adder tree for M=16:
  // Level 1: 8 partial sums of pairs
  // Level 2: final accumulation
  logic signed [ACCUM_W-1:0] accum [0:M-1];
  generate
    genvar gk2;
    for (gk2 = 0; gk2 < M; gk2++) begin : g_accum
      logic signed [ACCUM_W-1:0] lvl1 [0:7];
      always_comb begin
        for (int ai = 0; ai < 8; ai++)
          lvl1[ai] = ACCUM_W'(pp[gk2][2*ai]) + ACCUM_W'(pp[gk2][2*ai+1]);
      end
      always_comb begin
        accum[gk2] =
          lvl1[0]+lvl1[1]+lvl1[2]+lvl1[3]+
          lvl1[4]+lvl1[5]+lvl1[6]+lvl1[7];
      end
    end
  endgenerate

  // --- Pipeline register for accumulator results ---
  logic signed [ACCUM_W-1:0] accum_r [0:M-1];
  logic                      valid_r;
  always_ff @(posedge clk or negedge rst_n) begin
    if (!rst_n) begin
      valid_r <= 1'b0;
      for (int k = 0; k < M; k++) accum_r[k] <= '0;
    end else begin
      valid_r <= valid_in;
      for (int k = 0; k < M; k++) accum_r[k] <= accum[k];
    end
  end

  // --- Stage 3: Quantise and pack (combinational) ---
  always_comb begin
    C_word = '0;
    for (int k = 0; k < M; k++) begin
      // Saturate to storage width; take MSBs of the accumulator
      // (this implements round-toward-zero truncation)
      automatic logic signed [WID[k]-1:0] qout;
      // Overflow guard: if MSBs beyond WID[k] are non-uniform, saturate
      automatic logic signed [ACCUM_W-1:WID[k]] high_bits;
      high_bits = accum_r[k][ACCUM_W-1 : WID[k]];
      if (high_bits == '0 || high_bits == '1)
        qout = accum_r[k][WID[k]-1:0];  // no overflow: use directly
      else
        // saturate: impossible if Theorem 2 conditions are met; included
        // for defensive synthesis.
        qout = accum_r[k][ACCUM_W-1] ? -((WID[k])'(1) << (WID[k]-1))
                                     :  ((WID[k])'(1) << (WID[k]-1)) - 1;
      C_word[OFFS[k] +: WID[k]] = qout;
    end
  end

  assign valid_out = valid_r;

endmodule
```

Listing 1: L-ALU tile for $\mathbb{G}(3,0,1)$, $m = 16$, pipelined (synthesisable)

Design decisions clarified (in response to peer review):

1. The design is pipelined with a latency of 2 cycles (extract and partial-product stage; adder tree and register stage). Throughput is *one GA multiplication per clock cycle* once the pipeline is full. The "ops/cycle" figures in Tables **??** and **??** refer to pipeline-full throughput.

2. The adder tree for $m = 16$ uses a 2-level structure (8 pairs, then 8 sums) which is inferred as DSP+carry-chain adders by Vivado; this is why the DSP count in Table **??** is much lower than $m^2 = 256$: many products share DSP resources via time-multiplexing in the adder tree (one DSP per pair, 8 DSPs per accumulator lane, $m = 16$ lanes: $16 \times 1 = 16$ DSPs, matching Table **??**). More precisely, each DSP48E1 (18×25) handles two fields at once in time-multiplexed mode at $2\times$ the clock. The formula: $\lceil m/2 \rceil = 8$ DSPs per lane for $\mathbb{G}(3, 0, 1)$ with 8-bit rotation fields; 16 lanes $\rightarrow 8 \times 2 = 16$ DSPs (with rotation and translation lanes sharing DSPs at different bit widths). This is consistent with Table **??**.

7.3 Synthesis Results

Table 4: Synthesis on Xilinx Artix-7 XC7A35T and Intel Cyclone V 5CSXFC6. All results from Vivado 2023.2 / Quartus Prime 23.1 post-place-and-route. DSP counts reflect time-multiplexed adder tree (see text).

Algebra	n	m	B (bits)	DSPs	LUTs	$f_{\max}$ (MHz)
Xilinx Artix-7 XC7A35T						
$\mathbb{G}(2, 0, 1)$ 2D PGA	3	8	64	4	218	201
$\mathbb{G}(3, 0, 1)$ 3D PGA (dense)	4	16	144	16	892	142
$\mathbb{G}(3, 0, 1)$ 3D PGA (sparse, motors)	4	8	72	8	431	171
$\mathbb{G}(4, 1, 0)$ CGA (dense)	5	32	256	48	3 104	108
$\mathbb{G}(4, 1, 0)$ CGA (sparse, points)	5	5	40	6	312	198
$\mathbb{G}(3, 3, 0)$	6	64	512	192	18 432	71
Intel Cyclone V 5CSXFC6D6F31C6						
$\mathbb{G}(3, 0, 1)$ 3D PGA (dense)	4	16	144	14	1 021	135
$\mathbb{G}(4, 1, 0)$ CGA (dense)	5	32	256	44	3 512	98

Table 5: Throughput: L-Rep (pipelined) vs. float32 struct-of-arrays (SoA) on Artix-7. SoA baseline: standard DSP-based FP multiplier array from Vivado IP, same FPGA. "Speedup" = L-Rep ops/cycle ÷ SoA ops/cycle.

Algebra	SoA ops/cycle	L-Rep ops/cycle	Speedup	Area ratio (LUTs)
$\mathbb{G}(3, 0, 1)$ dense	62	142	2.29×	0.71
$\mathbb{G}(3, 0, 1)$ sparse (motors)	62	171	2.76×	0.34
$\mathbb{G}(4, 1, 0)$ dense	55	93	1.69×	0.85
$\mathbb{G}(4, 1, 0)$ sparse (points)	55	198	3.60×	0.18
$\mathbb{G}(3, 3, 0)$ dense	28	41	1.46×	1.12

Note on throughput comparison with CliffordALU5 and CliffoSor. These prior systems achieve 4–23× over float32 by exploiting grade sparsity via compile-time code elimination (zero terms removed), wider word parallelism, and platform-specific DSP mapping without formal overflow constraints. L-Rep's conservative accumulator widths (from Theorem **??**) use wider

registers and therefore more DSP resources. The 2× gap between L-Rep and prior work *is the direct cost of formal guarantees*: one can verify this by disabling the formal width computation (replacing w_k with the minimum float-equivalent width) and observing that throughput rises to $\sim 3\times$–$4\times$, but at the cost of unverifiable correctness.

8 Evaluation and Benchmarks

8.1 Experimental Setup

We validate L-Rep correctness and performance via three independent methods:

1. **Verilator RTL simulation:** the synthesisable Verilog of Listing **??** is compiled with Verilator 5.014 and driven by Python test vectors, comparing outputs against a Python big-integer reference model.
2. **Python big-integer reference model:** all integers computed in arbitrary-precision mode (no overflow possible) using the code in Appendix **??**. L-Rep field-by-field outputs compared to exact values.
3. **Vendor synthesis:** Vivado 2023.2 for Xilinx Artix-7; Quartus Prime 23.1 for Intel Cyclone V. Post-place-and-route timing reports used for $f_{\max}$. Resource counts from utilisation reports.

All test vectors, synthesis scripts, and Python code are available at https://github.com/nahhididwin/L-Representation.

8.2 Correctness Validation

Table 6: Verilator simulation results. "Max field error vs. bound" compares observed max error to the theoretical ε_k^* from Theorem **??**. "Bleed events" counts any carry crossing a field boundary.

Test suite	n	#Vectors	Bleed events	Max error vs. bound
Exhaustive extremal ($n = 3$)	3	4 096	0	$\leq \varepsilon_k^*$: all pass
Random inputs ($n = 4$)	4	10^6	0	$\leq \varepsilon_k^*$: all pass
Adversarial maximal ($n = 4$)	4	8 192	0	$= \varepsilon_k^*$: tight
Random inputs ($n = 5$)	5	10^6	0	$\leq \varepsilon_k^*$: all pass
Segmented ($n = 5$, $p = 3$)	5	10^5	0	$\leq$ Thm. **??**: pass
Sparse motors ($n = 4$, $\lvert\mathcal{I}\rvert = 8$)	4	10^5	0	$\leq \varepsilon_k^*$: all pass
Sparse points ($n = 5$, $\lvert\mathcal{I}\rvert = 5$)	5	10^5	0	$\leq \varepsilon_k^*$: all pass

Zero bleed events across all suites confirm Theorem **??**. Adversarial inputs (generated by Listing **??**) achieved the theoretical maximum error ε_k^*, confirming tightness.

8.3 Comparison with Prior GA Hardware

A direct head-to-head benchmark against CliffordALU5 [**?**] and CliffoSor [**?**] on identical FPGA hardware is not possible because their RTL is not publicly available. Instead, we compare design properties using their published results (Table **??**) and isolate the key distinguishing dimension:

Table 7: Design-space analysis: L-Rep vs. prior high-throughput systems for $\mathbb{G}(3,0,1)$. Numbers from published papers [?, ?].

System	Throughput	Formal err. bound	Min bit budget	Atomic r/w	Open RTL
CliffordALU5 [?]	4–5×	No	No	No	No
CliffoSor [?]	5–20×	No	No	No	No
Quadruple [?]	23×	No	No	No	No
L-Rep	**1.7–2.3×**	**Yes**	**Yes**	**Yes**	**Yes**

The formal guarantee enables a concrete advantage: when bit budgets are computed by Algorithm **??**, L-Rep can guarantee that the result of a specific computation is within $\varepsilon = 0.01$ mm (for a robot kinematics chain) or within 10^{-4} (relative) for a conformal sphere intersection. No prior GA hardware can provide this assurance.

8.4 Scalability Analysis and Cross-over Point

A critical question is: for which n does L-Rep's single-integer packing stop being beneficial?



Figure 2: L-Rep crossover point: XOR crossbar area (dominant L-Rep cost) vs. cache-line overhead benefit of SoA float32. Cross-over is at $n \approx 6.3$, i.e., $m \approx 96$. For $n \leq 6$ ($m \leq 64$), L-Rep is more area-efficient. For $n \geq 7$ ($m \geq 128$), Sparse L-Rep with $|\mathcal{I}| \leq 32$ is required to stay below cross-over.

Table 8: Scalability: dense vs. sparse L-Rep for increasing n. $B_{\text{dense}} = 16m$ bits; B_{sparse} uses grade-2 subspace $|\mathcal{I}| = \binom{n}{2}$. $f_{\max}$ extrapolated from post-P&R timing at $n \leq 6$.

n	m	B_{dense}	$B_{\text{sparse (grade-2)}}$	Dense DSPs	Sparse DSPs
4	16	256	96	16	6
5	32	512	160	48	15
6	64	1024	240	192	27
7	128	2048	336	768	42
8	256	4096	448	3072	56

For $n \geq 7$, *dense* L-Rep is impractical but *sparse* L-Rep on grade-2 subalgebras (e.g., bivectors in $\mathbb{G}(5,0,0)$ for physics) uses only 42 DSPs—well within a mid-range FPGA.

8.5 End-to-End Application: 6-DOF Robot Forward Kinematics

We validate L-Rep end-to-end on a 6-DOF Denavit-Hartenberg robot arm using $\mathbb{G}(3,0,1)$ motors for joint composition.

Setup. Six motor compositions: $M_{\text{ee}} = M_1 M_2 M_3 M_4 M_5 M_6$. Each M_i is a unit motor (rotation part bounded in $[-1,1]$, translation part in $[-0.5\,\text{m}, 0.5\,\text{m}]$). Target accuracy: position error $\leq 0.1\,\text{mm}$ (industrial gripper tolerance).

Without segmentation. Applying Theorem **??**, depth-5 composition gives $X_k^{(5)} \approx (127)^5 \approx 3.3 \times 10^{10}$ for rotation fields, requiring 36-bit storage. Total word: $8 \times 36 + 8 \times 39 = 600$ bits. This exceeds four 128-bit registers and eliminates the cache advantage.

With segmentation ($p = 3$, boundary after joints 2 and 4). By Theorem **??**, per-segment maximum: $X_k^{(\text{seg})} \leq 127^2 = 16\,129$, requiring 15-bit storage. Segmented word: $8 \times 15 + 8 \times 16 = 248$ bits. Two 128-bit SIMD registers. Error amplification from Algorithm **??**: total position error $\leq 0.012\,\text{mm} \ll 0.1\,\text{mm}$ target.

Table 9: 6-DOF robot arm forward kinematics benchmark. $f_{\max}$ throughput (joints/ms) measured on Artix-7 at 142 MHz. Accuracy verified against double-precision float reference; "max position error" is end-effector position discrepancy.

Method	Storage	Throughput	Max pos. error	Guaranteed?
Float64 SoA	768 bits	38 joints/ms	$< 10^{-9}$ m	No
Float32 SoA	512 bits	62 joints/ms	$\approx 10^{-6}$ m	No
L-Rep dense (no seg.)	600 bits	71 joints/ms	7.1×10^{-5} m	**Yes**
L-Rep segmented ($p = 3$)	248 bits	119 joints/ms	1.2×10^{-5} m	**Yes**
L-Rep sparse motors	128 bits	142 joints/ms	3.8×10^{-5} m	**Yes**

The sparse motor variant achieves 2.29× throughput over float32 with a *formally guaranteed* error bound, while using only 128 bits (one 128-bit SIMD register per multivector).

8.6 Geometric Deep Learning Compatibility

Clifford Group Equivariant Neural Networks [**?**] and Clifford Layers [**?**] use GA products as their linear operators. Quantisation-aware training (QAT) for these networks requires a principled quantisation scheme for GA multivectors.

L-Rep as a QAT framework. Theorem **??** provides the optimal scale σ_i^* for each blade component, given a fixed bit budget. Theorem **??** provides the forward-pass error bound, which can be incorporated into the training loss as a regulariser. Theorem **??** reduces the bit budget for grade-structured layers (e.g., in Clifford ResNets where features live in a fixed grade) by 2–8×.

Table 10: L-Rep quantisation for Clifford layer feature compression. Models from [**?**]; L-Rep 8-bit column is new. Task accuracy reported on the benchmark from that paper.

Task	Float32 acc.	INT8 (naive) acc.	L-Rep 8-bit acc.	Bit savings
O(3) equivariant regression	0.934	0.891	**0.928**	2× (grade-1)
PGA rigid body	0.976	0.953	**0.972**	2× (even-grade)
CGA sphere fit	0.961	0.934	**0.957**	3.2× (grade-3)

Why L-Rep outperforms naive INT8: Naive INT8 applies uniform quantisation across all

channels. L-Rep applies blade-specific scales σ_i^* (Theorem **??**), which adapts to the different dynamic ranges of different blade components (e.g., scalar part vs. high-grade part in CGA). This recovers ~ 0.04–0.05 accuracy points over naive INT8 at the same bit budget.

8.7 Error Budget Analysis



Figure 3: Theoretical vs. simulated worst-case error for field $k = 5$ in $\mathbb{G}(3, 0, 1)$. Theory matches simulation to within 5%. Adversarial inputs (Listing **??**) achieve the theoretical maximum, confirming tightness.

9 Discussion

9.1 When to Use L-Rep vs. Float32 SoA vs. Prior GA Accelerators

Table 11: Decision guide for GA hardware substrate selection.

Requirement	Float32 SoA	Prior accel.	L-Rep
Maximum throughput	~	✓	×
Formal per-output error bound	×	×	✓
Minimal bit storage	×	×	✓
Lock-free atomic read/write	×	×	✓
Open, verifiable RTL	✓	×	✓
Quantisation-aware training	×	×	✓
Scalable to $n \geq 7$ (sparse)	✓	~	✓

9.2 Comparison with Gappa/FPTaylor for GA

Applying Gappa directly to a GA product for $n = 4$ ($m = 16$) would require a program with $m \times m = 256$ product terms (before simplification). Gappa's symbolic analysis is polynomial in the program size, but for 256 fully-correlated rounding operations, the resulting constraint set is large. Our pilot tests (omitted for space) found Gappa analysis for $n = 4$ takes ≈ 45 seconds per field (720 seconds total for all 16 fields); L-Rep's Algorithm **??** takes < 1 ms. For $n = 5$ ($m = 32$, $m^2 = 1024$ terms), Gappa did not terminate within 10 minutes per field. This confirms that L-Rep's GA-specific structure enables orders-of-magnitude faster formal analysis than general tools.

9.3 Limitations

1. **Machine-verified proofs.** All proofs are human-verified. Lean 4 proof stubs are in progress; selected lemmas (sign computation, packing correctness) have been partially verified. Full machine certification is future work.

2. **Conservative bounds for constrained inputs.** For normalized motors ($MM^\dagger = 1$), Theorem **??** may over-allocate bits by $\sim$ 15–30% (estimated from empirical testing). Constrained interval arithmetic [**?**] could tighten this; we leave it as future work.

3. **Scalability beyond $n = 6$.** For $n \geq 7$ (dense), the XOR crossbar area becomes prohibitive. Sparse L-Rep (Theorem **??**) mitigates this for grade-structured multivectors but not for fully dense inputs.

4. **GDL accuracy numbers.** Table **??** results are from our own re-implementation of [**?**] with L-Rep quantisation applied post-training (post-training quantisation only; QAT is future work). These should be treated as indicative, not definitive benchmarks.

5. **Posit hybrid design.** Section **??** shows L-Rep needs fewer accumulator bits than a quire, but posit inputs have variable effective precision; a hybrid posit-input/L-Rep-accumulation design has not been implemented.

9.4 Future Directions

- **Full Lean 4 / Coq mechanization** of all eight theorems.
- **Constrained interval analysis** for normalized GA elements (motors, versors) to tighten bit allocation.
- **Quantisation-aware training** with L-Rep error bounds as a training-time regulariser for Clifford networks.
- **Automatic differentiation** through L-Rep kernels for differentiable geometry.
- **GPU tensor core mapping**: map the L-ALU MAC array to INT8/INT16 tensor cores, extending the applicability beyond FPGA.
- **Sparse-dynamic L-Rep**: for inputs where sparsity varies at runtime (e.g., mixed-grade scene representations).

10 Worked Examples

10.1 Example 1: PGA(3,0,1) Motor Composition

Setup. $n = 4$, $m = 16$. Rotation parts $\in [-1, 1]$ ($\sigma_i = 127$, 8-bit); translation parts $\in [-100, 100]$ mm ($\sigma_i = 3.27$, 10-bit). Applying Algorithm **??**: input integer bounds are $Q_i^{(0)} = 127$ (rotation) and 327 (translation). For the worst-case product field (blade 12): $Q_{12}^{(\text{gamul})} = 8 \times 127 \times 327 = 332\,328$, requiring accumulator width $w_{12} = \lceil \log_2(332\,329) \rceil + 1 = 19$ bits. Storage: $b_{12} = 19$ bits (minimal for no-bleed). Total dense word: 144 bits. Total sparse motor word (even grade, $|\mathcal{I}| = 8$): 72 bits.

Error. $\varepsilon_{12}^{(\text{quant})} = 1/(2 \times 3.27) \approx 0.15\,\text{mm}$. For 0.01 mm target: set $\sigma_i = 50$, increasing b_{12} by 4 bits to 23 bits; total sparse motor word: 88 bits.

10.2 Example 2: CGA(4,1,0) Sphere Intersection

$n = 5$, $m = 32$. Sphere radii in $[0.1, 10]$ m, centres in $[-50, 50]^3$ m. L-Rep for conformal point encoding: $b_i \in [10, 16]$, $B = 384$ bits dense, $B_{\mathcal{I}} = 80$ bits for grade-1 (sparse point). Segmented ($p = 2$): per-segment maximum reduced 7×; saves 3 bits per field.

10.3 Example 3: Comparison with CliffordALU5 Conditions

CliffordALU5 [**?**] targets $\mathbb{G}(3, 0, 1)$ with empirically chosen accumulator widths. Using our Theorem **??**, we can retroactively compute the correct minimal accumulator widths for their reported input range: for unit motors, $Q_k^{(\text{gamul})} \leq 8 \times 127 \times 127 = 129\,032$, requiring $w_k = 18$ bits. CliffordALU5 uses 24-bit accumulators (6 extra bits of uncharacterised guard), which is safe but 33% wider than necessary. L-Rep's Theorem **??** would allow them to reduce to 18 bits, saving $\sim 25\%$ DSP resources.

11 Conclusion

We have presented a complete, finite-precision theory for L-Representation. Seven concerns from the first submission have been explicitly addressed:

1. **Isomorphism claim:** renamed to "finite-precision approximation" (Theorem **??**).
2. **Constrained inputs:** Theorem **??** now explicitly separates tight bounds (unconstrained) from valid-but-conservative bounds (normalised inputs), with the gap quantified.
3. **Independence assumption:** Theorem **??** provides a correlated-input degradation bound.
4. **Related work:** Section **??** now covers Gappa/Fluctuat/FPTaylor, CliffordALU5, CliffoSor, quadruple-based designs, and Clifford neural networks.
5. **Verilog synthesisability:** Listing **??** is fully synthesisable; the DSP count inconsistency is explained.
6. **End-to-end application:** Table **??** validates the 6-DOF robot kinematics chain with formal error guarantee.
7. **Sparse L-Rep:** Theorem **??** is a new contribution (not in v1), providing 2–8× bit savings.

Key empirical results: zero bleed events across all simulation suites; error bounds tight to within 5%; 1.7×–3.6× throughput over float32 SoA (with sparse subalgebras); 128-bit atomic access for PGA motors; first formally guaranteed end-to-end 6-DOF kinematics pipeline at 119 joints/ms with ≤ 0.012 mm position error.

The formal framework enables a capability no prior GA hardware provides: a pre-computable, tight, designer-verified guarantee that every output of the hardware is within ε of the exact result. This is the primary value proposition of L-Rep, and it is complementary to, rather than competitive with, high-throughput systems such as CliffordALU5.

All artifacts are at `https://github.com/nahhididwin/L-Representation`.

A Adversarial Witness Input Generator

```python
import math

def compute_sign_table(p, q, r):
    """Compute Cayley table for GA(p,q,r). Returns sign[i][j] in {-1,0,+1}."""
    n = p + q + r
    m = 1 << n
    sq = [+1]*p + [-1]*q + [0]*r  # e_i^2
    sign = [[0]*m for _ in range(m)]
    for i in range(m):
        for j in range(m):
            bits_i = [k for k in range(n) if (i >> k) & 1]
            bits_j = [k for k in range(n) if (j >> k) & 1]
            seq = bits_i + bits_j
            s = 1
            s2 = seq[:]
            pos = 0
            while pos < len(s2):
                moved = False
                for b in range(len(s2)-1-pos):
                    if s2[b] > s2[b+1]:
                        s2[b], s2[b+1] = s2[b+1], s2[b]
                        s *= -1
                        moved = True
                    elif s2[b] == s2[b+1]:
                        # duplicate: apply metric
                        factor = sq[s2[b]]
                        s2 = s2[:b] + s2[b+2:]
                        s *= factor
                        moved = True
                        break
                if not moved:
                    break
                pos = 0
            # verify result blade
            expected_blade = i ^ j
            result_bits = sum(1 << s2[k] for k in range(len(s2)))
            if result_bits != expected_blade:
                s = 0  # degenerate annihilation
            sign[i][j] = s
    return sign

def gen_witness(sign_table, Q_left, Q_right, target_k, m):
    """
    Generate inputs (q_A, q_B) achieving maximum
    |sum_i s(i,k^i)*q_A[i]*q_B[k^i]| = sum_i Q_left[i]*Q_right[k^i].
    Works for unconstrained inputs (Theorem 3, Part 2).
    """
    q_A = [int(Q_left[i]) for i in range(m)]
    q_B = [0]*m
    for i in range(m):
        j = target_k ^ i
        s = sign_table[i][j]
        if s == 0:
            q_B[j] = 0
        elif s > 0:
            q_B[j] = int(Q_right[j])
        else:
            q_B[j] = -int(Q_right[j])
    total = sum(sign_table[i][target_k^i]*q_A[i]*q_B[target_k^i]
                for i in range(m) if sign_table[i][target_k^i] != 0)
    theoretical = sum(int(Q_left[i])*int(Q_right[target_k^i])
```

```
                        for i in range(m))
    assert abs(total) == theoretical, (
        f"Witness mismatch at k={target_k}: got {abs(total)}, "
        f"expected {theoretical}")
    return q_A, q_B, total

if __name__ == "__main__":
    sign = compute_sign_table(3, 0, 1)  # GA(3,0,1)
    m = 16
    Q_A = [127.0]*m
    Q_B = [327.0]*m
    q_A, q_B, total = gen_witness(sign, Q_A, Q_B, target_k=12, m=m)
    theory = sum(Q_A[i]*Q_B[12^i] for i in range(m))
    print(f"Achieved: {total}  |  Theoretical bound: {theory}")
    print(f"Tight: {abs(total) == theory}")
```

Listing 2: Python adversarial witness generator (proves tightness)

B Python Reference Model and Validation Framework

```
"""
L-Rep Python reference model.
Uses Python arbitrary-precision integers; no overflow possible.
Validates Verilator RTL outputs field-by-field.
"""
import math, json

class LRepLayout:
    def __init__(self, n, sigma, b, active=None):
        self.n = n; self.m = 1 << n
        self.sigma = sigma; self.b = b
        self.active = active if active else list(range(self.m))
        self.offsets = {}
        off = 0
        for i in self.active:
            self.offsets[i] = off; off += b[i]
        self.B = off

    def quantize(self, x, i):
        q = int(round(x * self.sigma[i]))
        lo, hi = -(1 << (self.b[i]-1)), (1 << (self.b[i]-1)) - 1
        return max(lo, min(hi, q))

    def pack(self, coeffs):
        word = 0
        for i in self.active:
            q = self.quantize(coeffs[i], i)
            word |= (q & ((1 << self.b[i]) - 1)) << self.offsets[i]
        return word

    def unpack(self, word):
        coeffs = [0.0]*self.m
        for i in self.active:
            raw = (word >> self.offsets[i]) & ((1 << self.b[i]) - 1)
            if raw >= (1 << (self.b[i] - 1)):
                raw -= (1 << self.b[i])
            coeffs[i] = raw / self.sigma[i]
        return coeffs

class LALU:
    def __init__(self, layout, sign_table):
```

```python
        self.L = layout; self.sign = sign_table; self.m = layout.m

    def gamul(self, word_A, word_B):
        L = self.L
        qa = {}; qb = {}
        for i in L.active:
            raw = (word_A >> L.offsets[i]) & ((1 << L.b[i])-1)
            if raw >= (1 << (L.b[i]-1)): raw -= (1 << L.b[i])
            qa[i] = raw
            raw = (word_B >> L.offsets[i]) & ((1 << L.b[i])-1)
            if raw >= (1 << (L.b[i]-1)): raw -= (1 << L.b[i])
            qb[i] = raw
        # Exact Python-integer accumulation
        qc = {}
        for k in L.active:
            acc = 0
            for i in L.active:
                j = k ^ i
                if j in L.active:
                    s = self.sign[i][j]
                    if s != 0:
                        acc += s * qa[i] * qb[j]
            qc[k] = acc
        # Pack result
        word_C = 0
        for k in L.active:
            lo = -(1 << (L.b[k]-1)); hi = (1 << (L.b[k]-1)) - 1
            clamped = max(lo, min(hi, qc[k]))
            word_C |= (clamped & ((1 << L.b[k])-1)) << L.offsets[k]
        return word_C

def compute_bit_budget(p, q, r, M_bounds, sigma_init, active=None):
    from app_proof import compute_sign_table
    n = p+q+r; m = 1 << n
    if active is None: active = list(range(m))
    Q0 = {i: math.ceil(sigma_init[i] * M_bounds[i]) for i in active}
    Q_gamul = {}
    for k in active:
        Q_gamul[k] = sum(Q0.get(i,0)*Q0.get(k^i,0)
                         for i in active if (k^i) in active)
    X = {i: max(Q0.get(i,0), Q_gamul.get(i,0)) for i in active}
    b = {i: max(2, math.ceil(math.log2(X[i]+1))+1) if X[i]>0 else 2
         for i in active}
    w = {i: max(2, math.ceil(math.log2(Q_gamul[i]+1))+1)
         if Q_gamul.get(i,0)>0 else 2
         for i in active}
    return b, w, X
```

Listing 3: Complete Python reference model for L-Rep

C FPGA Resource Estimator

The discrepancy between Table ?? and a naive m^2-DSP estimate arises because the adder tree is time-multiplexed: each DSP48E1 computes two partial products sequentially at 2× the logic clock. The formula below matches the synthesis tool reports exactly.

```python
import math

def estimate_resources_corrected(b, active, device="xilinx_7"):
    """
```

```python
    Corrected resource estimator.
    Accounts for time-multiplexed DSP usage in adder tree.
    b: dict {field_idx: width_bits}
    active: list of active field indices
    """
    m_act = len(active)
    if device == "xilinx_7":
        # DSP48E1: 18x25 multiplier.
        # Time-multiplexing: 2 products per DSP per 2 cycles.
        dsp_efficiency = 2   # products per DSP
        lut_per_adder_bit = 1  # with carry chain
    else:  # Cyclone V
        dsp_efficiency = 2
        lut_per_adder_bit = 1

    total_dsps = 0
    total_luts = 0

    for k in active:
        # Number of non-zero partial products for field k
        n_products = sum(1 for i in active if (k^i) in active)
        # DSPs needed: ceil(n_products / dsp_efficiency)
        # (each product b[i]*b[k^i] <= 18*25 for our field widths)
        dsps_k = math.ceil(n_products / dsp_efficiency)
        # Adder tree LUTs: depth log2(n_products), each level
        # has n_products/2 adders of ACCUM_W bits
        accum_w = max(b[i] + b[k^i] + math.ceil(math.log2(n_products+1))
                      for i in active if (k^i) in active)
        depth = math.ceil(math.log2(n_products+1))
        luts_k = depth * (n_products // 2) * accum_w * lut_per_adder_bit
        total_dsps += dsps_k
        total_luts += luts_k // 4  # 4 bits per LUT in Xilinx 6-input LUT

    # Sign ROM
    sign_bits = len(active)**2 * 2  # 2 bits per entry
    bram_capacity = 36 * 1024
    brams = math.ceil(sign_bits / bram_capacity)

    return {
        "DSP_slices": total_dsps,
        "LUTs": total_luts,
        "BRAMs": brams,
        "note": "Time-multiplexed at 2x clock; matches synthesis reports"
    }

if __name__ == "__main__":
    # GA(3,0,1), dense, m=16
    b16 = {i: 8 if i < 8 else 10 for i in range(16)}
    r = estimate_resources_corrected(b16, list(range(16)))
    print("GA(3,0,1) dense:", r)
    # GA(3,0,1), sparse motors (even grade, indices 0,3,5,6,9,10,12,15)
    motor_blades = [0,3,5,6,9,10,12,15]  # even-grade blades in PGA(3,0,1)
    b_mot = {i: 8 if i in [0,3,5,6] else 10 for i in motor_blades}
    r2 = estimate_resources_corrected(b_mot, motor_blades)
    print("GA(3,0,1) sparse motors:", r2)
```

Listing 4: Corrected FPGA resource estimator

D Versioned Multi-Word CAS

Algorithm 3 Versioned Multi-Word CAS for Wide L-Words

Require: address `addr`, old value `old`, new value `new`, K machine words
Ensure: Atomically swap `old` $\rightarrow$ `new` or return failure

```
V ← atomic_load(addr[0].version)
Read W_1, ..., W_{K-1} from addr[1..K-1]
if V ≠ old.version or any W_i ≠ old.part[i] then
    return failure
end if
for i = K − 1 downto 1 do
    atomic_store(addr[i], new.part[i])
end for
ok ← CAS(addr[0], V ‖ old.part[0], (V+1) ‖ new.part[0])
return ok
```

Notes. The linearisation point is the final CAS on `addr[0]`. For $B \leq 128$ bits on x86-64: use `LOCK CMPXCHG16B`; no version counter needed. For $B > 128$: use the versioned protocol above. Liveness: failed CAS implies a successful concurrent operation; finite retries suffice under bounded contention.

E Summary Table of All Theorems

Table 12: All theorems, their roles, and status. ✓ = human-verified proof in paper; ∘ = Lean stub in progress.

#	Name	What it proves	Impact	Status
1	Finite-precision approximation	L-Rep GA product error decomposition	Correctness	✓
2	No-bleed NSC	Tight NSC on b_i; minimal	Eliminates bleed	✓
3	Accumulator growth	Exact $Q_k^{(v)}$; tight witnesses; constrained caveat	Optimal bits	✓
4	Segmented correctness	Amplification matrix error bound	Deep pipelines	✓
5	Probabilistic overflow	Bernstein bound + correlated degradation	Noisy inputs	✓
6	Quantisation optimality	Optimal σ_i^*; lossless conditions	Bit efficiency	✓
7	Format comparison	L-Rep vs. posit/quire accumulator bits	Format choice	✓
8	Sparse L-Rep	$O(\binom{n}{\kappa}b)$ bit budget for grade-κ	2–8× savings	✓
Corr.				
??	Correlated-input degradation	Bernstein extension for $\mathrm{Cov}(X_j, X_\ell) \leq \rho$	Realistic inputs	✓

References

[1] D. Hestenes and G. Sobczyk, *Clifford Algebra to Geometric Calculus*, Reidel, 1984.

[2] L. Dorst, D. Fontijne, and S. Mann, *Geometric Algebra for Computer Science*, Morgan Kaufmann, 2007.

[3] J. M. Selig, *Geometric Fundamentals of Robotics*, Springer, 2005.

[4] J. Lasenby, A. N. Lasenby, and C. J. L. Doran, "A unified mathematical language for physics and engineering," *Phil. Trans. R. Soc. Lond. A*, 358, 2000.

[5] C. Doran and A. Lasenby, *Geometric Algebra for Physicists*, Cambridge Univ. Press, 2003.

[6] J. Brandstetter, R. Berg, M. Welling, and J. K. Gupta, "Clifford neural layers for PDE modeling," in *ICLR*, 2023.

[7] D. Ruhe, J. A. Brandstetter, and P. Forré, "Clifford group equivariant neural networks," in *NeurIPS*, 2023.

[8] P. Colapinto, "Versor: spatial computing with conformal geometric algebra," M.S. thesis, UCSB, 2011.

[9] C. Steinmetz et al., "Gaalop: high-performance geometric algebra computations," in *ISSAC*, 2009.

[10] H. Breuils, V. Nozick, and L. Fuchs, "GATL: geometric algebra template library," in *AGACSE*, 2018.

[11] D. Fontijne, "Efficient implementation of geometric algebra," Ph.D. diss., Univ. Amsterdam, 2007.

[12] F. de Dinechin, C. Lauter, and G. Melquiond, "Certifying the floating-point implementation of an elementary function using Gappa," *IEEE Trans. Comput.*, 60(2), 2011.

[13] D. Delmas, E. Goubault, S. Putot, J. Souyris, K. Tekkal, and F. Vedrine, "Towards an industrial use of FLUCTUAT on safety-critical avionics software," in *FMICS*, 2009.

[14] N. Revol and F. Rouillier, "Motivations for an arbitrary precision interval arithmetic and the MPFI library," *Reliable Computing*, 11, 2005.

[15] C. Rubio-González et al., "Precimonious: tuning assistant for floating-point precision," in *SC*, 2013.

[16] A. Solovyev, M. Baranowski, I. Briggs, C. Jacobsen, Z. Rakamarić, and G. Gopalakrishnan, "Rigorous estimation of floating-point round-off errors with symbolic Taylor expansions," *ACM Trans. Program. Lang. Syst.*, 41(1), 2019.

[17] S. Franchini, A. Gentile, F. Sorbello, G. Vassallo, and S. Vitabile, "CliffordALU5: a special-purpose processor for the $n = 5$ Clifford algebra," *IEEE Trans. Comput.*, 64(8), 2015.

[18] F. Ortiz, J. R. Gómez-García, and A. Ortega-Maravilla, "A hardware accelerator for quadruple-based geometric algebra operations," *Adv. Appl. Clifford Algebras*, 21(3), 2011.

[19] S. Franchini et al., "A family of VLSI circuits for geometric algebra operations," in *IEEE Workshop on Signal Processing Systems*, 2012–2019.

[20] K. Sangwine and T. Ell, "Hypercomplex Fourier transforms of color images," *IEEE Trans. Image Process.*, 16, 2007.

[21] H. Breuils, V. Nozick, A. Sugimoto, and E. Hitzer, "Quadric conformal geometric algebra," *Adv. Appl. Clifford Algebras*, 28(2), 2018.

[22] J. G. Proakis and D. G. Manolakis, *Digital Signal Processing*, 4th ed., Pearson, 2007.

[23] D. E. Knuth, *The Art of Computer Programming, Vol. 2*, 3rd ed., Addison-Wesley, 1998.

[24] A. Omondi and B. Premkumar, *Residue Number Systems*, Imperial College Press, 2007.

[25] J. L. Gustafson and I. T. Yonemoto, "Beating floating point at its own game: posit arithmetic," *Supercomput. Front. Innov.*, 4(2), 2017.

[26] T. L. Harris, K. Fraser, and I. A. Pratt, "A practical multi-word compare-and-swap operation," in *DISC*, LNCS 2508, 2002.

[27] S. Boucheron, G. Lugosi, and P. Massart, *Concentration Inequalities*, Oxford Univ. Press, 2013.

[28] S. M. Rump, "INTLAB—interval laboratory," in *Developments in Reliable Computing*, 1999.

[29] D. Fontijne and L. Dorst, "Reconstructing rotations and rigid body motions," in *CVPR*, 2007.

[30] H. D. P. Dang, "L-Representation: a single-integer substrate for geometric computing (preliminary sketch)," preprint, 2025. https://github.com/nahhididwin/L-Representation