

V3.10 BOM 核对清单（按位号顺序）

共 178 个位号，其中 157 个需要贴片。贴完一个在左侧方框打勾。坐标以 PCB 左上角为原点，单位 mm。

板上丝印印错了 —— 别信板上的字，认坐标

有极性/方向 —— 贴反不工作

不贴

| 贴 | 位号  | 值 / 型号    | 封装                | 位置 (x, y)   | 阶段            | 备注                |
|---|-----|-----------|-------------------|-------------|---------------|-------------------|
|   | C1  | 10uF      | C_0805_2012Metric | 78.6, 93.3  | A 电源          |                   |
|   | C2  | 1uF       | C_0603_1608Metric | 62.0, 98.3  | A 电源          |                   |
|   | C3  | 1uF       | C_0603_1608Metric | 66.5, 98.3  | A 电源          |                   |
|   | C4  | 1uF       | C_0603_1608Metric | 71.0, 98.3  | A 电源          |                   |
|   | C5  | 1uF       | C_0402_1005Metric | 109.6, 79.2 | A 电源          |                   |
|   | C6  | 1uF       | C_0603_1608Metric | 78.6, 67.0  | A 电源          | 板上印着 C18          |
|   | C10 | 100nF     | C_0603_1608Metric | 66.4, 84.5  | C 传感器 + GNSS  |                   |
|   | C11 | 100nF     | C_0603_1608Metric | 70.6, 84.5  | C 传感器 + GNSS  |                   |
|   | C12 | 100nF     | C_0603_1608Metric | 74.8, 84.5  | C 传感器 + GNSS  |                   |
|   | C13 | 100nF     | C_0603_1608Metric | 79.1, 84.5  | C 传感器 + GNSS  |                   |
|   | C14 | 100nF     | C_0603_1608Metric | 61.8, 87.2  | C 传感器 + GNSS  |                   |
|   | C15 | 4.7uF     | C_0603_1608Metric | 66.1, 87.2  | C 传感器 + GNSS  |                   |
|   | C16 | 100nF     | C_0603_1608Metric | 70.4, 87.2  | C 传感器 + GNSS  |                   |
|   | C17 | 100nF     | C_0603_1608Metric | 78.5, 61.4  | C 传感器 + GNSS  |                   |
|   | C18 | 10uF      | C_0805_2012Metric | 78.9, 64.6  | C 传感器 + GNSS  | 板上印着 C6           |
|   | C19 | 15pF C0G  | C_0603_1608Metric | 104.6, 87.7 | B MCU + Flash |                   |
|   | C20 | 15pF C0G  | C_0603_1608Metric | 107.6, 87.7 | B MCU + Flash |                   |
|   | C21 | 100pF     | C_0402_1005Metric | 101.0, 67.5 | E 1090 接收链    |                   |
|   | C22 | 100nF     | C_0603_1608Metric | 95.7, 95.2  | B MCU + Flash |                   |
|   | C23 | 100nF     | C_0603_1608Metric | 99.8, 95.2  | B MCU + Flash |                   |
|   | C24 | 100nF     | C_0603_1608Metric | 103.8, 95.2 | B MCU + Flash |                   |
|   | C25 | 100nF     | C_0603_1608Metric | 109.2, 77.4 | B MCU + Flash | 板上印着 R33，尺寸相同会真贴错 |
|   | C26 | 100nF     | C_0603_1608Metric | 107.8, 95.2 | B MCU + Flash |                   |
|   | C27 | 100nF     | C_0603_1608Metric | 111.9, 95.2 | B MCU + Flash |                   |
|   | C28 | 1uF       | C_0603_1608Metric | 86.5, 87.7  | B MCU + Flash |                   |
|   | C29 | 1uF       | C_0603_1608Metric | 89.5, 87.7  | B MCU + Flash |                   |
|   | C30 | 100pF     | C_0402_1005Metric | 120.4, 62.1 | E 1090 接收链    | 板上印着 L14，尺寸相同会真贴错 |
|   | C31 | 100pF C0G | C_0402_1005Metric | 106.0, 71.2 | E 1090 接收链    |                   |
|   | C32 | 100pF C0G | C_0402_1005Metric | 114.5, 71.2 | E 1090 接收链    |                   |
|   | C33 | 100pF C0G | C_0402_1005Metric | 120.9, 71.2 | E 1090 接收链    |                   |
|   | C34 | 100pF C0G | C_0402_1005Metric | 129.4, 71.2 | E 1090 接收链    |                   |
|   | C35 | 100pF C0G | C_0402_1005Metric | 141.2, 71.2 | E 1090 接收链    |                   |
|   | C36 | 100pF     | C_0402_1005Metric | 103.0, 66.5 | E 1090 接收链    |                   |
|   | C37 | 100nF     | C_0402_1005Metric | 109.6, 85.0 | E 1090 接收链    |                   |
|   | C38 | 100pF     | C_0402_1005Metric | 137.3, 69.2 | E 1090 接收链    |                   |
|   | C39 | 100pF     | C_0402_1005Metric | 140.0, 83.6 | D 978 收发      |                   |
|   | C40 | 3.6pF     | C_0402_1005Metric | 123.6, 76.3 | D 978 收发      |                   |
|   | C41 | 2.7pF     | C_0402_1005Metric | 126.9, 76.3 | D 978 收发      |                   |
|   | C42 | 6.2pF     | C_0402_1005Metric | 130.2, 76.3 | D 978 收发      |                   |
|   | C43 | 3pF       | C_0402_1005Metric | 137.6, 78.3 | D 978 收发      |                   |
|   | C44 | 3.6pF     | C_0402_1005Metric | 121.7, 78.0 | D 978 收发      |                   |
|   | C45 | 100pF     | C_0402_1005Metric | 119.2, 84.3 | D 978 收发      |                   |
|   | C46 | 3pF       | C_0603_1608Metric | 118.7, 86.2 | E 1090 接收链    | 板上印着 C47，尺寸相同会真贴错 |
|   | C47 | 200pF     | C_0603_1608Metric | 118.7, 88.4 | E 1090 接收链    | 板上印着 C46，尺寸相同会真贴错 |
|   | C48 | 1uF       | C_0402_1005Metric | 99.6, 65.5  | E 1090 接收链    |                   |

| 贴 | 位号  | 值 / 型号       | 封装                | 位置 (x, y)    | 阶段            | 备注 |
|---|-----|--------------|-------------------|--------------|---------------|----|
|   | C49 | 100nF        | C_0603_1608Metric | 55.6, 80.1   | E 1090 接收链    |    |
|   | C51 | 1nF          | C_0603_1608Metric | 55.6, 85.2   | E 1090 接收链    |    |
|   | C52 | 100nF        | C_0402_1005Metric | 60.4, 96.2   | E 1090 接收链    |    |
|   | C53 | 100pF        | C_0402_1005Metric | 110.2, 61.2  | E 1090 接收链    |    |
|   | C54 | 100pF        | C_0402_1005Metric | 105.3, 68.1  | E 1090 接收链    |    |
|   | C55 | 100pF        | C_0603_1608Metric | 90.2, 74.0   | E 1090 接收链    |    |
|   | C56 | 100pF        | C_0603_1608Metric | 85.1, 74.0   | E 1090 接收链    |    |
|   | C57 | 100pF        | C_0402_1005Metric | 63.4, 63.3   | C 传感器 + GNSS  |    |
|   | C58 | 100pF        | C_0402_1005Metric | 56.5, 64.6   | C 传感器 + GNSS  |    |
|   | C59 | 100pF        | C_0402_1005Metric | 56.3, 62.4   | C 传感器 + GNSS  |    |
|   | C60 | 22uF         | C_0805_2012Metric | 136.2, 93.1  | D 978 收发      |    |
|   | C61 | 100nF        | C_0603_1608Metric | 121.2, 97.0  | D 978 收发      |    |
|   | C62 | 100nF        | C_0603_1608Metric | 125.1, 97.0  | D 978 收发      |    |
|   | C63 | 100nF        | C_0603_1608Metric | 129.0, 97.0  | D 978 收发      |    |
|   | C64 | 100nF        | C_0603_1608Metric | 132.9, 97.0  | D 978 收发      |    |
|   | C65 | 100nF        | C_0603_1608Metric | 136.8, 97.0  | D 978 收发      |    |
|   | C66 | 22uF         | C_0805_2012Metric | 123.2, 100.5 | D 978 收发      |    |
|   | C67 | 1uF          | C_0603_1608Metric | 126.9, 93.1  | D 978 收发      |    |
|   | C68 | 18pF         | C_0603_1608Metric | 123.1, 93.8  | D 978 收发      |    |
|   | C69 | 18pF         | C_0603_1608Metric | 127.7, 100.5 | D 978 收发      |    |
|   | C81 | 470pF C0G    | C_0402_1005Metric | 118.6, 73.5  | E 1090 接收链    |    |
|   | C82 | 100nF        | C_0402_1005Metric | 83.0, 84.5   | B MCU + Flash |    |
|   | C83 | 100nF        | C_0402_1005Metric | 93.6, 79.5   | B MCU + Flash |    |
|   | C84 | 1uF          | C_0402_1005Metric | 93.6, 82.0   | B MCU + Flash |    |
|   | C85 | 100nF        | C_0402_1005Metric | 96.0, 79.5   | B MCU + Flash |    |
|   | C86 | 100nF        | C_0402_1005Metric | 96.0, 82.0   | B MCU + Flash |    |
|   | C87 | 10nF C0G     | C_0603_1608Metric | 97.8, 84.4   | B MCU + Flash |    |
|   | R1  | 10k          | R_0603_1608Metric | 79.0, 87.2   | C 传感器 + GNSS  |    |
|   | R2  | 4.7k         | R_0603_1608Metric | 61.4, 106.1  | C 传感器 + GNSS  |    |
|   | R3  | 4.7k         | R_0603_1608Metric | 61.4, 108.7  | C 传感器 + GNSS  |    |
|   | R4  | 1k           | R_0603_1608Metric | 110.6, 87.7  | B MCU + Flash |    |
|   | R5  | 10k          | R_0603_1608Metric | 95.7, 98.3   | B MCU + Flash |    |
|   | R6  | 10k          | R_0603_1608Metric | 99.8, 98.3   | B MCU + Flash |    |
|   | R7  | 5.1k         | R_0603_1608Metric | 103.8, 98.3  | B MCU + Flash |    |
|   | R8  | 5.1k         | R_0603_1608Metric | 107.8, 98.3  | B MCU + Flash |    |
|   | R9  | 27R          | R_0603_1608Metric | 92.5, 87.7   | B MCU + Flash |    |
|   | R10 | 27R          | R_0603_1608Metric | 95.6, 87.7   | B MCU + Flash |    |
|   | R11 | 3.32k        | R_0402_1005Metric | 98.8, 68.0   | E 1090 接收链    |    |
|   | R17 | 10k          | R_0603_1608Metric | 121.4, 105.2 | D 978 收发      |    |
|   | R18 | 10k          | R_0603_1608Metric | 136.2, 62.1  | E 1090 接收链    |    |
|   | R19 | 52.3R        | R_0402_1005Metric | 138.5, 71.2  | E 1090 接收链    |    |
|   | R21 | 0R           | R_0603_1608Metric | 115.2, 85.0  | E 1090 接收链    |    |
|   | R22 | 0R           | R_0603_1608Metric | 87.5, 71.2   | E 1090 接收链    |    |
|   | R23 | 0R           | R_0603_1608Metric | 91.4, 71.2   | E 1090 接收链    |    |
|   | R24 | 0R DNP(旁路外接) | R_0402_1005Metric | 112.7, 66.0  | 不贴 (DNP)      |    |
|   | R25 | 0R DNP(旁路板载) | R_0402_1005Metric | 114.8, 66.0  | 不贴 (DNP)      |    |
|   | R26 | 10k          | R_0603_1608Metric | 58.8, 76.4   | C 传感器 + GNSS  |    |
|   | R27 | 10k          | R_0603_1608Metric | 61.8, 73.3   | C 传感器 + GNSS  |    |
|   | R30 | 1k DNP       | R_0402_1005Metric | 108.0, 66.6  | 不贴 (DNP)      |    |

| 贴 | 位号  | 值 / 型号                       | 封装                   | 位置 (x, y)    | 阶段            | 备注                 |
|---|-----|------------------------------|----------------------|--------------|---------------|--------------------|
|   | R31 | 1k                           | R_0603_1608Metric    | 115.0, 87.3  | E 1090 接收链    |                    |
|   | R32 | 10k                          | R_0603_1608Metric    | 112.5, 75.2  | E 1090 接收链    |                    |
|   | R33 | 100k                         | R_0603_1608Metric    | 108.7, 75.2  | E 1090 接收链    | 板上印着 C25, 尺寸相同会真贴错 |
|   | R34 | 10k                          | R_0603_1608Metric    | 55.6, 77.5   | E 1090 接收链    |                    |
|   | R35 | 10k                          | R_0603_1608Metric    | 55.6, 82.6   | E 1090 接收链    |                    |
|   | R36 | 1k DNP                       | R_0603_1608Metric    | 61.4, 103.5  | 不贴 (DNP)      |                    |
|   | R47 | 10k                          | R_0603_1608Metric    | 132.5, 85.0  | D 978 收发      |                    |
|   | R50 | 10k                          | R_0603_1608Metric    | 94.0, 85.2   | B MCU + Flash |                    |
|   | R51 | 10k                          | R_0603_1608Metric    | 96.0, 85.2   | B MCU + Flash |                    |
|   | R52 | 10k                          | R_0402_1005Metric    | 60.0, 83.0   | C 传感器 + GNSS  |                    |
|   | R53 | 10k                          | R_0402_1005Metric    | 63.0, 84.4   | C 传感器 + GNSS  |                    |
|   | R54 | 10R                          | R_0402_1005Metric    | 109.6, 82.1  | E 1090 接收链    |                    |
|   | R55 | 10k                          | R_0603_1608Metric    | 59.1, 80.3   | C 传感器 + GNSS  |                    |
|   | R56 | 10k                          | R_0603_1608Metric    | 132.3, 89.7  | D 978 收发      |                    |
|   | R57 | 33R                          | R_0603_1608Metric    | 85.7, 95.3   | E 1090 接收链    |                    |
|   | L1  | 18nH 0402CS-18NXGRW          | L_0402_1005Metric    | 105.5, 69.8  | E 1090 接收链    |                    |
|   | L2  | 33nH                         | L_0402_1005Metric    | 61.8, 64.8   | C 传感器 + GNSS  |                    |
|   | L7  | 6.8uH                        | L_0805_2012Metric    | 131.5, 93.1  | D 978 收发      |                    |
|   | L8  | 100nH                        | L_0402_1005Metric    | 142.6, 87.0  | D 978 收发      |                    |
|   | L9  | 7.5nH                        | L_0402_1005Metric    | 124.2, 78.0  | D 978 收发      |                    |
|   | L10 | 27nH                         | L_0402_1005Metric    | 120.8, 76.3  | D 978 收发      |                    |
|   | L11 | 6.8nH                        | L_0402_1005Metric    | 134.2, 76.3  | D 978 收发      |                    |
|   | L12 | 6.8nH                        | L_0402_1005Metric    | 137.6, 76.3  | D 978 收发      |                    |
|   | L13 | 7.5nH                        | L_0402_1005Metric    | 119.2, 83.2  | D 978 收发      |                    |
|   | L14 | 100nH                        | L_0402_1005Metric    | 120.4, 63.3  | E 1090 接收链    | 板上印着 C30, 尺寸相同会真贴错 |
|   | L15 | 33nH                         | L_0402_1005Metric    | 58.0, 67.6   | C 传感器 + GNSS  |                    |
|   | D1  | B5819W                       | D_SOD-123            | 97.8, 91.3   | B MCU + Flash | 有极性, 认阴极标记带        |
|   | D2  | TPESD8L3.3 0.3pFtyp 0.5pFmax | D_0402_1005Metric    | 128.3, 62.1  | E 1090 接收链    |                    |
|   | D3  | TPESD8L3.3 0.3pFtyp 0.5pFmax | D_0402_1005Metric    | 140.0, 86.9  | D 978 收发      |                    |
|   | D4  | TPESD8L3.3 0.3pFtyp 0.5pFmax | D_0402_1005Metric    | 60.0, 90.4   | B MCU + Flash |                    |
|   | D5  | TPESD8L3.3 0.3pFtyp 0.5pFmax | D_0402_1005Metric    | 60.0, 93.6   | B MCU + Flash |                    |
|   | F2  | 6V/200mA                     | Fuse_0805_2012Metric | 129.8, 105.2 | D 978 收发      |                    |
|   | F3  | 6V/200mA                     | Fuse_0805_2012Metric | 140.2, 62.1  | E 1090 接收链    |                    |
|   | F4  | 6V/200mA                     | Fuse_0805_2012Metric | 61.8, 67.4   | C 传感器 + GNSS  |                    |
|   | F5  | 6V/200mA                     | Fuse_0805_2012Metric | 56.4, 69.7   | C 传感器 + GNSS  |                    |
|   | Q2  | AO3401A                      | SOT-23               | 125.1, 105.2 | D 978 收发      |                    |
|   | Q3  | AO3401A                      | SOT-23               | 132.0, 62.1  | E 1090 接收链    |                    |
|   | Q4  | AO3401A                      | SOT-23               | 61.8, 70.2   | C 传感器 + GNSS  |                    |
|   | Q5  | AO3401A                      | SOT-23               | 57.8, 72.6   | C 传感器 + GNSS  |                    |
|   | U1  | ME6211C33M5                  | SOT-23-5             | 69.4, 93.3   | A 电源          | 认 pin1 (缺角/圆点)     |
|   | U2  | TPS7A2033PDBVR               | SOT-23-5             | 63.1, 93.3   | A 电源          | 认 pin1 (缺角/圆点)     |
|   | U3  | TPS7A2033PDBVR               | SOT-23-5             | 74.3, 93.3   | A 电源          | 认 pin1 (缺角/圆点)     |
|   | U4  | BNO085                       | BNO085_LGA-28        | 63.7, 78.3   | C 传感器 + GNSS  | 认 pin1 (缺角/圆点)     |
|   | U5  | BMP388                       | BMP388_LGA-10        | 71.3, 81.2   | C 传感器 + GNSS  | 认 pin1 (缺角/圆点)     |
|   | U6  | QMC5883P                     | LGA-16_3x3mm_P0.5mm  | 71.3, 77.0   | C 传感器 + GNSS  | 认 pin1 (缺角/圆点)     |

| 贴 | 位号   | 值 / 型号                    | 封装                                    | 位置 (x, y)    | 阶段            | 备注                       |
|---|------|---------------------------|---------------------------------------|--------------|---------------|--------------------------|
|   | U7   | ATGM336H-6N-74            | ATGM336H_LCC-18                       | 70.4, 66.4   | C 传感器 + GNSS  | 认 pin1 (缺角/圆点)           |
|   | U8   | RP2040                    | QFN-56-1EP_7x7mm_P0.4mm_EP3.2         | 88.4, 80.5   | B MCU + Flash | 认 pin1 (缺角/圆点)           |
|   | U9   | W25Q128JVS1Q              | SOIC-8_5.3x5.3mm_P1.27mm              | 103.4, 82.1  | B MCU + Flash | 认 pin1 (缺角/圆点)           |
|   | U10  | CC1312R1F3RGZR            | QFN-48-1EP_7x7mm_P0.5mm_EP5.1         | 126.2, 85.0  | D 978 收发      | 认 pin1 (缺角/圆点)           |
|   | U11  | QPL9547TR7                | DFN-8-1EP_2x2mm_P0.5mm_EP0.8          | 101.6, 71.2  | E 1090 接收链    | 认 pin1 (缺角/圆点)           |
|   | U12  | BGA2817                   | SOT-363_SC-70-6                       | 117.7, 71.2  | E 1090 接收链    | 认 pin1 (缺角/圆点)           |
|   | U14  | AD8313ARMZ                | MSOP-8_3x3mm_P0.65mm                  | 114.1, 82.1  | E 1090 接收链    | 认 pin1 (缺角/圆点)           |
|   | U15  | TLV3501(TOKMAS)           | SOT-23-6                              | 83.1, 91.3   | E 1090 接收链    | 认 pin1 (缺角/圆点)           |
|   | U16  | XA17-G4K                  | SOT-363_SC-70-6                       | 114.6, 62.1  | E 1090 接收链    | 认 pin1 (缺角/圆点)           |
|   | U17  | XA17-G4K                  | SOT-363_SC-70-6                       | 58.8, 63.3   | C 传感器 + GNSS  | 认 pin1 (缺角/圆点)           |
|   | FL1  | TA0970A                   | TA0970A_SMD3838-6                     | 110.2, 71.2  | E 1090 接收链    | SAW 滤波器分输入输出, 贴反不工作      |
|   | FL2  | TA0970A                   | TA0970A_SMD3838-6                     | 125.1, 71.2  | E 1090 接收链    | SAW 滤波器分输入输出, 贴反不工作      |
|   | Y1   | 12MHz CL=10pF ABM8-272-T3 | Crystal_SMD_3225-4Pin_3.2x2.5mm       | 100.4, 87.7  | B MCU + Flash | 无源晶体, 转 180° 等价, 长边对长边即可 |
|   | Y2   | 48MHz ABM8W-7pF           | Crystal_SMD_3225-4Pin_3.2x2.5mm       | 133.8, 81.7  | D 978 收发      | 无源晶体, 转 180° 等价, 长边对长边即可 |
|   | Y3   | 32.768kHz FC-135          | Crystal_SMD_3215-2Pin_3.2x1.5mm       | 122.7, 91.3  | D 978 收发      |                          |
|   | J1   | J3_HAT_2x20_SMD排针         | PinHeader_2x20_P2.54mm                | 92.6, 106.3  | F 对外接口        |                          |
|   | J2   | U.FL_GNSS_EXT(经尾线转SMA)    | U.FL_Hirose_U.FL-R-SMT-1_Vertical     | 52.9, 74.1   | C 传感器 + GNSS  |                          |
|   | J4   | USB-C_16P                 | USB_C_Receptacle_HRO_T C-31-M-12      | 53.5, 92.0   | B MCU + Flash |                          |
|   | J5   | U.FL_978                  | U.FL_Hirose_U.FL-R-SMT-1_Vertical     | 145.5, 83.5  | D 978 收发      |                          |
|   | J6   | U.FL_1090_EXT(经尾线转SMA)    | U.FL_Hirose_U.FL-R-SMT-1_Vertical     | 124.3, 62.1  | E 1090 接收链    |                          |
|   | J7   | U.FL_IFA_TEST(π后调试口)      | U.FL_Hirose_U.FL-R-SMT-1_Vertical     | 103.1, 61.3  | E 1090 接收链    |                          |
|   | J8   | U.FL→内置patch              | U.FL_Hirose_U.FL-R-SMT-1_Vertical     | 52.9, 64.4   | C 传感器 + GNSS  |                          |
|   | ANT1 | IFA_1090                  | ANT_IFA_1090MHz                       | 85.5, 57.8   | 不贴 (板载天线)     |                          |
|   | ZP1  | DNP 并-天线侧                 | C_0603_1608Metric                     | 85.5, 63.6   | 不贴 (DNP)      |                          |
|   | ZP2  | DNP 并-电台侧                 | C_0603_1608Metric                     | 90.5, 63.6   | 不贴 (DNP)      |                          |
|   | ZS1  | OR 串                      | L_0603_1608Metric                     | 88.0, 62.9   | E 1090 接收链    |                          |
|   | SW1  | RESET短接焊盘                 | SolderJumper-2_P1.3mm_Open_Pad1.0x1.5 | 88.7, 91.3   | 不贴 (短接焊盘)     |                          |
|   | SW2  | BOOTSEL短接焊盘               | SolderJumper-2_P1.3mm_Open_Pad1.0x1.5 | 92.9, 91.3   | 不贴 (短接焊盘)     |                          |
|   | TP1  | TestPoint                 | TestPoint_Pad_1.0x1.0mm               | 102.0, 91.3  | 不贴 (测试点焊盘)    |                          |
|   | TP2  | TestPoint                 | TestPoint_Pad_1.0x1.0mm               | 104.9, 91.3  | 不贴 (测试点焊盘)    |                          |
|   | TP3  | TestPoint                 | TestPoint_Pad_1.0x1.0mm               | 107.8, 91.3  | 不贴 (测试点焊盘)    |                          |
|   | TP4  | TestPoint                 | TestPoint_Pad_1.0x1.0mm               | 110.7, 91.3  | 不贴 (测试点焊盘)    |                          |
|   | TP5  | TestPoint                 | TestPoint_Pad_1.0x1.0mm               | 113.5, 91.3  | 不贴 (测试点焊盘)    |                          |
|   | TP6  | TestPoint                 | TestPoint_Pad_1.0x1.0mm               | 116.4, 91.3  | 不贴 (测试点焊盘)    |                          |
|   | TP7  | TestPoint                 | TestPoint_Pad_1.0x1.0mm               | 80.7, 78.7   | 不贴 (测试点焊盘)    |                          |
|   | H1   | —                         | MountingHole_2.7mm_M2.5               | 54.0, 56.0   | 不贴 (安装孔)      |                          |
|   | H2   | —                         | MountingHole_2.7mm_M2.5               | 146.0, 56.0  | 不贴 (安装孔)      |                          |
|   | H3   | —                         | MountingHole_2.7mm_M2.5               | 54.0, 106.0  | 不贴 (安装孔)      |                          |
|   | H4   | —                         | MountingHole_2.7mm_M2.5               | 146.0, 106.0 | 不贴 (安装孔)      |                          |