



Online COD Sensor Modbus Protocol

MODBUS RTU Transmission Mode

Encoding system	8-bit binary Each 8-bit byte in the protocol contains two 4-bit hexadecimal characters (0-9, A-F)
Bit per byte	1 start bit 8 data bits, the least significant bit is sent first No parity check bit 1 stop bit
Baud rate	9600bps
Message parsing: 32-bit floating-point number parsing method (ABCD first adjusts the order to DCBA, then parsing)	
Set slave ID	Original address 01 , after setting address 02 01 10 08 00 00 01 02 02 00 2E F0 01 10 08 00 00 01 03 A9
Get temperature and COD 31.43 °C / 8 mg/L	01 03 20 00 00 04 4F C9 01 03 08 DA 77 FB 41 00 00 00 41 F6 47
Get BOD/TOC 3.2	01 03 20 04 00 02 8E 0A 01 03 04 CD CC 4C 40 31 90
Get Turbidity 10 NTU	01 03 21 00 00 02 CE 37 01 03 04 00 00 20 41 23 C3
Get COD user calibration parameters K=1 B=9	SEND: 01 03 22 00 00 04 4E 71 GET: 01 03 08 00 00 80 3F 00 00 10 41 58 27
Set COD user calibration parameters K=1 B=9	SEND: 01 10 22 00 00 04 08 00 00 80 3F 00 00 10 41 03 A8 GET: 01 10 22 00 00 04 CB B2
Get slave address ID 01	FF 03 08 00 00 01 93 B4 FF 03 02 01 00 90 00
Get the brush rotation interval of 30 min	01 03 32 00 00 01 8A B2 01 03 02 1E 00 B1 E4
Set the brush rotation interval 10 minutes	01 10 32 00 00 01 02 0A 00 B3 33 01 10 32 00 00 01 0F 71 (Convert 10 to hexadecimal 0A)
Turn on the brush	01 10 13 00 00 00 00 8C 93 01 10 13 00 00 00 C4 8D