

[← Go Back](#)

Hardware

Stella ▼

Tutorials

Arduino Stella User Manual

UWB-Activated
Workspace and
Equipment Control


Home / Hardware / Stella / **UWB-Activated Workspace and Equipment Control**

UWB-Activated Workspace and Equipment Control

Learn how to create a UWB-based access control and equipment safety system for industrial workspaces using precise proximity detection.

Author · Taddy Chung · Last revision · 06/19/2025

This application note shows how to create a UWB-based workspace access control and equipment safety system. You will learn how to build a system where users carry an Arduino Stella as a personal keychain, enabling automatic workspace access and equipment operation based on precise proximity detection.



Introduction

Industrial workspaces require controlled access and equipment safety systems to ensure that only authorized

ON THIS PAGE

Introduction

- Goals
- Hardware and Software Requirements +
- System Overview +
- Hardware Setup +
- Implementing the Workspace Control System +
- System Operation & Deployment
- System Testing
- Complete UWB Activated Workspace & Equipment Control Example
- Conclusion

that may require specialized care and capabilities. Traditional solutions, such as RFID cards or key fobs, require manual interaction and lack the precision necessary for advanced safety features in some remote or keyless activations. Ultra-wideband (UWB) technology offers an approach that provides hands-free, centimeter-accurate proximity detection.

In this application note, we will create a UWB-based workspace control system where users carry Arduino Stella devices as personal tags. These tags automatically unlock workspace doors when users approach within the defined radius and enable machinery operation when they are within a separately defined radius, for example. When users move away, the system automatically secures the workspace and disables equipment, ensuring both security and safety.

This implementation demonstrates the ability of UWB technology to create responsive industrial environments that enhance productivity and safety through customizable capabilities. The application note example demonstrates two distinct proximity zones: a larger access zone for workspace entry and a precise safety zone for equipment operation, highlighting UWB's attractive

Goals

This application note has the following objectives:

- Create a UWB-based workspace access control system using Arduino Stella as personal tags

- Implement dual-zone proximity detection for workspace access and equipment operation with Portenta UWB Shield

- Configure automated door control and machine safety systems with hands-free, secure access control without manual interaction

- Showcase UWB technology's precision for industrial safety applications

Hardware and Software Requirements



Required hardware

Hardware Requirements

Portenta UWB Shield
(SKU: ASX00074) (x1)

Portenta C33 (SKU: ABX00074) (x1)

Arduino Stella (SKU: ABX00131) (x1)

USB-C® cable (SKU:

Relay modules (If implemented in real world scenario) (x2)

Software Requirements

Arduino IDE 2.0+

Portenta UWB Shield

library (for the Portenta UWB Shield)

Arduino Stella library (for the Arduino Stella)

Arduino Renesas

Portenta Boards core (for the Portenta C33)

Arduino mbed OS Boards core (for the Arduino Stella)

System Overview

UWB Technology for Industrial Access Control

Ultra-Wideband technology can provide the precision and reliability for industrial access control applications. Unlike traditional proximity technologies that may require additional technical and hardware considerations, UWB's centimeter-level accuracy ensures that access and equipment control only occur when the user or personnel are in the correct physical location, in a compact form factor.

The system works on two


Workspace Access Zone: When an authorized user carrying an Arduino Stella approaches within a particularly programmed distance of the UWB Shield base station, the workspace door automatically unlocks, granting access to the authorized area. Otherwise, the workspace door remains locked.

Equipment Operation Zone: When the authorized user approaches machinery or equipment within the defined operational safety radius, the equipment becomes enabled for operation. This proximity requirement helps the user be positioned safely near the controls, and the machine is enabled only when the user is present within the operating radius.

The system automatically reverses these actions when the authorized user moves away, providing continuous safety monitoring and access control without requiring manual interaction. It also helps to prevent accidental access to the workspace and the equipment.

System Architecture

The system consists of the following elements:



Arduino Stella (Personal

Tag): Worn by users as a keychain or badge, providing unique identification and proximity detection

Portenta C33 + UWB**Shield (Base Station):**

Installed in the workspace, monitoring proximity and controlling access systems

Door and Equipment**Control System:**

Connected to the Portenta C33 and Portenta UWB Shield station's GPIO output, managing workspace access and controlling machinery operation

Visual Feedback: LED indicators on both devices show system status and proximity zones

Hardware Setup

UWB Shield Station

Installation

The Portenta C33, equipped with the Portenta UWB Shield, will be configured as the workspace control hub and installed in the workspace. Connect the UWB Shield to the Portenta C33 using the High-Density connectors, ensuring proper alignment and secure connection.


Position the Portenta UWB Shield station strategically within the workspace to provide optimal coverage of the entrance area and the

coverage area can be customized, and for the present application note example, we will use:

30 cm (A) for machinery/equipment control

1 meter (B) for workspace door control

These values define the activation zones based on user proximity. Ensure the station has a clear line of sight to all areas where users are expected to move.



Portenta UWB Shield
Setup

The station will be programmed to control external systems using two GPIO outputs from the Portenta C33. We can use:

Pin D2 for the door control relay, which activates within 1 meter


Pin D3 for the machine control relay, which activates within 30 cm

Use these pins with appropriate relay modules that interface with your door locks and equipment control systems. Ensure proper electrical isolation and safety protocols when connecting to industrial equipment in a real-world implementation.

In this application note example, we can use these two pins to turn on LEDs to simulate activation status.

Arduino Stella Configuration

The Arduino Stella requires no hardware modification and can be modeled as a keychain, clipped to clothing or integrated into user identification badges. The device's compact size and battery operation make it ideal for personal carrying without interfering with activities.



Arduino Stella Setup

Implementing the Workspace Control System

Portenta UWB Shield Station Implementation

The base station manages all proximity detection and control system activation. The base station is configured as a **Controlee/Responder** in the UWB protocol, meaning it responds to ranging requests initiated by the Arduino Stella.

Below is the complete code implementing dual zone proximity control for the Portenta UWB Shield:

```

1  /**
2   UWB Workspace Acc
3   Base Station (Con
4  */
5
6  // Include required
7  #include <Portental
8
9  // Define proximity
10 #define WORKSPACE_A
11 #define EQUIPMENT_C
12
13 // GPIO pin definit
14 #define DOOR_CONTRC
15 #define MACHINE_COM
16
17 // Variables for LE
18 unsigned long lastR
19 const int RED_LED_B
20
21 // Variables for pr
22 unsigned long lastP
23 #define DEBOUNCE_T1
24
25 // System state tra
26 bool doorUnlocked =
27 bool machineEnabled
28 bool lastDoorState

```

In this code, you can adjust the perimeters and the pins to use as triggers in the following lines:

```

1  // Define proximity th
2  #define WORKSPACE_ACCE
3  #define EQUIPMENT_OPER
4
5  // GPIO pin definition
6  #define DOOR_CONTROL_P
7  #define MACHINE_CONTRC

```

Personal Stella Implementation

The Arduino Stella provides user identification and proximity sensing. It is configured as a **Controller/Initiator**, meaning it initiates the ranging requests and processes the distance information. The Arduino Stella controls its built-in LED (`p37`) based on its proximity to the base station, with dynamic blinking rates based on distance.

Below is the complete code for the Arduino Stella. To compile and upload the code to Arduino Stella, please select **Arduino Nano 33 BLE** as the target board:



```

1  /**
2   UWB Tag (Controll
3  */
4
5  // Include required
6  #include <StellaUWE
7
8  // Define proximity
9  #define WORKSPACE_A
10 #define EQUIPMENT_C
11
12 // Variables for LE
13 int blinkInterval =
14 bool ledState = fal
15 bool lastLedPhysica
16 unsigned long lastS
17 unsigned long lastB
18 #define DEBOUNCE_T1
19
20 // Stella's built-i
21 #define LED_PIN p37
22
23 /**
24  Processes ranging
25  @param rangingDat
26  */
27 void rangingHandler
28   Serial.print("GOT

```

In this code, you can adjust the perimeters in the following lines:

```


1  // Define proximity th
2  #define WORKSPACE_ACCE
3  #define EQUIPMENT_OPER

```

System Operation & Deployment


Once you have uploaded the corresponding code to the **Arduino Stella** and the

UWB workspace control system operating with dual zone proximity detection to provide automated access control and equipment safety management. With this, the system will do the following tasks:



Workspace Access Zone: When an authorized user approaches within 1 meter of the Portenta UWB Shield station, the system automatically unlocks the workspace door by activating the door control relay connected to pin D2.

The base station's **green LED** illuminates to confirm the unlocked status. At the same time, the user's Arduino Stella begins slow blinking at 500 ms intervals to indicate workspace access authorization.



Equipment Operation Zone (30 centimeters): When the user moves within 30 centimeters of the Portenta UWB Shield station, the pin D3 connected to the machine control relay is activated, enabling connected equipment for operation.

equipment is enabled. At the same time, the Arduino Stella switches to rapid blinking at 100 ms intervals to indicate the equipment operation zone.

The system provides comprehensive visual feedback through multiple LED indicators, allowing users and supervisors to quickly understand the current system status.

The Portenta UWB Shield station uses three different colored LEDs to indicate different aspects of system operation.

Red LED continuously blinks to indicate that the UWB system is operational and actively monitoring user proximity.

Green LED provides visual confirmation of workspace door status, remaining illuminated when the workspace is unlocked and turning off when the area is secured.

Blue LED indicates equipment status, glowing when machinery is enabled for operation and turning off when equipment is disabled.

The user's Arduino Stella also provides visual feedback about their authorization status. The LED remains off when the user is outside the workspace beyond the 1 meter threshold, indicating they are beyond the authorization required area.


Upon entering the workspace zone within 1 meter of the base

confirm workspace access authorization.

When the user approaches equipment within the 30 centimeter operation zone, the LED switches to fast blinking at 100 ms intervals, providing feedback that they are in position to operate the machinery.

System Testing

The following animation illustrates a workflow where an Arduino Stella user approaches the workspace, operates machinery, completes their task and leaves. The system automatically manages workspace access and equipment control and then secures everything when the authorized user leaves.



You can test out the UWB-activated workspace and equipment control by following these testing steps:

Workspace Access Testing:

approach the workspace from multiple directions while monitoring the 1 meter activation zone. Verify that the door control pin activates consistently at the correct

threshold. The LED indicators should represent door status throughout these movements.

Equipment Operation Testing:

test the 30 cm equipment activation zone from various approach angles and verify immediate equipment shutdown when you move beyond the safety radius. Check that equipment control only activates when workspace access is already granted and test quick entry and exit movements to verify that debouncing prevents false activations.

System Integration Testing:


Validate the operations visually from approach to operation to departure. Test system responsiveness during quick zone transitions, check LED feedback to ensure it matches control outputs, and check system behavior with multiple approach patterns.

With this, you will have tested an example of the UWB technology's centimeter level precision through immediate response to proximity changes and visual feedback of operational status, showing its intuitive implementation for industrial applications.

Complete UWB Activated Workspace &

Equipment Control Example

All the necessary files to test this application note example can be downloaded [here](#).



Conclusion

In this application note, you have learned to create a basic UWB-based workspace control system that can provide security and safety improvement in industrial environments requiring quick area transitions. By implementing the centimeter level precision of UWB technology, we have made a system that provides uninterrupted automatic access control and equipment operation management using Arduino Stella and the Portenta UWB Shield as a base station.

The application note's dual-zone implementation example shows UWB's capability to create multiple control levels within a single system, from broad workspace access to precise equipment operation zones. You can extend this system to support multiple users, additional equipment zones, and integration with existing industrial control systems.

Suggest changes	Need support?	License
The content on docs.arduino.cc is facilitated through a public GitHub repository. If you see anything wrong, you can edit this page here.	Help Center Ask the Arduino Forum Discover Arduino Discord	The Arduino documentation is licensed under the Creative Commons Attribution-Share Alike 4.0 license.

Was this article helpful?

