mahindra Rise

powerol by Mahindra

62.5kVA Generator

GENSET PARAMETERS	
kVA (Prime)	62.5
kW (Prime)	50
Engine Make & Model	Mahindra & Mahindra Ltd. (4905 G18)
Alternator Make	Stamford/ Leroy Somer
Phase	3 Phase
Voltage	400 V, 3-phase
Frequency / Engine Speed	60 Hz /1800 rpm
Rated Current (A)	90.2 (3-phase)
Power Factor (p.f.)	0.8 (Lag)
Fuel Tank Capacity (Litre)	185
Noise Level	79dBA at 1meters
Conformance to Standards	ISO 8528

ENGINE PARAMETERS	
Model	4905 G18
Make	Mahindra & Mahindra Ltd.
Rated power @100% Load (HP)	82
Cylinders	4
Aspiration	TCI
Displacement (in CC)	2731
Bore x Stroke (in mm)	96 x 122
Governing Class	A1
Lubricant Capacity (in Litre)	10
Radiator Coolant Capacity (in Litre)	15
Fuel	High Speed Diesel
Lube Oil Specification	Maximile 10K CF4
Starting System (V)	12 V, Electrical
Cooling System	Water cooled with Radiator

FUEL CONSUMPTION	
Fuel Consumption @ 100% Load (Prime)	15.3 Litre/hrs.
Fuel Consumption @ 75% Load (Prime)	11.3 Litre/hrs.

LOGISTIC DATA	
Dimensions (L x W x H) (in mm)	Silent Set : 2400 x 1050 x 1523 (H - w/o silencer & foot)
Approx. Net Wt. (in Kg.)	Silent Set : 1293

ALTERNATOR PARAMETERS	
Make	Stamford/ Leroy Somer
Type	Brushless, Single Bearing, Self Excited
Voltage	400 V, 3 - Phase
Phase	3 Phase
Frequency	60 Hz
Speed	1800 RPM
Voltage Regulation	+/- 1%
Insulation class	H
Ingress Protection	IP 23

CONTROL PANEL PARAMETERS	
Control Panel Type	Manual control Panel with microprocessor based controller (Standard)/ AMF (Optional)
Controller Make & Type	Deep Sea Controller (4521/7320)
Protection Features offered by controller	Engine - High Water Temperature, Low Lube oil pressure, Low Fuel Level Electrical - Generator Under/ Over Voltage, Generator Under/Over Frequency, Generator Over Current, Generator kW Overload

powerol by Mahindra

Mahindra & Mahindra Ltd.
Mahindra Powerol
MHEL, 1st Floor, Gate No. 12,
A-1/1, Talawade Chakan Rd,
Chakan Industrial Area, Phase-IV, Nigoje,
Maharashtra, 410501.

poweroldg@mahindra.com

mahindrapowerol.com

kVA CPCB2 - DEC 22