

API Specification for IT Integration

V1.0 First Version - May 2023

V1.1 Minor Revision - June 2023

V1.2 Add Production Servers - August 2023

V1.3 Use 8443 to Access the Production Servers - August 2023

V1.4 Put parameters in URL for B07 and B09 - September 2023

V1.5 Response with user_id in B09 - October 2023

V1.6 Add B10 to include device packages together with user packages - October 2023

V1.7 Add B03-2 to return the content name of the packages - November 2023

V1.8 Add B11 to delete the device provision - December 2023

V1.9 B03-02 add partner_content_id to contents - March 2024

V1.10 B11 user_id optional - April 2024

V1.11 B09 add fid to platform/device_provisions - April 2024

How to Hit The Servers

The staging server can be accessed by <http://34.101.95.173:8003>.

The production server can be accessed by <https://iapi-cpe.sysln.id:8443>.

How to Generate EQOTT

EQOTT=MD5('EQOTT'+API_VERSION); //API_VERSION='v1'

Here EQOTT='498043bbf992b879829051da39eafec0' for your reference.

How to Generate Token

DATE = UTC+7 Date format 'YYYY-MM-DD'. Ex: '2023-03-16';

KEY='firstmedia@acv3874428te632df53123oo';

TOKEN=MD5(DATE + KEY);

Test sample:

If DATE='2023-05-29', TOKEN='35f874e64eb200b4f2abf38b9ed426d7'

B01 Create Account

Description	Create an account
URL	v1/platform/account

Method	PUT
URL Params	N/A
Header	EQOTT Token
Request Body	(Required) fid: first media customer id (Optional) password (Optional) name (Optional) mobile (Optional) email Sample: { "fid": "test@gmail.com", "password": "passwd2", "name": "Jason Test", "email": "test@gmail.com", "mobile": "123456789" }
Mechanism	Multiple calls with the same fid will overwrite the database record and return the same user_id. We don't do format checking for any input data field.
Success Response Status Code: 200	<pre>{ "code": 0, "msg": "SUCCESS", "data": { "email": "test@gmail.com", "fid": "test@gmail.com", "mobile": "123456789", "name": "Jason Test", "user_id": "64745f54cafc08c8127d9b5b" } }</pre>
Error Response Status Code: 200	<pre>{ "code": 400, "msg": "Fid or password error", "data": {} }</pre>

B02 Delete Account

Description	Delete an account
URL	v1/platform/account
Method	DELETE
URL Params	N/A
Header	EQOTT Token
Request Body	(Required) user_id // from API B01 Sample: { "user_id": "64745f54cafc08c8127d9b5b" }
Mechanism	The database record of the account will be deleted. If the record of the given user_id cannot be found, the API will return an error.
Success Response Status Code: 200	{ "code": 0, "msg": "SUCCESS", "data": {} }
Error Response Status Code: 200	{ "code": 400, "msg": "User ID invalid", "data": {} }

B03 Get Package List

Description	Get the package list
URL	v1/platform/packages
Method	GET
URL Params	N/A
Header	EQOTT Token

Request Body	N/A
Mechanism	Get the package list in the database including both channel packages and VOD packages.
Success Response Status Code: 200	<pre> { "code": 0, "msg": "SUCCESS", "data": [{ "id": "6470a272d5aaaceaf4fbf2ff", "name": "Regional News Pack\n(FTTH & HFC) ", "package_id": "pkg_chn_0048", "type": "channel", "clude_type": "include", "channel_content_ids": ["684", "1142", "1460", "2557", "2221", "1259",] }, { "id": "6470a275d5aaaceaf4fbf30a", "name": "MACH 1 Gbps", "package_id": "pkg_chn_0016", "type": "channel", "clude_type": "exclude", "channel_content_ids": [] }] } </pre>
Error Response Status Code: 200	

B03-2 Get Package List with Content Name

Description	Get the package list with content names
URL	v1/platform/packages2

Method	GET
URL Params	package_id - optional to specify a package, return all packages in default. lang - optional for language of the content name, en in default
Header	EQOTT Token
Request Body	N/A
Mechanism	Get the package list in the database with content names.
Success Response Status Code: 200	<pre> { "code": 0, "msg": "SUCCESS", "data": [{ "id": "64a523ee084a6da0f484ef8e", "name": "Box Office HD\n(FTTH & HFC)", "package_id": "pkg_chn_0026", "type": "channel", "clude_type": "include", "contents": [{ "content_id": "207", "name": "MTV LIVE HD", "partner_content_id": "CH0000207" }, { "content_id": "95", "name": "Animax HD", "partner_content_id": "CH0000095" }, { "content_id": "13", "name": "MTV 90s HD", "partner_content_id": "CH0000013" }] }, { "id": "64e41d18b20dbf9dbd520ec0", "name": "VOD GEM", </pre>

	<pre> "package_id": "pkg_vod_0009", "type": "video", "clude_type": "include", "contents": [{ "content_id": "3268", "name": "Delivery Man E10", "partner_content_id": "VO0003268" }, { "content_id": "3269", "name": "Delivery Man E09", "partner_content_id": "VO0003269" },] }] } </pre>
Error Response Status Code: 200	

B04 (Legacy) Add User Provision

B05 (Legacy) Remove User Provision

B06 Set User Provisions

Description	Set packages for the given user account.
URL	v1/platform/user_provisions
Method	POST
URL Params	N/A
Header	EQOTT Token
Request Body	user_id: user id, code: package_code1, package_code2, ... Sample: {

	<pre> "user_id": "64745f54cafc08c8127d9b5b", "code": "pkg_vod_0005, pkg_chn_0016" } </pre>
Mechanism	The package codes in the parameter will overwrite the records. To remove all the packages for the user, please give an empty code list in the request.
Success Response Status Code: 200	<pre> { "code": 0, "msg": "SUCCESS", "data": [{ "id": "6475d3c79d8554ae714b99eb", "name": "MACH 1 Gbps", "package_id": "pkg_chn_0016" }, { "id": "6476bb9b21d35960dc61941a", "name": "VOD Animax", "package_id": "pkg_vod_0005" }] } </pre>
Error Response Status Code: 200	<pre> { "code": 3002, "msg": "Invalid User or Device Id", "data": {} } { "code": 2002, "msg": "Invalid Package code:pkg_chn_0099", "data": {} } </pre>

B07 Get User Provisions

Description	Get the packages of the given user account.
URL	v1/platform/user_provisions
Method	GET

URL Params	User_id Sample: v1/platform/user_provisions?user_id=64d48a8a403f80414ff6b899
Header	EQOTT Token
Request Body	N/A
Mechanism	Get the packages of given user_id
Success Response Status Code: 200	<pre>{ "code": 0, "msg": "SUCCESS", "data": [{ "id": "6475d3c79d8554ae714b99eb", "name": "MACH 1 Gbps", "package_id": "pkg_chn_0016" }, { "id": "6476bb9b21d35960dc61941a", "name": "VOD Animax", "package_id": "pkg_vod_0005" }] }</pre>
Error Response Status Code: 200	<pre>{ "code": 3002, "msg": "Invalid User or Device Id", "data": {} }</pre>

B08 Set Device Provisions

Description	Set packages for the binded device of a specific user.
URL	v1/platform/device_provisions
Method	POST
URL Params	N/A
Header	EQOTT

	Token
Request Body	device_id: device id, user_id: user id, code: package_code1, package_code2, ... Sample: <pre>{ "user_id": "64745f54cafc08c8127d9b5b", "device_id": "cfb0dad0-80b5-4f3b-ad10-18bc6811c1d5", "code": "pkg_vod_0005, pkg_chn_0016" }</pre>
Mechanism	The package codes in the parameter will overwrite the records. If the user_id doesn't exist in the database, the API call will fail. For the new device, a new record will be inserted into the database. To remove all the packages for the device, please give an empty code list in the request.
Success Response Status Code: 200	<pre>{ "code": 0, "msg": "SUCCESS", "data": [{ "id": "6475d3c79d8554ae714b99eb", "name": "MACH 1 Gbps", "package_id": "pkg_chn_0016" }, { "id": "6476bb9b21d35960dc61941a", "name": "VOD Animax", "package_id": "pkg_vod_0005" }] }</pre>
Error Response Status Code: 200	<pre>{ "code": 2002, "msg": "Invalid Package code:pkg_chn_0099", "data": {} } { "code": 3002, "msg": "Invalid User or Device Id", "data": {} }</pre>

	}
--	---

B09 Get Device Provisions

Description	Get the packages of the given device_id
URL	v1/platform/device_provisions
Method	GET
URL Params	Device_id Sample: v1/platform/device_provisions?device_id=cfb0dad0-80b5-4f3b-ad10-18bc6811c1d5
Header	EQOTT Token
Request Body	N/A
Mechanism	Get the packages of given device_id. The user_id which the device belongs to will be returned as well.
Success Response Status Code: 200	<pre>{ "code": 0, "msg": "SUCCESS", "user_id": "64745f54cafc08c8127d9b5b", "fid": "31827601", "data": [{ "id": "6475d3c79d8554ae714b99eb", "name": "MACH 1 Gbps", "package_id": "pkg_chn_0016" }, { "id": "6476bb9b21d35960dc61941a", "name": "VOD Animax", "package_id": "pkg_vod_0005" }] }</pre>
Error Response Status Code: 200	<pre>{ "code": 2001, "msg": "Invalid Device Id",</pre>

	<pre>"data": {} }</pre>
--	-------------------------

B10 Get User and Device Provisions

Description	Get the user and device packages of the given user account.
URL	v1/platform/user_device_provisions
Method	GET
URL Params	User_id Sample: <u>v1/platform/user_device_provisions?user_id=64d48a8a403f80414ff6b899</u>
Header	EQOTT Token
Request Body	N/A
Mechanism	Get the user and device packages of the given user_id
Success Response Status Code: 200	<pre>{ "code": 0, "msg": "SUCCESS", "data": { "user_devices": [{ "device_id": "device_64afa425699d0b6e8e0d0d8b123", "device_package_ids": ["pkg_chn_0001", "pkg_vod_0010", "pkg_vod_0002"] }, { "device_id": "device_64afa425699d0b6e8e0d0d8b_new", "device_package_ids": ["pkg_vod_0004", "pkg_vod_0009"] }], "user_package_ids": [</pre>

	<pre> "pkg_vod_0009", "pkg_vod_0005"] } } </pre>
Error Response Status Code: 200	<pre> { "code": 3002, "msg": "Invalid User or Device Id", "data": {} } </pre>

B11 Delete Device Provisions

Description	Delete device provisions.
URL	v1/platform/device_provisions
Method	DELETE
URL Params	N/A
Header	EQOTT Token
Request Body	user_id(optional): user id, device_id(mandatory): device id Sample: <pre> { "user_id": "64745f54cafc08c8127d9b5b", "device_id": "cfb0dad0-80b5-4f3b-ad10-18bc6811c1d5" } </pre>
Mechanism	Delete the device packages of the given user_id, device_id. It's different from setting the device_packages to an empty list using B08. This API will delete the DB record of the device packages and thus the device will not be able to login to the service again, while setting the device_packages to an empty list using B08 will only result in playback failure, but the STB will still be able to login to the service normally.
Success Response Status Code: 200	<pre> { "code": 0, "msg": "SUCCESS", "data": {} } </pre>

	}
Error Response Status Code: 200	<pre>{ "code": 3002, "msg": "Invalid User or Device Id", "data": {} } { "code": 6001, "msg": "No Data Found", "data": {} }</pre>