

ASCII TABLE V.1.0

DEC	HEX	CHAR	NAME
0	0	NUL	null character
1	1	SOH	start of header
2	2	STX	start of text
3	3	ETX	end of text
4	4	EOT	end of transmission
5	5	ENQ	enquiry
6	6	ACK	acknowledge
7	7	BEL	bell (ring)
8	8	BS	backspace
9	9	HT	horizontal tab
10	A	LF	line feed
11	B	VT	vertical tab
12	C	FF	form feed
13	D	CR	carriage return
14	E	SO	shift out
15	F	SI	shift in
16	10	DLE	data link escape
17	11	DC1	device control 1
18	12	DC2	device control 2
19	13	DC3	device control 3
20	14	DC4	device control 4
21	15	NAK	negative acknowledge
22	16	SYN	synchronize
23	17	ETB	end transmission block
24	18	CAN	cancel
25	19	EM	end of medium
26	1A	SUB	substitute
27	1B	ESC	escape
28	1C	FS	file separator
29	1D	GS	group separator
30	1E	RS	record separator
31	1F	US	unit separator
127	5F	DEL	delete control character

ascii non-printable

DEC	HEX	CHAR
32	20	Space
33	21	!
34	22	"
35	23	#
36	24	\$
37	25	%
38	26	&
39	27	'
40	28	(
41	29	)
42	2A	*
43	2B	+
44	2C	,
45	2D	-
46	2E	.
47	2F	/
48	30	0
49	31	1
50	32	2
51	33	3
52	34	4
53	35	5
54	36	6
55	37	7
56	38	8
57	39	9
58	3A	:
59	3B	;
60	3C	<
61	3D	=
62	3E	>
63	3F	?

DEC	HEX	CHAR
64	40	@
65	41	A
66	42	B
67	43	C
68	44	D
69	45	E
70	46	F
71	47	G
72	48	H
73	49	I
74	4A	J
75	4B	K
76	4C	L
77	4D	M
78	4E	N
79	4F	O
80	50	P
81	51	Q
82	52	R
83	53	S
84	54	T
85	55	U
86	56	V
87	57	W
88	58	X
89	59	Y
90	5A	Z
91	5B	[
92	5C	\
93	5D	]
94	5E	^
95	5F	_

+32

-32

DEC	HEX	CHAR
96	60	`
97	61	a
98	62	b
99	63	c
100	64	d
101	65	e
102	66	f
103	67	g
104	68	h
105	69	i
106	6A	j
107	6B	k
108	6C	l
109	6D	m
110	6E	n
111	6F	o
112	70	p
113	71	q
114	72	r
115	73	s
116	74	t
117	75	u
118	76	v
119	77	w
120	78	x
121	79	y
122	7A	z
123	7B	{
124	7C	
125	7D	}
126	7E	~



Students



Pisciniers



nephcode/42jacuzzi

