

System API

Development Documentation

V1.1.0

Update Records

Date	Description
2022-10-31	First Edition Release
2023-02-22	Modify the API
2024-06-20	Update API and documentation

Contents

- 1 Introduction
- 1.1 SystemApiUtil Class
 - 1.1.1 SystemApiUtil
 - 1.1.2 Show the Status Bar
 - 1.1.3 Hide the Status Bar
 - 1.1.4 Show the Navigation Bar
 - 1.1.5 Hide the Navigation Bar
 - 1.1.6 Set the System Time
 - 1.1.7 Silent Installation
 - 1.1.8 Register for Broadcasting1
 - 1.1.9 Unbind Broadcast
 - 1.1.10 Reboot Device
 - 1.1.11 Shut Down the Device
- 1.2 SystemUtil Class
 - 1.2.1 Get CPU usage
 - 1.2.2 Get memory usage
 - 1.2.3 Get CPU temperature
 - 1.2.4 Determine the module of NFC(PN512)
 - 1.2.5 Obtain th SDK functions supported by the device

1 Introduction

1.1 SystemApiUtil Class

Package: com.common.apiutil.system

Includes show/hide status bar, show/hide navigation bar, set system time, silent installation, register/unbind broadcast, restart, shutdown

1.1.1 SystemApiUtil

```
/**
 * @Function Get the SystemApiUtil control object
 *
 * @Parameter context
 *
 * */

public SystemApiUtil (Context context)
```

1.1.2 Show the Status Bar

```
/**
 * @Function Show the status bar
 *
 * */

public synchronized void showStatusBar()
```

1.1.3 Hide the Status Bar

```
/**
 * @Function Hide the status bar
 *
 * */

public synchronized void hideStatusBar()
```

1.1.4 Show the Navigation Bar

```
/**
 * @Function Show the navigation bar
 *
 * */
```

```
public synchronized void showNavigationBar()
```

1.1.5 Hide the Navigation Bar

```
/**
 * @Function Hide the navigation bar
 *
 * */

public synchronized void hideNavigationBar()
```

1.1.6 Set the System Time

```
/**
 * @Function Set the system time
 *
 * @Parameter
 * 1.timeInMillis: Time
 *
 * */

public synchronized void setSystemTime(long timeInMillis)
```

1.1.7 Silent Installation

```
/**
 * @Function Silent installation
 *
 * @Parameter
 * 1.appPath: Path name
 * 2.packageName: Package name
 *
 * */

public synchronized void installApp(String appPath, String packageName)
```

1.1.8 Register for Broadcasting

```
/**
 * @Function Register for broadcasting
 *
 * Register for broadcast, silently install immediately wake up the app (call
 before invoking installApp)
```

```

*
* */

public synchronized void registerWakeUpAppBroadcast()

```

1.1.9 Unbind Broadcast

```

/**
 * @Function Unbind broadcast
 *
 * */

public synchronized void unRegisterWakeUpAppBroadcast()

```

1.1.10 Reboot Device

```

/**
 * @Function Reboot Device
 *
 * */

public synchronized void rebootDevice()

```

1.1.11 Shut Down the Device

```

/**
 * @Function Shut down
 *
 * */

public synchronized void shutdown()

```

1.2 SystemUtil Class

Package: com.common.apiutil.util

System property control API

1.2.1 Get CPU usage

```

/**
 * @Function Get the CPU usage
 *
 * @Return CPU usage; ResultCode: please refer the quick guidance document.
 *

```

```
* */  
  
public static int getCpuRate()
```

1.2.2 Get memory usage

```
/**  
 * @Function Get memory usage  
 *  
 * @Return Memory usage; ResultCode: please refer the quick guidance document.  
 *  
 * */  
  
public static int getMemRate()
```

1.2.3 Get CPU temperature

```
/**  
 * @Function Get CPU temperature  
 *  
 * @Return CPU temperature; ResultCode: please refer the quick guidance document.  
 *  
 * */  
  
public static int getCpuTem()
```

1.2.4 Determine the module of NFC(PN512)

```
/**  
 * @Function Determine the module of NFC  
 *  
 * @Return True or false  
 *  
 * */  
  
public static boolean isPN512NFC()
```

1.2.5 Obtain the functions supported

```
/**  
 * @Function Obtain the functions supported  
 *  
 * @Return  
 * Print = 1
```

```
* QR Code = 2
* Magnetic Stripe Card = 3
* Money box = 4
* ID Card = 5
* IC Card = 6
* NFC = 7
* PSAM = 8
* Tamper Test = 9
* LED = 10
* Relay = 11
* RS485/232 = 12
* Wiegand/Door Magnetic = 13
* Nixie tube test = 14
* System API = 15
* Can Bus = 16
* GPIO = 17
* Serial port= 18
* Sample LCD = 19
*
* */
```

```
public static String[] getDeviceSupport()
```