

quick reference

Controls, bindings, behaviors, and Play pages across two pages.

regular controls

<i>Turn Main</i>	Menu navigation / navigate menu / edit value
<i>Click Main</i>	Menu selection / select, edit, confirm
<i>Back</i>	Exit location / exit edit, overlay, or menu level
<i>Play</i>	Transport / play or pause
<i>Shift + Play</i>	Stop / external sync arms a one-shot resync
<i>Fn + Play</i>	Reset stop / stop, reset position, silence owned notes
<i>Fn + turn Main right</i>	Single step / advance one tick while paused/stopped
<i>Shift + Back</i>	Clear layer / re-initialize active layer
<i>Shift + Fn + Main</i>	Context help / hold modifiers, click menu item

navigation + bindings

<i>Fn + left column</i>	Navigate to Layer 1-8 / bottom row = layer 1
<i>Hold Fn</i>	Preview / layers and Play pages
<i>Fn + right column</i>	Navigate Play pages / exits if already active
<i>Fn + Aux click</i>	Bind focused value/action / value to turn, action to click

Auto-map maps *Aux 1-3* to important values/actions in the current menu area. It temporarily overrides manual bindings.

1-Cutoff

Aux 1 turn

1!Assign

Aux 1 click

special grid modes

Sample assign	<i>Shift</i> + cell maps row; <i>Shift + Fn</i> + cell maps column
Probability map	Trigger chance: never, low, high, always. <i>Shift</i> + cell = row; <i>Shift + Fn</i> + cell = column
Play Mix	Grid becomes a mixer for each layer's volume
Play Pan	Grid moves around layers' stereo positions
Play FX	Press mapped cells to trigger live effects
Trigger Gate	Block, allow, or use custom probability per layer
Transpose	Temporarily transpose synth and MIDI layers
XY	Mappable two-axis surface for live-manipulating parameters

behaviors

none	Inactive layer	keys	Finger-drumming
sequencer	Manual rhythm anchor	looper	Recorded grid gestures
life	Birth/survival/death cells	brain	Pulses and trails
ant	Walking grid agent	bounce	Moving collisions
shapes	Geometric regions	raindrops	Drops and ripples
dla	Branching growth		

triggers

activate	Cell turns on
stable	Cell stays on
deactivate	Cell turns off
scanned	Scanner finds active cell
scanned empty	Scanner visits inactive cell

patch orientation

1. Route **sequencer** or **looper** to **sampler** for a rhythm loop.
2. Add **life**, **raindrops**, **bounce**, or **dla** to a **synth**.
3. Use probability on sequencer cells so patterns feel alive.
4. Bind aux encoders to parameters or actions you keep reaching for.

Factory preset hint: **life** on Layer 1, **sequencer** rhythm on Layer 2.

Sample browser: . . parent; [folder] folder; file rows are samples; (empty) means no entries. *Play / Space* previews the highlighted sample. Long names clip or scroll without overlapping other OLED text.

Bench safety: Power through the enclosure USB-C breakout; remove both the board microSD card and OLED microSD card before closing the case.

If the grid behaves unexpectedly, check the OLED. You are probably in an overlay or Play page. Use *Back* or *Fn* to leave.

cell state to sound

From behavior state and direct input to MIDI, internal audio, routing, and optional live FX.

