amazon rme

AMAZON BASE BUILDING MAINTENANCE STANDARD

GLOBAL CENTRAL RME STANDARDS & COMPLIANCE

Task Title	LIGHT, SAFETY LIGHTING AND SIGNAGE - 10
APM Object	LIGHT.SAFETY
APM EC	AMZ.LIGHT.SAFETY
BBM Handbook Title	Safety Lighting and Signage
General tasks always required	Follow safety procedures - e.g. 1MRA, LOTO, PPE, etc. Ensure that all WOs are carried out by qualified, certified staff with appropriate familiarisation and supervision as required Add notes for each observation and create a FWO if necessary to eliminate defects Use appropriate tools, chemicals and industry standard practices (RME policy permitting) Ensure relevant logs, readings and certification is uploaded to APM prior to WO closure These tasks are based on industry guidance, SME knowledge and HIE learning. Please ensure vendor specific requirements are followed. To suggest improvements please raise a SIM SIM - Link to SIM template

Last Update: (Version)	Jul-23	**Geo Applied:**	Intl APM Instance	**F-Gas**	Not Identified	**Activies may be covered by No-Go restrictions:**	TBC	**Special Certificaion Required:**	TBC	**Delivered By:**	Carried out by trained on site technician certified in the electrical field	**OCB:**	BBM
Evidence for CT:	YES	**Pricing template Position:**	10	**Related CT Areas:**	CT.ELEC.EMERGENCYAC			**Assets included in this PM:**	SAFETY LIGHTING AND SIGNAGE	**Schedule With:**	-		

Description of System / Technology (According to BBM Handbook)

All sites with the above listed Base Building Asset should conduct routine maintenance and inspections according to this standard PM package. The Amazon maintenance standard supports compliance, reduces safety risks,improves asset reliability & efficiency. Some maintenances captures several assets within one PM package -> Ensure that corrective/reactive maintenance for assets where proactive maintenance is contained under another asset is created against the original asset.

Additional Information

All sites with the above listed Base Building Asset should conduct routine maintenance and inspections according to this standard PM package. The Amazon maintenance standard supports compliance, reduces safety risks,improves asset reliability & efficiency. Some maintenances captures several assets within one PM package -> Ensure that corrective/reactive maintenance for assets where proactive maintenance is contained under another asset is created against the original asset.

Task Index	Component	Tasks	Tasks Nested for frequencies > weekly									
			Daily	Weekly	Monthly	3 Monthly	6 Monthly	12 Monthly	24 Monthly	36 Monthly	48 Monthly	60 Monthly
1	General check	Only central battery station - Is the room properly ventilated						PM				
2	General check	Are the components clean & free from debris -> carry out a functional cleaning if necessary						PM				
3	General check	Visual check of the equipment for damage & missing components (incl.lights & signages)			SC			PM				
4	General check	Identify & secure essential spare parts for reactive maintenance			SC			PM				
5	Safety	Are disconnecting devices lockable in the safe position (LOTO)						PM				
6	Safety	Test all safety relevant switches for correct function						PM				
7	Documentation	Are the circuit diagrams and relevant technical documentation available and complete						PM				
8	Documentation	Are there manual entries in the drawings or technical documentation that indicate changes to the installation						PM				
9	Functional test	Carry out a flick test - simulate a power outage & check the system for correct function (ensure all emergency lighting turn on or stay illuminated)			SC			PM				
10	Functional test	Only for em. lights with local batteries - Check for alarms at the light/signage			SC			PM				
11	Thermographic scan	Perform thermographic scans of the electrical cabinet and central battery system -> Create a WO for over-temperature to determine the root cause immediately						PM				
12	Thermographic scan value	Add a detailed note for all over-temperature measurements -> list the location and temperature -> Upload the thermographic scans						PM				
13	Panel & electrical installation	Is the air filter & grid of the cooling inlets clean -> clean or change filter if necessary			SC			PM				
14	Panel & electrical installation	Are the cooling fans operating appropriately and doesn`t make any unusual noise			SC			PM				
15	Panel & electrical installation	Are there any alarms indicated -> if yes identify the root cause immediately			SC			PM				
16	Panel & electrical installation	Has a circuit breaker tripped -> if yes identify the root cause immediately			SC			PM				
17	Panel & electrical installation	Visual check of cable connections -> e.g., pinched insulation in the contact area						PM				
18	Panel & electrical installation	Visual check for the protection against direct contact with live parts						PM				
19	Panel & electrical installation	Have any obvious changes been made (e.g. rewiring, hanging cables)						PM				
20	Panel & electrical installation	Are all cables properly routed						PM				
21	Panel & electrical installation	Are all components properly labeled or marked						PM				
22	Panel & electrical installation	Are all components properly attached						PM				
23	Panel & electrical installation	Are all metal parts connected to the protection earth (ground)						PM				
24	Panel & electrical installation	Is the ground connection to the building ground as designed?						PM				
25	Panel & electrical installation	Ensure all cable connections are correctly torqued according to manufacturers specification						PM				
26	Battery & Charger	Only central battery station - Measure the voltage of each battery (disconnected) -> if necessary, plan for a replacement						PM				
27	Battery & Charger	Only central battery station -Measure the charging voltage and current before & after functional test -> Compare to design specification & plan component exchange in case of an issue						PM				
28	Battery & Charger	Only central battery station - Check the internal uninterruptable power supply of the unit for correct function						PM				
29	Battery & Charger	Only central battery station - Check the batteries for leakage or damage						PM				
30	Battery & Charger	Only central battery station - Check the fluid level of the batteries and top up if required						PM				
31	Functional cleaning	Carry out a functional cleaning if required						PM				
32	Final Check	Check the O&M manual and carry out additional required tasks						PM				

Change Log

July 2023 - First issue in new format. Simplification of task scope, aligmment with CT. Removed task regarding CE certification.