amazon rme

AMAZON BASE BUILDING MAINTENANCE STANDARD

GLOBAL CENTRAL RME STANDARDS & COMPLIANCE

Task Title	ELECTRICAL SYSTEM, LOW VOLTAGE, SWITCHBOARD - 11
APM Object	ELEC.LV.SWBD
APM EC	AMZ.ELEC.LV.SWBD
BBM Handbook Title	Low Voltage Switchboard
General tasks always required	Follow safety procedures - e.g. 1MRA, LOTO, PPE, etc. Ensure that all WOs are carried out by qualified, certified staff with appropriate familiarisation and supervision as required Add notes for each observation and create a FWO if necessary to eliminate defects Use appropriate tools, chemicals and industry standard practices (RME policy permitting) Ensure relevant logs, readings and certification is uploaded to APM prior to WO closure These tasks are based on industry guidance, SME knowledge and HIE learning. Please ensure vendor specific requirements are followed. To suggest improvements please raise a SIM SIM - Link to SIM template

Last Update: (Version)	Jun-24	**Geo Applied:**	Intl APM Instance	**F-Gas**	Not Identified	**Activies may be covered by No-Go restrictions:**	Yes	**Special Certificaion Required:**	TBC	**Delivered By:**	Carried out by trained on site technician	**OCB:**	BBM
Evidence for CT:	TBC	**Pricing template Position:**	11	**Related CT Areas:**	CT.ELEC.ELECINST CT.ELEC.FIXEDWIRE CT.ELEC.THERMAL	**Assets included in this PM:**	LV SWITCHBOARD	**Schedule With:**	ELEC.LV.CABS ELEC.LV.BSBR ELEC.LV.PFC ELEC.MET BLDG.EARTHING				

Description of System / Technology (According to BBM Handbook)

Switchboard is a component of an electrical distribution system which divides an electrical power feed into branch circuits while providing a protective circuit breaker or fuse for each circuit in a common enclosure.

Additional Information

All sites with the above listed Base Building Asset should conduct routine maintenance and inspections according to this standard PM package. The Amazon maintenance standard supports compliance, reduces safety risks,improves asset reliability & efficiency.
Some maintenances captures several assets within one PM package -> Ensure that corrective/reactive maintenance for assets where proactive maintenance is contained under another asset is created against the original asset.
Note: This PM includes the low voltage main distribution panels/switchboards.

Task Index	Component	Tasks	Tasks Nested for frequencies > weekly								
			Daily	Weekly	Monthly	3 Monthly	6 Monthly	12 Monthly	24 Monthly	36 Monthly	48 Monthly	60 Monthly
1	Station outside check	Is the entrance freely accessible & free of obstacles			SC			PM				
2	Station outside check	Are there any visual damage or excessive vegetation at the building or around			SC			PM				
3	Station outside check	Check roof & roof drainage - clean drain inlets if necessary			SC			PM				
4	Station outside check	Check if the lightning protection is fixed appropriately & not damaged			SC			PM				
5	Station outside check	Are there any damage or corrosion at the cable trays			SC			PM				
6	Station outside check	Is the door locked properly - protection against unauthorized entry			SC			PM				
7	Station inside check	Does the light work properly			SC			PM				
8	Station inside check	Is the heater working			SC			PM				
9	Station inside check	Check heater for dirt, damage, corrosion			SC			PM				
10	Station inside check	Are there any water leaks visible at the walls or ceiling			SC			PM				
11	Station inside check	Are there any damage at the walls or ceiling			SC			PM				
12	Station inside check	Are technical installations damaged or loose (e.g. cable trays, MCP, fire extinguisher)			SC			PM				
13	Station inside check	Are flammable or unnecessary goods stored in the room			SC			PM				
14	Station inside check	Check the function of the room ventilation - natural & mechanical			SC			PM				
15	Safety	Are all relevant safety notices visible and free from damage			SC			PM				
16	Safety	Is appropriate fire-fighting equipment available in the rooms			SC			PM				
17	Safety	Inspect and test all tools, test instruments to ensure serviceable condition						PM				
18	Safety	Are disconnecting devices lockable in the open position (LOTO)						PM				
19	Documentation & display	Are the circuit diagrams and relevant technical documentation available and complete						PM				
20	Documentation & display	Are technical drawings hanging at the wall						PM				
21	Documentation & display	Is there an active alarm displayed -> identify and eliminate the root cause			SC			PM				
22	Documentation & display	Check correct function of the display elements (e.g. electrical current, voltage, etc.)			SC			PM				
23	Switchgear	Is the panel/cabinet clean - free from debris						PM				
24	Shut down	De-energize the system						PM				
26	Shut down	Measure whether the system is voltage-free						PM				
27	Shut down	Block of neighboring live parts						PM				
28	Thermographic scan	Perform thermographic scans of the whole system (e.g. Switchgear, Busbars, etc.) -> Create a WO for over-temperature to determine the root cause immediately						PM				
29	Thermographic scan value	Add a detailed note for all over-temperature measurements -> list the location and temperature -> Upload the thermographic scan						PM				
30	Switchboard	Check for leakages of SF gas						PM				
31	Switchboard	Are all cables, terminal blocks & devices properly labeled or marked						PM				
32	Switchboard	Test the condition and mechanical operation of all switches, contactors, etc.						PM				
33	Switchboard	Lubricate, clean or schedule a replacement of mechanical components of disconnecting devices						PM				
34	Switchboard	Check all safety and Disconnecting devices for correct function						PM				
35	Switchboard	Are the correct disconnecting devices installed (e.g. switch connector, fuses, circuit breaker, etc.)						PM				
36	Switchboard	Are the settings at the disconnecting devices correct						PM				

37	Switchboard	Inspect all cable and busbar terminations for signs of overheating						PM					
38	Switchboard	Inspect all cables and connections insulation/shields for damage						PM					
39	Switchboard	Ensure all cable & busbar connections are correctly torqued according to manufacturers specification						PM					
40	Switchboard	Check if the system is properly connected to the PE (ground), check also for damage & corrosion						PM					
41	Switchboard	Test and maintain surge protection device according to manufacturer recommendation						PM					
42	Switchboard	Carry out functional cleaning						PM					
43	Re-energize	Re-energize system & measure system voltage using appropriate tools						PM					
44	Final Check	Check the O&M manual and carry out additional required tasks						PM					

Change Log

July 2023 - First issue in new format. Simplification of task scope, alignment with CT.
June 2024 - Changed Object and Title according to the last OCB changes, from ELEC.LV.SWITCHGEAR to ELEC.LV.SWBD. Removed task regarding LOTO.