

create_cell

NAME

`create_cell`
Creates one or more cells referencing a library cell, module, or `via_def`

SYNTAX

```
collection create_cell
    [-design design]
    cell_names
    reference
```

Data Types

```
design      collection
cell_names list
reference   collection
```

ARGUMENTS

`-design design`
Specifies the design in which to create the cells. If no `design` is specified, the cells are created in the current design.

`cell_names`
Specifies the names of the cells to be created in the design. Each cell name must be unique.

`reference`
Specifies the name of the library cell or module the created cells should instantiate, the reference must already exist.

The `reference` may also be a `via_def` when creating through-silicon via ("TSV") cells, in which case the `via_def` must be of type "through_silicon_via_def". TSV cells, which are identified by their `is_tsv` attribute being true, are created by this command if the `reference` is either a TSV `via_def` or a design with `design_type` "tsv". If a TSV design, it must meet certain criteria, which as of this writing are:

- Its `design_type` attribute must be "tsv",
- It must have exactly one port with two terminals,
- Its `boundary` attribute must be set.

DESCRIPTION

This command creates new cells in the current design (unless otherwise specified by `-design`). One cell is created for each of the names listed.

EXAMPLES

The following example creates three instances of the library cell `myLib/ND2`.

```
prompt> create_cell {U23 U1/U24 U2/U7/U25} myLib/ND2
{U23 U1/U24 U2/U7/U25}
```

The following example creates three instances of the library cell `ND2`. It will work similar to `*/ND2`

```
prompt> create_cell {U23 U1/U24 U2/U7/U25} ND2
{U23 U1/U24 U2/U7/U25}
```

The following example creates two instances of the module `MID`.

```
prompt> create_cell {U110 U111} [get_modules MID]
{U110 U111}
```

The following example creates an instance of the lib cell `myLib/ND4` using `get_blocks` to find the reference. `get_blocks -all` is needed if the lib_cell is not open already.

```
prompt> create_cell U210 [get_blocks -all myLib:ND4.design]
{U110 U111}
```

SEE ALSO

[create_module\(2\)](#)
[create_net\(2\)](#)
[connect_net\(2\)](#)

[edit_module\(2\)](#)
[get_lib_cells\(2\)](#)
[get_modules\(2\)](#)
[get_blocks\(2\)](#)
[remove_cells\(2\)](#)

Version V-2023.12-SP5-6

Copyright (c) 2025 Synopsys, Inc. All rights reserved.

Man(1) output converted with [man2html](#)