

```

1
2  =====
3  Phonik Protocol
4  =====
5
6  Phonik PABX Telnet system
7  ..
8  ==NACK
9  ..VERS= =>Read Version
10 ==VERS=DX-SERIES V3.
11 ==VERS=DXE-SERIES V3.
12 ==VERS=JSD-SERIES V3.
13 ==VERS=CIX-SERIES V3.
14 ==VERS=DX-COMPACT V5.Super Diamond-32C
15 ==VERS=DX-COMPACT V5.Super Diamond-80C
16 ==VERS=DX-COMPACT V5.Super Diamond-144C
17 ==VERS=DX-Super Diamond V5.Super D-64
18 ==VERS=DX-Super Diamond V5.Super D-128
19 ==VERS=DX-Super Diamond V5.Super D-256
20 ==VERS=DX-Super Diamond V5.Super D-512
21
22  =====
23  ASCII Protocol
24  =====
25  ..DATE= =>Read Date
26  ==DATE=yy/mm/dd-w =>Respond
27
28  ..TIME= =>Read Time
29  ==TIME=hh:mm:ss =>Respond
30
31  ..STOP =>Disconnect
32  ==STOP
33
34  -----
35  CHECK IN/OUT
36  -----
37  note: numb=1001,1002,101,102,xxx,xx,..
38
39  ..ROOMnumb= =>Read Room Status
40  ..ROOMnumb=r =>Set Room Status
41  ==ROOMnumb=r ;r=0-9
42
43  ..NAMEnumb= =>Read Name
44  ..NAMEnumb=name =>Set Name
45  ==NAMEnumb=name ;name=text 16 digits
46
47  -----
48  EXT. SERVICE
49  -----
50
51  ..WAKEnumb= =>Read Wake Up Time
52  ..WAKEnumb=hhmm =>Set Wake Up Time
53  ..WAKEnumb=0 =>Clear Wake Up Time
54  ==WAKEnumb=hhmm ;hhmm=HourMinute(0000-2359)
55  ==WAKEnumb=0
56
57  ..LOCKnumb= =>Read Lock Status
58  ..LOCKnumb=k =>Set Lock Status
59  ==LOCKnumb=k ;k=0 (Clear),1 (Set)
60
61  ..LANGnumb= =>Read Language
62  ..LANGnumb=l =>Set Language
63  ==LANGnumb=l ;l=1-4 (Language1-4)
64

```