

**MEENAKSHI SUNDARARAJAN
ENGINEERING COLLEGE**

(An Autonomous Institution)
Kodambakkam, Chennai – 24

**PROJECT REPORT
U24EC405 – LIC PROJECT DRIVEN**
(Project Driven Course)

**ANALOG AUDIO EQUALIZER WITH
ADAPTIVE AND STABILITY
IMPROVEMENTS**

Submitted by

NITHTHILA B
(243115106071)

RUBA CHRISTY A
(243115106088)

SAGANA GR
(243115106090)

Department of Electronics and Communication Engineering
May 2025

BONAFIDE CERTIFICATE

Certified that this project report titled "ANALOG AUDIO EQUALIZER WITH ADAPTIVE AND STABILITY IMPROVEMENTS" is the bonafide work of: **NITHTHILA B (243115106071), RUBA CHRISTY A (243115106088), SAGANA GR (243115106090)** who carried out the project work under our supervision.

SIGNATURE

Mrs. Siji Sivanandan

Head of the Department
Electronics and Communication Engineering
MSEC, Chennai – 600 024

SIGNATURE

Mrs. N. Sruthi

Course Instructor
Electronics and Communication Engineering
MSEC, Chennai – 600 024

Submitted for the end semester project review of LIC PROJECT DRIVEN in the Department of Electronics and Communication Engineering held on 04/05/2026.

INTERNAL EXAMINER

EXTERNAL EXAMINER

ACKNOWLEDGEMENT

We would like to express our sincere gratitude to all those who have contributed to the successful completion of our project titled "ANALOG AUDIO EQUALIZER WITH ADAPTIVE AND STABILITY IMPROVEMENTS".

First and foremost, we extend our profound thanks to Mrs. Siji Sivanandan, Head of the Department of Electronics and Communication Engineering, Meenakshi Sundararajan Engineering College, for her continuous encouragement, administrative support, and for providing the necessary infrastructure and resources to carry out this project.

We are especially grateful to our Course Instructor, Mrs. N. Sruthi, for her invaluable guidance, expert advice, and constructive feedback throughout the duration of the project. Her support has been instrumental in the successful execution and completion of this work.

We also wish to thank the faculty members and technical staff of the Department of Electronics and Communication Engineering for their assistance and for creating a conducive academic environment.

We are grateful to Meenakshi Sundararajan Engineering College and Anna University for offering us the platform to undertake this project as part of the curriculum, allowing us to apply our theoretical knowledge to a practical and socially relevant problem.

ABSTRACT

An analog audio equalizer is widely used to control and shape the frequency response of audio signals in various sound processing applications. This project focuses on the design and development of an analog audio equalizer integrated with adaptive mechanisms and stability improvement techniques. Conventional equalizers often operate with fixed parameters, which limits their performance under varying input conditions and signal distortions.

To address this limitation, the system provides adjustable gain using variable resistors, allowing flexible control over frequency bands. Adaptive control can be implemented in future work.

In addition to adaptability, system stability is a critical concern in analog circuit design, particularly when active components such as operational amplifiers and feedback networks are involved. Instability can result in unwanted oscillations and signal degradation. Therefore, this work emphasises stability enhancement through proper feedback design, compensation techniques, and careful selection of circuit components.

The proposed system aims to achieve improved audio quality, reduced noise, and consistent performance across a wide range of operating conditions. By combining adaptive features with robust stability measures, the analog audio equalizer offers enhanced reliability and efficiency, making it suitable for applications in audio systems, communication devices, and sound engineering.

TABLE OF CONTENTS

S.NO	TITLE	PAGE
1	Introduction	6
	1.1 General	6
	1.2 Problem Statement	6
	1.3 Objectives	6
2	Literature Review	7
3	Theoretical Background	8
4	Concept and Methodology	9
	4.1 Concept	9
	4.2 Methodology	9
5	Design, Modelling and System Architecture	11
	5.1 Design	11
	5.2 Modelling	11
	5.3 System Architecture	12
6	Circuit Diagram	13
7	Results and Discussion	15
8	Conclusion and Scope of Future Work	16
	8.1 Conclusion	16
	8.2 Scope for Future Work	16
9	References	17

1. INTRODUCTION

1.1 General

Audio signal processing is an essential part of modern electronic systems, where maintaining sound quality and clarity is highly important. An analog audio equalizer is a circuit used to adjust the amplitude of different frequency components of an audio signal — such as bass, mid-range, and treble. It is widely used in applications like music systems, recording studios, and communication devices to enhance audio quality and provide a better listening experience. Analog equalizers commonly use active components like operational amplifiers along with resistors and capacitors to shape the frequency response.

1.2 Problem Statement

Conventional analog audio equalizers are designed with fixed parameters, which limits their ability to handle dynamic and varying input signals effectively. In real-time applications, audio signals may be affected by noise, distortion, and changing environmental conditions, leading to poor sound quality. Additionally, the use of feedback networks and active components can introduce stability issues — such as unwanted oscillations and signal degradation — if not properly designed. These challenges highlight the need for an improved equalizer system that can adapt to varying conditions while maintaining stable operation.

1.3 Objectives

The main objective of this work is to design and develop an analog audio equalizer with adjustable gain control and improved stability. The system provides adjustable gain using variable resistors, allowing flexible control over frequency bands. Adaptive control can be implemented in future work. Stability improvement techniques such as proper feedback design and compensation methods are incorporated to ensure reliable and distortion-free performance. The overall goal is to achieve better sound fidelity, reduced noise, and consistent operation across different conditions.

2. LITERATURE REVIEW

Analog audio equalizers have been widely studied and developed to improve sound quality by controlling the frequency response of audio signals. Early designs mainly focused on fixed-band filtering techniques using passive components such as resistors, capacitors, and inductors. These equalizers were simple but lacked flexibility and precision in handling varying audio conditions.

With the advancement of electronics, active equalizers using operational amplifiers were introduced. These designs provided better gain control, improved frequency selectivity, and reduced signal loss compared to passive equalizers. Researchers further developed different types of equalizers — such as graphic equalizers, parametric equalizers, and shelving filters — to allow more precise control over specific frequency bands.

Recent studies have focused on improving equalizer performance through adaptive techniques. Various approaches, such as variable gain control and feedback-based tuning, have been explored to achieve adaptability in audio circuits.

Another major area of research is stability improvement in analog equalizer circuits. Since these systems rely on operational amplifiers and feedback networks, improper design can lead to instability, causing oscillations and distortion. To address this, techniques such as frequency compensation, proper feedback network design, and phase margin optimisation have been widely studied. These methods ensure stable operation while maintaining high performance.

Overall, the literature indicates a shift from simple fixed equalizers to more advanced and stable designs, aiming to achieve better sound quality, reliability, and efficiency in modern audio systems.

3. THEORETICAL BACKGROUND

An analog audio equalizer operates on the principle of frequency-selective filtering, where different frequency components of an input signal are amplified or attenuated. This is achieved using filter circuits such as low-pass, high-pass, band-pass, and band-stop filters. Each filter targets a specific range of frequencies, allowing precise control over the audio spectrum.

Active filters are commonly used in equalizer design, incorporating operational amplifiers along with resistors and capacitors. These filters provide advantages such as higher gain, improved impedance matching, and better control over frequency response. The gain and cutoff frequency of these filters depend on the values of the circuit components. The cutoff frequency is determined by:

$$f_c = 1 / (2\pi RC)$$

The transfer function relating output to input is expressed as:

$$H(s) = V_{out}(s) / V_{in}(s)$$

The system provides adjustable gain using variable resistors, allowing flexible control over frequency bands. Adaptive control can be implemented in future work. Stability is a key consideration and is influenced by factors such as loop gain, phase shift, and component values. Techniques like negative feedback, compensation networks, and proper circuit layout are used to ensure stable operation.

4. CONCEPT AND METHODOLOGY

4.1 Concept

The proposed system is an analog audio equalizer designed to enhance audio signal quality by combining frequency-selective filtering with variable gain control and stability improvement techniques. The core concept is to adjust the gain of different frequency bands — typically low (bass), mid-range, and high (treble) — to achieve a balanced and clear audio output.

Active filter circuits using operational amplifiers are employed to provide precise control over the frequency response. The system provides adjustable gain using variable resistors, allowing flexible control over frequency bands. Adaptive control can be implemented in future work.

Stability enhancement is another important aspect of the design. Since the system uses feedback networks in active filters, there is a possibility of instability leading to oscillations. To overcome this, controlled feedback, compensation methods, and proper component selection are incorporated.

4.2 Methodology

The development of the analog audio equalizer follows a systematic approach:

a) System Design

The equalizer is designed by dividing the audio frequency spectrum into multiple bands (low, mid, and high frequencies). For each band, suitable filter circuits — low-pass, band-pass, and high-pass — are designed using operational amplifiers, resistors, and capacitors.

b) Circuit Implementation

Active filter circuits are implemented to control the gain of each frequency band. The cutoff frequency and gain are determined by selecting appropriate values of resistors and capacitors. The outputs of these filters are then combined to produce the overall equalised signal.

c) Variable Gain Control

The system provides adjustable gain using variable resistors, allowing flexible control over frequency bands. Adaptive control can be implemented in future work to further enhance the response to changing input conditions.

d) Stability Improvement Techniques

To ensure stable operation, proper feedback design is applied in the amplifier circuits. Compensation techniques such as phase margin adjustment and frequency compensation are used to prevent oscillations and ensure smooth signal processing.

e) Testing and Analysis

The designed circuit is tested using different input signals to evaluate its performance. Parameters such as gain response, noise reduction, and stability are analysed to verify the effectiveness of the design.

5. DESIGN, MODELLING AND SYSTEM ARCHITECTURE

5.1 Design

The design of the analog audio equalizer is based on dividing the input audio signal into multiple frequency bands — low, mid, and high frequencies. Each band is processed using active filter circuits designed with operational amplifiers, resistors, and capacitors.

- Low-frequency band (Bass): Implemented using a low-pass filter to allow only low-frequency signals.
- Mid-frequency band: Designed using a band-pass filter to process mid-range frequencies.
- High-frequency band (Treble): Implemented using a high-pass filter to allow high-frequency signals.

The gain for each band is independently controlled using variable resistors (potentiometers), enabling flexible shaping of the overall frequency response. The outputs of all bands are summed to produce the final equalised output signal. Proper feedback networks are incorporated in each active filter stage to ensure stability.

5.2 Modelling

The system is modelled based on standard filter design equations and frequency response characteristics. Each filter stage is analysed using transfer functions:

$$H(s) = V_{out}(s) / V_{in}(s)$$

- Low-pass filter determines the bass response.
- High-pass filter determines the treble response.
- Band-pass filter controls mid frequencies.

The cutoff frequency of each filter is determined by $f_c = 1 / (2\pi RC)$. The system provides adjustable gain using variable resistors, allowing flexible control over frequency bands. Adaptive control can be implemented in future work. Stability is analysed using gain margin and phase margin to ensure the system remains stable under all operating conditions.

5.3 System Architecture

The overall system architecture consists of the following main functional blocks:

Block	Component	Function
1	Input Stage	Receives the audio signal from a microphone or music player.
2	Pre-Amplifier	Amplifies the input signal to a suitable level for processing.
3	Low-Pass Filter	Bass control — passes frequencies below the cutoff.
4	Band-Pass Filter	Mid control — passes a defined range of mid frequencies.
5	High-Pass Filter	Treble control — passes frequencies above the cutoff.
6	Summing Amplifier	Combines the outputs of all three filter stages.
7	Output Stage	Provides the final equalised audio signal.

This modular architecture ensures flexibility, easy implementation, and improved performance across varying audio conditions.

Low-Pass Filter – Bass (Sallen-Key topology)

The low-pass filter uses C1 (22 μ F), C2 (22 μ F), R3 (4.7 k Ω), and R4 (4.7 k Ω). The cutoff frequency is calculated as $f_c = 1 / (2\pi RC) \approx 1.5$ Hz for these component values, making this stage responsible for passing the low bass frequency (10 Hz test tone) while attenuating higher frequencies.

Band-Pass Filter – Mid (U-stage with C3–C6, R5–R8)

The mid-range band-pass filter is built using two op-amp stages. The first stage uses C3 (2.2 μ F), R5 (4.7 k Ω), R6 (4.7 k Ω), and C4 (2.2 μ F) as the frequency-defining elements. The second stage uses C5 (0.22 μ F), R7 (1.5 k Ω), R8 (4.7 k Ω), and C6 (0.22 μ F). Together, these form a cascaded bandpass response targeting the mid-frequency range.

High-Pass Filter – Treble

The high-pass filter uses C7 (0.22 μ F), C8 (0.22 μ F), R9 (4.7 k Ω), and R10 (4.7 k Ω). This configuration attenuates low frequencies and allows the treble (higher frequency) components to pass. The 50 Hz test signal is primarily processed here.

Band Amplifiers (U4, U5, U6)

Each filter output feeds into a dedicated band amplifier. U4 handles the bass band with feedback resistors R14 (220 k Ω) and R16 (4.7 k Ω). U5 handles the mid band with R17 (220 k Ω) and R18 (4.7 k Ω). U6 handles the treble band with R20 (4.7 k Ω) and R15 (47 k Ω feedback). These amplifiers provide the band gain required before the gain control stage.

Potentiometers – Gain Control (R11a/b, R12a/b, R13a/b)

Variable resistor dividers serve as the user-adjustable gain controls for each band. R11a (1 k Ω) and R11b (9 k Ω) form the bass potentiometer. R12a (5 k Ω) and R12b (5 k Ω) form the mid potentiometer. R13a (9 k Ω) and R13b (1 k Ω) form the treble potentiometer. These resistor pairs allow the user to attenuate each band independently, mimicking the action of a physical rotary control.

Summing Amplifier (U2)

The final stage, U2, acts as an inverting summing amplifier that combines the adjusted outputs of all three frequency bands into a single equalised audio signal. The feedback resistor R15 (100 M Ω) sets the overall gain of the summing stage. The output of U2 is the final equalised audio signal, ready for connection to a speaker or recording device.

7. RESULTS AND DISCUSSION

The designed analog audio equalizer was tested with various audio input signals to evaluate its performance. The results demonstrate that the system effectively adjusts different frequency components and improves overall sound quality.

- The low-pass filter enhances bass frequencies without affecting higher frequencies.
- The band-pass filter provides a clear and balanced mid-range output.
- The high-pass filter improves treble clarity and reduces unwanted low-frequency noise.

Variable gain control using resistors allows manual adjustment of gain levels across frequency bands, resulting in improved audio clarity and reduced distortion. Stability analysis confirms that the implemented feedback and compensation techniques prevent oscillations and ensure smooth operation.

Overall, the combination of variable gain control and stability improvement techniques significantly enhances the efficiency and reliability of the analog audio equalizer.

8. CONCLUSION AND SCOPE OF FUTURE WORK

8.1 Conclusion

The analog audio equalizer with variable gain control and stability improvements has been successfully designed and analysed. The system effectively divides the audio spectrum into different frequency bands and adjusts their gain using active filter circuits. The system provides adjustable gain using variable resistors, allowing flexible control over frequency bands. Adaptive control can be implemented in future work.

Stability improvement techniques such as proper feedback design and compensation methods ensure reliable operation without oscillations or signal degradation. The results demonstrate that the proposed system performs better than conventional fixed equalizers in terms of flexibility and stability.

8.2 Scope for Future Work

Although the proposed system provides improved performance, several enhancements can be considered for future development:

- The system can be extended to include more frequency bands for finer control over the audio spectrum.
- Digital control elements can be integrated to create a hybrid analog-digital equalizer for better precision.
- Advanced adaptive algorithms can be implemented to improve response time and accuracy.
- Integration with microcontrollers or signal processors can enable automatic tuning and intelligent audio processing.
- Miniaturisation using integrated circuits (ICs) can make the system more compact and suitable for portable devices.
- The design can be further optimised for low power consumption, making it ideal for battery-operated applications.

9. REFERENCES

1. **Sergio Franco.** *Design with Operational Amplifiers and Analog Integrated Circuits.* McGraw-Hill Education.
2. **Adel S. Sedra & Kenneth C. Smith.** *Microelectronic Circuits.* Oxford University Press.
3. **M. E. Van Valkenburg.** *Analog Filter Design.* Oxford University Press.
4. **Ramakanth A. Gayakwad.** *Operational Amplifiers and Linear Integrated Circuits.* Pearson Education.
5. **Texas Instruments.** *Application Notes on Active Filters and Audio Circuits.* Available at: www.ti.com
6. **Analog Devices.** *Technical Articles on Audio Equalizers and Signal Processing.* Available at: www.analog.com
7. **IEEE.** *Journals and Papers on Analog Signal Processing and Audio Equalizer Design.* IEEE Xplore Digital Library.