



# Unveiling SAR Resolution

A deep dive into Synthetic Aperture Radar (SAR) capabilities and the factors defining its precision.

Submitted by:

Sreejata Bhattacharjee(25CEM5R10)

Garnisha(25CEM5R02)

Harshidha(25CEM5R04)

Charvisree(25CEM5R06)

Submitted to Dr Narayanarao



An aerial photograph of a city, likely New York City, showing a dense grid of skyscrapers and streets. A semi-circular radar footprint is overlaid on the lower-left portion of the image, indicating the area covered by a Synthetic Aperture Radar (SAR) sensor. The footprint is centered on a point and extends outwards, with a smaller inner circle representing the core resolution area.

# The Essence of SAR Resolution

## What is SAR Resolution?

SAR resolution defines the smallest discernible detail in a radar image. It's crucial for accurate mapping and analysis.

## Key Dimensions

Resolution is typically measured in two primary dimensions: ground range (across-track) and azimuth (along-track).





# SAR Data Availability & Sources



## Global Satellites

Numerous satellites provide SAR data, including Sentinel-1, TerraSAR-X, and COSMO-SkyMed.



## Public & Commercial Archives

Data is accessible through platforms like ESA's Copernicus Open Access Hub and commercial providers.



## Diverse Applications

Used for environmental monitoring, disaster response, and defense applications worldwide.



# Polarization in SAR



Polarization refers to the orientation of the electric field of the radar wave. It provides valuable information about the target's physical properties.

- Linear Polarization (HH, HV, VV, VH)
- Circular Polarization (CR, CL)

Polarization helps to:

- Differentiate **water, soil, vegetation, urban areas**
- Identify **surface roughness**
- Estimate **soil moisture**
- Study **forest structure and biomass**
- Improve **land use / land cover classification**

Circular polarization offers unique insights into complex scattering mechanisms, enhancing target characterization.






# Pulse Repetition Frequency (PRF)

PRF is the number of radar pulses transmitted per second. It directly influences both range and azimuth resolution.

- Higher PRF: Better azimuth resolution, but increased range ambiguity.
- Lower PRF: Reduced range ambiguity, but poorer azimuth resolution.

Continuously Varying Pulse Repetition Frequency (CVPRF) is an advanced technique to mitigate these trade-offs.

- Radar sends a pulse → waits for the echo → measures time delay.
- If the echo returns before the next pulse is transmitted, the range is measured correctly → unambiguous.
- If the echo arrives after the next pulse, radar gets confused → range ambiguity.



$$PRF(Hz) = \frac{c}{2 \times (Unambiguous\ Range)} = \frac{1}{PRT}$$

$$PRT = \frac{2 \times (Unambiguous\ Range)}{c}$$

# Spatial Resolution: Ground Range & Azimuth


## Ground Range Resolution

The ability to distinguish between two objects located at different distances from the sensor, perpendicular to the flight path (across-track).

## Azimuth Resolution

The ability to distinguish between two objects located along the flight path of the sensor (along-track). SAR achieves fine azimuth resolution by synthesizing a large antenna.


# Radiometric & Polarimetric Resolution



1

## Radiometric Resolution

The ability to distinguish between subtle differences in signal intensity, indicating variations in target reflectivity.



2

## Polarimetric Resolution

The ability to measure and differentiate the full polarization state of the backscattered signal, revealing detailed target characteristics.



# SAR Imaging Modes: Resolution Overview

Synthetic Aperture Radar (SAR) systems employ various imaging modes, each optimized for different applications by balancing coverage area with achievable resolution. Understanding these modes is crucial for selecting the right data for specific tasks.

1

## ScanSAR

ScanSAR trades high resolution for wide area coverage. It achieves this by rapidly steering the radar beam across multiple adjacent swaths. This results in a broader image but at a significantly coarser azimuth (along-track) resolution, typically ranging from 20 to 100 meters.

2

## Stripmap Mode

Stripmap mode is the most common operational SAR mode, collecting data in a continuous strip along the flight path. The antenna beam points to the side at a fixed angle, providing a constant ground track. Resolution in Stripmap mode is generally 3 to 10 meters in both range and azimuth, offering a good balance of coverage and detail.

3

## Dwell Mode (Extended Staring)

While "Dwell Mode" isn't a universally standard term, it often refers to an extended staring or continuous observation strategy over a fixed, small ground area. By collecting echoes for a longer duration, it can achieve enhanced resolution beyond standard stripmap, typically in the 1 to 3 meter range, though not as fine as Spotlight.

4

## Spotlight Mode

Spotlight mode offers the highest resolution by continuously steering the radar beam to illuminate a specific, small ground patch for an extended integration time. This allows for the synthesis of a much longer effective aperture. Azimuth resolution can be exceptionally fine, often in the 0.25 to 1 meter range, but with very limited area coverage.

## radar satellite imaging modes

### ScanSAR



ScanSAR

A wide, sweeping radar beam is for  
better cover in large area

### Stripmap



Stripmap

A narrower radar beam scans a continuous strip of  
continuous strip a continuous the land

### Spotlight



Spotlight

Focused extensive duration of  
coarser differently and small extending



# SAR Imaging Modes: Resolution Equations

Understanding the achievable resolution for different Synthetic Aperture Radar (SAR) imaging modes requires examining the specific formulas that govern their performance.

## Stripmap Mode

In Stripmap mode, both range and azimuth resolutions are relatively constant, offering a balanced view. Azimuth resolution is primarily limited by the physical antenna length.

$$\rho_a = \frac{L_{ant}}{2}$$
$$\rho_r = \frac{c}{2B}$$

Where:

- $\rho_a$  = Azimuth Resolution
- $\rho_r$  = Range Resolution
- $L_{ant}$  = Physical Antenna Length
- $c$  = Speed of Light
- $B$  = Transmitted Bandwidth

## Spotlight Mode

Spotlight mode achieves the finest azimuth resolution by continuously steering the antenna beam, effectively increasing the synthetic aperture length through extended observation of a target.

$$\rho_a = \frac{\lambda}{2 \Delta\theta_{ap}}$$
$$\rho_r = \frac{c}{2B}$$

Where:

- $\rho_a$  = Azimuth Resolution
- $\rho_r$  = Range Resolution
- $\lambda$  = Wavelength
- $\Delta\theta_{ap}$  = Total Angular Extent of Synthetic Aperture
- $c$  = Speed of Light
- $B$  = Transmitted Bandwidth

## ScanSAR Mode

ScanSAR sacrifices azimuth resolution for wider area coverage by cyclically switching the radar beam between multiple sub-swaths. This burst-mode operation limits the integration time per target.

$$\rho_a \approx \frac{v T_{burst}}{2N_{swaths}}$$
$$\rho_r = \frac{c}{2B}$$

Where:

- $\rho_a$  = Azimuth Resolution
- $\rho_r$  = Range Resolution
- $v$  = Platform Velocity
- $T_{burst}$  = Burst Duration
- $N_{swaths}$  = Number of Swaths
- $c$  = Speed of Light
- $B$  = Transmitted Bandwidth

These equations highlight the fundamental trade-offs between resolution, coverage, and complexity inherent in SAR system design and operation.



# RAR & SLAR Resolution

## SLAR Resolution

SLAR uses the physical length of its antenna to determine azimuth (along-track) resolution. This resolution degrades significantly with increasing distance from the sensor. Ground range (across-track) resolution is dependent on pulse duration and the radar's incidence angle. It's a foundational radar type, typically deployed on aircraft.


## RAR Resolution

RAR, also known as SLAR, refers to radar systems that achieve resolution directly through the physical dimensions of their antenna. Azimuth resolution is limited by the antenna's beamwidth, meaning the further away the target, the coarser the resolution. Ground range resolution is controlled by the radar pulse length. SAR was developed to overcome these limitations.





# Factors Affecting SAR Resolution



## Factors affecting Range Resolution (Distance from Sensor)

- **Bandwidth (B)**: A larger bandwidth results in finer range resolution, allowing better distinction of targets at different distances.
- **Platform Altitude**: Higher altitudes generally decrease spatial resolution.
- **Pulse Compression**:
  - Techniques like chirp signals improve resolution by effectively increasing bandwidth.

## Factors affecting Azimuth Resolution (Direction of Travel)

- **Antenna Length (L)**: A physically longer antenna gives better resolution, but SAR synthesizes a long "virtual" antenna using platform motion.
- **Wavelength ( $\lambda$ )**: Shorter wavelengths generally improve resolution.
- **Platform Velocity & Integration Time**: Longer processing time (capturing data over a longer path) and velocity help create a larger synthetic aperture, improving resolution.
- **Doppler Bandwidth**: Resolution is related to the Doppler shift within the beamwidth, affected by incidence angle and platform motion.
- **Acquisition Mode**: Modes like **Spotlight SAR** focus energy on a specific area longer, improving azimuth resolution.

# RAR & SLAR Resolution


## RAR Resolution

Real Aperture Radar (RAR) resolution is limited by the physical antenna size, resulting in coarser resolution at longer ranges.

## SLAR Resolution

Side-Looking Airborne Radar (SLAR) also uses a real aperture, with resolution degrading with increasing distance from the sensor.

| Radar Parameters             |                   |                         |
|------------------------------|-------------------|-------------------------|
| Mode                         | RAR               | SAR                     |
| Central frequency/wavelength | 17.1 GHz/0.0175 m | 17.1 GHz/0.0175 m       |
| Range resolution             | 0.5 m             | 0.5 m                   |
| Azimuth resolution           | NA                | 4.4 mrad (<2 m @ 500 m) |
| Maximum Range                | 400 m             | 4 km                    |
| Sampling frequency           | 200 Hz            | 6 min                   |
| Output Data format           | 1D Range profile  | 2D Images               |





# SAR, RAR, & SLAR Resolution: A Comparative Look

| Feature                  | SLAR (Side-Looking Airborne Radar)         | RAR (Real Aperture Radar)                                                        | SAR (Synthetic Aperture Radar)                                        |
|--------------------------|--------------------------------------------|----------------------------------------------------------------------------------|-----------------------------------------------------------------------|
| Category                 | General category for side-looking systems. | A specific type of SLAR using a physical aperture.                               | A specific type of SLAR using a "virtual" aperture.                   |
| Azimuth Resolution (R_a) | Limited by physical beamwidth.             | Dependent on antenna length (L) and Range (R): $R_a = \frac{R \cdot \lambda}{L}$ | <b>Independent of range</b> and wavelength: $R_a \approx \frac{L}{2}$ |
| Antenna Length           | Usually long (to narrow the beam).         | Physically limited by what an aircraft can carry.                                | Small physical antenna that acts like a massive one.                  |
| Spatial Resolution       | Generally coarse.                          | Becomes worse as altitude/range increases.                                       | <b>Constant high resolution</b> regardless of altitude.               |
| Processing               | Simple signal reception.                   | Direct recording of echoes.                                                      | Complex; uses Doppler shift and phase history.                        |
| Best Used For            | Basic mapping, low-altitude flight.        | Simple target detection at close ranges.                                         | Spaceborne imaging, high-res earth observation.                       |

# Comparing Radar Systems: RAR, SLAR, & SAR

Each radar system utilizes distinct principles to achieve imaging, impacting their resolution capabilities and operational applications.



## Real Aperture Radar (RAR)

RAR's resolution is directly limited by the physical size of its antenna. The radar beam naturally widens with distance, leading to reduced clarity for distant targets.



## Side-Looking Airborne Radar (SLAR)

An airborne variant of RAR, SLAR employs an antenna fixed to the side of an aircraft. Its azimuth resolution notably diminishes as the range to the target increases.




## Synthetic Aperture Radar (SAR)

SAR overcomes physical antenna size constraints by synthetically creating a much larger "virtual" antenna. This allows for high-resolution imaging, largely independent of distance, through sophisticated signal processing.



# Polarization in SAR

Polarization in Synthetic Aperture Radar (SAR) refers to the orientation of the electric field of the transmitted and received electromagnetic waves. By controlling and analyzing these orientations, SAR systems can extract rich information about the physical properties and dielectric characteristics of observed targets, such as surface roughness, moisture content, and target geometry.



## Key Polarization Modes


1

Horizontal transmit, Horizontal receive.  
Ideal for detecting smooth surfaces and water bodies.

2

Vertical transmit, Vertical receive.  
Effective for vegetation penetration and volumetric scattering from rough surfaces.

## SYNTHETIC-APERTURE RADAR



# Circular Polarization in SAR

Unlike linear polarization, circular polarization involves an electric field that rotates as the radar wave propagates. This dynamic orientation offers unique insights into target characteristics.

## Rotating Electric Field


The electric field vector rotates 360 degrees for every wavelength traveled, providing information from all linear orientations simultaneously.

## Enhanced Target Characterization


Circular polarization is particularly effective for identifying complex scattering mechanisms and targets with specific geometries, such as helical structures or rough surfaces.

## Improved Discrimination


While indirectly improving spatial resolution, circular polarization significantly enhances the ability to differentiate between various target types and reduce image speckle, boosting overall interpretability.




(i) Locus of an elliptically polarized wave



(a) Horizontal polarization, Vertical polarization



(b) Linear 45 degree polarization, Linear -45 degree polarization




(c) Left circular polarization, Right circular polarization


(ii) Typical polarizations



(a) HH






(b) HV and VH




(c) VV

(iii) Scattering with respect to polarization







$$R_r = \frac{CT}{2 \cos \theta}$$

$R_r$  : Range resolution

$C$  : Speed of light ( $3E+8$  m/s)




$T$  : Pulse duration (i.e. How long each pulse lasts)

$\theta$  : Depression angle

$$R_a = \overline{SR} \cdot \beta$$

SR: Slant range

$\beta$ : Antenna beam width







HH polarization (red)  
Transmits horizontal waves  
Receives horizontal waves

HV polarization (green)  
Transmits horizontal waves  
Receives vertical waves

VV polarization (blue)  
Transmits vertical waves  
Receives vertical waves

3-Polarization color overlay





# Radar Resolution Equations

## 1. Side-Looking Airborne Radar (SLAR) / Real Aperture Radar (RAR)

In the context of remote sensing, **SLAR** usually refers to a Real Aperture Radar system. Therefore, the resolution equations for SLAR and RAR are identical. The resolution is physically limited by the pulse length and the physical size of the antenna. ⓘ

### Range Resolution

This determines the system's ability to distinguish between two targets that are close to each other in the direction perpendicular to the flight path (cross-track). ⓘ

- **Slant Range Resolution ( $\delta_r$ ):**

$$\delta_r = \frac{c\tau}{2}$$

(Alternatively, using bandwidth  $B$ , where  $\tau \approx 1/B$ :  $\delta_r = \frac{c}{2B}$ )

- **Ground Range Resolution ( $\delta_g$ ):**

$$\delta_g = \frac{c\tau}{2 \sin \theta}$$

## 2. Synthetic Aperture Radar (SAR)

SAR uses signal processing to synthesize a much longer antenna aperture effectively, allowing for much finer azimuth resolution that is independent of the range. ⓘ

### Range Resolution

The range resolution physics for SAR is the same as RAR. However, SAR systems almost exclusively use "pulse compression" (chirp), so the resolution is defined by bandwidth rather than simple pulse duration. ⓘ

- **Slant Range Resolution ( $\delta_r$ ):**

$$\delta_r = \frac{c}{2B_{chirp}}$$

### Azimuth Resolution

This is the distinguishing feature of SAR. The resolution is theoretically independent of the range and the wavelength.

- **Azimuth Resolution ( $\delta_a$ ):**

$$\delta_a = \frac{L}{2}$$

(Note: This counter-intuitive result means a **smaller** physical antenna yields better resolution in SAR, because a smaller antenna has a wider beam, allowing the target to stay in the "view" of the radar for a longer time, facilitating a longer synthetic aperture synthesis.)

### Azimuth Resolution

This determines the ability to distinguish targets parallel to the flight path (along-track). In RAR/SLAR, this is diffraction-limited and degrades (becomes larger/worse) as the distance to the target increases. ⓘ

- **Azimuth Resolution ( $\delta_a$ ):**

$$\delta_a = \frac{\lambda R}{L}$$

(or  $\delta_a = \beta R$ , where beamwidth  $\beta = \lambda/L$ ) ⓘ



EO



SAR

NICEGAN(C)

Pix2Pix

CycleGAN

Proposed





# Quad POL SAR

## Advantages of Fully Polarimetric SAR

- A. Superior Target Classification:** By measuring all four polarization channels, full-pol SAR allows for precise identification of land cover types, vegetation types, and urban features through complex scattering mechanism analysis (e.g., Pauli decomposition).
- B. Detailed Scattering Mechanism Identification:** It can distinguish between surface scattering (flat surfaces/water), double-bounce scattering (urban structures/tree trunks), volume scattering (forest canopies/vegetation), and helical scattering.
- C. High-Precision Parameter Inversion:** It offers the highest accuracy in retrieving physical parameters like soil moisture, above-ground biomass, and crop residue coverage, often outperforming dual-pol systems by 17% or more in classification accuracy.
- D. Advanced Target Characterization:** It can identify complex, non-symmetric targets, such as industrial structures, that produce helix scattering, which are undetectable by non-fully polarimetric systems.
- E. Improved Landslide/Disaster Detection:** It enables the identification of rapid changes, such as landslides, by distinguishing between bare soil (surface scattering) and surrounding vegetation, even when optical sensors are limited by cloud cover.
- F. Synthetic Polarization:** The coherent collection of all four channels allows users to mathematically synthesize any combination of transmit and receive polarizations after data acquisition, enhancing the flexibility of analysis.

| Parameter                               | Value                                                                                 |
|-----------------------------------------|---------------------------------------------------------------------------------------|
| Center Frequency                        | 5.4 GHz                                                                               |
| Polarization                            | single, dual, quad                                                                    |
| Antenna Size                            | 15 m (A) × 1.232 m (E)                                                                |
| Number of Panels                        | 4                                                                                     |
| Array Columns (Azimuth)                 | 24                                                                                    |
| Array Rows (Elevation)                  | 64 (32 in H, 32 in V)                                                                 |
| Radio Frequency (RF) Peak Power         | 15,360 W                                                                              |
| Average Power Consumption               | 8000 W max                                                                            |
| Pulse Width                             | 10–60 us (programmable)                                                               |
| Signal Bandwidth                        | 2~240 MHz (programmable)                                                              |
| Transmit Duty Cycle                     | 20% max                                                                               |
| Receiver Noise Figure (at Module Input) | 2.5 dB max                                                                            |
| Receiver Channels                       | 2                                                                                     |
| Pulse Repetition Frequency              | 1000~6000 Hz (programmable)                                                           |
| Sampling Frequency                      | 533.33 MHz (IF sampling)                                                              |
| Quantization                            | 8 bits                                                                                |
| Data Compression                        | Block Adaptive Quantization (BAQ) 3 bits, BAQ 4 bits, High-4 bits, 8 bit (Selectable) |
| Output Data Rate                        | 1280 Mbps max                                                                         |



# Mathematical Formulations

The mathematical formulas are applied through signal processing algorithms, converting raw radar echoes into a two-dimensional image.

## ❑ Range Compression:

Since radar systems use long, linear frequency-modulated (LFM) pulses to increase energy, the received echoes are passed through a matched filter (autocorrelation) to compress them into a narrow pulse, enhancing range resolution.

## ❑ Azimuth Compression (Focusing):

As the radar platform moves, it captures echoes from a target at multiple positions. These signals have different phase shifts. A matched filter, which accounts for the quadratic phase variation of the Doppler signal, is applied to coherently combine these signals, effectively creating a large "synthetic" antenna.


Algorithms:

**Range-Doppler Algorithm (RDA):** Uses frequency-domain processing for both range and azimuth.

**Chirp Scaling Algorithm (CSA):** Removes the need for interpolation in Range Cell Migration Correction (RCMC).


**Omega-K Algorithm ( $\omega_K$ ):** Employs Stolt mapping to avoid azimuth frequency dependency, useful for wide apertures.

**Backprojection Algorithm (BPA):** A time-domain approach that offers high-quality imaging, suitable for complex geometries and non-linear paths




# Radar Geometry: RAR, SLAR, & SAR

Understanding the unique geometric setups of Real Aperture Radar (RAR), Side-Looking Airborne Radar (SLAR), and Synthetic Aperture Radar (SAR) is fundamental to grasping their operational principles and imaging capabilities.



Real Aperture Radar (RAR)

RAR systems use a stationary antenna that emits a radar beam. The width of this beam naturally diverges with distance from the antenna, directly influencing the resolution cell size on the ground.



Side-Looking Airborne Radar (SLAR)

SLAR operates from a moving platform (typically an aircraft), utilizing an antenna that transmits a fan-shaped beam to the side, perpendicular to the flight path. The antenna's physical length determines the azimuth resolution, which degrades with increasing range.



Synthetic Aperture Radar (SAR)

SAR systems employ a smaller physical antenna on a moving platform (aircraft or satellite). By processing a series of radar echoes collected over time, SAR synthesizes a much longer "virtual" antenna, allowing it to achieve high and consistent resolution regardless of the distance to the target.



# Factors Affecting RAR,SLAR and SAR Resolution

Radar resolution, a critical measure of imaging capability, is influenced by distinct system parameters and environmental conditions across Real Aperture Radar (RAR), Side-Looking Airborne Radar (SLAR), and Synthetic Aperture Radar (SAR) systems.

## Range Resolution: Bandwidth & Pulse Length

For all radar types (RAR, SLAR, SAR), range resolution is primarily determined by the **bandwidth** of the transmitted pulse. A wider bandwidth (shorter pulse duration) allows for finer distinction between objects positioned along the radar's line of sight, regardless of the system.

## RAR & SLAR Azimuth: Antenna Length & Range

The azimuth (along-track) resolution in RAR and SLAR systems is directly dependent on the **physical length of the antenna** and the **distance (slant range)** to the target. As the range increases, the radar beam spreads, leading to a significant degradation in azimuth resolution. Longer physical antennas improve this, but are limited by practical size constraints.

## SAR Azimuth: Synthetic Aperture & Processing

SAR overcomes the azimuth resolution limitations of RAR/SLAR by employing sophisticated **signal processing techniques**. It synthesizes a much larger "virtual antenna" from multiple pulses collected as the platform moves. This makes SAR's azimuth resolution largely **independent of slant range** and primarily determined by the length of the synthetic aperture, often reaching half the physical antenna length, leading to consistently high resolution.

## Platform Motion & Data Acquisition

For SLAR and SAR, the **platform's velocity** and stability are crucial. In SAR, the accurate measurement of platform motion is essential for coherently combining radar echoes to form the synthetic aperture. Any inaccuracies in motion compensation can degrade the final resolution.

# Satellite and System Parameters for SAR Resolution

Synthetic Aperture Radar (SAR) resolution is meticulously crafted, not just through advanced processing, but also by a critical combination of satellite orbital characteristics and inherent radar system design parameters. These factors collectively dictate the precision and clarity of the final imagery.



## Pulse Bandwidth

The **bandwidth** of the transmitted radar pulse is the primary determinant of SAR's range resolution. A wider bandwidth (shorter pulse duration) allows for the precise differentiation of objects positioned along the radar's line of sight, improving depth perception in the image.



## Physical Antenna Length

While SAR synthesizes a large aperture, the **physical length of the antenna** on the satellite or aircraft is crucial. It defines the initial beam footprint and the duration over which coherent radar echoes are collected, indirectly influencing the maximum achievable synthetic aperture length and azimuth resolution.



## Integration Time

Also known as the **synthetic aperture length**, this refers to the total time a target remains within the radar's beam while coherent data is collected. A longer integration time allows for the creation of a longer synthetic aperture, which directly translates to superior azimuth resolution, independent of range.



## Incidence Angle

The **incidence angle** (the angle at which the radar beam strikes the ground) significantly impacts the conversion of slant range resolution to ground range resolution. Steeper angles can reduce ground range resolution, while also influencing factors like shadowing, layover, and the strength of the backscattered signal.

Optimizing these parameters is key to designing SAR systems that meet specific imaging requirements for various applications, from environmental monitoring to disaster response.



# Major SAR Satellites and Their Capabilities

Modern Synthetic Aperture Radar (SAR) systems are deployed on a variety of satellites, each engineered with specific parameters to cater to diverse applications. These missions provide invaluable data for global monitoring, disaster response, and scientific research.

|                            |                          |                                                                |                                                                        |
|----------------------------|--------------------------|----------------------------------------------------------------|------------------------------------------------------------------------|
| Sentinel-1                 | ESA                      | C-band, dual polarization, wide-swath imaging.                 | Land and ocean monitoring, emergency management, climate change.       |
| TerraSAR-X / TanDEM-X      | Germany                  | X-band, very high resolution, bistatic configuration for DEMs. | High-precision topography, deformation monitoring, security.           |
| RADARSAT-2 / Constellation | Canada                   | C-band, full polarization, configurable beams, rapid revisit.  | Ice and maritime surveillance, disaster response, resource management. |
| ALOS-2 PALSAR-2            | JAXA (Japan)             | L-band, long wavelength for forest penetration, multi-mode.    | Forest mapping, ground deformation, disaster damage assessment.        |
| Capella Space / ICEYE      | Commercial (USA/Finland) | X-band, very high resolution, rapid revisit, smallsats.        | Commercial intelligence, defense, infrastructure monitoring.           |

The continuous evolution of these SAR missions pushes the boundaries of Earth observation, providing increasingly detailed and timely information across a broad spectrum of scientific and commercial needs.

# SLAR Resolution: Equations and Factors


Side-Looking Airborne Radar (SLAR) resolution, while simpler than SAR, is fundamentally determined by specific geometric and system parameters. Understanding these core equations is vital for assessing the clarity and detail in SLAR imagery.

## Range Resolution ( $\delta_r$ )

SLAR range resolution refers to the radar's ability to distinguish between two targets located at different distances along the radar's line of sight. It is primarily governed by the radar's pulse duration and the incidence angle of the beam on the ground.

$$\delta_r = \frac{cl}{2\sin\theta_i}$$

- $c$ : The speed of light.
- $\tau$ : The transmitted pulse duration. A shorter pulse duration results in finer range resolution.
- $\theta_i$ : The incidence angle (the angle between the radar beam and the normal to the ground surface). A larger incidence angle (closer to grazing) improves ground range resolution, though at very steep angles, the **ground range resolution degrades** if not adjusted for the cosine term. For slant range resolution, it's just  $c\tau / 2$ .






# Spatial Resolution: Ground Range & Azimuth


Spatial resolution is a critical parameter for Synthetic Aperture Radar (SAR), defining the smallest feature size distinguishable in an image. Unlike conventional radars, SAR decouples resolution from physical antenna size, enabling exceptionally fine detail through advanced signal processing.

## Ground Range Resolution

SAR ground range resolution refers to the ability to distinguish between two targets located at different perpendicular distances from the radar's flight path, once their slant range distances have been projected onto the ground. This resolution is primarily determined by the transmitted pulse bandwidth (which dictates slant range resolution) and the radar's incidence angle. Steeper incidence angles generally lead to finer ground range resolution by stretching the slant range pixels across a smaller ground distance.



Relationship between slant-range resolution and ground-range resolution (after Lillesand and Kiefer, 1994).



Dependence of azimuth resolution ( $R_a$ ) on antenna beam width ( $\beta$ ) and ground range ( $GR$ ). (After Lillesand and Kiefer, 1994)

# Choosing the Right Radar: Resolution-Driven Applications

Selecting the appropriate radar technology depends heavily on the spatial resolution required for the specific application. Each system—RAR, SLAR, and SAR—offers distinct advantages tailored to different observational needs.



## Real Aperture Radar (RAR)

Best for general surveillance, basic navigation, or applications where broad coverage and system simplicity outweigh the need for fine detail. Its resolution is directly tied to antenna size, making it suitable for less demanding scenarios like basic weather patterns.



## Side-Looking Airborne Radar (SLAR)

A good choice for moderate-resolution mapping over regional areas, typically from airborne platforms. Used in applications like rapid disaster assessment, environmental monitoring, or geological surveys where a balance between detail and coverage is needed.



## Synthetic Aperture Radar (SAR)

Indispensable for tasks requiring very high spatial resolution, independent of range. SAR excels in deformation monitoring, detailed urban infrastructure mapping, ice flow tracking, and precise change detection across complex environments.

**Understanding these distinctions ensures that the chosen radar system delivers the optimal data quality for the intended purpose, minimizing unnecessary complexity or insufficient detail.**



# Visualizing SAR Resolution


The resolution of Synthetic Aperture Radar (SAR) imagery directly impacts the level of detail observable on the Earth's surface. From broad-scale patterns to intricate features, varying resolutions serve diverse applications in remote sensing. Observe how different resolution levels reveal progressively finer elements within the landscape.



(a)




(b)



As the resolution improves, the ability to identify and analyze smaller objects and more subtle changes in terrain becomes significantly enhanced, enabling precision in monitoring and analysis across various domains.

# SAR's Resolution Advantage: Beyond Physical Limits

Synthetic Aperture Radar (SAR) fundamentally redefines resolution capabilities compared to its predecessors, Real Aperture Radar (RAR) and Side-Looking Airborne Radar (SLAR). While RAR and SLAR are constrained by the physical size of their antennas and the inherent beam spreading with distance, SAR overcomes these limitations through advanced signal processing.




This decoupling of resolution from physical antenna dimensions and range is SAR's defining advantage, allowing it to achieve exceptionally fine spatial detail from distant platforms, a feat impossible with conventional radar designs.



# Conventional Radar vs. SAR System Design

The fundamental differences in resolution capabilities between conventional radar and SAR systems stem directly from their architectural designs. While conventional radars rely on physically large antennas, SAR achieves its superior resolution through ingenious signal processing, allowing for more compact hardware on orbiting platforms.





## Key Design Distinctions

Conventional radar (like RAR) on a satellite would require an enormous antenna to achieve high azimuth resolution, which is impractical for space deployment. SAR, however, synthesizes a much larger virtual antenna through data collection and processing, enabling smaller physical antennas and thus more feasible satellite designs.

# Inverse Synthetic Aperture Radar (ISAR)

- **ISAR (Inverse Synthetic Aperture Radar)** images moving targets using target motion.
- Resolution indicates the ability to distinguish **closely spaced features** on the target.
- **Range Resolution ( $\Delta R$ ):**
  - Depends on radar **bandwidth**
  - $\Delta R = \frac{c}{2B}$
- **Cross-Range Resolution ( $\Delta CR$ ):**
  - Depends on **target's angular motion**
  - $\Delta CR = \frac{\lambda}{2\Delta\theta}$
- Higher bandwidth and greater target rotation → **better ISAR resolution**
- Used for **ship, aircraft, and space object imaging**





- **SAR = picture of Earth**
- **InSAR = change in Earth**



# Polarimetric SAR Resolution


- **PolSAR (Polarimetric SAR)** uses multiple polarization channels (HH, HV, VH, VV)
- **Range Resolution:**
  - Depends on radar **bandwidth**
  - $\Delta R = \frac{c}{2B}$
- **Azimuth Resolution:**
  - Depends on SAR system parameters and platform motion
- **Polarimetric Resolution:**
  - Ability to distinguish different **scattering mechanisms**
  - Improved using multi-polarization amplitude and phase information
- Polarimetry **does not change spatial resolution**, but enhances **target discrimination**
- PolSAR uses different radar polarizations to study surface characteristics and scattering mechanisms.



- **SAR = image**
- **PolSAR = material/type of object**

# Interferometric SAR (InSAR) Resolution

- **InSAR (Interferometric SAR)** uses phase difference between two SAR images
- Measures **surface elevation and deformation**
- **Range Resolution:**
  - Depends on radar **bandwidth**
  - $\Delta R = \frac{c}{2B}$
- **Azimuth Resolution:**
  - Depends on SAR system parameters (similar to SAR)
- **Height (Vertical) Resolution:**
  - Depends on **perpendicular baseline**, wavelength, and geometry
  - Larger baseline → better height sensitivity
- Applications: **DEM generation, ground subsidence, earthquake studies**




• **InSAR = measuring how much the ground moved**



# Polarimetric SAR Interferometry (PolInSAR) Resolution

- **PolInSAR** combines **Polarimetry (PolSAR)** and **Interferometry (InSAR)**
- Uses **multi-polarization interferometric phase** information
- **Range Resolution:**
  - Depends on radar **bandwidth**
  - $\Delta R = \frac{c}{2B}$
- **Azimuth Resolution:**
  - Same as SAR, depends on system geometry
- **Vertical (Height) Resolution:**
  - Depends on **perpendicular baseline**, wavelength, and polarization
  - Improved height estimation using **polarimetric diversity**
- Applications: **forest height estimation, vegetation structure, biomass mapping**



PolInSAR = height & structure

# References

1. Henderson, F. M., & Lewis, A. J. (Eds.). (1998). Principles & applications of imaging radar: Manual of remote sensing (3rd ed., Vol. 2). John Wiley & Sons.(Classic reference on SAR principles, including spatial resolution basics.)National Research Council. (1998).
2. Development and application of small spaceborne synthetic aperture radars (Chapter 2: SAR Issues). The National Academies Press. <https://doi.org/10.17226/9492>(Discusses RAR vs. SAR imaging and resolution differences.)Woodhouse, I. H. (2017). Introduction to microwave remote sensing. CRC Press.(Comprehensive treatment of radar resolution including SAR/real aperture comparisons.)European Space Agency. (2018).
3. Advanced training course on land remote sensing: SAR overview (Session on resolution). University of Leicester.(Course material that explains resolution improvement from RAR to SAR.)SARMAP. (2009). SAR-Guidebook: Synthetic Aperture Radar fundamentals (pp. real aperture radar resolution). SARMAP AG.(Technical guide describing RAR and SAR resolution formulas.)NASA Earthdata. (2024).
4. SAR Marine User's Manual – Chapter 1: Principles of Synthetic Aperture Radar. NOAA.(Details range and azimuth resolution formulas for SAR systems.)Zhang, W., Zhao, R., Yao, Y., Wan, Y., Wu, P., Li, J., Li, Y., & Zhang, Y. (2025).
5. Multi-resolution SAR and optical remote sensing image registration methods: A review, datasets, and future perspectives. arXiv. <https://arxiv.org/abs/2502.01002>(Recent review including discussion of resolution implications for multi-resolution SAR analysis.)Ge, N., Rodriguez Gonzalez, F., Wang, Y., Shi, Y., & Zhu, X. X. (2018).
6. Spaceborne staring spotlight SAR tomography: A first demonstration with TerraSAR-X. arXiv. <https://arxiv.org/abs/1807.06826>(Demonstrates how higher azimuth resolution is achieved in advanced SAR modes.)Aberman, K., & Eldar, Y. C. (2016).
7. Sub-Nyquist SAR via Fourier domain range Doppler processing. arXiv. <https://arxiv.org/abs/1608.04138>(Discusses range and azimuth sampling/resolution tradeoffs in SAR signal processing.)Goodman, R., & Carrara, W. (2005). Azimuth resolution. In A. K. (Ed.), Handbook of image and video processing (2nd ed.). Academic Press.(Covers the theoretical basis of azimuth (cross-range) resolution relevant to RAR/SAR.)



THANK YOU