



DMX Profile

Table of Contents

DMX Configuration	04
DMX Configuration Compatibility Chart.....	05
DMX Loss Behavior	06
DMX Profiles	07
Profile 1: CCT Universal - 8Bit (3CH)	07
Profile 2: CCT - 8Bit (5CH)	08
Profile 3: RGB - 8Bit (5CH)	09
Profile 4: CCT&RGB - 8Bit (9CH)	10
Profile 5: HSI-8Bit (4CH)	11
Profile 6: HSIC+ -8Bit (7CH)	12

Version	Date	Note
V1.0	November 2025	First Release
V1.1	March 2026	amaran Halo series products compatible

DMX Configuration

You can select from six different DMX configuration profiles for the fixture. The available options are listed in the table below.

Profile 1 – CCT Universal – 8Bit (3 Channels): Used when combining different amaran series fixtures without distinction. This profile limits the color temperature range to 2700K–6500K and disables green–magenta adjustment, making it compatible across all series.

Profile 2 – CCT – 8Bit (5 Channels): Used for controlling only the color temperature adjustment function of the fixture. It enables all CCT-related functions, including brightness adjustment, color temperature adjustment, extended CCT range, and green–magenta adjustment.

Profile 3 – RGB – 8Bit (5 Channels): Used for controlling the RGB color output of the fixture.

Profile 4 – CCT & RGB – 8Bit (9 Channels): Used for both color temperature and RGB color control, allowing smooth transitions between white light of different color temperatures and colored light.

Profile 5 – HSI – 8Bit (4 Channels): Used for HSI color control of the fixture.

Profile 6 – HSIC+ – 8Bit (7 Channels): Used for both CCT and HSI color control, allowing smooth transitions between white light of different color temperatures and colored light.

DMX Configuration Compatibility Chart

Product Model	Profile 1	Profile 2	Profile 3	Profile 4	Profile 5	Profile 6
	CCT Uni-versal -8Bit	CCT-8Bit	RGB-8Bit	CCT&RGB -8Bit	HSI-8Bit	HSIC+ -8Bit
	3 Channels	5 Channels	5 Channels	9 Channels	4 Channels	7 Channels
amaran Ray 360c	✓	✓	✓	✓	✓	✓
amaran Ray 660c	✓	✓	✓	✓	✓	✓
amaran Halo 60x	✓					
amaran Halo 100x	✓					
amaran Halo 200x	✓					
amaran Halo 300x	✓					
amaran Halo 600x	✓					

DMX Loss Behavior

Hold Last Settings: holds the last control levels after the DMX signal is lost;

Black Out: black out after the DMX signal is lost;

Fade to Black: fade to black over 60 seconds after the DMX signal is lost;

Hold 2 mins & Fade Out: hold the last controlsignal for 2 minutes and fade out over 60 seconds after the DMX signal is lost.

DMX Profiles

Profile 1: CCT Universal - 8Bit (3CH)					
Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0-255	0-100	0-100%	0% / 0
2	CCT	0-255	0-100	2700K-6500K	3200K / 34
Control Channels					
3	Strobe	0-255	0-100	Strobe On/Off	Off / 0
		0-13	0-5	Off	0 / 0
		14-128	6-50	Random (1Hz- >25Hz)	
		129-255	51-100	Constant (1Hz- >25Hz)	

Profile 2: CCT - 8Bit (5CH)					
Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0-255	0-100	0-100%	0% / 0
2	CCT	0-255	0-100	CCT+ Off 2300K-10000K	3200K / 30
				CCT+ On 2300K-10000K	3200K / 17
3	±Green	0-255	0-100	-G to 0G to +G	Neutral / 50% / 133
		0-10	0-4	No Effect*	
		11-20	5-8	-100 / Full Minus Green	
		21-119	9-46	-99% - -1%	
		120-145	47-57	0% /Neutral	
		146-244	58-96	1% - 99%	
		245-255	97-100	100% / Full Plus Green	
Control Channels					
4	Strobe	0-255	0-100	Strobe On/Off	Off / 0
		0-13	0-5	Off	0
		14-128	6-50	Random (1Hz- >25Hz)	
		129-255	51-100	Constant (1Hz- >25Hz)	
5	CCT+	0-255	0-100	CCT+ On/Off	Off / 0
		0-127	0-49	CCT+ Off	
		128-255	50-100	CCT+ On	
*Do not patch “No Effect” range into consoles					

Profile 3: RGB - 8Bit (5CH)					
Channel	Function	Value	Percent	Description	Default % / DMX
CCT is Locked at 6500K					
1	Intensity	0-255	0-100	0-100%	0% / 0
2	Red	0-255	0-100		100% / 255
3	Green	0-255	0-100		100% / 255
4	Blue	0-255	0-100		100% / 255
Control Channels					
5	Strobe	0-255	0-100	Strobe On/Off	Off/0
		0-13	0-5	Off	0
		14-128	6-50	Random (1Hz- >25Hz)	
		129-255	51-100	Constant (1Hz- >25Hz)	

Profile 4: CCT&RGB - 8Bit (9CH)

Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0-255	0-100	0-100%	0% / 0
2	CCT	0-255	0-100	CCT+Off2300K-10000K	3200K / 30
				CCT+On1800K-20000K	3200K / 17
3	±Green	0-255	0-100	-G to 0G to +G	Neutral / 50% / 133
		0-10	0-4	No Effect*	
		11-20	5-8	-100 / Full Minus Green	
		21-119	9-46	-99% - -1%	
		120-145	47-57	0% / Neutral	
		146-244	58-96	1% - 99%	
		245-255	97-100	100% / Full Plus Green	
4	Crossfade	0-255	0-100	White Light to RGB	0% / 0
5	Red	0-255	0-100		100% / 255
6	Green	0-255	0-100		100% / 255
7	Blue	0-255	0-100		100% / 255
Control Channels					
8	Strobe	0-255	0-100	Strobe On/Off	Off/0
		0-13	0-5	Off	0
		14-128	6-50	Random (1Hz- >25Hz)	
		129-255	51-100	Constant (1Hz- >25Hz)	
9	CCT+	0-255	0-100	CCT+ On/Off	Off/0
		0-127	0-49	CCT+ Off	
		128-255	50-100	CCT+ On	
*Do not patch “No Effect” range into consoles					

Profile 5: HSI-8Bit (4CH)					
Channel	Function	Value	Percent	Description	Default % / DMX
CCT is Locked at 6500K					
1	Intensity	0-255	0-100	0-100%	0% / 0
2	Hue	0-255	1-360		0
3	Saturation	0-255	0-100	White Light to RGB	0%
Control Channels					
4	Strobe	0-255	0-100	Strobe On/Off	Off/0
		0-13	0-5	Off	0
		14-128	6-50	Random (1Hz- >25Hz)	
		129-255	51-100	Constant (1Hz- >25Hz)	

Profile 6: HSIC+ -8Bit (7CH)					
Channel	Function	Value	Percent	Description	Default % / DMX
1	Intensity	0-255	0-100	0-100%	0% / 0
2	CCT	0-255	0-100	CCT+Off2300K-10000K	3200K / 30
				CCT+ On1800K-20000K	3200K / 17
3	±Green	0-255	0-100	-G to 0G to +G	Neutral / 50% / 133
		0-10	0-4	No Effect*	
		11-20	5-8	-100 / Full Minus Green	
		21-119	9-46	-99% - -1%	
		120-145	47-57	0% / Neutral	
		146-244	58-96	1% - 99%	
		245-255	97-100	100% / Full Plus Green	
4	Hue	0-255	1°-360°		0
5	Saturation	0-255	0-100	White Light to RGB	0%
Control Channels					
6	Strobe	0-255	0-100	Strobe On/Off	Off / 0
		0-13	0-5	Off	0
		14-128	6-50	Random (1Hz- >25Hz)	
		129-255	51-100	Constant (1Hz- >25Hz)	
7	CCT+	0-255	0-100	CCT+ On/Off	Off / 0
		0-127	0-49	CCT+ Off	
		128-255	50-100	CCT+ On	
*Do not patch “No Effect” range into consoles					