Programming Maqueen to respond to remote control

on start

radio set group `1`

---

on radio received `receivedNumber ▾`

if (`receivedNumber ▾` = ▾ `0`) **then**

  Motor Stop All

⊕

if (`receivedNumber ▾` = ▾ `1`) **then**

  Motor `M1 ▾` dir `CW ▾` speed `100`

  Motor `M2 ▾` dir `CW ▾` speed `100`

⊕

if (`receivedNumber ▾` = ▾ `2`) **then**

  Motor `M1 ▾` dir `CCW ▾` speed `100`

  Motor `M2 ▾` dir `CCW ▾` speed `100`

⊕

if (`receivedNumber ▾` = ▾ `3`) **then**

  Motor `M1 ▾` dir `CW ▾` speed `100`

  Motor `M2 ▾` dir `CCW ▾` speed `100`

⊕

if (`receivedNumber ▾` = ▾ `4`) **then**

  Motor `M1 ▾` dir `CCW ▾` speed `100`

  Motor `M2 ▾` dir `CW ▾` speed `100`

⊕