Basic Introduction

Accessing Documents

General Information

STREAM

DELTA PRO

DELTA 2

DELTA 2 MAX

Smart Home Panel

Smart Plug

PowerStream Micro-inverter

Wave Air Conditioner

Glacier

Power Kits

PowerOcean

DELTA Pro Ultra

DELTA Pro 3

Smart Home Panel II

River 2 Pro

Code package download

Support

ModuleType definition

Field	Field's Type	Description

HTTP communication mode

Get Quota

Obtaining real-time data: POST: /iot-open/sign/device/quota

PowerOcean

Set Command	GetCmdRequest	GetCmdResponse
Phase A data		
	`{ "sn": "HJ31ZDH2ZF690029", "params": { "quotas": [ "pcsAPhase" ] } }`	`{ "code": "0", "message": "Success", "data": { "pcsAPhase": { "vol": 229.70134, "amp": 3.6087508, "actPwr": -810.62787, "reactPwr": 173.24965, "apparentPwr": 828.9349 } }, "eagleEyeTraceId": "", "tid": "" }`
Phase B data		
	`{ "sn": "HJ31ZDH2ZF690029", "params": { "quotas": [ "pcsBPhase" ] } }`	`{ "code": "0", "message": "Success", "data": { "pcsBPhase": { "vol": 229.49283, "amp": 3.2976089, "actPwr": -738.08673, "reactPwr": 167.15356, "apparentPwr": 756.7776 } }, }`

Set Command	GetCmdRequest	GetCmdResponse
		"eagleEyeTraceId": "", "tid": "" }
Phase C data		

	{
	"sn": "HJ31ZDH2ZF690029",
	"params": {
	"quotas": [
	"pcsCPhase"
	]
	}
	}
		{
		"code": "0",
		"message": "Success",
		"data": {
		"pcsCPhase": {
		"vol": 229.82661,
		"amp": 3.4730835,
		"actPwr": -776.1484,
		"reactPwr": 186.35483,
		"apparentPwr": 798.20703
		}
		},
		"eagleEyeTraceId": "",
		"tid": ""
		}

PV data		

	{
	"sn": "HJ31ZDH2ZF690025",
	"params": {
	"quotas": [
	"mpptHeartBeat"
	]
	}
	}
		{
		"code": "0",
		"message": "Success",
		"data": {
		"mpptHeartBeat": [
		{
		"mpptPv": [
		{
		"vol": 0,
		"amp": 0.085432455,
		"pwr": 0
		},
		{
		"vol": 26.255978,
		"amp": 0,
		"pwr": 0
		}
		]
		}
		]
		},
		"eagleEyeTraceId": "",
		"tid": ""
		}

Set Command	GetCmdRequest	GetCmdResponse
MPPT power		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "mpptPwr" ] } }`	`{ "code": "0", "message": "Success", "data": { "mpptPwr": 0 }, "eagleEyeTraceId": "", "tid": "" }`
Battery SoC		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "bpSoc" ] } }`	`{ "code": "0", "message": "Success", "data": { "bpSoc": 42 }, "eagleEyeTraceId": "", "tid": "" }`
Battery power		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "bpPwr" ] } }`	`{ "code": "0", "message": "Success", "data": { "bpPwr": -104 }, "eagleEyeTraceId": "", "tid": "" }`

Set Command	GetCmdRequest	GetCmdResponse
Load power		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "sysLoadPwr" ] } }`	`{ "code": "0", "message": "Success", "data": { "sysLoadPwr": 101 }, "eagleEyeTraceId": "", "tid": "" }`
Grid power		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "sysGridPwr" ] } }`	`{ "code": "0", "message": "Success", "data": { "sysGridPwr": -3 }, "eagleEyeTraceId": "", "tid": "" }`

PowerHeat

Set Command	GetCmdRequest	GetCmdResponse
Current temperature of zone B		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "sectorB" ] } }`	`{ "code": "0", "message": "Success", "data": { "sectorB": { "tempCurr": 22.7 } }, "eagleEyeTraceId": "", "tid": "" }`
Current temperature of zone A		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [`	`{ "code": "0", "message": "Success", "data": { "sectorA": {`

Set Command	GetCmdRequest	GetCmdResponse
	"sectorA"] } }	"tempCurr": 22.5 } }, "eagleEyeTraceId": "", "tid": "" }

Ambient temperature and inlet and outlet temperature	{
	"sn": "HJ31ZDH2ZF690025",
	"params": {
	"quotas": [
	"hpMaster"
	]
	}
	}
		{
		"code": "0",
		"message": "Success",
		"data": {
		"hpMaster": {
		"tempInlet": 22.5,
		"tempOutlet": 22.5,
		"tempAmbient": -3270
		}
		},
		"eagleEyeTraceId": "",
		"tid": ""
		}

Current temperature of hot water	{
	"sn": "HJ31ZDH2ZF690025",
	"params": {
	"quotas": [
	"sectorDhw"
	]
	}
	}
		{
		"code": "0",
		"message": "Success",
		"data": {
		"sectorDhw": {
		"tempCurr": 22.5
		}
		},
		"eagleEyeTraceId": "",
		"tid": ""
		}

Set Command	GetCmdRequest	GetCmdResponse
Error code	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "emsErrCode" ] } }`	`{ "code": "0", "message": "Success", "data": { "emsErrCode": { "errCode": [ 601 ] } }, "eagleEyeTraceId": "", "tid": "" }`

PowerGlow

Set Command	GetCmdRequest	GetCmdResponse
Power of the heating rod and current water temperature	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "hrEnergyStream" ] } }`	`{ "code": "0", "message": "Success", "data": { "hrEnergyStream": [ { "temp": 22, "hrPwr": 0 } ] }, "eagleEyeTraceId": "", "tid": "" }`
Error code	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "emsErrCode" ] } }`	`{ "code": "0", "message": "Success", "data": { "emsErrCode": { "errCode": [ 601 ] } }, "eagleEyeTraceId": "", "tid": "" }`

Set Command	GetCmdRequest	GetCmdResponse
		`}`

PowerPulse

Set Command	GetCmdRequest	GetCmdResponse
Power of the EV charger		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "evPwr" ] } }`	`{ "code": "0", "message": "Success", "data": { "evPwr": 0 }, "eagleEyeTraceId": "", "tid": "" }`
EV charger status		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "chargingStatus" ] } }`	`{ "code": "0", "message": "Success", "data": { "chargingStatus": "EV_CHG_STS_AVAILABLE" }, "eagleEyeTraceId": "", "tid": "" }`
Error code(Binary array)		
	`{ "sn": "HJ31ZDH2ZF690025", "params": { "quotas": [ "errorCode" ] } }`	`{ "code": "0", "message": "Success", "data": { "errorCode": "AAAAAAAAAAA=" }, "eagleEyeTraceId": "", "tid": "" }`

Historical data

Obtaining historical data (timespan not exceeding a week): POST: /iot-open/sign/device/quota/data

Set Command	GetCmdRequest	GetCmdResponse
Obtaining historical data (timespan not exceeding a week)	{ "sn": "HJ31ZDH2ZF690025", "params": { "code": "JT303_Dashboard_Overview_Summary_Week", "beginTime": "2024-06-17 00:00:00", "endTime": "2024-06-23 23:59:59" } }	{ "code": "0", "message": "Success", "data": { "code": "0", "message": "Success", "data": [{ "indexName": "pv_to_powerglow", "indexValue": 13.81, "unit": "kWh" }, { "indexName": "From Solar", "indexValue": 32.27, "unit": "kWh" }, { "indexName": "Self-sufficiency", "indexValue": 95.17, "unit": "%" }, { "indexName": "pv_to_powerplus", "indexValue": 16.31, "unit": "kWh" }, { "indexName": "pv_to_heatpump", "indexValue": 0, "unit": "kWh" }, { "indexName": "pv_to_powerplus_pct", "indexValue": 0.7162, "unit": "%" }, { "indexName": "To Battery", "indexValue": 9.1, "unit": "kWh" }, { "indexName": "From

Set Command	GetCmdRequest	GetCmdResponse

		Battery",
		"indexValue": 3.88,
		"unit": "kWh"
		},
		{
		"indexName": "From Grid",
		"indexValue": 5.13,
		"unit": "kWh"
		},
		{
		"indexName": "To Grid",
		"indexValue": 9.42,
		"unit": "kWh"
		},
		{
		"indexName": "To Home",
		"indexValue": 22.77,
		"unit": "kWh"
		}
		],
		"eagleEyeTraceId": "",
		"tid": ""
		},
		"eagleEyeTraceId": "",
		"tid": ""
		}

GetAllQuotaResponse

GET: /iot-open/sign/device/quota/all: GetAllQuotaResponse

Field	Field's Type	Description
mpptPwr	float	MPPT power
bpSoc	float	Battery Soc
bpPwr	float	Battery power
sysLoadPwr	float	Load power
sysGridPwr	float	Grid power
evPwr	float	Power of the EV charger
chargingStatus	String	EV charger status

Field	Field's Type	Description
errorCode	string	Error code

pcsAPhase

Field	Field's Type	Description
vol	float	Voltage
amp	float	Current
actPwr	float	Active power
reactPwr	float	Reactive power
apparentPwr	float	Apparent power

pcsBPhase

Field	Field's Type	Description
vol	float	Voltage
amp	float	Current
actPwr	float	Active power
reactPwr	float	Reactive power
apparentPwr	float	Apparent power

pcsCPhase

Field	Field's Type	Description
vol	float	Voltage
amp	float	Current
actPwr	float	Active power
reactPwr	float	Reactive power
apparentPwr	float	Apparent power

mpptPv

Field	Field's Type	Description
vol	float	PV voltage
amp	float	PV current
pwr	float	PV power

sectorB

Field	Field's Type	Description
tempCurr	float	Current temperature of zone B

sectorA

Field	Field's Type	Description
tempCurr	float	Current temperature of zone A

hpMaster

Field	Field's Type	Description
tempInlet	float	Inlet temperature
tempOutlet	float	Outlet temperature
tempAmbient	float	Ambient temperature

sectorDhw

Field	Field's Type	Description
tempCurr	float	Current temperature

emsErrCode

Field	Field's Type	Description
errCode	int[]	Error code PowerHeat: 601 PowerGlow: 602

mpptHeartBeat

Field	Field's Type	Description
mpptPv	json	mpptPv

mpptPv

Field	Field's Type	Description
vol	float	PV voltage
amp	float	PV current
pwr	float	PV power

MQTT communication mode

Report Device Quota

Usage of Topic	Topic	From	To
Report device quota	/open/${certificateAccount}/${sn}/quota	device	app

Please see HTTP GetAllQuotaResponse and Set & Set Reply for the fields definition.

Example

```
JSON
{
    "id": 1479773,
    "version": "1.0",
    "time": 871405684,
    "moduleType": 1,
    "needAck": 1,
    "typeCode": "pdStatus",
    "params": {
        "fsmState": 5,
        "iceMkMode": 1,
        "flagTwoZone": 1,
        "tmpR": 845,
        "tmpL": -85,
        "tmpAver": 335,
        "iceTm": 0,
        "iceTmTag": 0,
        "err": 0,
        "doorStat": 0,
        "icePercent": 0,
        "batFlag": 0,
        ...
    }
}
```

Report Device status

Usage of Topic	Topic	From	To
Report Device status	/open/${certificateAccount}/${sn}/status	device	app

Message Format

```
Plaintext
{
    "id": "123456789",
    "version": "1.0",
    "timestamp": 1634841971000,
    "params": {
        "status": 0
    }
}
```

Field

Field	Field Type	Description
status	int	Device online or not 0: No, 1: Yes

Was this page helpful?

YES NO

Was this page helpful?

We'd like to hear from you.Click here to give your feedback or suggestions.