Genetec Restricted Security Area (RSA) Surveillance & Perimeter Protection

Engineering & Licensing Reference Guide — Security Center 5.13 / 5.14 (Quanergy LiDAR, SpotterRF Radar, Southwest Microwave PIDS & RPM II)

1. Overview & Licensing Architecture

Restricted Security Area (RSA) Surveillance unifies short-range tracking sensors (3D LiDAR, laser, radar-video fusion), long-range ground/air radars, and perimeter fence intrusion detection systems (PIDS) on dynamic Plan Manager maps with automated PTZ camera tracking and camera-to-camera handoff.

Requires Security Center Professional or Enterprise base package and Plan Manager Standard (included in 5.13 Base Packages). Choose RSA Standard (event/alarm only), RSA Professional (up to 20 Short-Range Sensors, 5 Radars, 1 Fence PIDS up to 10 km), or RSA Enterprise (unlimited sensors, radars, and fence zones).

Genetec Part Number	Category	MSRP (USD)	Connection Rule & Compatibility
GSC-GAP-RSA-STA	RSA Base (Standard)	,000.00	1 per system. Events/alarms for Event-to-Action only (no map target tracking). Fence length not licensed.
GSC-GAP-RSA-PRO	RSA Base (Professional)	,000.00	1 per system. Full target tracking on maps. Capped at max 20 SRS, 5 RAD, and 1 FEN (up to 10 km fence).
GSC-GAP-RSA-ENT	RSA Base (Enterprise)	,000.00	1 per system. Full unlimited RSA target tracking (>20 SRS, >5 RAD, >1 FEN, or >10 km fence).
GSC-GAP-RSA-1SRS	Short-Range Sensor	.00	1 per sensor: Quanergy M8 LiDAR (Qortex DTC v2.2, ports 17161/17168), Axis D2xxx/Q1xxx/Perimeter Defender, Bosch IVA, Optex PIE-1, SightLogix, Ouster, Opsys, Magos SR-150/250/500.
GSC-GAP-RSA-1RAD	Radar Tracking	,000.00	1 per radar: SpotterRF / Spotter Global (C/CK/A/3D Series, NetworkedIO 4.10.1, port 80), Teledyne FLIR Ranger (port 8005), Echodyne EchoGuard, Navtech Witness, Dedrone, Magos SR-1000.
GSC-GAP-RSA-1FEN	Perimeter Fence PIDS	,000.00	1 per PIDS controller: Southwest Microwave INTREPID MicroPoint POE-S / 316-336 POE-S / Model 390-395 (port 50001), Senstar FiberPatrol/OmniTrax/FlexZone (ports 850-859), Fiber SenSys EchoPoint, FFT Aura.
GSC-GAP-RSA-1KM / 10KM / 100KM	RSA Fence Length	,000 - ,000	Required with GSC-GAP-RSA-1FEN in Enterprise mode: up to 1 km (,000), 10 km (,000), 100 km (,000), 1000 km (,000).
GSC-1PSWM-RPMII	Southwest Microwave RPM II	,500.00	Standalone non-RSA plugin: 1 license per 5 Southwest Microwave INTREPID RPM II polling modules (Pro/Enterprise).

2. Multi-Role Server & Inter-System Gateway (IS Gateway) Sizing Rules

RSA 5.3.0+ uses the Genetec Inter-System Gateway (IS Gateway 1.4+) running containerized tracking drivers on Windows Server 2022/2025.

Co-Hosting Rule: The RSA Plugin role adds +4 GB RAM and +2 CPU cores to the Directory/Expansion server. When deploying IS Gateway container drivers or >5 tracking radars/LiDARs, allocate +8 GB RAM and +4 CPU cores (or isolate IS Gateway on a dedicated expansion server). Never co-host IS Gateway containers on a high-throughput Archiver.