

How to load SDD on to a Panasonic FZ55 MK1 and MK3 (G4545755)

Refer to: HOW TO SET-UP THE PANASONIC (OUT OF THE BOX)
(TOPIX Cloud Diagnostics/Download and Installation).

Before you start you will need:

1. A power supply for the FZ55
2. Any outstanding Windows updates must be completed
If Windows has any outstanding updates this will appear as a red dot on the arrows icon in the toolbar in the bottom right of the PC main screen
3. You must have a good internet connection through WiFi

HOW TO LOAD SDD ON TO A WINDOWS 10 LTSC VERSION 1809 PANASONIC FZ55 MK1

1. Uninstall any versions of SDD

Go to: **Windows/Settings/Apps/Apps & Features**

Uninstall SDD

The machine will reboot after the uninstall

2. Disable **Real-Time Threat Protection**

Go to: **Windows/Settings/Update & Security/Windows Security/Virus & Threat Protection**

Under **Virus & Threat Protection Settings** – select **Manage Settings**

Real-Time Protection and **Cloud Delivered Protection** will both be set to **ON**. Move both to **OFF**

As soon as the protection is turned **OFF** the following step must be completed immediately

3. Download and install the SDD file

Go to: TOPIX LINKS PAGE / **SDD Manual Software Download**

Download the file and follow the instructions to install SDD

If you see a **Malicious file** pop-up select more information, then run anyway

When SDD installation has completed, the machine will reboot

Delete SDD install from the downloads folder

4. Re-instate real time protection

Go to: **Windows/Settings/Update & Security/Windows Security/Virus & Threat Protection**

Under **Virus & Threat Protection Settings** – select **Manage Settings**

Turn **ON Real-Time Protection** and **Cloud Delivered Protection**

HOW TO LOAD SDD ON TO A WINDOWS 11 PANASONIC FZ55 MK3

1. Uninstall any versions of SDD

Go to: **Windows/Settings/Apps/Installed apps**

Uninstall SDD

The machine will reboot after the uninstall

2. Disable **Real-Time Threat Protection**

Go to: **Windows/Settings/Update & Security/Windows Security/Virus & Threat Protection**

Under **Virus & Threat Protection Settings** – select **Manage Settings**

Real-Time Protection and **Cloud Delivered Protection** will both be set to **ON**. Move both to **OFF**

As soon as the protection is turned **OFF** the following step must be completed immediately

3. Download and install the SDD file

Go to: TOPIX LINKS PAGE / **SDD Manual Software Download**

Download the file and follow the instructions to install SDD

If you see a **Malicious file** pop-up select more information, then run anyway

When SDD installation has completed, the machine will reboot

Delete SDD install from the downloads folder

4. Re-instate real time protection

Go to: **Windows/Settings/Update & Security/Windows security/Virus & threat protection**

Under **Virus & Threat Protection Settings** – select **Manage Settings**

Turn **ON Real-Time Protection** and **Cloud Delivered Protection**.

For instructions on how to install the JLR software, and troubleshooting support take a look at the links below;

- Refer to: HOW TO SET-UP THE PANASONIC (OUT OF THE BOX)
(TOPIx Cloud Diagnostics/Download and Installation).
- Refer to: DOWNLOAD AND INSTALLING JLR SOFTWARE
(TOPIx Cloud Diagnostics/Download and Installation).
- (Frequently asked questions/3. Subscriptions and installation).
- Refer to: FZ55 MK3 TROUBLESHOOTING
(TOPIx Cloud Diagnostics/Download and Installation).

NOTE:

Microsoft may alter the functionality of downloads at any time, so these instructions could become outdated.