Source Code

```
#include <signal.h>
#include <stdio.h>
#include <unistd.h>
#include <stdlib.h>
static volatile sig_atomic_t stop = 0;
static void handle_sigint(int sig) {
   (void)sig;
   stop = 1;
}
int main(void) {
   struct sigaction sa;
   sa.sa_handler = handle_sigint;
   sigemptyset(&sa.sa_mask);
   sa.sa_flags = 0;
   sigaction(SIGINT, &sa, NULL);
   printf("PID=%ld; press Ctrl+C to stop gracefully.\n", (long)getpid());
   while (!stop) {
      puts("Working...");
      sleep(1);}
   puts("SIGINT received; exiting cleanly.");
   return EXIT_SUCCESS;  }
```

Output :

