GUIDE FOR NETWORK ENGINEERS

Intent guide for network engineers

How to define, read and edit your network intent in Oktavia, in any domain: from the page of each service or with Argos, understanding scopes and without skipping any control.

Built by Oktanet | Mexico · 2026 | Public document

CONTENTS

1. Who this guide is for
2. The idea: declare, don't type
3. Where you work
4. The domains
5. Scopes: where each value goes
6. The service page
7. The JSON you are editing
8. The Configurator, as a fallback
9. With Argos
10. Extending a service
11. State intent
12. Taking the change to the network
13. Recipes by domain
14. Optimizing intent
15. Good practices

1. Who this guide is for

For network and automation engineers, at customers or partners, who design and maintain a network's intent in Oktavia. It applies to any domain: Campus, WAN, Security, Management and, at service providers, Transport and Customer Services.

By the end you will know which scope each value belongs in, how to read, test and edit intent from the page of each service, how to ask Argos for it, and how to take a change to the network without skipping any control.

You don't need to program. Being able to read JSON helps, and this guide covers what you need.

2. The idea: declare, don't type

In Oktavia you don't write commands per device: you declare how the network should be. That declaration is the **intent**, and it is the source of truth. It has two sides:

	CONFIG INTENT	STATE INTENT
Answers	How it should be configured.	How it should be running.
Example	These NTP servers, these VLANs, these BGP neighbors.	Neighbors up, tunnels encrypted, VLANs present.

	CONFIG INTENT	STATE INTENT
Compared with	The device configuration.	What the device reports.
In the console	Services tab: the page of each service.	Rules tab.

Editing intent **does not touch the network**. Saving only changes what the network should be, so after saving, an audit will show as failures whatever hasn't reached the devices yet. The change travels through a cycle with human approval (section 12).

3. Where you work

It is the same intent seen from several places. What you save in one appears in the others.

PLACE	USE IT FOR
Domain services Services → Campus, WAN… → Services	Daily work. The list of the domain's services and, for each one, its page: declared values, what changes on the devices, testing with a real device, and extending. This is the recommended starting point.
Argos Argos → Configure → Services by domain	Asking for a change in your own words or bringing it in from a device backup, seeing what changes per device and closing the cycle. It also explains a service to you.
Configurator Automation → Configuration generator	Fallback tool: field-by-field forms, reviewing a service across all scopes, import and export.
JSON proposal	Large changes prepared outside the platform: upload to the Configurator, review as a delta and apply.

How to read a template, test it with a device and extend it without writing Jinja is covered in the Services and templates guide.

4. The domains

Every catalog service belongs to a domain, and each domain has a console with the same tabs: Summary, Services, Rules, Compliance, Changes, Workflows and Telemetry. A WAN engineer works in WAN without seeing the rest, and the Scope at the top narrows everything to one site.

DOMAIN	WHAT IT COVERS	TYPICAL SERVICES
Campus	The site network.	VLANs, ports, spanning tree, gateways, DHCP, internal routing, wireless.
WAN	What connects sites.	BGP and its policies, FlexVPN and GRE tunnels, SD-WAN, exit routes, NAT.

DOMAIN	WHAT IT COVERS	TYPICAL SERVICES
Security	Who gets in and what passes.	Firewall, ACLs, zones, administrators and access hardening.
Management	The device baseline.	NTP, SNMP, syslog, DNS, SSH, version and model.
Transport Service providers	The core.	IS-IS, Segment Routing, TI-LFA, BFD.
Services Service providers	What each customer buys.	VPNv4, L3VPN, pseudowires, QoS.

Data center and cloud will join as domains with the same way of working: what you learn here applies just the same.

5. Scopes: where each value goes

Intent is declared once, at the most general scope possible, and devices inherit it. This is the most important design decision: a good scope avoids hundreds of exceptions.

#	SCOPE	APPLIES TO	USE IT FOR
1	`defaults`	The whole organization.	The baseline: domain, NTP, syslog, banner.
2	`by_site`	One site.	What is specific to a site.
3	`by_site_type`	A type of site.	The common design of offices or branches.
4	`by_role`	A function.	The standard for `wan_router`, `lan_switch`, `pe`…
5	`by_platform`	A vendor or OS.	What changes by platform.
6	`by_model`	A model.	Approved software versions.
7	`by_tag`	Devices with a tag.	Groups that don't follow site or role.
8	`by_filter`	A combination.	For example, a role within a site.
9	`by_device`	One device.	IPs, interfaces, neighbors and real exceptions.

Layers apply in that order and **the last one wins**. This is how merging works:

- **Objects merge field by field.** What a scope doesn't mention keeps arriving from above.
- **Lists are replaced whole.** They never add up.
- **`"enabled": false`** turns the service off for the devices in that scope.

```
defaults              ntp.servers = ["192.0.2.1", "192.0.2.2"]
by_role / wan_router  ntp.servers = ["198.51.100.9"]

wan_router  →  ["198.51.100.9"]
lan_switch  →  ["192.0.2.1", "192.0.2.2"]
```

The router receives one server, not three: its list replaced the one above.

> **Two classic mistakes.** First, lists: if routers need the two common servers plus their own, their list carries all three. Second, order: `by_site_type` comes after `by_site`, so if both declare a field the type wins. For a one-site exception use `by_filter` or `by_device`.

6. The service page

This is the most direct way to see and change your intent. Open **Services**, pick the domain and go to the **Services** tab, formerly called Intent.

The domain list

It holds every service in the domain, declared or not, with its **Platform** (`ios`, `iosxe`, `xr`…), **Declared in**, devices, failures, % and **Tests**: how many config and state tests validate it, or "no tests". Undeclared services come last, with a link to declare them. Click a service to open its page.

Declared values

The **Declared values** fold shows every scope where the service is declared —`defaults`, `by_role`, `by_site`, `by_device`, `by_model`, `by_platform`…— with its values. The scope label says how many devices it wins on:

- **Wins on N devices**: this is the declaration that applies to them.
- **No effect**: a more specific scope beats it on all its devices. Worth reviewing.
- **Disabled**: it has `enabled: false`.

Edit values, **Template** and **Extend here** sit on the same row.

Changing a value

1. Click **Edit values** on the scope you want to change. Pick the wrong scope and you will change more or fewer devices than you think.
2. Edit the JSON that opens.
3. Click **See what changes**. It shows, per device, the lines of the desired configuration that would change: – what is there today, + what your change leaves. Secrets stay hidden.

```
r1
  router bgp 65001
+  neighbor 198.51.100.1 timers 10 30
```

4. If a device you didn't expect shows up, check the scope before going on.
5. Click **Save**. Oktavia validates the JSON and updates the compliance rules and the expected configuration. Saving does not touch the devices.
6. Move on to the next service, even in another domain. A notice at the top of the console collects the devices with saved changes.
7. When you finish, click **Close the cycle** in that notice: everything travels in a single cycle with Argos.

Test with a device

Before editing, you can test. Pick a device from the menu, grouped by site, and you get three columns: the device's values and which scopes they come from (each scope opens its declaration), the service template, and what it generates today on that device. In the third column, whatever comes from parameters is highlighted; the rest is fixed in the template.

Change the values and click **Test these values**: Oktavia renders with the same engine used by audits and shows the difference, **without saving**. On IOS XR you see the XML built by the NETCONF lane instead of a Jinja template. If the test says "nothing changes", check the device inventory: some values, such as `ospf_config.router_id`, come from there and win over the service's values.

At the bottom of the page are the devices where the service is active, by site and with ⚠ on the failing ones, and the tests that validate it. Each part is covered in detail in the Services and templates guide.

> **What you need to know.** Editing requires being an organization administrator. To declare a service that has no values yet, use its link at the end of the list. If someone saved while you were editing, Oktavia rejects the change and asks you to reload, so you don't overwrite their work.

7. The JSON you are editing

Each declaration is an object with the service's fields. This is an `ntp`:

```
{
  "servers": ["192.0.2.1", "192.0.2.2"],
  "source_interface": "Loopback0",
  "vrf": "Mgmt"
}
```

A list of objects, such as `vlan_database`, has one element per VLAN. The table shows each in its own row:

```
{
  "entries": [
    { "id": 100, "name": "data" },
    { "id": 200, "name": "voice" }
  ]
}
```

Rules when editing:

- **Write only what this scope defines.** The rest is inherited. Copying inherited values freezes them here, and the standard stops arriving.
- **Adding to a list means rewriting it:** include the existing elements and the new one.
- **To go back to inheriting**, remove the declaration from the Configurator. If a device must not have something inherited, turn the service off with `"enabled": false` or declare the value it should have.

Secrets

Keys are never shown or written in clear text. On screen they appear as ••••; leave them that way and Oktavia keeps the saved value. For a new key, store it in the credential vault and use its reference:

```
{ "address": "203.0.113.2", "remote_as": 64501, "password": "<<vault:bgp>>" }
```

If you type a secret in clear text, Oktavia rejects the save and asks for the reference.

8. The Configurator, as a fallback

Daily work now fits in the service page and in Argos. The Configurator still exists as a fallback tool, useful for:

- **Declaring with forms** guided field by field, if you prefer them to JSON.
- **Reviewing where something is declared** across all scopes, with its effective or shadowed status.
- **Previewing** the lines a device would receive.
- **Importing or exporting**: JSON proposals, CSV and the full intent.
- **Tidying up**: Standardization lifts what is repeated across many devices to a common scope, and separates what only reorganizes from what changes devices.

When saving, it writes only the fields you touched. And if you are about to override inherited lists, it warns you which ones first: read it.

Its assistant no longer lives here: it is now **Argos → Configure → Services by domain** (section 9).

Bringing in an existing network

You don't have to start from scratch. Argos compares what is declared with what devices have and, reading their backups, brings into intent what is configured but undeclared. It arrives as a proposal to review. Careful: importing is not approving. If a device has a mistake and you import it, it becomes intent.

9. With Argos

Services by domain

In **Argos → Configure → Services by domain** you ask for the change in your own words. What used to be the Configurator assistant now lives here.

1. Pick the domain and the service. Only those for the platforms in your network appear.
2. Say which values you want and where, for example `timers 10 30 en los wan_router`. You can also bring them in from a device backup.
3. Argos proposes the change on a card. Click 🔍 **What changes on the devices** to see each device's desired configuration before saving.
4. If it is what you wanted, click **Apply and close the cycle**. The change follows the cycle in section 12 and you approve it in the Digital Twin.

Explain this service

On every service page, ✦ **Explain this service** asks Argos, with local AI or with Claude, to explain what it does, each parameter, what it generates on the chosen device, and tips for using it. Argos receives the template, the masked values and the generated output; never secrets or the full running configuration.

To tidy up intent with Argos, see Optimizing intent.

10. Extending a service

If a service template doesn't include what you need —per-neighbor BGP timers, BFD on OSPF, `bandwidth` on an interface—, it isn't edited: it is extended. You work with parameters, not with Jinja.

- **Advanced options**, on the service page, enables tested extensions from the Oktavia catalog with one click.
- **Extend here** guides you in three steps: what to add (from the catalog or generated with Argos), its parameters with their network test, and the advanced template, already resolved.

Before publishing, a deterministic gate checks the extension: blocked commands, no literal secrets, removal only with `no` or `default`, and no changes to lines of another service. It is published only after it is validated on real devices, without touching the network. Its values stay in the intent, in the same scope, and reach the devices through the cycle.

The full detail, with recipes, is in the Services and templates guide.

11. State intent

The **Rules** tab of each console shows how the network should be running, also in one table: rule, result, device, parameter and expected value, with failures first. Pick a site to see its devices and results.

- **Automatic from config**: Oktavia derives it from your intent. If you declare a tunnel, the rule requires it to be up. It isn't edited: it changes when you edit the config.
- **Manual**: you define it in Compliance rules, for example a threshold.
- **Set by hand**: an automatic rule someone set manually; it no longer follows the config.

Configuration rules, one per declared service, are in the fold below. They compare the device configuration with your intent.

12. Taking the change to the network

After saving, the console notice gathers the pending devices and proposes a single cycle with Argos; an IOS XR core goes in its own lane. Every change follows the same path:

1. **Audit.** Oktavia compares intent with the devices and finds what is missing.
2. **Propose.** Each difference becomes a ticketed change in the Digital Twin, with its diff and rollback.
3. **Review and approve.** A person approves it; it can be tested first without applying.
4. **Apply and verify.** A new audit confirms the device matches the intent.

On an IOS XR core the change is a single network transaction with *commit confirmed*: if you don't confirm, the devices roll back on their own.

Software version and model are not applied to devices: they are compared with what each device reports. After changing them an audit is enough, with no cycle.

13. Recipes by domain

Management · Change the NTP servers for the whole network

1. In Management → Services, open NTP. With no site selected, Declared values shows all its declarations.
2. Edit the `defaults` one with the complete server list.
3. If declarations appear in other scopes, decide with the right people whether they are real exceptions. Those that aren't, remove in the Configurator so they inherit.

Campus · Add a VLAN to a site

1. In Campus → Services, pick the site and open VLAN.
2. Edit the declaration that wins on its switches and add the element to `entries`, keeping the existing ones.

3. If the VLAN must cross links between switches, also review their trunks.
4. Then check in Campus → Topology, picking the site, which switches it lives on and which gateway it ends at.

WAN · Add a BGP neighbor

1. In WAN → Services, pick the site and open BGP. Neighbors almost always live in `by_device`.
2. Add the neighbor to the list, with its key as a vault reference.
3. Check whether prefix-lists or route-maps are needed. Before saving, use **Test with a device** with that router to see the new lines.
4. After closing the cycle, check the adjacency in WAN → Topology and the path in Routing analysis.

Security · Adjust an ACL

1. In Security → Services, open the ACL. If it is in a common scope, changing it affects all the devices the label shows.
2. For a single device, leave the common one alone: declare it in its `by_device` with the complete list.

Services (provider) · Give a customer bandwidth

1. In the Services domain, open `l3vpn` or `l2vpn` and, with **Edit values**, add `bandwidth_mbps` to the customer's site or circuit. **See what changes** compares today's NETCONF plan with the plan for your change.
2. With the `xr_qos` service declared on the `pe` role, Oktavia derives the policy.
3. Take the change to the core as a network transaction and review the service in Customer services.

14. Optimizing intent

Over time intent piles up copies: the same value declared device by device. It works, but every change gets more expensive. The **Optimize** tab in each console finds them for you.

- **Safe**: simulated against every device and none changes. It only tidies intent.
- **Changes N devices**: it declares a shared value and those devices receive something different. It reaches the network through the cycle.
- **Review**: a person decides; for example, choosing a value across vendors in Standardization.

The check before saving

When you click **Review selection**, Oktavia resolves the intent of every device with and without the change and compares them. If they do not differ, the expected configuration does not change either, and it says so. If any device differs, it shows which one and in which service, and **Apply** stays blocked until you confirm you understand, even if the recommendation was marked safe. After saving, it compares what was stored with the forecast and warns you if they do not match.

Backups

The same tab keeps full backups of the organization's intent: an automatic one before each optimization and the ones you make with **Back up now**. **Restore** leaves intent identical to the backup and saves the current one first. The download has no secrets, so it is for reading, not for restoring. Restoring changes the intent, not the devices: what already reached the network is corrected with a cycle.

How to do it

1. Run an audit, with no open cycles, and click **Back up now**.
2. Start with the lowest-risk domain. Select two or three safe rows and click **Review selection**.
3. Read the check. If it warns that devices change, unselect that row and leave it for later.
4. Apply and audit again: compliance must stay the same and the cycle must propose no changes.
5. If nothing moved, apply the rest of that domain's safe rows and go on to the next. Leave the ones that change devices for last, one by one and with their cycle.

Example: the first batch in Management

Review selection saves nothing, so you can try it with every row selected before deciding.

1. Open **Services** → **Management** → **Optimize** and confirm you are in the right organization: recommendations and backups belong to the active organization.
2. Scroll to **Intent backups** and click **Back up now**. A row with source "Manual" appears.
3. Click **Select the safe ones** and then **Review selection**. The per-device check appears below the buttons.
4. If it warns that a device changes, **Apply** stays blocked. Don't tick the confirmation: click **Cancel**, unselect that row and leave it for later.
5. Keep two or three rows of one service, for example the NTP copies, and review again. It must say the resolved intent does not change.
6. Click **Apply to intent**. You will see how many were saved and the backup name. Reload with ↻.

7. Run an audit. No cycle is needed: nothing changed on the devices. Compliance must stay the same and the applied rows must no longer appear.

8. If you see "What was saved does not match the forecast", stop and review it before closing any cycle. **Restore** returns intent to how it was.

Rows that say **Changes N devices** are applied separately, one at a time, and reach the network with their cycle. Rows that say **Review** have no checkbox: they are decided in Standardization.

With Argos

Type `optimiza la intención` for the summary per domain, or `optimiza la intención de gestión` for one domain's recommendations. Argos informs and takes you to the tab; applying happens there, so everything goes through the check and the backup.

Compliance rules are tidied separately, on the same tab: automatic ones follow intent on their own, and redundant ones change what Oktavia verifies, not what the network does. That is why they are confirmed in Argos, with backup and audit. Secrets are never recommended: they are moved by hand.

Hardening goes per role or platform; keep the site scope for real exceptions, such as a local NTP or syslog.

15. Good practices

- **Start with the most general.** Go down a scope only when there is a reason.
- **`by_device` is for what belongs to the device:** IPs, interfaces, neighbors and agreed exceptions.
- **Design by site type** so new sites are born the same.
- **Read "how many devices"** before saving. If the number surprises you, don't save.
- **Back up before tidying.** And don't mix safe rows with ones that change devices in one batch: if something goes wrong, you will know which it was.
- **Review anything marked "No effect".** A declaration that wins on no device confuses the next engineer.
- **No secrets in clear text.** Everything through the vault.
- **Standardize before hardening.** If you harden with everything in `by_device`, the role standard never exists.
- **Verify with compliance, not memory.** A change ends when the audit confirms it.

To go deeper: the Services and templates guide; in Spanish, when to use each scope, the Service Vars reference and domain consoles.

About Oktanet

Oktanet is a Mexican network automation company focused on controlled, traceable, and scalable operations for enterprise environments in Latin America.

For a demonstration on your own environment, reach us at oktanet.io.

LinkedIn · **YouTube**

© 2026 Oktanet · Oktavia · Public document, with no confidential customer information.