GUIDE FOR NETWORK ENGINEERS

Services and templates: view, test and extend without development

How to see what each service generates on your devices, test a change before saving it, and add what the template doesn't include. You work with parameters; Oktavia takes care of the template, the gate and the tests.

Built by Oktanet | Mexico · 2026 | Public document

CONTENTS

1. Who this guide is for
2. The idea: parameters, not Jinja
3. Your domain's services
4. The service page
5. Declared values and "See what changes"
6. Test with a device
7. Explain this service
8. IOS XR: no Jinja, XML instead
9. Extending a service
10. The gate before publishing
11. An extension's network tests
12. Custom services
13. With Argos: Services by domain
14. Recipes
15. Good practices

1. Who this guide is for

For network and automation engineers, at customers or partners, who maintain a network's services in Oktavia: Campus, WAN, Security and Management in an enterprise; Transport, Services, Security and Management at a provider.

By the end you will be able to read a service end to end, test a value against a real device without saving anything, and add to a service what its template doesn't include, without writing Jinja and without asking for development.

This guide complements the Intent guide, which explains scopes and the change cycle. If this is your first time with Oktavia, start there.

2. The idea: parameters, not Jinja

Every Oktavia service has a tested base template that turns values into configuration. That template **is not edited**: it is **extended**. That way an Oktavia update doesn't overwrite your work, and your work doesn't break the template.

Your work as an engineer is in the **parameters**: which values, in which scope and with which network test. An extension's template comes from the Oktavia catalog or is proposed by Argos, and a deterministic gate

decides whether it can be published.

PIECE	WHO MAKES IT	WHERE IT LIVES
Base template	Oktavia.	The service catalog. Not touched.
Extension	The Oktavia catalog, with one click, or Argos from your description.	Next to the service it extends.
Values	You.	The intent (`service_vars`), in the scope you choose.
Tests	Oktavia derives them from the template and the parameters.	The compliance of every audit.

Saving values does not touch the network. They reach the devices through the usual cycle: audit, compliance, Digital Twin, you approve, and verification confirms it.

3. Your domain's services

Open **Services** and pick the domain. The tab formerly called Intent is now called **Services**: it lists every service in the domain, declared or not.

COLUMN	WHAT IT SAYS
Platform	Which systems the service exists for: `ios`, `iosxe`, `xr`…
Declared in	The scopes where it has values.
Devices	How many devices it applies to.
Failures and %	Its compliance in the last audit.
Tests	How many config and state tests validate it; "no tests" if none.

Undeclared services come last, with a link to declare them. The domain **Summary** also shows each service's platform.

4. The service page

Each service in the list opens its own page. It gathers in one place everything you need to understand and change it:

1. **Declared values**: every scope where it is declared, with its values, and the buttons to edit them, view the template and extend (section 5).

2. **Test with a device**: values, template and result, side by side, for a real device (section 6).
3. ✦ **Explain this service**: Argos explains what it does and what it generates (section 7).
4. ＋ **Extend this service** and **Advanced options**: what you can add to it (section 9).
5. **Devices where it is active**, by site, with ⚠ on the failing ones, and **Tests that validate it**.

Tests come in two kinds. **Config** tests compare the running configuration with what the template generates, one rule per device. **State** tests check that the service works on the network.

5. Declared values and "See what changes"

The **Declared values** fold shows every scope where the service lives —`defaults`, `by_role`, `by_site`, `by_device`, `by_model`, `by_platform`…— with its values. **Edit values**, **Template** and **Extend here** sit on the same row.

Edit and see what changes

1. Click **Edit values** on the scope you want to change. A JSON editor opens.
2. Change the values.
3. Click **See what changes**. Oktavia shows, per device, the lines of the desired configuration that would change: – what is there today, + what your change leaves. Secrets stay hidden.
4. If it is what you expected, click **Save**. If not, adjust and look again.

```
r1
  router bgp 65001
+  neighbor 198.51.100.1 timers 10 30
```

These are real configuration lines, not just values. If a device you didn't expect shows up in the list, your scope is wider than you thought: don't save yet.

> **What you need to know.** Editing requires being an organization administrator. Secrets always go as a vault reference, `<<vault:…>>`; never in clear text.

6. Test with a device

This is the best way to understand a service. Pick a device from the menu, grouped by site, and you get three columns side by side:

COLUMN	WHAT IT SHOWS
1. Values	The device's values for this service and which scopes they come from. Each scope is a button that opens its declaration for editing.
2. Template	The service's Jinja template.
3. What it generates	The configuration it generates today on that device.

The template, the JSON and the XML are colored as in VS Code. In column 3, whatever comes from the device's parameters is **highlighted**; hover over it to see which parameter it comes from. Anything not highlighted is fixed in the template.

Test these values

In column 1 you can change the values and click **Test these values**. Oktavia renders with the same engine used by audits and shows you the difference. **Nothing is saved.** Use it to answer "what would happen if…?" before touching intent.

> **If the test says "nothing changes".** Some values come from the device inventory, for example `ospf_config.router_id`, and win over the service's values. If you change one of those in the service, the configuration doesn't move. Check the device inventory.

7. Explain this service

Click ✦ **Explain this service** and Argos, with local AI or with Claude, explains:

- what the service does;
- each parameter;
- what it generates on the device you picked;
- tips for using it well.

Argos receives the template, the masked values and the generated output. It never receives secrets or the device's full running configuration.

8. IOS XR: no Jinja, XML instead

On IOS XR there is no Jinja template. The NETCONF lane builds the YANG XML from the same values. The service page works the same way, with these differences:

- **Column 2**: explains how the NETCONF lane builds the configuration.
- **Column 3**: shows the XML for the chosen device. The device's values are highlighted here too, so you can tell what comes from variables from what is fixed in the lane.
- **See what changes** and **Test these values** compare today's NETCONF plan with the plan for your change, exactly as the Digital Twin would push it, with *commit confirmed*.

This applies to core services and to customer services. There is a recipe in section 14.

9. Extending a service

When the base template doesn't include what you need, you extend it. There are two ways in:

- **Advanced options**: tested extensions from the Oktavia catalog, enabled with one click. For example, in OSPF: timers, BFD and area types; in BGP: per-neighbor timers, address-family and aggregates; on interfaces: `bandwidth`.
- **Extend here**, on the row of the scope where you want the values, or **+ Extend this service**.

Extend here, in three steps

1. **What do you want to add?** Pick it from the Oktavia catalog with one click, or describe it and generate it with Argos (local AI or Claude).
2. **Parameters.** What you fill in, and its network test.
3. **Advanced template.** Already resolved and folded, in case you want to adjust it.

The extension's values stay in the intent (`service_vars`), in the same scope where you clicked **Extend here**. They reach the devices through the cycle: audit → compliance → Digital Twin → you approve → verification.

10. The gate before publishing

Before an extension is published, a deterministic gate checks it. It is not an AI opinion: these are fixed rules.

RULE	WHAT IT CHECKS
Blocked commands	The template carries no forbidden commands.
No literal secrets	Not even type 7. Secrets go as `<<vault:…>>`.
Clean removal	Removing the extension only uses `no` or `default`.
Collateral	If the extension changes lines that belong to another service, it is not published.

Then click **Validate on these devices**: Oktavia renders the extension on real devices without touching the network. **It is published only once validated.**

11. An extension's network tests

An extension doesn't end at the configuration: it also says how to check that it works. There are two kinds of test.

State tests

They check that something is up: BGP or OSPF neighbors, interfaces, BFD, IS-IS, routes. They are derived from the parameters. For example, `neighbors[].address` yields the list of neighbors that must be established.

Value tests

They compare what is seen on the network with what you declared. It is not enough for the neighbor to be up: it also has to have the right value.

- BGP timers negotiated with each neighbor.
- OSPF hello and dead per interface.
- SNMPv3 users: group and protocols, without keys.

The catalog extensions `bgp_timers` and `ospf_timers` already ship with their value test. When you audit you will see, for example, "BGP · timers negotiated with the neighbor". Value tests exist today on IOS and IOS XE.

12. Custom services

When what you need doesn't extend an existing service, create a new one in **Services → Custom services**.

1. Describe the service or paste a sample configuration.
2. Argos proposes the template, the fields and a sample of values.
3. The same gate from section 10 decides whether it can be published.

From there you can also open **View template** for any service, to read it without editing it.

13. With Argos: Services by domain

If you'd rather ask in your own words, open **Argos → Configure → Services by domain**. What used to be the Configurator assistant now lives here.

1. Pick the domain and the service. Only those for the platforms in your network appear.
2. Say which values you want and where, for example `timers 10 30 en los wan_router`. You can also bring them in from a device backup.
3. Argos proposes the change. Click 🔍 **What changes on the devices** to see the desired configuration per device before saving.
4. If it is what you wanted, click **Apply and close the cycle**. You still approve the change in the Digital Twin.

14. Recipes

BGP · Timers 10/30 on one neighbor

You want to detect a provider failure sooner. The BGP template has no per-neighbor timers; the catalog extension `bgp_timers` does.

1. In **Services → WAN**, open the BGP service.
2. In **Declared values**, find the router's scope, usually `by_device`, and click **Extend here**.
3. Pick **BGP · per-neighbor timers** from the catalog and fill in the parameters:

```
{
  "neighbors": [
    { "address": "198.51.100.1", "keepalive": 10, "hold": 30 }
  ]
}
```

4. Click **See what changes**. A single new line should appear, on that device:

```
r1
  router bgp 65001
+  neighbor 198.51.100.1 timers 10 30
```

5. Save and close the cycle. Approve the change in the Digital Twin.
6. After verification, review the device's compliance: the value test **BGP · timers negotiated with the neighbor** appears. The neighbor negotiates the lower hold: if the other side has a lower one, that is what you will see.

Interfaces · Add `bandwidth`

The interfaces template has no `bandwidth`, and you need it for OSPF or EIGRP cost and for a percentage-based QoS. `bandwidth` does not change the real link speed.

1. Open the router's interfaces service and, in **Advanced options**, enable **Interfaces · bandwidth** (`interface_bandwidth`).
2. Fill in one entry per interface, in kbps:

```
{
  "interfaces": [
    { "name": "GigabitEthernet4", "bandwidth_kbps": 50000 }
  ]
}
```

3. In **Test with a device**, pick the router and check column 3. What is highlighted comes from your parameters:

```
interface GigabitEthernet4
 bandwidth 50000
!
```

4. Save and close the cycle. The extension's state test checks that the interface stays up.

A new service with Argos from a sample config

You want an IP SLA probe toward the provider gateway on every branch router, and there is no service for it.

1. Open **Services → Custom services** and paste the configuration you already use on a device:

```
ip sla 10
 icmp-echo 198.51.100.1 source-interface GigabitEthernet2
 frequency 30
ip sla schedule 10 life forever start-time now
```

2. Argos proposes the template, the fields (for example, probe number, target, source interface and frequency) and a sample of values. Check that what varies is a field and what is fixed stays fixed.
3. Click **Validate on these devices** with two or three routers. If the gate rejects something, fix it before moving on.
4. Publish, declare the values in the right scope, for example `by_role`, and close the cycle.

IOS XR · A new BGP route reflector client

You are adding a new PE as a route reflector client and want to see the XML that changes before saving.

1. In **Services → Transport**, open the core BGP service (`xr_bgp`).
2. In **Test with a device**, pick the route reflector. Column 3 shows its XML, with the values highlighted.
3. In column 1, add the new PE's loopback to `clients`. Remember: a list is rewritten whole.

```
{
  "asn": 65000,
  "route_reflector": true,
  "clients": ["192.0.2.11", "192.0.2.12", "192.0.2.13"]
}
```

4. Click **Test these values**. Oktavia compares today's NETCONF plan with the plan for your change and shows the new neighbor:

```
+ <neighbor>
+   <neighbor-address>192.0.2.13</neighbor-address>
+   <remote-as>65000</remote-as>
+   <update-source>Loopback0</update-source>
+   <address-families>
+     <address-family>
+       <af-name>vpnv4-unicast</af-name>
+       <route-reflector-client/>
+     </address-family>
+   </address-families>
+ </neighbor>
```

5. If it is as expected, edit the declaration with **Edit values**, check **See what changes** and save.

6. The core changes as a single transaction with *commit confirmed*: if you don't confirm, the devices roll back on their own.

15. Good practices

- **Test before saving.** "Test these values" saves nothing: use it freely.
- **Read "See what changes" device by device.** If a device you didn't expect appears, check the scope.
- **Prefer the catalog.** A catalog extension is already tested and ships with its network test.
- **Extend, don't copy.** The base template is not edited; your work lives in the extension and the values.
- **Declare at the most general scope possible.** Same as with intent: `by_device` only for what belongs to the device.
- **Give every extension its test.** A service with "no tests" won't warn you when it stops working.
- **No secrets in clear text.** Everything through the vault, with `<<vault:…>>`.
- **Verify with compliance.** A change ends when the audit confirms it.

For scopes and the change cycle, continue with the Intent guide.

About Oktanet

Oktanet is a Mexican network automation company focused on controlled, traceable, and scalable operations for enterprise environments in Latin America.

For a demonstration on your own environment, reach us at oktanet.io.

LinkedIn · **YouTube**

© 2026 Oktanet · Oktavia · Public document, with no confidential customer information.