Processor/Bricklet

U101A
XMC1404
U101B
XMC1404
U101C
XMC1404
U101D
XMC1404
U101E
XMC1404
Boot
J101
blue
D103
"status led"
1k
R124
Debug
P111
C12816MHz
10pF
C129
10pF
X101
SPI Slave/CH0
P0.13 : USIC0_CH0-DX2F : SEL
P0.14 : USIC0_CH0-DX1A : CLK
P0.15 : USIC0_CH0-DX0B : MOSI
P2.0 : USIC0_CH0-DOUT0 : MISO
RGB LED
CLP6C-FKB-CK1P1G1BB7R3R3
D101
R101 51
R102 51
R103 100
Ideal Diode 5V Power for ESP
Q105
SSM3J355R,LF
U103
DMMT5401
10k R140
47k R133
FB L103
P101
CON-SENSOR2
RP101
82
220pF
5V->3.3V
U110
TPS70933DBVR
FB
L101
C103 1uF
C106 1uF
C110 2.2uF
C111 100uF
C109 100uF
Ersatz TPS70933QDBVRQ1
VCCPWR
R107 300k
R108 100k
V12
RTC-XTAL1
RTC-XTAL2
X102
32.768kHz
15pF C118
15pF C119
REL101
AGQ200S12Z
P104
OUT
D107
B0520LW-7
Q103
2N7002P
R118 1k
25mA max -> @12V -> 480 Ohm
P105
INPUT
R111 1k
R112 1k
R116 1k
R117 1k
C113 100nF
U109
HCPL2731
RP105
10k
INO
IN1
D105
B0520LW-7
C112 100nF
C114 100nF
C104 100nF
C107 100nF
R104 1k
R105 1k
AC/DC
F101
FUSE
P103
R128
MOV-10D391KTR
U111
IRM02-12
U112
WPMDL110
C105 4.7uF/50V
C124 1uF
C125 1uF
C126 1uF
C108 100uF
RS485
U113
SP3491
RP102
10k
C132 100nF
PTC102 PTC 0.45A
C115 4.7uF/50V
P110
MODBUS
R134 750
R135 DNP
R136 750
R137 120
D102 SMAJ12CA
D111 SMAJ12CA
D103 SMAJ12CA
L104A
L104B
L104C
L104D
WE-SL
PTC101
0ZCJ0016FF2E
VCCPWR
P106
DNP
Relay
F102
FUSE
P102
MOV-10D391KTR
R113
AQH3213AX
U108
R114 120
Q102
SI2305CDS-T1-GE3
R115 1k
RELAY
J102
DM3CS
RP103
82
R109 10k
R106 10k
SD-CS
SD-MOSI
SD-CLK
SD-MISO
SD-CDS
DAT2
DAT3
CMD
VDD
CLK
VSS
DAT0
DAT1
CDS
SHD
DRILL

Copyright Tinkerforge GmbH 2022.
This documentation describes Open Hardware and is licensed under the CERN OHL v. 1.1.
You may redistribute and modify this documentation under the terms of the CERN OHL v.1.1. (http://ohwr.org/cernohl). This documentation is distributed WITHOUT ANY EXPRESS OR IMPLIED WARRANTY, INCLUDING OF MERCHANTABILITY, SATISFACTORY QUALITY AND FITNESS FOR A PARTICULAR PURPOSE. Please see the CERN OHL v.1.1 for applicable conditions

Copyright (©) 2022, B.Nordmeyer <bastian@tinkerforge.com>
Licensed under CERN OHL v.1.1

Tinkerforge GmbH

Sheet: /
File: working.kicad_sch

Title: Energy Manager Bricklet

Size: A3	Date: 2022-03-23	**Rev: 1.4**
KiCad E.D.A. eeschema 7.0.6		Id: 1/1