

Document Title: XR-500 Industrial Cooling Controller Maintenance Manual Product Name:
XR-500 Industrial Cooling Controller Document Type: Maintenance Manual Revision Number:
Rev 2.1 Document ID: MAN-XR500-MNT-001 Date: October 18, 2024

1. **Product Overview** This document provides complete preventive maintenance, routine service protocols, and field diagnostic procedures for the XR-500 Industrial Cooling Controller. The XR-500 manages industrial chilling circuits, secondary fluid distribution, and thermal processing loops through precise modulation of expansion valves, pumps, and cooling fans. Featuring a ruggedized die-cast aluminum housing, the device is engineered to withstand aggressive industrial environments while maintaining accurate thermal control. Regular maintenance as detailed herein guarantees long-term reliability and compliance with operational parameter boundaries.
2. **Technical Specifications**
 - Input Power Requirements: 24V DC nominal (acceptable input range 21.6V to 26.4V DC)
 - Power Draw: 48 Watts maximum
 - Temperature Measurement: 4 Channels, PT1000 RTD standard (3-wire)
 - Control Outputs: 4x 0–10V / 4–20 mA software-selectable
 - Relay Contact Rating: 5A resistive at 250V AC
 - Hydronic Pressure Boundary: 2.8 MPa (28 bar) maximum system fluid pressure
 - Loop Circulation Rate: Nominal 120 L/min (Operating envelope: 40 L/min to 180 L/min)
 - Communications: Modbus RTU (RS-485), BACnet/IP, Modbus TCP
 - Ambient Environment Limits: The unit can operate continuously at ambient temperatures from -10°C to 50°C
 - Ingress Protection: IP65 certified when properly glanded
 - Total Unit Mass: 3.4 kg
3. **Installation Requirements** During maintenance operations requiring temporary removal or reinstallation of the module, ensure the host mounting panel remains free of warp or flex. The chassis must be secured using four M6 stainless steel fasteners tightened to 4.5 N·m. Ensure a clearance zone of 150 mm surrounding all sides of the box to facilitate natural air convection cooling. Cable entries through the bottom gland plate must be preserved using IP65-rated fittings. Signal cables (RTDs, 0–10V lines, communications) and high-voltage power lines (relay circuits) must be dressed in separate channels to minimize electromagnetic interference. RS-485 bus cabling requires shielded, 120-ohm twisted-pair conductors, grounded exclusively at the controller chassis earth terminal.
4. **Operating Conditions** The XR-500 is specified for continuous operation in non-condensing environments with relative humidity ranging between 5% and 95%. When installed at elevations exceeding 2000 meters above sea level, apply a derating factor of 0.5°C per 100 meters to the upper ambient temperature threshold. Direct solar radiation exposure must be shielded to avoid supplemental thermal loading on the enclosure shell. The controlled cooling loop fluid must consist of an approved water/glycol solution (up to 50% concentration) or conditioned industrial process water. Maximum system fluid pressure must remain at or below 2.8 MPa during all operational

phases. If the loop flow rate drops below 40 L/min, the unit will log a low-flow fault and trigger safety shutdown routines.

5. Safety Information Maintenance and servicing must be performed solely by authorized electrical and refrigeration personnel. Hazardous potential (up to 250V AC) may persist on relay terminals even after disconnecting the primary 24V DC controller power supply. Verify that all external high-voltage sources supplying relay load circuits are isolated and locked out prior to removing the front panel or terminal cover. Apply proper grounding procedures and ESD wrist straps when handling exposed circuit cards. Operating the device beyond the specified 24V DC $\pm 10\%$ voltage range may cause irreversible physical damage to internal power supply components.
6. Maintenance / Service Procedures Every 6 Months:
 - Perform visual check of outer housing, cable glands, and sealing gaskets. Replace crushed or damaged IP65 cable glands.
 - Check terminal block connections for proper mechanical tension; re-torque screw terminals to 0.5 N·m.
 - Clean exterior surfaces using a soft cloth dampened with mild soapy water. Do not use solvent-based cleaners. Every 12 Months:
 - Perform 3-point calibration verification on all PT1000 RTD input channels using a precision resistance decade box.
 - Inspect fluid loop pressure transducer signals against calibrated master reference gauges to confirm the fluid line remains within safe parameters below 2.8 MPa.
 - Check internal RTC battery voltage (CR2032). Replace battery if voltage measures below 2.8V DC.
7. Troubleshooting
 - Symptom: No power indication / blank screen. Root Cause: 24V DC power feed absent or reversed wiring polarity. Correction: Verify source supply output. Ensure incoming supply voltage reads between 21.6V DC and 26.4V DC at the main terminal block. Correct reversed wiring.
 - Symptom: E-102 Overpressure Fault active. Root Cause: Fluid loop pressure exceeding 2.8 MPa operational rating. Correction: De-pressurize hydronic loop to safe limits. Check relief valves, expansion tanks, and pressure sensor calibration.
 - Symptom: E-204 Low Flow Condition. Root Cause: Primary coolant circulation falling under 40 L/min threshold. Correction: Clean inline fluid filters, check pump contactors, and confirm bypass valves are properly calibrated for nominal 120 L/min flow.
 - Symptom: Modbus network dropout. Root Cause: Missing or extra 120-ohm bus termination resistors or floating shield. Correction: Confirm termination resistor is enabled only on physical end-of-line devices and verify shield grounding connection.
8. Additional Notes When upgrading system firmware, connect a PC to the primary Ethernet port using an RJ45 patch cable and execute the XR-500 Configuration Utility (v3.0 or higher). Save parameter configurations prior to firmware upload. The embedded RTC battery (CR2032) maintains internal system clock integrity during power loss and exhibits a typical operational lifespan of 5 years under normal ambient conditions.
- 8.

