

LED	Status	Description
red	flashes, 1 Hz	operating voltage OK, faulty bus connection
red	lights	"BUS OFF" caused e.g. by short circuit, wire break, faulty connector
green	flashes, 2.5 Hz	operating voltage OK, bus connection OK
green/red	green flashing, 2.5 Hz and red flashing 1x at each 3rd pulse of the green LED	guarding error, either node guard or heartbeat
green	flashes, 1 Hz	bus stopped
green	lights	master failure, encoder remains in the preoperational operating status > guard and heartbeat error are not indicated
green/red	green lights/ red flashing, 2.5 Hz	non reproducible indication (no clear description of the indication)