

test_scenario_gen.vr

\$VCS_HOME/doc/examples/nativetestbench/openvera/rvm/scenarios/test_scenario_gen.vr

```
//
// Test the scenario generator
//
#include "scenarios.vrh"
class my_atm_cell_scenario_gen_callbacks extends atm_cell_scenario_gen_callbacks{
    virtual task post_scenario_gen_t(atm_cell_scenario_gen gen,
                                     atm_cell_scenario scenario,
                                     var bit drop)
    {
        scenario.display();
        printf("-----\n");
    }
}
program test_gen {
    atm_cell_scenario_gen gen = new("Singleton");
    my_atm_cell_scenario_gen_callbacks cb = new;
    gen.register_callback(cb);
    // Drain the output channel
    fork
    {
        while (1) {
            atm_cell cell = gen.out_chan.get_t();
        }
    }
    join none
    rvm_note(gen.log, "Generating 25 cells or 10 scenarios...");
    gen.stop_after_n_insts = 25;
    gen.stop_after_n_scenarios = 10;
    gen.start_xactor();
    void = gen.notify.wait_for_t(gen.DONE);
    delay(100);
    printf("=====\n");
    // Make sure it can be restarted...
    rvm_note(gen.log, "Generating 10 more cells or 3 scenarios...");
    gen.stop_after_n_insts = 10;
    gen.stop_after_n_scenarios = 3;
```

```
gen.reset_xactor();  
gen.start_xactor();  
void = gen.notify.wait_for_t(gen.DONE);  
delay(100);  
gen.log.report();  
}
```