Electrical Inspection Checklist and OSHA Requirements (29 CFR 1910.303)

For routine walk-throughs of panels, switchboards, disconnects and electrical rooms, with key checks for installations over 600 V.

OSHA 29 CFR 1910.303

DATE	SHIFT
INSPECTOR	AREA / EQUIPMENT ID

Before you start

1. Mark every item OK, Defect or N/A, and note the location and equipment for each defect.
2. When an item fails, keep people clear of any exposed live parts, record the defect and assign the correction before the equipment returns to normal use.
3. The manufacturer's instructions, other Subpart S sections and site rules may add checks.

Legal basis: 29 CFR 1910.303: General (Part 1910, Subpart S: Electrical) Source: eCFR, Title 29, text as of 2026-11-09
Online version and sources: https://safetyindex.blog/us/standards/1910-303

SECTION A | Equipment condition and markings

No.	Check item	What to look for	OK	Defect	N/A	Notes
1	Installed as listed Ref. 1910.303(b)(2)	Installation and use match the instructions supplied with the listed or labeled product	☐	☐	☐	
2	Maker and rating markings Ref. 1910.303(e)(1)	Manufacturer name or trademark and voltage, current or wattage ratings are present and readable	☐	☐	☐	
3	Unused openings closed Ref. 1910.303(b)(7)(i)	Every unused opening in boxes, cabinets, raceways and housings is closed with protection equal to the enclosure wall	☐	☐	☐	
4	No damaged parts Ref. 1910.303(b)(7)(iv)	No broken, bent, cut, corroded or overheated parts affecting safe operation or strength	☐	☐	☐	
5	Internal parts clean Ref. 1910.303(b)(7)(iii)	No paint, plaster, cleaner, abrasive or corrosive residue on busbars, terminals or insulators	☐	☐	☐	
6	Firmly mounted Ref. 1910.303(b)(8)(i)	Equipment is firmly secured to its surface and not held by wooden plugs in masonry, concrete or plaster	☐	☐	☐	
7	Vents unobstructed Ref. 1910.303(b)(8)(iii)	Ventilating openings are not blocked by walls, stored items or adjacent equipment	☐	☐	☐	
8	Suitable for location Ref. 1910.303(b)(6)	Equipment in damp, wet, corrosive or high-temperature locations is identified for that environment	☐	☐	☐	

SECTION B | Connections and splices

No.	Check item	What to look for	OK	Defect	N/A	Notes
9	Connectors match conductor Ref. 1910.303(c)(1)(i)	Pressure connectors, splicing connectors and soldering lugs are identified for the conductor material and correctly installed	☐	☐	☐	

General guidance only, not legal advice. Check the current regulation and your employer's procedures.

SECTION B | Connections and splices

No.	Check item	What to look for	OK	Defect	N/A	Notes
10	No mixed metals Ref. 1910.303(c)(1)(ii)	Copper and aluminum conductors do not touch in one connector unless the device is identified for that use	☐	☐	☐	
11	Terminations sound Ref. 1910.303(c)(2)(i)	Conductors are terminated without damage using pressure connectors, solder lugs or splices to flexible leads; binding screws only on No. 10 or smaller	☐	☐	☐	
12	Terminal identification Ref. 1910.303(c)(2)(ii)	Terminals holding more than one conductor, and terminals on aluminum, are identified for that use	☐	☐	☐	
13	Splices insulated Ref. 1910.303(c)(3)(i)	Splices, joints and free conductor ends are covered with equivalent insulation or an identified insulating device; no bare joints	☐	☐	☐	

SECTION C | Disconnects and circuit marking

No.	Check item	What to look for	OK	Defect	N/A	Notes
14	Circuit labels Ref. 1910.303(f)(2)	Each service, feeder and branch circuit is legibly labeled with its purpose at its breaker, fuse or disconnect, unless the purpose is evident	☐	☐	☐	
15	Motor and appliance disconnects Ref. 1910.303(f)(1)	Each required disconnect for motors and appliances shows what it controls, unless its purpose is evident	☐	☐	☐	
16	Label durability Ref. 1910.303(f)(3)	Disconnect and circuit labels are intact and readable in the room's conditions	☐	☐	☐	
17	Lockable in open position Ref. 1910.303(f)(4)	Each required disconnect can accept a lock in the open (off) position	☐	☐	☐	
18	Series combination marking Ref. 1910.303(f)(5)(i)	Enclosures with series combination rated breakers or fuses carry the readily visible field caution marking	☐	☐	☐	

SECTION D | Working space and clearance (600 V or less)

No.	Check item	What to look for	OK	Defect	N/A	Notes
19	No storage Ref. 1910.303(g)(1)(ii)	No boxes, carts, pallets or materials kept in the working space in front of panels, switchboards and other equipment	☐	☐	☐	
20	Clear depth Ref. 1910.303(g)(1)(i)(A)	Depth in front of live parts or the enclosure front meets Table S-1: at least 3.0 ft up to 150 V to ground; 3.0, 3.5 or 4.0 ft at 151-600 V by condition	☐	☐	☐	
21	Clear width Ref. 1910.303(g)(1)(i)(B)	Space is as wide as the equipment or 30 in., whichever is greater, and doors swing to 90 degrees or more	☐	☐	☐	
22	Clear to full height Ref. 1910.303(g)(1)(i)(C)	Nothing intrudes from floor to headroom height except associated electrical equipment projecting 6 in. or less	☐	☐	☐	
23	Headroom Ref. 1910.303(g)(1)(vi)	At least 6.5 ft (6.25 ft for installations before August 13, 2007), or the equipment height if taller	☐	☐	☐	

General guidance only, not legal advice. Check the current regulation and your employer's procedures.

SECTION D | Working space and clearance (600 V or less)

No.	Check item	What to look for	OK	Defect	N/A	Notes
24	Lighting Ref. 1910.303(g)(1)(v)	Working space at indoor panels, switchboards and motor control centers is lit; equipment-room lights are not on automatic control only	☐	☐	☐	
25	Entrance Ref. 1910.303(g)(1)(iii)	The working space has at least one entrance of sufficient area	☐	☐	☐	
26	Dedicated space Ref. 1910.303(g)(1)(vii)(A)(1)	No foreign pipes, ducts or equipment in the panel footprint up to 6.0 ft above it or the structural ceiling, unless isolated or protected	☐	☐	☐	

SECTION E | Guarding of live parts

No.	Check item	What to look for	OK	Defect	N/A	Notes
27	Live parts guarded Ref. 1910.303(g)(2)(i)	Live parts at 50 volts or above are in approved enclosures with covers in place, or guarded by a qualified-only room, partitions, an elevated platform, or 8.0 ft or more of elevation	☐	☐	☐	
28	Protection from damage Ref. 1910.303(g)(2)(ii)	Equipment exposed to physical damage has guards or enclosures strong enough to prevent it	☐	☐	☐	
29	Entry warning signs Ref. 1910.303(g)(2)(iii)	Doors to rooms with exposed live parts carry conspicuous signs forbidding entry by unqualified persons	☐	☐	☐	
30	Arcing parts isolated Ref. 1910.303(d)	Parts that arc or spark in normal operation are enclosed or separated from combustible material	☐	☐	☐	
31	High-voltage entrances locked Ref. 1910.303(h)(5)(iii)(A)	Over-600 V rooms and enclosures with exposed live parts are locked or under constant observation by a qualified person	☐	☐	☐	
32	High-voltage signs Ref. 1910.303(h)(5)(iii)(B)	Permanent, conspicuous high-voltage danger signs at those entrances	☐	☐	☐	

DEFECTS FOUND AND ACTION TAKEN

Item no.	Defect description	Reported to	Action taken / date closed

SIGN-OFF

SAFE TO OPERATE? ☐ Yes ☐ No: tagged out of service

INSPECTOR SIGNATURE	DATE / TIME
SUPERVISOR REVIEW	DATE / TIME