



Proiect SCR

Centrala Astersik

Conferencing & Wait

Profesor Coordonator:

Prof.dr.ing.Virgil-Mircea Dobrota

Studenti:

Mal Bianca-Florentina

Opre Antonia-Casiana

Zegreanu Paul-Cristian

-Cerinta proiect

Semnificatia celor 3 parametrii este urmatoarea:

- X = 1 , nr grupei
- Y = 2 , conferencing
- Z = 5 , wait

Se implementeaza din managementul apelurilor telefonice ,functiile DIAL, RINGING, ANSWER, HANGUP.

-MeetMe.conf

```
[general]
#include meetme_general_additional.conf
#include meetme_general_custom.conf
[rooms]
#include meetme_additional.conf
conf => 777,1234,4321;conf => numarconferinta,pinuser,pinadmin
```

-SIP.conf

```
;
; SIP Configuration example for Asterisk
;
; Note: Please read the security documentation for Asterisk in order to
; understand the risks of installing Asterisk with the sample
; configuration. If your Asterisk is installed on a public
; IP address connected to the Internet, you will want to learn
; about the various security settings BEFORE you start
; Asterisk.
;
[general]
context=default ; Default context for incoming calls
disallow=all ; First disallow all codecs
allow=ulaw
allow=alaw ; Allow codecs in order of preference
allow=gsm
allow=ilbc
allow=h264
```

allow=h263

[1000]

type=friend

host=dynamic

secret=1234

context=internal

dtmfmode=rfc2833

nat=yes

canreinvite=no

videosupport=yes

allow=h264

allow=h263

[1125]

type=friend; abonatul poate apela si prima apeluri

host=dynamic; user-ul foloseste ip-ul da de PBX

secret=1234; parola pt autentificare

context=sipfunction; contextul de care apartine

dtmfmode=rfc2833; mod DTMF

nat=yes; utilizatorul foloseste NAT(Network Address Translation)

canreinvite=no; dupa ce apelul incepe, tot traficul audio si video trece prin Astresik, nu direct intre telefoane

videosupport=yes; permite suportul pt video

allow=h264; permite video de calitate inalta

allow=h263; permite video de calitate mai scazuta

[2125]

type=friend

host=dynamic

secret=1234

context=sipfunction

dtmfmode=rfc2833

nat=yes

canreinvite=no

videosupport=yes

allow=h264

allow=h263

-IAX.conf

; Inter-Asterisk eXchange driver definition

[general]

disallow=all

allow=ulaw

allow=alaw

allow=gsm

allow=ilbc

[2000]

type=friend

host=dynamic

secret=1234

context=internal

qualify=yes

dtmfmode=rfc2833

[3125]

type=friend;abonatul poate si primi apelul

host=dynamic;user-ul foloseste ip-ul dat de PBX

secret=1234;parola pt autentificare

context=iaxfunction;contextul din care face parte

qualify=yes;centrala verifica la un interval de ms daca abonatul este online

dtmfmode=rfc2833;protocolul folosit pt formarea tonurilor DTMF

[4125]

type=friend

host=dynamic

secret=1234

context=iaxfunction

qualify=yes

dtmfmode=rfc2833

Extensions.conf

```
; extensions.conf - the Asterisk dial plan

;

; Static extension configuration file, used by
; the pbx_config module. This is where you configure all your
; inbound and outbound calls in Asterisk.

;

; This configuration file is reloaded
; - With the "dialplan reload" command in the CLI
; - With the "reload" command (that reloads everything) in the CLI


[general]
static=yes
writeprotect=n


[incoming]
include => internal
include => public_category3


;-Configurarea apelurilor de intrare
exten => s,1,Answer();Raspunde

exten => s,2,Background(vm-enter-num-to-call);Reda un mesaj de fundal cerand
introducerea nr de apelat

exten => s,n,WaitExten(20);Asteapta introducerea unei extensii timp de 20 de secunde


[internal]


exten => 611,1, Answer();Raspunde
    same => 2, Playback(demo-echotest);Reda un mesaj demo
    same => 3, Echo();Realizeaza testul ecou
    same => 4, Playback(demo-echodone);Reda un mesaj finalizat
    same => 5, Hangup();Inchide


exten => 1000,1,Dial(SIP/1000,20);Se stabileste o conexiune(tip/identificator,timeout)
exten => 1125,1,Dial(SIP/1125,20)
exten => 2125,1,Dial(SIP/2125,20)
exten => 2000,1,Dial(IAX2/2000,20);Se stabileste o conexiune(tip/identificator,timeout)
```

exten => 3125,1,Dial(IAX2/3125,20)

exten => 4125,1,Dial(IAX2,4125,20)

[public_category3]

;-Configurare pt logare agent-

exten => 4001,1,AgentCallbackLogin(,,\$ {CALLERIDNUM}@internal);Autentificarea agentului folosind nr de apelant

exten => 4002,1,AgentCallbackLogin(,,1);Autentificarea agentului folosind identif. 1

exten => 4000,1,Queue(markq);Adauga apelul in lista

[sipfunction]

include => internal;Include contextul "internal"

;Conferinta

exten =>777,1,Ringing(2);Sunet de apel timp de 2 secunde

same => 2,Wait(2);Asteapta 2 secunde

same => 3,Answer();Raspunde

same => 4,MeetMe(777,cM);Ne conectam la camera 500 daca se cunoaste pinul

same => 5,HangUp();Inchide

exten =>888,1,Ringing(2);Sunet de apel timp de 2 secunde

same => 2,Wait(2);Asteapta 2 secunde

same => 3,Answer();Raspunde

same => 4,Wait(2);Asteapta 2 secunde

same => 5,Playback(conf-thereare);Sunet de "There are"

same => 6,MeetMeCount(777);Ne returneaza numarul de participanti in conferinta

same => 7,Playback(conf-peopleinconf);Sunet "People in conf"

same => 8,HangUp();Inchide

;admin

exten =>999,1,Ringing(2);Sunet de apel timp de 2 secunde

same => 2,Wait(2);Asteapta 2 secunde

same => 3,Answer();Raspunde

same => 4,Wait(2);Asteapta 2 secunde

```

same => 5,Authenticate(4321);Autentificare cu parola adminului specificata
same => 6,Flite(Welcome);Spune "Welcome"
same => 7,Wait(2);Asteapta 2 secunde
same => 8,Flite(Press-3-mute);Spune "Press-3-mute"
same => 9,WaitExten(2);In timpul alocat putem apasa tasta
same => 10,Flite(Press-4-unmute);Spune "Press-4-unmute"
same => 11,WaitExten(2);In timpul alocat putem apasa tasta
same => 12,Goto(7);Ne trimite la linia 7

exten => 3,1,MeetMeAdmin(777,M);Cu ajutorul comenzii "M" punem pe mute un user
same => 2,Playback(conf-muted);Pune pe mute conferinta
same => 3,Goto(999,7);Ne trimite la linia 7 din camera admin
exten => 4,1,MeetMeAdmin(777,m);Cu ajutorul comenzii "m" dezactiveaza mute-ul
same => 2,Playback(conf-unmuted);Scoate de pe mute conferinta
same => 3,Goto(999,7);Ne trimite la linia 7 din camera admin

[iaxfunction]
include => internal

exten => 333,1,Answer();Raspunde
exten => 333,2,Wait(10);Asteapta 10 secunde
exten => 333,3,Hangup();Incheiere apel

exten => 444,1,Answer();Raspunde
exten => 444,2,WaitExten(10);In timpul alocat abonatul poate apela o alta extensie

exten => 555,1,Answer();Raspunde
exten => 555,2,WaitMusicOnHold(10);Muzica se aude timp de 10 secunde
exten => 555,3,Hangup();Inchide

```