

17.6 Common Commands for All Languages

Cancel Request			DC2+PH
Command	DC2	PH	Parameter
HEX code	<12> ₁₆	<50> ₁₆ <48> ₁₆	None
Default value	None		

Valid range and term of command	When turning off the power switch	
	Valid range	
	Printer operation in progress	The command can be received even during the printer operation.
	Error	Commands can be received even if an error is occurring.

[Function]

This command cancels print jobs and clears the entire contents of receive buffer.

[Format]

[DC2] PH

[Return data format (normal)]

[ACK]<06>₁₆

[Return data format (when a command error occurs)]

[NAK]<15>₁₆

[Supplemental explanation]

1. The response data is returned after the cancel processing ends.
2. After sending the cancel request command, wait for response reception before sending the next data.

