Dell PowerFlex Appliance and PowerFlex Rack

PowerFlex Manager 5.x Compatibility Matrix

June 2026
Rev. 2.0

DELL Technologies

Notes, cautions, and warnings

NOTE: A NOTE indicates important information that helps you make better use of your product.

CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

WARNING: A WARNING indicates a potential for property damage, personal injury, or death.

Copyright © Dell Inc. All Rights Reserved. Dell Technologies, Dell, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.

Contents

Chapter 1: Introduction **4**
Common PowerFlex terms 4

Chapter 2: Revision history **5**

Chapter 3: Compatibility matrix for PowerFlex appliance **6**
PowerFlex Manager 5.1.x compatibility details 6
PowerFlex Manager 5.0 compatibility details 7

Chapter 4: Compatibility matrix for PowerFlex rack **9**
PowerFlex Manager 5.1.x compatibility details 9
PowerFlex Manager 5.0 compatibility details 10

1

Introduction

The compatibility matrix provides PowerFlex Manager compatibility information for PowerFlex appliance and PowerFlex rack.

Erasure coding is supported with PowerFlex core software 5.0.x and above. Mirroring is supported with PowerFlex core software 4.5.x.

The target audience for this document includes system administrators responsible for managing PowerFlex appliance and PowerFlex rack, sales engineers, and advanced service specialists.

SupportAssist is now known as Dell Technologies connectivity services. References in the documentation will be updated over time.

The Dell Code and Compatibility Knowledge Hub was previously known as the Release Certification Matrix (RCM) Portal. References in the documentation will be updated over time.

For additional PowerFlex appliance documentation, go to Dell PowerFlex Appliance: Technical Documentation.

For additional PowerFlex rack documentation, go to Dell PowerFlex Rack: Technical Documentation.

Common PowerFlex terms

The following table identifies common PowerFlex terms and associated acronyms.

Table 1. Common PowerFlex terms

Term	Acronym
device gateway target	DGWT
management virtual machine	MVM
metadata manager	MDM
PowerFlex data server	PDS
PowerFlex management cluster	PFMC
PowerFlex management platform	PFMP
storage data client	SDC
storage data target	SDT

See the PowerFlex glossary for more information about PowerFlex terms and acronyms.

2

Revision history

Table 2. Revisions

Date	Document revision	Description of changes
June 2026	2.0	Added support for PowerFlex Manager 5.1.x
November 2025	1.1	Technical update
October 2025	1.0	Initial release

3

Compatibility matrix for PowerFlex appliance

This section provides the PowerFlex Manager compatibility details for PowerFlex appliance.

PowerFlex Manager 5.1.x compatibility details

This section provides the PowerFlex Manager 5.1.x compatibility details for PowerFlex appliance components.

Table 3. PowerFlex Manager 5.1.x compatibility details

Component	Compatibility
Nodes	• PowerFlex R670/R770/R6725/R7725 (compute-only) • PowerFlex R660/R760 (storage-only) • PowerFlex R660/R760/R860/R6625/R7625 (compute-only) • PowerFlex R650/R750 (storage-only) • PowerFlex R650/R750/R6525/R7525 (compute-only) • PowerFlex R660 (management cluster) • PowerFlex R660/R650 (VMware NSX Edge node)
Operating system/hypervisor (for IC 51.391.00)	• PowerFlex management node (KVM) • VMware ESXi-8.0 (management cluster) • VMware-vCSA-all-8.0.x (management cluster) • VMware-ESXi-8.0 (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex appliance with operating systems that are provided by customer is limited to installation only and no update.
Operating system/hypervisor (for IC 51.384.00)	• PowerFlex management node (KVM) • VMware ESXi-8.0 (management cluster) • VMware-vCSA-all-8.0.x (management cluster) • VMware-ESXi-8.0 (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex appliance with operating systems that are provided by customer is limited to installation only and no update.
Adapters	• NVIDIA ConnectX-6 LX • NVIDIA ConnectX-6 DX • NVIDIA ConnectX-5 OCP/PCIe • NVIDIA ConnectX-4 rNDC • Intel X710/I350 rNDC • Broadcom 57414 V1 2x25 OCP • Broadcom 57414 V2 2x25 • Broadcom 57414 V1 2x25 • Broadcom 57608 2x100
Networking	Deployment requires a pair of the following switches: • Dell PowerSwitch S4148F-ON (access) • Dell PowerSwitch S5224F-ON (access) • Dell PowerSwitch S5248F-ON (access) • Dell PowerSwitch S5296F-ON (access) • Dell PowerSwitch S3248T-ON (management) • Dell PowerSwitch S5232F-ON (aggregation)

Table 3. PowerFlex Manager 5.1.x compatibility details (continued)

Component	Compatibility
	• Cisco Nexus 93180YC-FX3 (access or management-aggregation) • Cisco Nexus 93240YC-FX2 (access or leaf) • Cisco Nexus 9348GC-FX3 (management) • Cisco Nexus 9336C-FX2 (aggregation or spine) • Cisco Nexus 9364C-GX2 (spine or leaf) The following switches are supported but no longer shipped: • Dell PowerSwitch S4148T-ON (management) • Cisco Nexus 93180YC-FX • Cisco Nexus 9364C • Cisco Nexus 92348GC-X The following switches are end of support: • Cisco Nexus 3172TQ • Cisco Nexus 31108TC-V • Cisco Nexus 3132 • Cisco Nexus 3164 • Cisco Nexus 9236C • Cisco Nexus 93180YC-EX After deploying, PowerFlex Manager can monitor and update the Cisco Nexus and Dell PowerSwitch switches. PowerFlex Manager does not support monitoring and updating of the Cisco Nexus EPLD version.
Storage	PowerFlex 5.1.x PowerFlex 4.5.5.2
Security	CloudLink 8.3.x
Intelligent Catalog version	51.391.01 51.384.01

See the Code & Compatibility Knowledge Hub for more information.

PowerFlex Manager 5.0 compatibility details

This section provides the PowerFlex Manager 5.0 compatibility details for PowerFlex appliance components.

Table 4. PowerFlex Manager 5.0 compatibility details

Component	Compatibility
Nodes	• PowerFlex R660/R760 (storage-only) • PowerFlex R660/R760/R860/R6625/R7625 (compute-only) • PowerFlex R650/R750 (storage-only) • PowerFlex R650/R750/R6525/R7525 (compute-only) • PowerFlex R660 (management cluster) • PowerFlex R660/R650 (VMware NSX Edge node)
Operating system/hypervisor (for IC 50.390.00)	• PowerFlex management node (KVM) • VMware ESXi-8.0 (management cluster) • VMware-vCSA-all-8.0.x (management cluster) • VMware-ESXi-8.0 (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex appliance with operating systems that are provided by customer is limited to installation only and no update.
Adapters	• NVIDIA ConnectX-6 LX

Table 4. PowerFlex Manager 5.0 compatibility details (continued)

Component	Compatibility
	• NVIDIA ConnectX-6 DX • NVIDIA ConnectX-5 OCP/PCIe • NVIDIA ConnectX-4 rNDC • Intel X710/I350 rNDC • Broadcom 57414 V1 2x25 OCP • Broadcom 57414 V2 2x25 • Broadcom 57414 V1 2x25 • Broadcom 57508 V1 2x100
Networking	Deployment requires a pair of the following switches: • Dell PowerSwitch S4148F-ON (access) • Dell PowerSwitch S5224F-ON (access) • Dell PowerSwitch S5248F-ON (access) • Dell PowerSwitch S5296F-ON (access) • Dell PowerSwitch S4148T (management) • Dell PowerSwitch S5232F-ON (aggregation) • Cisco Nexus 93180YC-FX3 (access or management-aggregation) • Cisco Nexus 93240YC-FX2 (access or leaf) • Cisco Nexus 9348GC-FX3 (management) • Cisco Nexus 9336C-FX2 (aggregation or spine) • Cisco Nexus 9364C-GX2 (spine or leaf) The following switches are supported but no longer shipped: • Cisco Nexus 93180YC-FX • Cisco Nexus 9364C • Cisco Nexus 92348GC-X The following switches are end of support: • Cisco Nexus 3172TQ • Cisco Nexus 31108TC-V • Cisco Nexus 3132 • Cisco Nexus 3164 • Cisco Nexus 9236C • Cisco Nexus 93180YC-EX After deploying, PowerFlex Manager can monitor and update the Cisco Nexus and Dell PowerSwitch switches. PowerFlex Manager does not support monitoring and updating of the Cisco Nexus EPLD version.
Storage	PowerFlex 5.0
Security	CloudLink 8.2
Intelligent Catalog version	50.390.00

See the Code & Compatibility Knowledge Hub for more information.

4

Compatibility matrix for PowerFlex rack

This section provides the PowerFlex Manager compatibility details for PowerFlex rack components. PowerFlex Manager is deployed in one of the three modes, managed, lifecycle, or alerting. See PowerFlex glossary for more information on the deployment modes.

PowerFlex Manager 5.1.x compatibility details

This section provides the PowerFlex Manager 5.1.x compatibility details for PowerFlex rack components.

Table 5. PowerFlex Manager 5.1.x compatibility details

Component	Managed mode	Lifecycle mode
Nodes	• PowerFlex R670/R770/R6725/R7725 (compute-only) • PowerFlex R660/R760 (storage-only) • PowerFlex R660/R760/R860/R6625/R7625 (compute-only) • PowerFlex R650/R750 (storage-only) • PowerFlex R650/R750/R6525/R7525 (compute-only) • PowerFlex R660 (management cluster)	• PowerFlex R670/R770/R6725/R7725 (compute-only) • PowerFlex R660/R760 (storage-only) • PowerFlex R660/R760/R860/R6625/R7625 (compute-only) • PowerFlex R650/R750 (storage-only) • PowerFlex R650/R750/R6525/R7525 (compute-only) • PowerFlex R660 (management cluster) • PowerFlex R660/R650 (VMware NSX Edge node)
Operating system/ hypervisor (for RCM 3.9.1.0)	• PowerFlex management node (KVM) • VMware-ESXi-8.0 (compute-only) • VMware-vCSA-all-8.0.x (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex rack with operating systems that are provided by customer is limited to installation only and no update.	• PowerFlex management node (KVM) • VMware-ESXi-8.0 (compute-only) • VMware-vCSA-all-8.0.x (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex rack with operating systems that are provided by customer is limited to installation only and no update.
Operating system/ hypervisor (for RCM 3.8.4.0)	• PowerFlex management node (KVM) • VMware-ESXi-8.0 (compute-only) • VMware-vCSA-all-8.0.x (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex rack with operating systems that are provided by customer is limited to installation only and no update.	• PowerFlex management node (KVM) • VMware-ESXi-8.0 (compute-only) • VMware-vCSA-all-8.0.x (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex rack with operating systems that are provided by customer is limited to installation only and no update.
Adapters	• NVIDIA ConnectX-6 LX • NVIDIA ConnectX-6 DX • NVIDIA ConnectX-5 OCP/PCIe • NVIDIA ConnectX-4 rNDC • Intel X710/I350 rNDC • Broadcom 57414 V1 2x25 OCP • Broadcom 57414 v2 2x25 • Broadcom 57414 v1 2x25 • Broadcom 57608 2x100	Lifecycle mode when a supported adapter cannot be identified.

Table 5. PowerFlex Manager 5.1.x compatibility details (continued)

Component	Managed mode	Lifecycle mode
Networking	Managed mode requires a pair of the following server facing Dell and Cisco switches: The following switches are shipped and supported: • Dell PowerSwitch S3248T-ON • Dell PowerSwitch S5232F-ON • Dell PowerSwitch S4148F-ON • Dell PowerSwitch S5248F-ON • Cisco Nexus 9348GC-FX3 • Cisco Nexus 93180YC-FX3 • Cisco Nexus 9336C-FX2 • Cisco Nexus 93240YC-FX2 • Cisco Nexus 9364C-GX The following switches are supported but no longer shipped: • Dell PowerSwitch S4148T-ON • Cisco Nexus 93180YC-FX • Cisco Nexus 9364C • Cisco Nexus 92348GC-X The following switches are end of support: • Cisco Nexus 3172TQ • Cisco Nexus 31108TC-V • Cisco Nexus 3132 • Cisco Nexus 3164 • Cisco Nexus 9236C • Cisco Nexus 93180YC-EX PowerFlex Manager can monitor and update the accessible switches in managed mode. PowerFlex Manager does not support monitoring and updating of the Cisco Nexus EPLD version.	Lifecycle mode when a supported switch cannot be identified or cannot be granted with write access, provided the network configuration does not modify the node configuration. PowerFlex Manager can update only components with write access.
Storage	PowerFlex 5.1.x PowerFlex 4.5.5.2	PowerFlex 5.1.x PowerFlex 4.5.5.2
Security	CloudLink 8.3.x	CloudLink 8.3
RCM version	3.9.1.1 3.8.4.1	3.9.1.0 3.8.4.0

See the Code & Compatibility Knowledge Hub for more information.

PowerFlex Manager 5.0 compatibility details

This section provides the PowerFlex Manager 5.0 compatibility details for PowerFlex rack components.

Table 6. PowerFlex Manager 5.0 compatibility details

Component	Managed mode	Lifecycle mode
Nodes	• PowerFlex R660/R760 (storage-only) • PowerFlex R660/R760/R860/R6625/R7625 (compute-only) • PowerFlex R650/R750 (storage-only)	• PowerFlex R660/R760 (storage-only) • PowerFlex R660/R760/R860/R6625/R7625 (compute-only) • PowerFlex R650/R750 (storage-only)

Table 6. PowerFlex Manager 5.0 compatibility details (continued)

Component	Managed mode	Lifecycle mode
	• PowerFlex R650/R750/R6525/R7525 (compute-only) • PowerFlex R660 (management cluster)	• PowerFlex R650/R750/R6525/R7525 (compute-only) • PowerFlex R660 (management cluster) • PowerFlex R660/R650 (VMware NSX Edge node)
Operating system/ hypervisor (for RCM 3.9.0.0)	• PowerFlex management node (KVM) • VMware-ESXi-8.0 (compute-only) • VMware-vCSA-all-8.0.x (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex rack with operating systems that are provided by customer is limited to installation only and no update.	• PowerFlex management node (KVM) • VMware-ESXi-8.0 (compute-only) • VMware-vCSA-all-8.0.x (compute-only) • Embedded operating system 15 SP6 (storage-only) PowerFlex Manager support for PowerFlex rack with operating systems that are provided by customer is limited to installation only and no update.
Adapters	• NVIDIA ConnectX-6 LX • NVIDIA ConnectX-6 DX • NVIDIA ConnectX-5 OCP/PCIe • NVIDIA ConnectX-4 rNDC • Intel X710/I350 rNDC • Broadcom 57414 V1 2x25 OCP • Broadcom 57414 v2 2x25 • Broadcom 57414 v1 2x25 • Broadcom 57508 v1 2x100	Lifecycle mode when a supported adapter cannot be identified.
Networking	Managed mode requires a pair of the following server facing Dell and Cisco switches: The following switches are shipped and supported: • Dell PowerSwitch 4148T • Dell PowerSwitch S5232F-ON • Dell PowerSwitch S4148F-ON • Dell PowerSwitch S5248F-ON • Cisco Nexus 9348GC-FX3 • Cisco Nexus 93180YC-FX3 • Cisco Nexus 9336C-FX2 • Cisco Nexus 93240YC-FX2 • Cisco Nexus 9364C-GX The following switches are supported but no longer shipped: • Cisco Nexus 93180YC-FX • Cisco Nexus 9364C • Cisco Nexus 92348GC-X The following switches are end of support: • Cisco Nexus 3172TQ • Cisco Nexus 31108TC-V • Cisco Nexus 3132 • Cisco Nexus 3164 • Cisco Nexus 9236C • Cisco Nexus 93180YC-EX PowerFlex Manager can monitor and update the accessible switches in managed mode. PowerFlex Manager does not support monitoring and updating of the Cisco Nexus EPLD version.	Lifecycle mode when a supported switch cannot be identified or cannot be granted with write access, provided the network configuration does not modify the node configuration. PowerFlex Manager can update only components with write access.

Table 6. PowerFlex Manager 5.0 compatibility details (continued)

Component	Managed mode	Lifecycle mode
Storage	PowerFlex 5.0	PowerFlex 5.0
Security	CloudLink 8.2	CloudLink 8.2
RCM version	3.9.0.0	3.9.0.0

See the Code & Compatibility Knowledge Hub for more information.