Documentation: Policy synthesis via formal abstraction

Do abstraction of LTI system

Define LTI system as

$$\begin{aligned} x_{k+1} &= Ax_k + Bu_k + w_k \\ y_k &= Cx_k + Du_k + v_k \end{aligned} \tag{1}$$

with

- x state of size n
- u input of size m
- A matrix of size $n \times n$
- B matrix of size $n \times m$
- y the output (used to compare accuracy)
- C output matrix of size $q \times n$
- D matrix currently assumed to be zero

$$x_+ - \tilde{x}_+ = (A + BK)(x - \tilde{x}) + \mathbf{r} \tag{2}$$

with

- $\mathbf{r}$ in a polytope, i.e., $\mathbf{r} \in \mathcal{V}(r_i)$, the polytope generated from vertices r_i.

Consider a set defined as

$$\mathcal{R} := \{(\tilde{x}, x) \mid (x - \tilde{x})^T M (x - \tilde{x}) \leq \epsilon\} \tag{3}$$

Objective: Design M, K and ϵ such that if $(\tilde{x}, x) \in \mathcal{R}$ then also

$$\{(x_+ - \tilde{x}_+) | \text{ s.t. (2) } \forall \mathbf{r} \in \mathcal{V}(r_i)\} \subseteq \mathcal{R}.$$

More over for all $(\tilde{x}, x) \in \mathcal{R}$ it should hold that $d(\tilde{y}, y) \leq \epsilon$. The latter can be expressed as $C^T C \preceq M$. The former can be written with matrix inequalities as

$$\begin{aligned} (x_+ - \tilde{x}_+)^T M (x_+ - \tilde{x}_+) &\leq \epsilon \\ ((A + BK)(x - \tilde{x}) + \mathbf{r})^T M ((A + BK)(x - \tilde{x}) + \mathbf{r}) &\leq \epsilon \end{aligned}$$

Hence we get something of this form

$$(x-\tilde{x})^T M(x-\tilde{x}) \leq \epsilon^2 \implies ((A+BK)(x-\tilde{x})+\mathbf{r})^T M((A+BK)(x-\tilde{x})+\mathbf{r}) \leq \epsilon^2$$

S-procedure[a]
The implications

$$x^T F_1 x + 2g_1^T x + h_1 \leq 0 \implies x^T F_2 x + 2g_2^T x + h_2 \leq 0 \tag{4}$$

holds if and only if there exists $\lambda \geq 0$ such that

$$\lambda \begin{bmatrix} F_1 & g_1 \\ g_1^T & h_1 \end{bmatrix} - \begin{bmatrix} F_2 & g_2 \\ g_2^T & h_2 \end{bmatrix} \succeq 0 \tag{5}$$

[a] `https://en.wikipedia.org/wiki/S-procedure`

Using the S-procedure we get

$$(x-\tilde{x})^T(A+BK)^T M(A+BK)(x-\tilde{x}) + 2\mathbf{r}^T M(A+BK)(x-\tilde{x}) + \mathbf{r}^T M\mathbf{r} \leq \epsilon^2 \tag{6}$$

$$\lambda \begin{bmatrix} M & 0 \\ 0 & -\epsilon^2 \end{bmatrix} - \begin{bmatrix} (A+BK)^T M(A+BK) & (A+BK)^T M\mathbf{r} \\ \mathbf{r}^T M(A+BK) & \mathbf{r}^T M\mathbf{r} - \epsilon^2 \end{bmatrix} \succeq 0 \tag{7}$$

$$\begin{bmatrix} \lambda M - ((A+BK)^T M(A+BK)) & -(A+BK)^T M\mathbf{r} \\ -\mathbf{r}^T M(A+BK) & (1-\lambda)\epsilon^2 - \mathbf{r}^T M\mathbf{r} \end{bmatrix} \succeq 0 \tag{8}$$

$$\begin{bmatrix} \lambda M & 0 \\ 0 & (1-\lambda)\epsilon^2 \end{bmatrix} - \begin{bmatrix} ((A+BK)^T M(A+BK)) & (A+BK)^T M\mathbf{r} \\ \mathbf{r}^T M(A+BK) & \mathbf{r}^T M\mathbf{r} \end{bmatrix} \succeq 0 \tag{9}$$

$$\begin{bmatrix} \lambda M & 0 \\ 0 & (1-\lambda)\epsilon^2 \end{bmatrix} - \begin{bmatrix} (A+BK)^T M \\ \mathbf{r}^T M \end{bmatrix} M^{-1} \begin{bmatrix} (A+BK)^T M \\ \mathbf{r}^T M \end{bmatrix}^T \succeq 0 \tag{10}$$

$$\begin{bmatrix} \lambda M & 0 & (A+BK)^T M \\ 0 & (1-\lambda)\epsilon^2 & \mathbf{r}^T M \\ M(A+BK) & M\mathbf{r} & M \end{bmatrix} \succeq 0 \tag{11}$$

$$\begin{bmatrix} \lambda M^{-1} & 0 & M^{-1}(A+BK)^T \\ 0 & (1-\lambda)\epsilon^2 & \mathbf{r}^T \\ (A+BK)M^{-1} & \mathbf{r} & M^{-1} \end{bmatrix} \succeq 0 \tag{12}$$

$$\begin{bmatrix} \lambda M^{-1} & 0 & M^{-1}(A+BK)^T \\ 0 & (1-\lambda)\epsilon^2 & r_i^T \\ (A+BK)M^{-1} & r_i & M^{-1} \end{bmatrix} \succeq 0, \ \forall r_i \tag{13}$$

$$\tag{14}$$

Remark that this implies that $1-\lambda \geq 0$ hence $1 \geq \lambda \geq 0$. And remark that

The objective to find a minimal ϵ can be expressed as follows

$$\textbf{Objective}: \min_{M_{inv},L} \epsilon^2 \tag{15}$$

$$\begin{bmatrix} \lambda M_{inv} & 0 & M_{inv}A^T + L^T B^T \\ 0 & (1-\lambda)\epsilon^2 & r_i^T \\ AM_{inv} + BL & r_i & M_{inv} \end{bmatrix} \succeq 0 \tag{16}$$

$$\begin{bmatrix} M_{inv} & M_{inv}C^T \\ CM_{inv} & I \end{bmatrix} \succeq 0 \tag{17}$$

with $LM = K$ and $M^{-1} = M_{inv}$.