RA01 / RA62 系列模塊

promicro NRF52840	LORA PIN	HT-RA62 HF	RA-01SCH	RA-01SH	RA-01SH-P	RA-01SCH-P	說明
		SX1262	LLCC68	SX1262	SX1262	LLCC68	
	PIN1	ANT	ANT	ANT	ANF	ANF	
	PIN2	GND	GND	GND	GND	GND	
	PIN3	3.3V (>150 mA)	3.3V (>200 mA)	3.3V (>200mA)	3.3V (> 1A)	3.3V (> 1A)	**RA62:** 3V3 pin (≥150mA) **RA-01SH-P:** The recommended voltage is 3.3V and the peak current is above 1A. if using DC-DC, it is recommended that the ripple be controlled within 100mV **RA-01SCH-P:** The recommended voltage is 3.3V and the peak current is above 1A. if using DC-DC, it is recommended that the ripple be controlled within 100mV **RA-01SH:** Recommended 3.3V voltage, peak current recommended above 200mA recommended to use LDO for power supply; if DC-DC is used, the ripple is recommended to be controlled within 30mV **RA-01SCH:** Recommended 3.3V voltage, peak current above 200mA Suggest to use LDO for power supply; if use DC-DC recommend to control the ripple within 30mV
D10/P0.09	PIN4	RST	RESET	RESET	RESET	RESET	
NC	PIN5	TXEN	TXEN	TXEN	VCCPA	VCCPA	**22 dbm module:** **TEXN與DIO2短接(與開發版無關)** **29 dbm module:** **VCCPA -> 3.0 / 5.0 / 5.25 (min/ typical / max)**
D16/P0.10	PIN6	DIO1	DIO1	DIO1	DIO1	DIO1	
NC	PIN7	DIO2	DIO2	DIO2	DIO2	DIO2	**22 dbm module:** **TEXN與DIO2短接(與開發版無關)** **29 dbm module:** **NC**
NC	PIN8	DIO3	DIO3	DIO3	DIO3	DIO3	
	PIN9	GND	GND	GND	GND	GND	
D20/P0.29	PIN10	BUSY	BUSY	BUSY	BUSY	BUSY	
D2/P0.17	PIN11	RXEN	RXEN	RXEN	RF_EN	RF_EN	**22 dbm module:** **LORA RXEN與promicro D2連接** **29 dbm module:** **NC(RF_EN預設為HIGH)**
D14/P1.11	PIN12	SCK	SCK	SCK	SCK	SCK	
D19/P0.02	PIN13	MISO	MISO	MISO	MISO	MISO	
D18/P1.15	PIN14	MOSI	MOSI	MOSI	MOSI	MOSI	
D15/P1.13	PIN15	NSS	NSS	NSS	NSS	NSS	CS
	PIN16	GND	GND	GND	GND	GND	
	功率	22 dbm	22 dbm	22 dbm	29 dbm	29 dbm	RA-01SH-P (3.3V版本)29dbm: 3.3V 750MA (5V版本)31dbm: 5V 1000MA