

# REPORT 2.5 - GPS Transistor bakeoff-3: the reopen retest and a locked-and-still reading

Fable, 2026-09-16, in Matt's chat (the first Fable-main session). Tree at ab020d2, clean. His words on it, 2026-09-15: *"fix the reopen bug. I will let you test after work if I am not in a terrible mood which is very likely the way this morning is going"*; this morning: *"hold on the build. Let's finish the GPS test this morning. Tell me what you need"*, then *"Yes lock it and run the 15"*.

Data: docs/roundDownloads/bakeoff/20260916-075606/golf-bakeoff/T/20260916-073358-T/ (app log) and sdk-store-20260916-075557.json (the SDK's own store), both gitignored. Scored by bakeoff.ps1 -Task pull (Section 9 measure).

## 1. Verdict

**PASS, n = 1 retest.** The reopen bug of 2026-09-15 (app log lost 342 s after a Close all and reopen, session 20260915-075447-T) does not reproduce at bakeoff-3. The app log now matches the SDK store through a Close all, a reopen and 15 minutes locked.

## 2. What was done, in order

1. bakeoff.ps1 -Task setup installed bakeoff-3 over bakeoff-2 (same application ids). Every grant read back granted; battery unrestricted; RUN\_ANY\_IN\_BACKGROUND allow; both app checklists all OK except the Samsung never-sleeping line the app cannot read.
2. -Task start -Only T: GPS Transistor alone, session 20260916-073358-T, phone on the desk, plugged in, screen on.
3. From the desktop: recents (input keyevent 187), tap **Close all** (com.sec.android.app.launcher:id/clear\_all), relaunch GPS Transistor from its launcher intent 3 s later.
4. Status at 5 s and 65 s after the reopen: fixes.csv 102 then 162 lines.
5. input keyevent 26 locked the screen (mWakefulness=Dozing); left 15 min.
6. After the 15 min: still Dozing, 1,271 lines. Unlocked on his word; -Task stop -Only T (HOLD TO STOP, EXPORT ALL), -Task pull.

## 3. Numbers

| Source              | Span     | Fixes | Covered          | Gaps > 20 s | Longest gap | Median acc | Bar             |
|---------------------|----------|-------|------------------|-------------|-------------|------------|-----------------|
| app log, as scored  | 22.8 min | 1,324 | 21.9 min (96.0%) | 1           | 55 s        | 3.8 m      | FAIL as printed |
| app log, from row 2 | 21.9 min | 1,323 | 21.9 min         | 0           | 1.4 s       | 3.8 m      | PASS            |
| SDK store           | 21.9 min | 1,319 | 21.9 min (100%)  | 0           | 2 s         | 3.8 m      | PASS            |

The scorer's one "gap" is a scoring artifact, not a recorder gap: row 1 of the app log is the SDK's last-known fix from the previous session, handed over at start with its own old fix\_ms (07:33:03, 14.7 m accuracy) and logged at 07:33:58. The session started at 07:33:58. From row 2 on, the largest interval in 1,323 fixes is 1,448 ms. The SDK store, which has no such row, scores 100% with a 2 s longest gap on the same window.

The Close all, as the events log recorded it (events.csv):

| Wall time  | Event                                                    |
|------------|----------------------------------------------------------|
| 07:35:24.8 | sdk_headless_event name=terminate (the task was removed) |
| 07:35:25.0 | sdk_delivery_route route=headless                        |
| 07:35:27.7 | sdk_listeners subscribed=4;on=resume, route=listener     |

Fixes across the terminate-to-resume window: no interval over 1.4 s. The process kept its pid (17436) through the Close all; the heartbeat counter fixes\_this\_process did not reset.

Locked 15 min: 363 to 1,271 lines, 908 fixes in about 900 s, 1.0 per second, screen Dozing at both checks (n = 2 checks).

## 4. What this does and does not show

- **Shows:** the task-removed-and-reopened path, the one that produced yesterday's 342 s log gap, keeps the app log whole at bakeoff-3 (n = 1). Locked and still on a desk, plugged in, GPS Transistor alone holds 1 Hz for 15 min (n = 1).
- **Does not show:** a path where Android kills the process outright (the pid survived today); the bar's locked-screen clause (a round-length carry, screen off 90 percent of beats, music, golf-tracker closed - REPORT\_2.3 Section 9); battery drain (charging).

## 5. Follow-ups, not fixed here

1. **Scorer:** `bakeoff.ps1 -Task pull` scores the app log from its first row, which can be a pre-start last-known fix; it printed FAIL on a PASS run. A fix is to drop rows whose `fix_ms` precedes `started_wall_ms` in `meta.json`, or to score from `wall_ms`. Opus's, one line, not done today (the build is on hold on his word).
2. **The locked-screen carry** for the bar is still the open test (NEXT\_CHAT 2026-09-15, Section 3, item 1).