

Matt's Timer

Native Android app. Countdown timer + stopwatch, built for back-to-back sets. Installs from dist/MattsTimer.apk - 664 KB, no dependencies.

It cannot use the internet

The app declares exactly one permission: VIBRATE. There is no INTERNET permission in the manifest, so the phone will not let it reach the network under any circumstances. Nothing loads, nothing syncs, nothing needs signal. The chimes are synthesised on the device at startup rather than shipped as audio files.

The one rule that drives the layout

RESET restarts the selected preset and starts it immediately. Between back-to-back core sets that is one tap, not two. Both large buttons do this once the timer has finished, so you can hit either one without looking.

Presets

35s 45s 1m 5m 10m 20m 30m 60m, plus CUSTOM. 60 seconds and 1 minute collapsed into one tile.

The app **always launches on 35s**, regardless of what ran last. Presets go dim and inert while the timer is running, so a stray tap mid-set cannot wipe a live timer - pause or let it finish to change duration.

Custom lengths

CUSTOM opens a full-screen keypad. Digits shift in from the right as MM:SS - tap 2, 3, 0 for 2:30. SET & START applies it and starts it in one tap. The last custom value stays on the tile for one-tap recall, but it is never auto-selected at launch.

Buttons

State	Left (large)	Right (large)
Ready	START	RESET - restarts & runs
Running	PAUSE	RESET - restarts & runs
Paused	RESUME	RESET - restarts & runs
Finished	GO AGAIN	RESET - restarts & runs
Stopwatch running	STOP	LAP
Stopwatch stopped	START / RESUME	RESET

Sound and feedback

Soft bell tick at 3, 2, 1. At zero, a C-major arpeggio that lands on a full triad and rings twice - every tone is a sine with a soft attack and a natural decay, no buzzer. Screen goes red and flashes; the phone vibrates.

Sound and vibration toggle independently in the header and persist between sessions. Cues play on the alarm stream so they carry over gym noise.

Stopwatch

Second tab in the header. START / STOP, LAP while running, RESET when stopped. Laps list split and cumulative time, newest first. Hundredths resolution. The screen stays awake while anything is counting and

releases as soon as it stops; rotating the phone rebuilds the layout without disturbing a live set.

Install on the phone

Easiest: plug the phone into the desktop over USB with USB debugging on, and the install runs from here in one command - no files to move by hand.

By hand: copy `dist/MattsTimer.apk` to the phone over USB, tap it in Files, and allow "install unknown apps" for the file manager the first time. The build is signed with the local debug key, which is fine for sideloading to your own phone.

Rebuilding it

Needs JDK 17 and the Android SDK (compileSdk 35). No AndroidX, no Material library, no third-party dependencies - framework views only, which is why the APK is under 700 KB.

```
cd android && ./gradlew assembleRelease
```

Bumping `versionCode` in `android/app/build.gradle.kts` is only needed if an install ever refuses to replace the previous one.