

WidgetMax 3000 — User Manual

Page 1 of 2 | Document Ref: WM3K-UM-v2.4 | © Acme Corp

Chapter 1 — Installation

Thank you for purchasing the WidgetMax 3000. To install the device, first remove all packing material and verify the contents of the box: one main unit, one power adapter, two mounting screws, and one quick-start card. Place the main unit on a flat, dry surface within two metres of a power outlet. Connect the power adapter to the round port labelled DC-IN on the back of the unit. Press the power button for three seconds until the front LED turns solid green.

Chapter 2 — First-Time Setup

On first power-on, the WidgetMax 3000 enters setup mode. The front LED blinks blue for thirty seconds. During this window, open the WidgetMax companion app on your phone and tap Add Device. The app will detect the unit automatically. Enter your home Wi-Fi password when prompted. The LED turns solid green when the unit has joined the network. If the LED remains blinking after one minute, hold the reset pinhole on the back of the unit for ten seconds and start over.

Page 2 of 2 | WidgetMax 3000 User Manual

Chapter 3 — Daily Use

Once installed, the WidgetMax 3000 runs in the background. The front LED gives you status at a glance. Solid green means everything is working. Slow amber pulse means a firmware update is in progress — do not unplug the unit. Solid red means the unit has lost contact with the WidgetMax cloud — check your internet connection. The unit consumes about 4 watts during normal operation and up to 12 watts during firmware updates.

Chapter 4 — Troubleshooting

If the unit will not power on, verify the power adapter is fully seated and the outlet is live. If the LED is solid red for more than ten minutes, the unit cannot reach the cloud — restart your router and wait two minutes. If the companion app cannot find the device, ensure your phone and the WidgetMax 3000 are on the same Wi-Fi network. For all other issues, contact

support@acme-widgetmax.example with the serial number printed on the bottom of the unit.

Warranty: 2 years from date of purchase. Support hours: Mon-Fri 09:00-18:00 IST and 09:00-17:00 PT.