```
#include <stdio.h>
#include <stdlib.h>
#define BUFFER_SIZE 5
int buffer[BUFFER_SIZE];
int in = 0, out = 0;
int mutex = 1;
int empty = BUFFER_SIZE;
int full = 0;
int item = 0;
void wait(int *s) {
    (*s)--;
}
void signal(int *s) {
    (*s)++;
}
void produce() {
    if (empty == 0) {
        printf("Buffer is full\n");
        return;
    }
    wait(&empty);
    wait(&mutex);
    item++;
    buffer[in] = item;
    in = (in + 1) % BUFFER_SIZE;
    printf("Producer has produced: item%d\n", item);
    signal(&mutex);
    signal(&full);
}
```

```
void consume() {
    if (full == 0) {
        printf("Buffer is empty\n");
        return;
    }
    wait(&full);
    wait(&mutex);
    int consumed = buffer[out];
    out = (out + 1) % BUFFER_SIZE;
    printf("Consumer has consumed: item%d\n", consumed);
    signal(&mutex);
    signal(&empty);
}
int main() {
    int choice;
    printf("\n1WA24CS218");
    while (1) {
        printf("\nEnter your choice:\n");
        printf("1. Producer\n2. Consumer\n3. Exit\n");
        scanf("%d", &choice);
        switch (choice) {
            case 1:
                produce();
                break;
            case 2:
                consume();
                break;
            case 3:
                exit(0);
            default:
```

```
            printf("Invalid choice\n");
        }
    }
    return 0;
}
```

```
1WA24CS218
Enter your choice:
1. Producer
2. Consumer
3. Exit
1
Producer has produced: item1

Enter your choice:
1. Producer
2. Consumer
3. Exit
1
Producer has produced: item2

Enter your choice:
1. Producer
2. Consumer
3. Exit
2
Consumer has consumed: item1

Enter your choice:
1. Producer
2. Consumer
3. Exit
2
Consumer has consumed: item2

Enter your choice:
1. Producer
2. Consumer
3. Exit
3

Process returned 0 (0x0)   execution time : 11.373 s
Press any key to continue.
```