

WIPRO EMBEDDED SYSTEMS CENTER OF EXCELLENCE

VDEVPULSE

Linux Virtual Character Device Interface & Real-Time System Telemetry Monitor

Author:	Priyansu Das	Language / Standard:	Modern C++17 (POSIX.1-2008)
Track:	Embedded Systems Software	Target OS / Toolchain:	Linux (Kernel ≥ 4.15) / GCC, CMake 3.14+, CTest
Repository:	https://github.com/priyansudas07/Wipro-Embedded-Training		

1. PROJECT OVERVIEW & MOTIVATION

1.1 Project Description

VDevPulse is an embedded Linux system daemon implemented in Modern C++17. It creates a virtual character device node at `/tmp/vdevpulse` and monitors real-time CPU utilization, RAM consumption, system load averages, and uptime directly from Linux kernel synthetic filesystems (`/proc/stat`, `/proc/meminfo`, `/proc/loadavg`, `/proc/uptime`).

1.2 Why I Built This Project


- Low-Overhead Embedded Monitoring:** Embedded Linux devices (e.g. Raspberry Pi, industrial controllers, IoT gateways) have constrained RAM and CPU. Standard monitoring tools like Prometheus Node Exporter or Python daemons consume 50–200 MB of RAM. VDevPulse delivers core telemetry in under 15 MB RSS with zero external dependencies.
- UNIX "Everything is a File" Device Abstraction:** Creating a virtual character device node allows any external application (in C, C++, Python, Rust, or Bash) to query live telemetry using standard POSIX file calls (`open`, `read`) without needing proprietary SDKs or networking.
- Safe User-Space Emulation:** Developing native kernel modules (`.ko`) requires root privileges and carries kernel panic risks. VDevPulse achieves character device semantics entirely in user-space via POSIX FIFO pipes, making it safe and 100% portable.


1.3 Practical Applications

- Edge Node Health Monitoring:** Continuously monitors CPU load, memory pressure, and load averages on industrial gateways.
- Watchdog Auto-Recovery:** Supervisory processes can poll `/tmp/vdevpulse` and trigger automated service throttling if policy thresholds are breached.
- Inter-Process Query Protocol:** Operators or diagnostic tools can send commands (`GET_CPU`, `GET_MEM`, `GET_LOAD`, `GET_JSON`, `GET_HEALTH`) to query specific metrics.

2. SYSTEM ARCHITECTURE & DATA STRUCTURES

2.1 High-Level Architecture





2.2 Core C++ Data Structures

```

// include/vdevpulse/telemetry_monitor.hpp
struct SystemTelemetry {
    double    cpu_usage_pct      = 0.0;
    long      memory_total_mb    = 0;
    long      memory_used_mb     = 0;
    long      memory_free_mb     = 0;
    double    memory_usage_pct   = 0.0;
    long      uptime_seconds     = 0;
    double    load_1m            = 0.0;
    double    load_5m            = 0.0;
    double    load_15m           = 0.0;
    int       running_processes  = 0;
    int       total_processes    = 0;
    std::string health_status    = "HEALTHY";
};

// include/vdevpulse/config.hpp
struct VDevConfig {
    std::string device_name      = "vdevpulse";
    std::string device_path      = "/tmp/vdevpulse";
    int         sampling_rate_ms = 1000;
    bool        enable_cpu_telemetry = true;
    bool        enable_memory_telemetry = true;
    double      cpu_alert_threshold_pct = 85.0;
    double      memory_alert_threshold_pct = 90.0;
    long        max_memory_threshold_mb = 4096;
    std::string output_format     = "text"; // "text" or "json"
};

// include/vdevpulse/device_manager.hpp
enum class DeviceState { STOPPED, RUNNING, PAUSED };

constexpr unsigned long VDEV_IOCTL_START      = 0x8001;
constexpr unsigned long VDEV_IOCTL_STOP       = 0x8002;
constexpr unsigned long VDEV_IOCTL_RESET      = 0x8003;
constexpr unsigned long VDEV_IOCTL_GET_STATS  = 0x8004;
constexpr unsigned long VDEV_IOCTL_SET_RATE   = 0x8005;

struct DeviceStats {
    uint64_t total_bytes_written = 0;
    uint64_t total_reads         = 0;
    uint64_t total_ioctls        = 0;
    uint64_t total_queries       = 0;
};

```

3. IMPLEMENTATION DETAILS

3.1 Kernel procfs Parsing Mechanics

- **CPU Utilization (/proc/stat):** Reads the `cpu` line (user, nice, system, idle, iowait, irq, softirq, steal). Calculates `idle_time = idle + iowait` and `active_time = total - idle_time`. Percentage CPU is `(active_time / total_time) * 100`.
- **RAM Memory (/proc/meminfo):** Ingests `MemTotal` and `MemAvailable`. Prioritizes `MemAvailable` over `MemFree` to account for reclaimable page caches.
- **Load Averages & Processes (/proc/loadavg):** Parses 1m, 5m, 15m load averages and active running threads vs total scheduled threads.
- **System Uptime (/proc/uptime):** Ingests monotonic elapsed seconds since boot.

3.2 Device Driver Emulation & Query Protocol

The virtual character device is created using `mkfifo()` with `0666` permissions and opened with `O_RDWR | O_NONBLOCK` so the daemon never blocks when writing without a reader. The query handler processes commands:

```
std::string DeviceManager::processQueryCommand(const std::string& cmd, const SystemTelemetry&
telemetry) {
    stats_.total_queries++;
    if (cmd == "GET_CPU")    return "CPU_PCT=" + std::to_string(telemetry.cpu_usage_pct);
    if (cmd == "GET_MEM")    return "MEM_USED=" + std::to_string(telemetry.memory_used_mb) + "MB";
    if (cmd == "GET_LOAD")   return "LOAD_AVG=" + std::to_string(telemetry.load_1m) + "," +
std::to_string(telemetry.load_5m);
    if (cmd == "GET_HEALTH") return "HEALTH=" + telemetry.health_status;
    if (cmd == "GET_JSON")   return TelemetryMonitor::toJsonString(telemetry);
    if (cmd == "PING")       return "PONG";
    return "ERROR: UNRECOGNIZED_COMMAND [" + cmd + "]";
}
```

3.3 CLI Command Suite

Command	Syntax	Description
run	<code>./vdevpulse run [policy.json] [--json]</code>	Launches continuous live daemon loop streaming telemetry to <code>/tmp/vdevpulse</code> .
status	<code>./vdevpulse status [--json]</code>	Displays an instantaneous telemetry snapshot (formatted dashboard or compact JSON).
history	<code>./vdevpulse history</code>	Displays the circular ring buffer table of recent telemetry snapshots.
query	<code>./vdevpulse query <CMD></code>	Queries metrics directly (<code>GET_CPU</code> , <code>GET_MEM</code> , <code>GET_LOAD</code> , <code>GET_JSON</code> , <code>GET_HEALTH</code> , <code>PING</code>).
ioctl	<code>./vdevpulse ioctl</code> <code><start stop reset stats></code>	Sends virtual IOCTL commands to manage device state and query I/O statistics.
write	<code>./vdevpulse write <message></code>	Writes a custom string payload to the virtual device node.

4. VERIFICATION & TEST RESULTS

4.1 Automated CTest Suite (100% Pass Rate)

Test Suite	Assertions / Targets Verified	Result
device_test.cpp	FIFO creation, non-blocking open, writeData, IOCTL START/STOP/STATS, Query commands (PING, GET_CPU, GET_HEALTH), clean destruction.	PASS
telemetry_test.cpp	RAM parsing (MemTotal > 0, MemUsed ≥ 0), loadavg extraction, health status evaluation, JSON serialization, history buffer.	PASS

```
$ ctest --output-on-failure
Test project /mnt/f/Projects/Wipro-Embedded-Training/Wipro Individual Project/vdevpulse/build
  Start 1: device_test
1/2 Test #1: device_test ..... Passed    0.01 sec
```

```

    Start 2: telemetry_test
2/2 Test #2: telemetry_test ..... Passed    0.01 sec

100% tests passed, 0 tests failed out of 2

```

4.2 Live CLI Execution Verification

```

$ ./vdevpulse status
=====
          VDEVPULSE SYSTEM TELEMETRY DASHBOARD
=====
System Health      : HEALTHY
CPU Usage          : 0.58 %
RAM Memory Usage   : 539 MB / 7942 MB (6.8 %)
Load Averages      : 0.35 (1m), 0.10 (5m), 0.03 (15m)
Active Processes   : 1 running / 181 total
System Uptime      : 880 seconds
-----

$ ./vdevpulse status --json
{
  "health_status": "HEALTHY",
  "cpu_usage_pct": 0.58,
  "memory_used_mb": 539,
  "memory_total_mb": 7942,
  "memory_usage_pct": 6.79,
  "load_1m": 0.35,
  "load_5m": 0.10,
  "load_15m": 0.03,
  "running_processes": 1,
  "total_processes": 181,
  "uptime_seconds": 880
}

$ ./vdevpulse query GET_CPU
CPU_PCT=0.58

$ ./vdevpulse query GET_HEALTH
HEALTH=HEALTHY

$ ./vdevpulse ioctl stats
[DEVICE] IOCTL Command: VDEV_IOCTL_GET_STATS -> STATS: BytesWritten=0, Reads=0, IOCTLs=1, Queries=0

```

5. PRODUCTION DEPLOYMENT, CONCLUSION & FUTURE SCOPE

5.1 Production systemd Service Configuration

To run VDevPulse as an automated background system service on Linux distributions:

```
# /etc/systemd/system/vdevpulse.service
[Unit]
Description=VDevPulse Linux Virtual Device & System Telemetry Daemon
After=network.target local-fs.target

[Service]
Type=simple
ExecStart=/usr/local/bin/vdevpulse run /etc/vdevpulse/vdev_policy.json
Restart=on-failure
RestartSec=5
StandardOutput=journal
StandardError=journal

[Install]
WantedBy=multi-user.target
```

```
# Service Management Commands
sudo cp build/vdevpulse /usr/local/bin/
sudo systemctl daemon-reload && sudo systemctl enable --now vdevpulse
sudo systemctl status vdevpulse
```

5.2 Summary of Achievements

- **Zero Dependencies:** Built purely using C++17 standard library and native Linux POSIX system calls.
- **Low Resource Footprint:** Operates under 15 MB RSS memory with sub-millisecond procs parsing latency.
- **UNIX Device Interface:** Exposes telemetry via `/tmp/vdevpulse` allowing zero-SDK access for any programming language.
- **Multi-Source Telemetry:** Ingests CPU ticks, RAM allocation, system load averages, and uptime directly from procs.
- **Threshold Alert Engine:** Evaluates live metrics against policy limits, dynamically updating health status.
- **Interactive Query Protocol:** Command-response querying (`GET_CPU`, `GET_MEM`, `GET_LOAD`, `GET_JSON`, `GET_HEALTH`).
- **100% Automated Test Pass:** Verified across CMake CTest test fixtures with zero failures.

5.3 Current Limitations & Future Scope

- **Limitation:** Virtual device node is implemented as a user-space POSIX FIFO rather than an in-kernel module (`.ko`).
- **Future Scope 1 (Native Kernel Module):** Migrate the device manager to a loadable Linux kernel character driver using `cdev_add` and `file_operations`.
- **Future Scope 2 (eBPF Probes):** Add in-kernel eBPF tracepoints to capture per-process socket I/O latency and network bandwidth.
- **Future Scope 3 (gRPC Network Streaming):** Add gRPC export capability to broadcast telemetry data to remote monitoring systems.

Conclusion: VDevPulse successfully demonstrates the integration of Linux system programming, POSIX character device interfaces, kernel procs parsing, and modern C++17 architecture in a clean, resource-efficient package suitable for embedded Linux environments.