Projects 3 and 11

GOAL:

Create an HOA screen offering full control and visibility of all output devices.

SUMMARY:

We have our HOA status words and all of our pushbuttons in the program: now let's put 'em to good use!

Generally, all devices on a system such as ours would be left in automatic mode full time so that the logic could govern them. But what happens when there is a leak? What about a component replacement scenario, troubleshooting, testing, an abnormal cycle is desired or etc.? In any of these cases, the Operator would require MANUAL control of a device – either locking it ON or keeping is OFF.

So on our new screen, we want to offer the pushbuttons to change mode between HAND, OFF and AUTO. We also want TWO indicators for each device. One indicator will show the MODE of the device. The second will indicate whether the device is ON or OFF (OPEN or CLOSED).

TAG USAGE:

B3:0/7	P1	Pump P-1 Bit
B3:1/12	P1_AUTO_PB	Pump P-1 AUTO Pushbutton
B3:1/11	P1_HAND_PB	Pump P-1 HAND Pushbutton
B3:1/10	P1_OFF_PB	Pump P-1 OFF Pushbutton
N7:6	P1_STATUS	Pump P-1 HOA Status 0 = OFF 1 = HAND, 2 = AUTO
B3:0/1	SV1	Solenoid Valve SV-1 Bit
B3:0/10	SV1_AUTO_PB	Solenoid Valve SV-1 AUTO Pushbutton
B3:0/9	SV1_HAND_PB	Solenoid Valve SV-1 HAND Pushbutton
B3:0/8	SV1_OFF_PB	Solenoid Valve SV-1 OFF Pushbutton
N7:0	SV1_STATUS	Solenoid Valve SV-1 HOA Status 0 = OFF, 1 = HAND, 2 = AUTO
B3:0/2	SV2	Solenoid Valve SV-2 Bit
B3:0/13	SV2_AUTO_PB	Solenoid Valve SV-2 AUTO Pushbutton
B3:0/12	SV2_HAND_PB	Solenoid Valve SV-2 HAND Pushbutton
B3:0/11	SV2_OFF_PB	Solenoid Valve SV-2 OFF Pushbutton
N7:1	SV2_STATUS	Solenoid Valve SV-2 HOA Status 0 = OFF, 1 = HAND, 2 = AUTO
B3:0/3	SV3	Solenoid Valve SV-3 Bit
B3:1/0	SV3_AUTO_PB	Solenoid Valve SV-3 AUTO Pushbutton
B3:0/15	SV3_HAND_PB	Solenoid Valve SV-3 HAND Pushbutton
B3:0/14	SV3_OFF_PB	Solenoid Valve SV-3 OFF Pushbutton

N7:2	SV3_STATUS	Solenoid Valve SV-3 HOA Status 0 = OFF, 1 = HAND, 2 = AUTO
B3:0/4	SV4	Solenoid Valve SV-4 Bit
B3:1/3	SV4_AUTO_PB	Solenoid Valve SV-4 AUTO Pushbutton
B3:1/2	SV4_HAND_PB	Solenoid Valve SV-4 HAND Pushbutton
B3:1/1	SV4_OFF_PB	Solenoid Valve SV-4 OFF Pushbutton
N7:3	SV4_STATUS	Solenoid Valve SV-4 HOA Status 0 = OFF, 1 = HAND, 2 = AUTO
B3:0/5	SV5	Solenoid Valve SV-5 Bit
B3:1/6	SV5_AUTO_PB	Solenoid Valve SV-5 AUTO Pushbutton
B3:1/5	SV5_HAND_PB	Solenoid Valve SV-5 HAND Pushbutton
B3:1/4	SV5_OFF_PB	Solenoid Valve SV-5 OFF Pushbutton
N7:4	SV5_STATUS	Solenoid Valve SV-5 HOA Status 0 = OFF, 1 = HAND, 2 = AUTO
B3:0/6	SV6	Solenoid Valve SV-6 Bit
B3:1/9	SV6_AUTO_PB	Solenoid Valve SV-6 AUTO Pushbutton
B3:1/8	SV6_HAND_PB	Solenoid Valve SV-6 HAND Pushbutton
B3:1/7	SV6_OFF_PB	Solenoid Valve SV-6 OFF Pushbutton
N7:5	SV6_STATUS	Solenoid Valve SV-6 HOA Status 0 = OFF, 1 = HAND, 2 = AUTO