Labview
Keyboard Shortcuts

Johannes Rebling
University of Alberta
June 2012

Object/Movement	
Ctrl+K	**one position higher**
Ctrl+J	**one position lower**
Ctrl+Shift+K	**to the top**
Ctrl+Shift+J	**to the back**
Ctrl-click (drag)	**Duplicates selected object.**
Ctrl-Shift-A	**Performs last alignment operation on objects.**
Ctrl-D	**Performs last distribution operation on objects.**
Ctrl-mouse wheel	**Scrolls through subdiagrams of a Case, Event, or Stacked Sequence structure.**
Ctrl-U	Reroutes all existing wires and rearranges objects on the block diagram automatically.
While Quick Drop dialog active	**(ctrl+space)**
Ctrl-D	**creates controls and indicators for all unwired inputs and outputs of the selected block diagram object(s)**
Ctrl-Shift-D	**creates constants for all unwired inputs of the selected block diagram object(s).**
Ctrl-R	**removes the selected block diagram object(s) and any wires and constants connected to the selected object(s), and connects wires of identical data types that were wired to the inputs and outputs of the deleted object(s).**
Ctrl-T	moves the labels for all front panel control terminals to the left of the terminal and moves the labels for all front panel indicator terminals to the right of the terminal.
Ctrl-P	replaces the selected front panel or block diagram object(s) with the object you select in the Quick Drop dialog box.
Ctrl-I	inserts the object you select in the Quick Drop dialog box on the selected wire(s) on the block diagram.
Ctrl-Shift-I	inserts a single instance of the object you select in the Quick Drop dialog box on multiple selected wires.
Navigating	
Ctrl-Space	Displays the Quick Drop dialog box.
Ctrl-I	Displays the VI Properties dialog box.
File Operations	
Ctrl-O	Opens an existing VI.
Ctrl-W	Closes the VI.
Ctrl-Shift-S	Saves all open files.
Ctrl-Q	Quits LabVIEW.
Tools and Palettes	
Ctrl	**Switches to next most useful tool.**
Shift	**Switches to Positioning tool.**
Ctrl-Shift over open space	**Switches to Scrolling tool.**
Shift-right-click	**Displays a temporary version of the Tools palette at the location of the cursor.**
SubVIs	
Double-click subVI	Displays the subVI front panel.
Ctrl-double-click subVI	Displays the subVI block diagram and front panel.
Shift-drag VI icon to block diagram	Places that VI as a subVI on the block diagram with constants wired for controls that have non-default values.
Execution	
Ctrl-Run button	Recompiles the current VI.
Ctrl-Shift-Run button	Recompiles all VIs in memory.
Wiring	
Ctrl-B	Deletes all broken wires in a VI.
A	While wiring, temporarily disables automatic wire routing.
Double-click	While wiring, tacks down wire without connecting it.
Spacebar	While wiring, switches the direction of a wire between horizontal and vertical.
Spacebar	While moving objects, toggles automatic wiring.
Shift-click	Undoes last point where you set a wire.
Text	
Ctrl-=	**Increases the current font size.**
Ctrl--	**Decreases the current font size.**
Ctrl-0	**Displays the Font Style dialog box.**
Ctrl-1	Changes to the Application font in the Font Style dialog box.
Ctrl-2	Changes to the System font in the Font Style dialog box.
Ctrl-3	Changes to the Dialog font in the Font Style dialog box.
Ctrl-4	Changes to the current font in the Font Style dialog box.