

D Series

Installation Series Professional Amplifier Class - D



The D Series amplifier is a multi-channel professional Class-D amplifier, meticulously engineered to deliver exceptional reliability and performance. Its high efficiency is achieved through a combination of automatic temperature control and unique limiting functions, ensuring the amplifier operates efficiently by minimizing power loss and heat generation. Designed for long-term use, the D Series amplifiers offer consistent performance and durability, making them a reliable choice for professional audio installations. The innovative features and robust design make them an excellent choice for various settings, ensuring exceptional sound quality and ease of use.



Key Features

- Clip limiters
- Over temperature protections
- Short circuit protection
- Light weight and Portable

Parameter \ Model	D200	D300	D4200	D4300
Stereo/8Ω	250W×2	350W×2	200W×4	300W×4
Stereo/4Ω	400W×2	600W×2	350W×4	500W×4
Bridge/8Ω	700W×1	1000W×1	650W×2	900W×2
Bridge/4Ω	1000W×1 (Not recommended)	1200W×1	900W×2 (Not recommended)	1150W×2
Frequency Response	20HZ~20KHZ(0.5dB/-0.5dB)			
THD+N	<0.05%@8Ω 1KHz			
S/N Ratio	>98dB (A-weighted)			
Damping Factor	>500 (1 kHz @ 8 Ω)			
Crosstalk	>80dB			
Input Sensitivity	0.775V/1.44V			
Input Impedance (Bal/Unbal)	20KΩ/10KΩ			
Product Dimension (W x D x H) mm	482 x 220 x 48		482 x 350 x 44	
Net Weight (Kg)	2.5	2.5	4.8	5

Safety Instructions

- Do not use this product near water.
- Clean only with a dry cloth.
- Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
- Do not block any ventilation openings. Install following the manufacturer's instructions.
- Protect the power cord from being walked on or pinched, particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- Unplug the unit during lightning storms or when unused for long periods.
- Refer all servicing to qualified service personnel. Servicing is required periodically and when the unit is damaged, either mechanically or electrically, or is used in the smoky/dusty environment.