

The TTA Series amplifier is multi-channel professional amplifier, based on Class TD that combine the efficiency of Class D amplifiers with the sonic purity of Class B amplifiers. It tracks the audio signal at all frequencies, providing the required rail voltage with additional headroom that reduces the heat emission and maintain flat response even with complex loads. The Sonic Excellence, Versatile Performance & Enhanced cooling system makes this amplifier right choices that fits in both the horizons Touring Sound as well as Installations market. They incorporate the soft-start circuit with gradual volume increase, clip limiters and special protection features such as over temperature, overcurrent, DC and outputs short circuit.



### Key Features

- Indicators
- Clip limiters
- Over temperature protections
- DC & Outputs short circuit protection

Parameter \ Model	TTA300	TTA500	TTA600	TTA800	TTA1000	TTA1300	TTA450	TTA460
Power @8Ω per channel	350W×2	450W×2	650W×2	850W×2	1000W×2	1300W×2	450W×4	650W×4
Power @4Ω per channel	465W×2	750W×2	930W×2	1250W×2	1600W×2	1950W×2	750W×4	930W×4
Bridge/8Ω	930W	1460W	1860W	2500W	3200W	3900W	(Not recommended)	(Not recommended)
Bridge/4Ω	1116W (Not recommended)	1980W (Not recommended)	2604W (Not recommended)	3300W (Not recommended)	3800W (Not recommended)	4600W (Not recommended)	(Not recommended)	(Not recommended)
Frequency Response	20HZ~20KHZ(0.5dB/-0.5dB)							
THD+N	<0.05%@8Ω 1kHz							
S/N Ratio	>95dB (A-weighted)							
Damping Factor	>500 (1 kHz @ 8 Ω)							
Crosstalk	>75dB			>70dB			>70dB	
Input Sensitivity	0.775V/1.44V							
Input Impedance (Bal/Unbal)	20KΩ/10KΩ							
Product Dimension (W x D x H)	(483 x 442 x 88) mm				(483 x 462 x 88) mm		(483 x 462 x 88) mm	
Net Weight: (Kg)	15	17	18	20	24	26	23	25

### Safety Instructions

- Do not use this product near water.
- Clean only with a dry cloth.
- Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
- Do not block any ventilation openings. Install following the manufacturer's instructions.
- Protect the power cord from being walked on or pinched, particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- Unplug the unit during lightning storms or when unused for long periods.
- Refer all servicing to qualified service personnel. Servicing is required periodically and when the unit is damaged, either mechanically or electrically, or is used in the smoky/dusty environment.