

0. 安装依赖

...

```
sudo apt-get install v4l2loopback-dkms
```

```
sudo apt-get install v4l2loopback-utils
```

...

1. 开启摄像头设备树插件

这个步骤参考野火的这个文档: [15. 摄像头 — 快速使用手册—基于 LubanCat-RK3588 系列板卡 文档](#), 开启完之后重启

2. 编译 v4l2loopback 库

参考这个文档:

https://blog.csdn.net/m0_58944591/article/details/129836645?fromshare=blogdetail&sharetype=blogdetail&sharerId=129836645&sharerRefer=PC&sharesource=range_zero&sharefrom=from_link

2.1 获取源码, 编译

...

```
git clone https://gitee.com/ldl17/v4l2loopback
```

```
cd v4l2loopback
```

```
make
```

...

绝对会报错的, 如果报错说内核的某些文件格式不对, 参考这个文档解决:

https://blog.csdn.net/weixin_46667572/article/details/143928686?fromshare=blogdetail&sharetype=blogdetail&sharerId=143928686&sharerRefer=PC&sharesource=range_zero&sharefrom=from_link

解决完之后就能成功编译了, 结果如下:

```
Failed to open /dev/video0: No such device
cat@lubancat:~$ cd v4l2loopback
cat@lubancat:~/v4l2loopback$ ls
AUTHORS      README.md      release.sh      v4l2loopback.mod.c
COPYING      TODO           tests           v4l2loopback.mod.o
ChangeLog    currentversion.sh  udev            v4l2loopback.o
Kbuild       dkms.conf      utils           v4l2loopback_formats.h
Makefile     doc            v4l2loopback.c  vagrant
Makefile.manual  examples      v4l2loopback.h
Module.symvers  man           v4l2loopback.ko
NEWS           modules.order  v4l2loopback.mod
cat@lubancat:~/v4l2loopback$
```

3. 安装模块

这时有 ko 文件了, 可以直接 `sudo insmod v4l2loopback.ko` 安装, 安装完, 没报错可以用 `lsmod` 查看。应该就可以正常使用了

