






**Table B.52.8 – Current-carrying capacities in amperes
for installation methods E, F and G of Table B.52.1 –
Mineral insulation, copper conductors and sheath/PVC covered
or bare exposed to touch (see note 2) –
Metallic sheath temperature: 70 °C, reference ambient temperature: 30 °C**

Nominal cross-sectional area of conductor mm ²	Number and arrangement of cables for methods E, F and G of Table B.52.1				
	Two loaded conductors twin or single-core Method E or F	Three loaded conductors			
		Multi-core or single-core in trefoil formation Method E or F	Single-core touching Method F	Single-core flat vertical spaced Method G	Single-core horizontal spaced Method G
					
1	2	3	4	5	6
500 V					
1,5	25	21	23	26	29
2,5	33	28	31	34	39
4	44	37	41	45	51
750 V					
1,5	26	22	26	28	32
2,5	36	30	34	37	43
4	47	40	45	49	56
6	60	51	57	62	71
10	82	69	77	84	95
16	109	92	102	110	125
25	142	120	132	142	162
35	174	147	161	173	197
50	215	182	198	213	242
70	264	223	241	259	294
95	317	267	289	309	351
120	364	308	331	353	402
150	416	352	377	400	454
185	472	399	426	446	507
240	552	466	496	497	565
NOTE 1 For single-core cables the sheaths of the cables of the circuit are connected together at both ends.					
NOTE 2 For bare cables exposed to touch, values should be multiplied by 0,9.					
NOTE 3 D_e is the external diameter of the cable.					
NOTE 4 The values of 500 V and 750 V are the rated voltage of the cable.					