LYNS-TCi

CERTIFICATE OF CONFORMITY

Certificate No.: **AHC2408060119GC01**

Date of issue: 2024-12-12

Valid until: Indefinitely

Applicant	**Guangzhou Sanjing Electric Co., Ltd.** No.9, Lizhishan Road, Science City, Guangzhou High-tech Zone, Guangdong, P.R.China.
Device Type	Hybrid system (PV + DC coupled electrical energy storage)
Model	HS3-3K-S2-W-BX, HS3-3K-S2-G-BX, HS3-3K-S2-W-PX, HS3-3K-S2-G-PX, HS3-3.6K-S2-W-BX, HS3-3.6K-S2-G-BX, HS3-3.6K-S2-W-PX, HS3-3.6K-S2-G-PX, HS3-4K-S2-W-BX, HS3-4K-S2-G-BX, HS3-4K-S2-W-PX, HS3-4K-S2-G-PX, HS3-4.6K-S2-W-BX, HS3-4.6K-S2-G-BX, HS3-4.6K-S2-W-PX, HS3-4.6K-S2-G-PX, HS3-5K-S2-W-BX, HS3-5K-S2-G-BX, HS3-5K-S2-W-PX, HS3-5K-S2-G-PX, HS3-5K-S2-W-BX-BE, HS3-5K-S2- G-BX-BE, HS3-5K-S2-W-PX-BE, HS3-5K-S2-G-PX-BE, HS3-6K-S2-W-BX, HS3-6K-S2-G-BX, HS3-6K-S2-W-PX, HS3-6K-S2-G-PX, HS3-6K-S2-W-BX-IE, HS3-6K-S2-G-BX-IE, HS3-6K-S2-W-PX-IE, HS3-6K-S2-G-PX-IE
Trademark	SAJ
Technical data	Rated output power [W]: 3000 ~ 6000 Nominal output AC voltage [V]: 230 (L + N + PE, 50 Hz) (For further details see *A.2 Technical data of the power generating unit(s)* on p.2)
Software version	V1.000
Grid connection code	**EN 50549-1:2019 + A1:2023** Requirements for generating plants to be connected in parallel with distribution networks - Part 1-1: Connection to a LV distribution network - Generating plants up to and including Type B
Test specification	**EN 50549-10,** October 2022 Requirements for generating plants to be connected in parallel with distribution networks - Part 10: Tests for conformity assessment of generating units
Certification scheme	**CMPD-01**
Test report no.	**HC2408060119GC01** (2024-12-10)

The above-mentioned generating unit(s) are certified for **type A** generating modules.

This certificate confirms that the above-mentioned generating unit(s) with corresponding software meet the requirements of the referenced standard(s) / guideline(s) at the time of issuance of the certificate.

The generating units are considered to be compliant with the relevant articles (see Annex H, EN 50549-1:2019) of *Commission Regulation (EU) 2016/631 of 14 April 2016 establishing a network code on requirements for grid connection of generators* (NC RfG), provided that all settings as specified by the DSO and responsible party are complied with.

Further information on the assessment, including its scope and conditions, can be found in annex A.4 on p.4.

This certificate relates to type testing and does not imply LYNS's endorsement, approval, certification or on-going control of the product(s), either in terms of performance, design, manufacture or materials used. This certificate and the results stated herein relate solely to the sample product(s) tested and to the specific tests undertaken.

The certificate will remain valid for the stated period providing no changes are made to the product, production method etc. This certificate is only valid when this is also found at http://www.lyns-tci.com/en/certificate-search or contact Lyns-tci Technology Guangdong Co., Ltd..

This certificate is for the exclusive use of LYNS's Client and is provided pursuant to the agreement between LYNS and its Client. LYNS's responsibility and liability are limited to the terms and conditions of the agreement. LYNS assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned using this verification.

The certificate is comprised of 9 pages (including Annex of 8 pages).

Dongguan, 2024-12-12

LYNS-TCi TECHNOLOGY

Dipl.-Ing. Weizhao Zheng
Head of certification body

IAS ACCREDITED Product Certification Agency PCA-159

Certification body Lyns-tci Technology Guangdong Co., Ltd. accredited according to ISO/IEC 17065 for product certification.

Release No.: 1.1 (2023)

This document shall not be reproduced, except in full, without the written approval of Lyns-tci Technology Guangdong Co., Ltd.

Lyns-tci Technology Guangdong Co., Ltd.
Address: Room 1201, Unit 2, Building 18, No. 7, Science and Technology Boulevard, Houjie Town, Dongguan City, Guangdong, 523960 P.R.C
Tel: +86 769 85598986 E-Mail: cb@lyns-tci.com Web: www.lyns-tci.com

Annex to the Certificate No.: **AHC2408060119GC01**

A.1 Revision history of the certificate

Rev. No.	Date	Changes
Rev. 0	2024-12-12	Initial issue

A.2 Technical data of the power generating unit(s)

Product family	HS3-(3 ~ 6)K-S2-(W/G)-(B/P)X(-BE/IE) The type code defines the product's specification and configuration:	
	Digit / Letter	Description
	(3 ~ 6)K	Rated active output power, 3000 ~ 6000 W
	W	Wi-Fi with built-in AIO3 module
	G	with built-in 4G module
	B	Basic model
	P	Professional model
	X	X = 1, 2, 3, 4, 5, 6, 7, 8, representing the number of battery modules integrated into the system.
	IE	This model type is applicable exclusively to Ireland
	BE	This model type is applicable exclusively to Belgium
Model	Basic model	Professional model
	HS3-3K-S2-W-BX	HS3-3K-S2-W-PX
	HS3-3K-S2-G-BX	HS3-3K-S2-G-PX
	HS3-3.6K-S2-W-BX	HS3-3.6K-S2-W-PX
	HS3-3.6K-S2-G-BX	HS3-3.6K-S2-G-PX
	HS3-4K-S2-W-BX	HS3-4K-S2-W-PX
	HS3-4K-S2-G-BX	HS3-4K-S2-G-PX
	HS3-4.6K-S2-W-BX	HS3-4.6K-S2-W-PX
	HS3-4.6K-S2-G-BX	HS3-4.6K-S2-G-PX
	HS3-5K-S2-W-BX	HS3-5K-S2-W-PX
	HS3-5K-S2-G-BX	HS3-5K-S2-G-PX
	HS3-5K-S2-W-BX-BE	HS3-5K-S2-W-PX-BE
	HS3-5K-S2- G-BX-BE	HS3-5K-S2-G-PX-BE
	HS3-6K-S2-W-BX	HS3-6K-S2-W-PX
	HS3-6K-S2-G-BX	HS3-6K-S2-G-PX
	HS3-6K-S2-W-BX-IE	HS3-6K-S2-W-PX-IE
	HS3-6K-S2-G-BX-IE	HS3-6K-S2-G-PX-IE
DC input (PV)		
Max. DC input voltage [V]	600	
Operating MPPT voltage range [V]	90 ~ 550	
Max. input DC current [A]	16/16	20/20
Max. Short Circuit current [A]	20/20	25/25
Battery connection		
Battery voltage range [V]	380 ~ 550	
Battery charging current [A]	max. 15.8	
Battery discharging current [A]	"3K" model	9.2
	"3.6K" model	10.0
	"4K" model	12.4
	"4.6K" model	12.9
	"5K" model	15.2 or 13.9 ("BE" model)
	"6K" model	16.8 or 16.0 ("IE" model)

Annex to the Certificate No.: **AHC2408060119GC01**

Battery type	$LiFePO_4$	
AC connection		
No. of phases	☒ Single-phase ☐ Three-phase	
Nominal output AC voltage [V]	230 (L + N + PE, 50 Hz)	
Max. output AC current [A]	“3K” model	14.3
	“3.6K” model	15.7
	“4K” model	19.1
	“4.6K” model	20.0
	“5K” model	23.9 or 21.7 (“BE” model)
	“6K” model	26.1 or 25.0 (“IE” model)
Rated active output power [W]	“3K” model	3000
	“3.6K” model	3600
	“4K” model	4000
	“4.6K” model	4600
	“5K” model	5000
	“6K” model	6000 or 5750 (“IE” model)
Max. apparent output power [VA]	“3K” model	3300
	“3.6K” model	3600
	“4K” model	4400
	“4.6K” model	4600
	“5K” model	5500 or 5000 (“BE” model)
	“6K” model	6000 or 5750 (“IE” model)

Operating temperature range	Basic model	Charging: 0°C ~ +50°C Discharging: -10°C ~ +50°C
	Professional model	-30°C ~ +50°C
Storage temperature range	-10°C ~ +40°C	
Degree of protection	IP65	
Protection class	I	
Over voltage category	AC: III; DC: II	
Topology	No galvanic isolation	

Firmware version	V1.000

Manufacturer	**Guangzhou Sanjing Electric Co., Ltd.** No.9, Lizhishan Road, Science City, Guangzhou High-tech Zone, Guangdong, P.R.China.

A.3 Remarks for type testing

Testing laboratory	**LYNS-TCI TECHNOLOGY GUANGDONG CO., LTD.** Room 1201, Unit 2, Building 18, No. 7, Science and Technology Boulevard, Houjie Town, Dongguan City, Guangdong, 523960 P.R.C (Accredited acc. ISO/IEC 17025: A2LA Accreditation no. 5200.02)
Testing location	Same as above
Measurement period	2024-08-12 ~ 2024-11-14

A.4 Conformity assessment

Based on the test results submitted, this certificate provides the following conformity assessment according to the specifications listed on the cover sheet:

Clause(s) / subclause(s) of EN 50549-1:2019 or EN 50549-2:2019	Applicable Clause(s) / subclause(s) of EN 50549-10:2022	Remark	Verdict
4.4.2 Operating frequency range	5.2.1 Frequency operating range	---	PASS
4.4.3 Minimal requirement for active power delivery at underfrequency	5.2.1 Frequency operating range	---	PASS
4.4.4 Continuous operating voltage range	5.2.2 Voltage operating range	---	PASS
4.5.2 Rate of change of frequency (ROCOF) immunity	5.3.1 Immunity to disturbances - Rate of change of frequency (ROCOF)	---	PASS
4.5.3.2 Generating plant with non-synchronous generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	Generating units of non-synchronous generating technology.	PASS
4.5.3.3 Generating plant with synchronous generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	---	N/A
4.5.4 Over-voltage ride through (OVRT)	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	---	PASS
4.5.5 Phase jump immunity	5.3.2 Phase jump	---	PASS
4.6.1 Power response to overfrequency	5.4 Active response to frequency deviation	---	PASS
4.6.2 Power response to underfrequency	5.4 Active response to frequency deviation	---	PASS
4.7.2.2 Voltage support by reactive power, Capabilities	5.5.1 Power capabilities assessment	---	PASS
4.7.2.3 Voltage support by reactive power, Control modes	5.5.2 Voltage support by reactive power - test to determine the reactive power control modes	Available modes: • Q setpoint • Q(U) • cosφ setpoint • cosφ(P)	PASS
4.7.2.3.2 Set point control modes	5.5.2.3 Verification procedure for Set point control	---	PASS
4.7.2.3.3 Voltage related control modes	5.5.2.5 Verification procedure for power related control modes for reactive power	---	PASS
4.7.2.3.4 Power related control mode	5.5.2.5 Verification procedure for power related control modes for reactive power	---	PASS
4.7.3 Voltage related active power reduction	5.6 Voltage related active power reduction - P(U)	---	PASS
only EN 50549-2:2019 4.7.4.2.1.1 Voltage support during faults and voltage steps – General	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	EN 50549-2 is not within the scope of this certification.	N/A
only EN 50549-2:2019 4.7.4.2.1.2 Voltage support during faults and voltage steps - Optional Modes	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	EN 50549-2 is not within the scope of this certification.	N/A
4.7.4.2.2 Zero current mode for converter connected generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	---	PASS
4.8 EMC and power quality	5.7 EMC and power quality	---	PASS
only EN 50549-1:2019 4.9.3 Requirements on voltage and frequency protection	5.8.3 Verification procedure for generating plants to be connected to a LV distribution network with Interface protection as internal device or 5.8.4 Verification procedure for generating plants to be connected to a LV distribution	The AC output is redundantly switched off by: • a high-power switching bridge • two relays for both the line conductor and the neutral conductor (Relay Model:	PASS

Annex to the Certificate No.: **AHC2408060119GC01**

Clause(s) / subclause(s) of EN 50549-1:2019 or EN 50549-2:2019	Applicable Clause(s) / subclause(s) of EN 50549-10:2022	Remark	Verdict
	network with Interface protection as dedicated device	ZETTLER *AZSR170-1AE-12D.* Alternative: ZETTLER *AZSR165-1AE-12DL* or Hongfa *HF176F/12-HTF*). This ensures that the output circuit will be opened even in the event of a single failure. Available protection functions: • Voltage protection • Overvoltage 10 min mean protection • Frequency protection The settings of the function, as well as the enabling and disabling of the function, are field adjustable and are protected from unauthorized interference through password.	
only EN 50549-2:2019, 4.9.3. Requirements on voltage and frequency protection	5.8.5 Verification procedure for generating plants to be connected to a MV distribution network	EN 50549-2 is not within the scope of this certification.	N/A
4.9.4 Means to detect island situation	5.8.6 Islanding detection	Islanding Detection Technique: Active Frequency Drift	PASS
4.10.2 Automatic reconnection after tripping	5.9.3 Automatic reconnection after tripping	---	PASS
4.10.3 Starting to generate electrical power	5.9.4 Starting to generate electrical power	---	PASS
4.11.1 Ceasing active power	5.10 Active power reduction on set point	The units do not provide logic interface for terminating active power output. This needs at the project level (e.g. using an additional energy monitoring / communication unit with logic interface).	PASS
4.11.2 Reduction of active power on set point	5.10 Active power reduction on set point	---	PASS
4.12 Remote information exchange	5.11 Remote information exchange	Need to be evaluated at the project level.	N/A
only EN 50549-1:2019, 4.13 single fault tolerance of interface protection system and interface switch	5.12 Requirements regarding single fault tolerance of interface protection system and interface switch	---	PASS
	5.13 Model definition and model validation for generating units of synchronous generating technology	Generating units of non-synchronous generating technology.	N/A

A.5 Parameter list

Name of parameter set		"EN50549-PL"					
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	**Parameter**	**Remarks / additional information**	**configurable value range**	**Step size**	**unit**	**default value**	
4.3.2 Interface switch	Single fault tolerance for interface switch required	Requirement met	---	---	---	---	
4.4.2 Operating frequency range	Internal parameter not configurable	Requirement acc. EN 50549-1, table 1 can be met	---	---	---	---	
4.4.3 Minimal requirement for active power delivery at under frequency	Internal parameter not configurable	Requirement acc. EN 50549-1, clause 4.4.3 can be met	---	---	---	---	
4.4.4 Continuous operating voltage range	Upper limit	---	not configurable	---	$\%U_n$	110	
	Lower limit	---	not configurable	---	$\%U_n$	85	
4.5.2 Rate of change of frequency (ROCOF) immunity	Internal parameter not configurable	ROCOF withstand capability ≥ 2Hz/s	---	---	---	---	
4.5.3.2 Generating plant with non-synchronous generating technology (FRT)	Maximum power resumption time	---	Not configurable	---	---	≤ 1s	
	Enable under voltage ride through	---	Enable | Disable	---	---	Enable	
	Voltage-Time-Diagram	Voltage-Time-Diagram definition	Requirement acc. EN 50549-1, figure 6 (default requirement) can be met			Time	U
	V1		0.0 – 100.0	0.1	$\%U_n$		20,0
	T1		0.00 – 60.00	0.01	s	0.00	
	V2		0.0 – 100.0	0.1	$\%U_n$		20,0
	T2		0.00 – 60.00	0.01	s	1.50	
	V3		0.0 – 100.0	0.1	$\%U_n$		85.0
	T3		0.00 – 60.00	0.01	s	1.50	
4.5.4 Over-voltage ride through (OVRT)	Enable over voltage ride through	---	Enable | Disable	---	---	Enable	
	Voltage-Time-Diagram	Voltage-Time-Diagram definition	Requirement acc. EN 50549-1, figure 8 can be met			Time	U
	V1		0.0 – 130.0	0.1	$\%U_n$		1.25
	T1		0.00 – 60.00	0.01	s	0.00	
	V2		0.0 – 130.0	0.1	$\%U_n$		1.25
	T2		0.00 – 60.00	0.01	s	0.10	
	V3		0.0 – 130.0	0.1	$\%U_n$		1.20
	T3		0.00 – 60.00	0.01	s	0.10	
	V4		0.0 – 130.0	0.1	$\%U_n$		1.20
	T4		0.00 – 60.00	0.01	s	5.00	
	V5		0.0 – 130.0	0.1	$\%U_n$		1.15
	T5		0.00 – 60.00	0.01	s	5.00	
	V6		0.0 – 130.0	0.1	$\%U_n$		1.15
	T6		0.00 – 60.00	0.01	s	60.00	

Annex to the Certificate No.: **AHC2408060119GC01**

Name of parameter set		"EN50549-PL"				
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	**Parameter**	**Remarks / additional information**	**configurable value range**	**Step size**	**unit**	**default value**
	V7		0.0 – 130.0	0.1	$\%U_n$	1.10
	T7		0.00 – 60.00	0.01	s	60.00
4.6.1 Power response to over frequency (LFSM-O)	Activation frequency	Threshold frequency f1	50 - 65	0.01	Hz	50.20
	Power gradient	Droop	2 - 12	0.1	%	5.0
	Overfrequency reference power section	Power reference	P_M | P_{max}	---	---	P_{max}
	Delay time	Intentional delay	0 - 60	0.1	s	0.0
4.6.2 Power response to under frequency (LFSM-U)	Activation frequency	Threshold frequency f1	45 - 50	0.01	Hz	49.80
	Power gradient	Droop	2 - 12	0.1	%	5.0
	Underfrequency reference power section	Power reference	P_M | P_{max}	---	---	P_{max}
	Delay time	Intentional delay	0 - 60	0.1	s	0.0
4.7.2.2 voltage support by reactive power - Capabilities	Reactive power range overexcited	---	0 - 43.6%S_n	0.1	%S_n	43.6
	Reactive power range underexcited	---	-43.6%S_n - 0	0.1	%S_n	-43.6
	Minimum inductive power factor	Active factor range underexcited	0.80 - 1.00	0.01	---	0.90
	Minimum capacitive power factor	Active factor range overexcited	0.80 - 1.00	0.01	---	0.90
4.7.2.3 Control modes	Enabled control mode	---	Q setpoint Q(U) cosφ setpoint cosφ(P)	---	---	Q setpoint
4.7.2.3.2 Set point control modes (Q setpoint and excitation)	Reactive power setting value	---	-43.6%S_n - 43.6%S_n	0.1	%S_n	0
	Delay time	---	0 - 60	0.1	s	0.0
	Tau value	PT1-filtering time constant	0 - 60	0.1	s	2.0
4.7.2.3.2 Set point control modes (cosφ setpoint and excitation)	cosφ setting value	---	0.80 - 1.00 - 0.80	0.01	---	0.90
	Delay time	---	0 - 60	0.1	s	0.0
	Tau value	PT1-filtering time constant	0 - 60	0.1	s	3.3
4.7.2.3.3 Voltage related control modes - Q(U)	Voltage node 1	---	0 - 300	0.1	V	213.9
	Voltage node 2	---	0 - 300	0.1	V	223.1
	Voltage node 3	---	0 - 300	0.1	V	236.9
	Voltage node 4	---	0 - 300	0.1	V	246.1
	Reactive Power responding node 1	---	0 - 100	0.1	%S_n	43.6
	Reactive Power responding node 2	---	0 - 100	0.1	%S_n	0
	Reactive Power responding node 3	---	0 - 100	0.1	%S_n	0
	Reactive Power responding node 4	---	-100 - 100	0.1	%S_n	-43.6
	Delay time	---	0 - 60	0.1	s	0.0

Annex to the Certificate No.: **AHC2408060119GC01**

Name of parameter set		"EN50549-PL"				
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	**Parameter**	**Remarks / additional information**	**configurable value range**	**Step size**	**unit**	**default value**
	Tau value	PT1-filtering time constant	0 - 60	0.1	s	2.0
4.7.2.3.4 Power related control mode - cosφ(P)	PF Node 1	---	0 - 1	0.01	---	1.00
	PF Node 2	---	0 - 1	0.01	---	1.00
	PF Node 3	---	-1 - 1	0.01	---	0.90
	Power node 1	---	0 - 100	0.1	$\%S_n$	10.0
	Power node 2	---	0 - 100	0.1	$\%S_n$	50.0
	Power node 3	---	0 - 100	0.1	$\%S_n$	100.0
	Tau Value	PT1-filtering time constant	0 - 60	0.1	s	3.3
4.7.2.3.4 Power related control mode - (cos φ (P))	Ena	disable / enable	[0 / 1]	---	---	0
	PF	---	-0.90 – 0.90	0.01	---	- 0.9
	Time	---	0.5 – 1800.0	0.5	s	5.0
4.7.4.2.2 Zero current mode for converter connected generating technology	Threshold value of under voltage	---	not configurable	---	p.u.@U_n	0.50
	Threshold value of over voltage	---	not configurable	---	p.u.@U_n	1.20
4.9.2 Requirements on voltage and frequency protection	Undervoltage Protection value Level_1(V)	Undervoltage threshold stage 1	0 - 300	0.1	V	184.0
	Undervoltage Disconnection Time Level_1(V)	Undervoltage operate time stage 1	0 - 60000	1	ms	3000
	Undervoltage Protection value Level_2(V)	Undervoltage threshold stage 2	0 - 300	0.1	V	103.5
	Undervoltage Disconnection Time Level_2(V)	Undervoltage operate time stage 2	0 - 60000	1	ms	300
	Overvoltage Protection value Level_1(V)	Overvoltage threshold stage 1	0 - 300	0.1	V	253.0
	Overvoltage Disconnection Time Level_1(V)	Overvoltage operate time stage 1	0 - 60000	1	ms	100
	Overvoltage Protection value Level_2(V)	Overvoltage threshold stage 2	0 - 300	0.1	V	287.5
	Overvoltage Disconnection Time Level_2(V)	Overvoltage operate time stage 2	0 - 60000	1	ms	100
	10min overvoltage Protection Value	Overvoltage threshold 10min mean protection	0 - 300	0.1	V	253
	10-min mean Disconnection Time	Overvoltage operate time 10 min mean protection	---	---	---	10 min (update every 3s)
	Underfrequency Protection value Level_1	Underfrequency threshold stage 1	45 - 65	0.1	Hz	47.5
	Underfrequency Disconnection Time Level_1	Underfrequency operate time stage 1	0 - 60000	1	ms	100

Annex to the Certificate No.: **AHC2408060119GC01**

Name of parameter set		"EN50549-PL"				
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	**Parameter**	**Remarks / additional information**	**configurable value range**	**Step size**	**unit**	**default value**
	Overfrequency Protection value Level_2	Underfrequency threshold stage 2	45 - 65	0.1	Hz	---
	Overfrequency Disconnection Time Level_2	Underfrequency operate time stage 2	0 - 60000	1	ms	---
	Overfrequency Protection value Level_1	Overfrequency threshold stage 1	45 - 65	0.1	Hz	51.5
	Overfrequency Disconnection Time Level_1	Overfrequency operate time stage 1	0 - 60000	1	ms	100
	Level-2 overfrequency frequency value	Overfrequency threshold stage 2	45 - 65	0.1	Hz	---
	Level-2 overfrequency trip delay time	Overfrequency operate time stage 2	0 - 60000	1	ms	---
4.10.2 Automatic reconnection after tripping	Start up time following grid error	---	0 - 900	1	s	60
	Power gradient following grid error (%/min)	---	0 - 100	0.1	%/min	10.0
	Max. grid reconnection voltage	---	0 - 300	0.1	V	253.0
	Min. grid reconnection voltage	---	0 - 300	0.1	V	195.5
	Max. grid reconnection frequency	---	45 - 65	0.1	Hz	50.2
	Min. grid reconnection frequency	---	45 - 65	0.1	Hz	49.5
4.10.3 Starting to generate electrical power	Start up time	---	0 - 900	0.1	s	60.0
	Power gradient	---	0 - 100	0.1	%/min	10.0
	Max. grid start voltage	---	0 - 300	0.1	V	253.0
	Min. grid start voltage	---	0 - 300	0.1	V	195.5
	Max. grid start frequency	---	45 - 65	0.1	Hz	50.1
	Min. grid start frequency	---	45 - 65	0.1	Hz	49.5
4.11.1 Ceasing active power	---	---	---	---	---	Bluetooth
4.11.2 Reduction of active power on set point	Temporary Active Power Setting		0 - 100	0.1	%	100.0
	Active Power Slope Setting		[0 - 100]	0.1	%/min	29.0
4.12 Remote information exchange	---	---	---	---	---	---