Adsorber Model Equations Derivation

January 3, 2017

Showing $\LaTeX$ code with powerful *tcolorbox*

```
\begin{empheq}[box=\tcbhighmath]{equation*}
  \begin{split}
    -\diffty \ddzz{c_i} +  \ddz{(uc_i)}  + \ddt{c_i} + S_i = 0 \\
    -\diffty \ddzz{(Cy_i)} +  \ddzuv{u}{c_i} + \ddt{c_i} + S_i = 0 \\
    -\diffty \ddz{(\ddzuv{C}{y_i})} + \ddzuv{u}{c_i}  + \ddt{c_i} + S_i = 0 \\
    -\diffty \left \{ \ddzudv{y_i}{C} + \ddzudv{C}{y_i} \right \}
        + \ddzuv{u}{c_i}  + \ddt{c_i} + S_i = 0 \\
  \end{split}
\end{empheq}
```

$$\boxed{\begin{split}
-\mathcal{D}_L \frac{\partial^2 c_i}{\partial z^2} + \frac{\partial (uc_i)}{\partial z} + \frac{\partial c_i}{\partial t} + S_i = 0 \\
-\mathcal{D}_L \frac{\partial^2 (Cy_i)}{\partial z^2} + c_i \frac{\partial u}{\partial z} + u \frac{\partial c_i}{\partial z} + \frac{\partial c_i}{\partial t} + S_i = 0 \\
-\mathcal{D}_L \frac{\partial (y_i \frac{\partial C}{\partial z} + C \frac{\partial y_i}{\partial z})}{\partial z} + c_i \frac{\partial u}{\partial z} + u \frac{\partial c_i}{\partial z} + \frac{\partial c_i}{\partial t} + S_i = 0 \\
-\mathcal{D}_L \left\{ \frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i \frac{\partial^2 C}{\partial z^2} + \frac{\partial y_i}{\partial z}\frac{\partial C}{\partial z} + C \frac{\partial^2 y_i}{\partial z^2} \right\} + c_i \frac{\partial u}{\partial z} + u \frac{\partial c_i}{\partial z} + \frac{\partial c_i}{\partial t} + S_i = 0
\end{split}}$$

$$\boxed{\begin{split}
-\mathcal{D}_L \left\{ C \frac{\partial^2 y_i}{\partial z^2} + 2 \frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i \frac{\partial^2 C}{\partial z^2} \right\} + c_i \frac{\partial u}{\partial z} + u \frac{\partial c_i}{\partial z} + \frac{\partial c_i}{\partial t} + S_i = 0 \\
-\mathcal{D}_L \left\{ C \frac{\partial^2 y_i}{\partial z^2} + 2 \frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i \frac{\partial^2 C}{\partial z^2} \right\} + C y_i \frac{\partial u}{\partial z} + u \left\{ y_i \frac{\partial C}{\partial z} + C \frac{\partial y_i}{\partial z} \right\} + C \frac{\partial y_i}{\partial t} + y_i \frac{\partial C}{\partial t} + S_i = 0 \\
C \left\{ \frac{\partial y_i}{\partial t} + y_i \frac{\partial u}{\partial z} + u \frac{\partial y_i}{\partial z} \right\} + u y_i \frac{\partial C}{\partial z} + y_i \frac{\partial C}{\partial t} - \mathcal{D}_L \left\{ C \frac{\partial^2 y_i}{\partial z^2} + 2 \frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i \frac{\partial^2 C}{\partial z^2} \right\} + S_i = 0 \\
C \left\{ \frac{\partial y_i}{\partial t} + y_i \frac{\partial u}{\partial z} + u \frac{\partial y_i}{\partial z} \right\} + y_i \left\{ u \frac{\partial C}{\partial z} + \frac{\partial C}{\partial t} \right\} - \mathcal{D}_L \left\{ C \frac{\partial^2 y_i}{\partial z^2} + 2 \frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i \frac{\partial^2 C}{\partial z^2} \right\} + S_i = 0
\end{split}}$$

Rearranging

$$\boxed{\begin{split}
C \left\{ \frac{\partial y_i}{\partial t} + u \frac{\partial y_i}{\partial z} \right\} + y_i \left\{ C \frac{\partial u}{\partial z} + u \frac{\partial C}{\partial z} + \frac{\partial C}{\partial t} \right\} - \mathcal{D}_L \left\{ C \frac{\partial^2 y_i}{\partial z^2} + 2 \frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i \frac{\partial^2 C}{\partial z^2} \right\} + S_i = 0 \\
C \left\{ \frac{\partial y_i}{\partial t} + u \frac{\partial y_i}{\partial z} \right\} + y_i \left\{ \frac{\partial (Cu)}{\partial z} + \frac{\partial C}{\partial t} \right\} - \mathcal{D}_L \left\{ C \frac{\partial^2 y_i}{\partial z^2} + 2 \frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i \frac{\partial^2 C}{\partial z^2} \right\} + S_i = 0
\end{split}}$$

Total Mass Blance

$$\frac{\partial C}{\partial t} + \frac{\partial (Cu)}{\partial z} + \sum S_i = 0$$

Now Component Balance can be written as

$$C\left\{\frac{\partial y_i}{\partial t} + u\frac{\partial y_i}{\partial z}\right\} - y_i \sum S_i - \mathcal{D}_L\left\{C\frac{\partial^2 y_i}{\partial z^2} + 2\frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i\frac{\partial^2 C}{\partial z^2}\right\} + S_i = 0$$

$$C\left\{\frac{\partial y_i}{\partial t} + u\frac{\partial y_i}{\partial z}\right\} - \mathcal{D}_L\left\{C\frac{\partial^2 y_i}{\partial z^2} + 2\frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i\frac{\partial^2 C}{\partial z^2}\right\} + S_i - y_i \sum S_i = 0$$

Another way

$$-\mathcal{D}_L\left\{\frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i\frac{\partial^2 C}{\partial z^2} + \frac{\partial y_i}{\partial z}\frac{\partial C}{\partial z} + C\frac{\partial^2 y_i}{\partial z^2}\right\} + y_i\frac{\partial (Cu)}{\partial z} + (Cu)\frac{\partial y_i}{\partial z} + \frac{\partial (Cy_i)}{\partial t} + S_i = 0$$

$$-\mathcal{D}_L\left\{\frac{\partial C}{\partial z}\frac{\partial y_i}{\partial z} + y_i\frac{\partial^2 C}{\partial z^2} + \frac{\partial y_i}{\partial z}\frac{\partial C}{\partial z} + C\frac{\partial^2 y_i}{\partial z^2}\right\} + y_i\frac{\partial (Cu)}{\partial z} + Cu\frac{\partial y_i}{\partial z} + y_i\frac{\partial C}{\partial t} + C\frac{\partial y_i}{\partial t} + S_i = 0$$