

BITS PILANI K.K. BIRLA GOA CAMPUS

Department of Physics

What Quantum Trace Can a Heavy Particle Leave?

Curvature–Spectator Entanglement
and the Cosmological Collider

Step 10: Entropy–Signal Comparison

Group-B

Priyansh Rawat	2023B5A70968G
Mayank Sinha	2023B5A70942G
Samarth Bhatnagar	2023B5A70853G

Under Professor: Rudranil Basu

29 October 2026

1 Comparison at a common evaluation time

The Gaussian entropy belongs to the quadratic state, while the spectator bispectrum is calculated to first order in λ_3. We compare entropies and power at the common time $x = 0.01$. A selected mass/mixing control evaluates F at the same triangle $r = 0.03$ after regulator extrapolation.

M	g	S_q (nats)	$\Delta P_q/P_{q,0}$	$F(0.03)$
2	0.05	5.094×10^{-5}	9.297×10^{-4}	-5.084×10^{-11}
2	0.1	1.846×10^{-4}	0.003714	-3.986×10^{-10}
2	0.2	6.790×10^{-4}	0.01478	-2.936×10^{-9}
1.8	0.1	0.001377	0.005765	3.916×10^{-11}
2.4	0.1	7.630×10^{-5}	0.001825	4.488×10^{-11}




Figure 1: Selected entropy–signal points and the cubic-coupling control. A single-triangle value depends on oscillation phase as well as amplitude, so the left panel is not an entropy–clock-amplitude law.

The baseline entropy is 1.846×10^{-4} nats per real sector. Comparing different masses at one triangle can change the signal sign through its phase. The full clock fit at the baseline point, rather than F at a single r, is used for the mass assessment in Step 9.

2 Cubic control and recoverability

At fixed $M = 2$ and $g = 0.1$, changing λ_3 does not alter the quadratic covariance. The leading bispectrum scales linearly:

λ_3/H	S_q	$F(0.03)$
0	1.846×10^{-4}	0
0.005	1.846×10^{-4}	-1.993×10^{-10}
0.01	1.846×10^{-4}	-3.986×10^{-10}

This is a direct counterexample to inferring the three-point amplitude from Gaussian entropy alone: the same entropy accompanies zero, half-strength and full-strength cubic signals. It does not establish the absence of correlations within a restricted fixed-coupling parameter family. For an illustrative recoverability comparison we apply the same mock covariance $\Sigma = \sigma_F^2 I$ with $\sigma_F = 10^{-10}$ to all three signals. For the fitted baseline clock template t_i, the matched-template ratio is $\sqrt{t^T \Sigma^{-1} t}$. The template and covariance are specified assumptions, not a survey forecast.

λ_3/H	Known-template signal/noise
0	0
0.005	49.81
0.01	99.63

The signal/noise ratio changes with the cubic coupling while the Gaussian entropy stays fixed. Giving each signal the same fractional noise instead would conceal this amplitude dependence. The core project now includes the analytic single-field reference, validated Gaussian entropy map, analytic in-in test, converged baseline spectator signal and an explicit mass-fit stability assessment. Larger clock-amplitude scans over masses and mixings remain extensions. These calculations concern the specified fields and state; they do not constitute a cosmological Bell test or an observational detection.

References

[1] C. Weedbrook et al., *Gaussian Quantum Information*, Rev. Mod. Phys. 84, 621 (2012), arXiv:1110.3234.

[2] X. Chen and Y. Wang, *Quasi-Single Field Inflation and Non-Gaussianities*, JCAP 04 (2010) 027, arXiv:0911.3380.

[3] N. Arkani-Hamed and J. Maldacena, *Cosmological Collider Physics*, arXiv:1503.08043.

Code and supporting data: step10 on GitHub.

Contributions (equal)

Member	Contribution
Priyansh Rawat	Entropy–signal comparison and conclusions.
Samarth Bhatnagar	Cubic-coupling and common-covariance controls.
Mayank Sinha	Selected parameter comparisons, numerical tables and figure.